


QIAcuity® User Manual

For software version 3.5 (LTS)



REF

911000, 911020, 911040, 911050



QIAGEN GmbH, QIAGEN Strasse 1, 40724 Hilden, GERMANY

Table of Contents

1. Introduction	10
1.1. About this user manual	10
1.2. General information	11
1.2.1. Technical assistance	11
1.2.2. Policy statement	11
1.3. Intended use of the QIAcuity	11
1.4. Requirements for QIAcuity users	12
2. Safety Information	13
2.1. Proper use	13
2.2. Electrical safety	14
2.3. Environment	15
2.3.1. Operating conditions	15
2.4. Biological safety	16
2.4.1. Samples	16
2.5. Chemicals	16
2.6. Maintenance safety	17
2.7. Radiation safety	17
2.8. Symbols on the QIAcuity	18
3. General Description	19
3.1. QIAcuity principle	19
3.2. External features of QIAcuity	21
3.2.1. Touchscreen	21
3.2.1.1. Power switch	21
3.2.1.2. RJ-45 ethernet port	21
3.2.1.3. USB ports	22
3.2.1.4. Power cord socket	22
3.2.1.5. Cooling air outlet	23
3.2.1.6. External hand scanner	23
3.3. Thermal cyclers	23
3.4. Optical system	24
3.4.1. Available channels	24
4. Installation Procedures	25
4.0.1. Site requirements	25
4.0.2. Power requirements	26
4.0.3. Grounding requirements	26
4.1. Installation of AC power cord	26
4.2. Unpacking the QIAcuity	27
4.3. Packing the QIAcuity	27
4.4. Installing the QIAcuity	28
4.4.1. Removing the protective film from the QIAcuity touchscreen	28
4.4.2. Removing the shipping fixation screw	29
4.4.3. Connecting the power cord to the back of the QIAcuity	29
4.4.4. Powering on the QIAcuity	30
4.4.5. Removal of protective foam block of the drawer	30
4.4.6. Installing a fresh copy of the QIAcuity Software Suite	30
4.5. Upgrading the QIAcuity Software Suite to a newer version	34
4.5.1. Upgrading QIAcuity Software Suite from versions 3.1–3.2 (direct upgrade)	35
4.5.2. Upgrading QIAcuity Software Suite from version 3.0 to version 3.1	37
4.5.3. Upgrading QIAcuity Software Suite from version 2.5 to version 3.0	39

4.5.4. Upgrading QIAcuity Software Suite from version 2.2 to version 2.5	41
4.5.5. Upgrading QIAcuity Software Suite from version 2.0 to version 2.2	43
4.5.6. Upgrading QIAcuity Software Suite from version 1.2.18 to version 2.0	44
4.5.7. Upgrading QIAcuity Software Suite from version 1.1.3 to version 1.2.18	47
4.5.8. Backup QIAcuity Software Suite	51
4.5.8.1. Creating backup	51
4.5.8.2. Restore from backup	52
4.6. Uninstalling the QIAcuity Software Suite	53
4.7. Upgrading the instrument software to a newer version	55
4.7.1. Upgrading QIAcuity Control Software to version 3.5	56
4.7.1.1. USB drive preparation on the PC	56
4.7.1.2. Control Software update on the QIAcuity instrument	57
4.7.2. Upgrading QIAcuity Control Software to version 3.2 or lower	58
4.8. Establishing a connection between the QIAcuity instrument and the QIAcuity Software Suite	59
4.8.1. Private LAN direct connection of one instrument to a co-located Software Suite computer	59
4.8.2. Instrument and Software Suite computer connection via LAN	60
4.8.3. Private LAN with multiple instruments connected to a Software Suite computer	60
4.8.4. Instrument in dedicated subnet with computer also connected to corporate LAN	61
4.8.5. Configuring an ethernet connection between the QIAcuity instrument and the QIAcuity Software Suite	61
4.8.6. Configuring a direct cable connection between the QIAcuity instrument and the QIAcuity Software Suite	65
4.8.7. Configuring the connection to the QIAcuity Software Suite in the QIAcuity instrument software	68
4.9. Getting started with the QIAcuity	71
4.9.1. Configuration of the QIAcuity	71
4.9.2. Procedure	71
4.9.3. Setting basic system data	72
4.9.3.1. To set the preferred QIAcuity name	72
4.9.4. Managing users	73
4.9.5. Access policy	74
4.9.5.1. Password expiration	74
4.9.5.2. Automatic log-off and blocking user account	75
4.9.6. Synchronizing labware with the QIAcuity Software Suite	75
5. Operating Plates	77
5.1. QIAcuity Nanoplate 26K 24-well	77
5.2. QIAcuity Nanoplate 26K 8-well	78
5.3. QIAcuity Nanoplate 8.5K 24-well	78
5.4. QIAcuity Nanoplate 8.5K 96-well	78
5.5. Reaction setup	79
6. Operating the QIAcuity Instrument	81
6.1. Entering text and numbers	82
6.2. Turning on the instrument and logging in	83
6.3. Setting up a run	83
6.4. Setting up an experiment	84
6.4.1. Loading the trays and starting a run	84
6.4.2. Configuring a plate and starting a run	86
6.4.3. Plate configuration procedure	87
6.4.4. Linking a plate to a pre-defined plate without existing barcode	90
6.5. Tracking the run status	91
6.6. Continuous loading and unloading of plates	93
6.7. Aborting a run	94
6.8. Error clearing	95
6.9. Automatic error clearing during the run	97
6.10. Rerunning a plate	97
6.11. Editing the run schedule	98

6.12. Viewing notifications	99
6.13. Disk monitoring	99
6.14. Logging out	101
6.14.1. Automatic logout	102
6.14.2. Accessing the run status when you are logged out	103
7. Operating the QIAcuity Software Suite	104
7.1. Getting started	104
7.1.1. Software workspace	104
7.1.1.1. Main toolbar	104
7.1.1.2. Navigation areas	104
7.1.1.3. Information bar	105
7.2. Concepts of the QIAcuity Software Suite	106
7.2.1. Log-in screen	106
7.2.2. User management	107
7.2.3. Navigating in the User Management panel	108
7.2.4. New user creation	108
7.2.5. Editing an existing user	113
7.2.6. User activation	117
7.2.7. User deactivation	118
7.2.8. Log in (Instrument and PC software)	119
7.2.9. Instrument access (Instrument software)	119
7.2.10. Plates (Instrument and PC software)	119
7.2.10.1. All plates	119
7.2.10.2. Owned plates	120
7.2.10.3. Other permissions	120
7.2.11. Templates (Instrument and PC software)	122
7.2.12. Archive (PC software)	123
7.2.13. User management (PC software)	124
7.2.14. System configuration (PC software)	126
7.2.15. Default roles	127
7.2.16. New role creation	130
7.2.17. Editing existing role	133
7.2.18. Role deletion	135
7.2.19. Account security	136
7.3. Setting up an experiment	137
7.3.1. Creating a new plate	137
7.4. Plate configurator	139
7.4.1. Defining general data	139
7.4.2. Plate ownership	140
7.4.3. Assigning the owner of the plate	140
7.4.4. Removing an owner of the plate	141
7.4.5. Defining the dPCR parameters	141
7.4.5.1. Priming tab	142
7.4.5.2. Cycling tab	142
7.4.5.3. Gradient cycling	143
7.4.5.4. Imaging tab	145
7.4.5.5. High multiplexing	146
7.4.6. Reaction mixes tab	148
7.4.6.1. Creating new reaction mix	149
7.4.7. Analysis rules	150
7.4.7.1. Adding analysis rules	151
7.4.7.2. Configuring analysis rules	152
7.4.8. Editing, deleting, and saving reaction mixes as template	162
7.4.9. Importing reaction mixes from templates	163

7.4.10. Defining samples, controls, and non-template controls	164
7.4.10.1. Samples	164
7.4.10.2. Controls	167
7.4.10.3. Non Template Controls	168
7.4.11. Defining plate layouts	169
7.4.11.1. Plate view	169
7.4.11.1.1. Adding a reaction mix to the plate	169
7.4.11.1.2. Adding samples to the plate	170
7.4.11.1.3. Adding controls to the plate	171
7.4.11.1.4. Adding NTCs to the plate	172
7.4.11.1.5. Help	173
7.4.11.1.6. Plate layout with skipped analysis rules	173
7.4.11.1.7. Plate layout with defined gradient cycling	174
7.4.11.1.8. List view	175
7.4.12. Plate layout: CSV import/export	176
7.4.12.1. CSV structure	176
7.4.12.1.1. ### PLATE TEMPLATE	177
7.4.12.1.2. ### REACTION MIXES	177
7.4.12.1.3. ### SAMPLES	178
7.4.12.1.4. ### CONTROLS	178
7.4.12.1.5. ### NTCs	178
7.4.12.1.6. ### WELLS	178
7.4.12.1.7. ### ANALYSIS RULES	179
7.4.12.1.8. ### REPORT TEMPLATE	179
7.4.12.1.9. ### REPORT TEMPLATE FOR REACTION MIXES	179
7.4.12.2. Import plate layout from CSV	180
7.4.12.3. When will the CSV import function fail?	181
7.4.12.4. Possible errors and warnings	182
7.4.13. Saving plate	185
7.4.14. Managing your plates	185
7.4.14.0.1. Information icons	187
7.4.14.1. Sorting	188
7.4.14.2. Search	188
7.4.14.3. Filtering	189
7.4.14.4. Export and import plate data	190
7.5. Setting up templates	191
7.5.1. Creating a new plate template	191
7.5.2. Saving existing plate as a plate template	192
7.5.3. Using a plate template to create a new plate	193
7.5.4. Creating a new reaction mix template	194
7.5.5. Managing your templates	196
7.5.5.1. Sorting	197
7.5.5.2. Searching	197
7.5.5.3. New template	197
7.6. Analysis	197
7.6.1. Accessing the analysis environment	198
7.6.2. Plates after QIAcuity Software Suite version upgrade	199
7.6.3. Volume Precision Factor (VPF)	200
7.6.3.1. Identification of VPF status on plates	201
7.6.3.2. Loading VPF	203
7.6.4. Custom cross talk matrix	204
7.6.4.1. Preparing custom cross talk matrix (CXTM)	205
7.6.4.2. Saturation detection	211
7.6.4.3. Usage of custom cross talk matrix	215

7.6.4.3.1. Template level	215
7.6.4.3.2. Plate level	217
7.6.5. Images	220
7.6.5.1. Image quality control	221
7.6.6. Invalidation of images	221
7.6.7. Image corrective measures	222
7.6.8. Dust and other particles	223
7.6.9. Low amplification areas	224
7.6.10. Areas of bad filling	225
7.6.11. Amplitude multiplexing	225
7.6.12. Cross talk correction	226
7.6.13. Reference channel discrepancies	226
7.6.14. General analysis options	228
7.6.14.1. Selecting wells for analysis	228
7.6.14.2. Hyperwells	229
7.6.14.3. Using hyperwells in second-level analysis	230
7.6.14.3.1. Hyperwells in Gene Expression analysis	230
7.6.14.3.2. Hyperwells in Copy Number Variation analysis	232
7.6.14.4. Multiple imaging steps	235
7.6.14.5. Diagram options	236
7.6.14.6. Horizontal and vertical wells results presentation	237
7.6.14.7. Dilution calculation option	237
7.6.14.8. Usage of dilution calculation feature in analysis	238
7.6.14.8.1. Dilution factor results visualization	239
7.6.14.9. Conversion factor	240
7.6.14.9.1. Usage of conversion factor in analysis	242
7.6.14.9.2. Conversion factor results visualization	242
7.6.14.9.3. Range sliders	244
7.6.14.9.4. Ongoing background actions on plate	245
7.6.15. Absolute quantification	246
7.6.15.1. Total number of copies	246
7.6.15.2. Copies per microliter	247
7.6.15.3. Replicates	248
7.6.15.3.1. Mean concentration	248
7.6.15.3.2. Standard deviation	249
7.6.15.3.3. Coefficient of variation	249
7.6.15.4. Setting up an absolute quantification analysis	249
7.6.15.5. List tab for absolute quantification	251
7.6.15.6. Analysis behavior when Analysis rules are applied	252
7.6.15.6.1. Overall Quality Control Status	253
7.6.15.6.2. QC failure visualization	253
7.6.15.6.3. Overall Quality Control Status details	255
7.6.15.6.4. QC validation messages	255
7.6.15.6.5. Threshold fallback	256
7.6.15.7. Export to CSV	256
7.6.15.7.1. Current results	257
7.6.15.7.2. Multiple occupancy	260
7.6.15.7.3. Error handling	263
7.6.15.7.4. RFU values	264
7.6.15.7.5. RFU values (compact)	265
7.6.15.7.6. Importing of exported CSV file to Microsoft Excel	266
7.6.15.8. Signalmap tab for absolute quantification	267
7.6.15.9. Heatmap tab for absolute quantification	270
7.6.15.10. Histogram tab for absolute quantification	272

7.6.15.10.1. Copy, Copy all, and Download functions	273
7.6.15.10.2. Reference channel on histogram	273
7.6.15.11. 1D Scatterplot tab for absolute quantification	273
7.6.15.11.1. Changing the thresholds for all selected wells (Common threshold)	276
7.6.15.11.2. Changing the threshold individually per well	277
7.6.15.11.3. Setting amplitude multiplexing on 1D Scatterplot	278
7.6.15.11.4. Reference channel on 1D Scatterplot	281
7.6.15.11.5. Copy, Copy all, and Download functions	281
7.6.15.12. 2D Scatterplot tab for absolute quantification	282
7.6.15.12.1. Single pair mode	282
7.6.15.12.2. Selected pairs mode	283
7.6.15.12.3. Setting the common thresholds for all selected wells and each axis (channel)	284
7.6.15.12.4. Assigning partitions to a group using free hand (Polygon mode)	286
7.6.15.12.5. 2D Scatterplot Custom analysis	288
All selected wells mode	288
Samples mode	290
7.6.15.12.6. Unifying axis values of 2D Scatterplot for download and report purposes	293
7.6.15.12.7. Copy, Copy all, and Download functions	293
7.6.15.13. Concentration diagram tab for absolute quantification	294
7.6.16. Mutation detection	295
7.6.16.1. Setting up a mutation detection analysis	296
7.6.16.2. List tab for mutation detection	298
7.6.16.3. CSV export: Current results	299
7.6.16.4. Heatmap tab for mutation detection	301
7.6.16.5. Point diagram tab for mutation detection	302
7.6.16.6. Concentration diagram for mutation detection	303
7.6.17. Genome editing	305
7.6.17.1. Setting up a genome editing analysis	305
7.6.17.2. List tab for genome editing	306
7.6.17.3. Heatmap tab for genome editing	308
7.6.17.4. Point diagram tab for genome editing	309
7.6.17.5. Concentration diagram tab for genome editing	310
7.6.18. Copy Number Variation	311
7.6.18.1. Setting up a Copy Number Variation analysis with reference target	311
7.6.18.2. Setting up a Copy Number Variation analysis with reference sample	313
7.6.18.3. List tab for copy number variation	316
7.6.18.3.1. CSV export: Current results	317
7.6.18.4. Heatmap tab for Copy Number Variation	319
7.6.18.5. Point diagram tab for Copy Number Variation	321
7.6.18.6. Concentration diagram tab for Copy Number Variation	323
7.6.19. Gene expression	325
7.6.19.1. Setting up a gene expression analysis	326
7.6.19.2. List tab for gene expression	329
7.6.19.3. Heatmap for gene expression	331
7.6.19.4. Point diagram for gene expression	331
7.6.19.5. Concentration diagram for gene expression	333
7.7. Reports	335
7.7.1. Manual creation of a new plate report from analysis results	335
7.7.2. Automatic creation of report – Report template	339
7.7.2.1. Skipping items in reports	348
7.7.3. Managing reports of a plate in the report environment	349
7.7.4. Sign report	351
7.7.5. Run details in report	354
7.8. Archive	356

7.8.0.1. Configuring network drive as archive	357
7.8.1. Automatic archiving	357
7.8.2. Manual plate archiving	358
7.8.3. Bulk plate archiving	358
7.8.4. Archive and restore a plate from the archive	359
7.9. Audit trail	360
7.9.1. Audit trail tracker settings	360
7.9.2. Events List	361
7.9.2.1. Events list table	361
7.9.3. Search	362
7.9.3.1. Search for instrument ID, affected plate ID, user login, and role name	362
7.9.4. Filters	362
7.9.4.1. Filter by specific date or specific time frame	362
7.9.4.2. Filter: Category	363
7.9.4.3. Filter: Event type	364
7.9.4.4. Filter: Initiated by	365
7.9.5. Check details	365
7.9.5.1. Tracked differences in detailed audit trail events	366
7.9.5.1.1. Created	366
7.9.5.1.2. Modified	367
7.9.5.1.3. Deleted	368
7.9.6. AT part of plate	368
7.9.7. Exporting to PDF	370
7.10. General software use	371
7.10.1. Entering data	371
7.10.2. Displaying errors, warnings, and additional information	371
7.10.3. System error	371
7.10.4. Warning message	371
7.10.5. Information message	372
7.11. QIAcuity Lab Automation Service	373
8. Maintenance Procedures	374
8.1. Cleaning agents	374
8.1.0.1. General cleaning of the QIAcuity	374
8.1.1. Disinfection	374
8.1.1.1. Removal of RNase contamination	375
8.1.1.2. Removal of nucleic acid contamination	375
8.1.1.3. General instructions	375
8.2. Servicing	376
8.3. Regular maintenance procedure of QIAcuity	376
8.4. Periodic maintenance	377
8.4.1. Air filter change	377
8.4.2. Calibration of thermal cycler	378
8.5. Decontaminating the QIAcuity	378
8.6. Regular maintenance procedure for QIAcuity instrument software	378
8.6.1. Deleting temporary data	378
8.7. Regular maintenance procedure for QIAcuity Software Suite	380
9. Troubleshooting	381
9.1. General information	381
9.2. Contacting QIAGEN Technical Service	381
9.3. Performing a system testing on the QIAcuity instrument	381
9.4. Creating a support package with the QIAcuity instrument software	383
9.4.1. Problem starting the QIAcuity instrument software	386
9.5. Software support package	386

9.5.1. Problem with starting the Software Suite	387
9.5.2. Problem at logging screen	388
9.5.3. Problem during the Software Suite runtime	389
9.6. Creating a support package with the QIAcuity Software Suite	389
9.7. Troubleshooting the instrument and software	390
9.8. Accessing the system status and clearing errors	392
10. Technical Specifications	394
10.1. Operating conditions	394
10.2. Transport conditions	394
10.3. Storage conditions	394
10.4. Mechanical data and hardware features	394
11. Glossary	396
Appendix A – Legal	397
Declaration of conformity	397
Waste Electrical and Electronic Equipment (WEEE)	397
California Proposition 65	397
Liability Clause	398
Declaration list of China RoHS (SJT 11364-2014)	398
Appendix B – QIAcuity Accessories	400
Ordering information	400
Appendix C – User Management Permissions	404
Appendix D – Archive QIAcuity Plates to a Network Drive	407
Document Revision History	408

1. Introduction

Thank you for choosing QIAcuity. We are confident it will become an integral part of your laboratory. Before using QIAcuity, it is essential that you read this user manual carefully and pay attention to the safety information. The instructions and safety information in the user manual must be followed to ensure safe operation of the instrument and to maintain the instrument in a safe condition.

1.1. About this user manual

This user manual provides information about QIAcuity in the following sections:

- Introduction
- Safety Information
- General Description
- Installation Procedures
- Operating Plates
- Operating the QIAcuity Instrument
- Operating the QIAcuity Software Suite
- Maintenance Procedures
- Troubleshooting
- Technical Specifications
- Appendix A – Legal
- Appendix B – QIAcuity Accessories
- Appendix C – User Management Permissions
- Appendix D – Archive QIAcuity Plates to a Network Drive
- Document Revision History

1.2. General information

1.2.1. Technical assistance

At QIAGEN®, we pride ourselves on the quality and availability of our technical support. QIAGEN Technical Service Departments are staffed by experienced scientists with extensive practical and theoretical expertise in molecular biology and the use of QIAGEN products. If you have any questions or experience any difficulties regarding the QIAcuity or QIAGEN products in general, do not hesitate to contact us.

QIAGEN customers are a major source of information regarding advanced or specialized uses of our products. This information is helpful to other scientists as well as to the researchers at QIAGEN. We therefore encourage you to contact us if you have any suggestions about product performance or new applications and techniques.

For technical assistance and more information, see QIAGEN Technical Support at support.qiagen.com or call one of the QIAGEN Technical Service Departments or local distributors (visit www.qiagen.com).

1.2.2. Policy statement

It is QIAGEN's policy to improve products as new techniques and components become available. QIAGEN reserves the right to change specifications at any time.

To produce useful and appropriate documentation, we appreciate your comments about this user manual. Contact QIAGEN Technical Service.

1.3. Intended use of the QIAcuity

QIAcuity systems are designed to determine absolute amounts of target DNA in a sample by using a digital PCR (dPCR) approach.

Digital PCR uses the procedure of end-point PCR but splits the PCR reaction into many single partitions in which the template is randomly distributed across all available partitions. After PCR, the target molecule is detected by measuring the fluorescence – either of sequence-specific DNA probes or of intercalating dyes – in all valid partitions. As the template is distributed randomly, Poisson statistics can be used to calculate the amount of target DNA per valid partition. The total amount of target DNA in all partitions of a well is then calculated by multiplying the amount of target DNA per partition with the number of valid partitions. Calculation of target concentration is determined by referring back to the volume in all analyzable partitions, that is, partitions that were filled with reaction mix. The total number of filled partitions is identified by a fluorescent dye, present in the reaction mix itself. Absolute quantification by dPCR eliminates the need of standard curves to determine amounts of target DNA in a given sample.

Aside from absolute quantification, the QIAcuity software provides analysis modules for mutation detection, genome editing analysis, copy number variation (CNV), and gene expression analysis.

QIAcuity systems are intended to be used only in combination with QIAGEN kits indicated for use with the QIAcuity systems for the applications described in the kit handbooks, such as QIAcuity Nanoplates and QIAcuity PCR Reagents.

If QIAcuity is used with products other than QIAGEN kits or QIAGEN assays designed for dPCR, it is the user's responsibility to validate the performance of such product combinations for any particular application.

The QIAcuity system is intended for use by professional users trained in molecular biological techniques and the operation of the QIAcuity system.

The QIAcuity system is intended for research use only (RUO) applications. This product is not intended for the diagnosis, prevention, or treatment of a disease.

QIAcuity software version 3.5 is a long-term support (LTS) release, for which QIAGEN provides a 7 year support period including regular security risk assessments and comprehensive troubleshooting support.

1.4. Requirements for QIAcuity users

This table covers the general level of competence and training necessary for transportation, installation, use, maintenance, and servicing of the QIAcuity systems.

Table 1. Requirements for QIAcuity users

Task	Personnel	Training and experience
Delivery	No special requirements	No special requirements
Installation	Laboratory technicians or equivalent	Appropriately trained or experienced personnel familiar with the use of computers and automation in general
Routine use (running protocols)	Laboratory technicians or equivalent	Appropriately trained or experienced personnel familiar with the use of computers and automation in general
Assay design and validation	Scientist or equivalent	Appropriately trained or experienced personnel familiar with molecular biological techniques
Dust filter replacement	Laboratory technicians or equivalent	Appropriately trained or experienced personnel familiar with the use of computers and automation in general
Preventive maintenance	QIAGEN service personnel or service technicians of an authorized agent	Trained and authorized by QIAGEN
Servicing	QIAGEN service personnel or service technicians of an authorized agent	Trained and authorized by QIAGEN

2. Safety Information

Before using the QIAcuity, it is essential that you read this user manual carefully and pay attention to the safety information. The instructions and safety information in the user manual must be followed to ensure safe operation of the instrument and to maintain the instrument in a safe condition.

The following types of safety information appear in this manual.

WARNING



The term **WARNING** is used to inform you about situations that could result in **personal injury** to you or other persons.

Details about these circumstances are given in a box like this one.

CAUTION



The term **CAUTION** is used to inform you about situations that could result in **damage to an instrument** or other equipment.

Details about these circumstances are given in a box like this one.

The advice given in this manual is intended to supplement, not supersede, the normal safety requirements prevailing in the user's country.

2.1. Proper use

WARNING/ CAUTION



Risk of personal injury and material damage

Improper use of the QIAcuity may cause personal injuries or damage to the instrument. The QIAcuity must only be operated by qualified personnel who have been appropriately trained. Servicing of the QIAcuity must only be performed by a QIAGEN Field Service Specialist.

Perform the maintenance as described in Section 8 Maintenance Procedures. QIAGEN charges for repairs that are required due to incorrect maintenance.

WARNING



Risk of personal injury and material damage

The QIAcuity is too heavy to be lifted by one person. To avoid personal injury or damage to the instrument, do not lift the instrument alone. The bottom plane shall be used for lifting. Do not lift at the touchscreen.

WARNING



Risk of personal injury and material damage

Do not attempt to move the QIAcuity during operation.

CAUTION



Damage to the instrument

Avoid spilling water or chemicals onto the QIAcuity. Damage caused by water or chemical spillage voids your warranty.

In case of emergency, power off the QIAcuity at the power switch located in the back of the instrument and unplug the power cord from the power outlet.

CAUTION



Damage to the instrument

Only use QIAcuity-specific consumables with QIAcuity. Do not use the plates without applied top seals. Damage caused by use of other consumables will void your warranty.

CAUTION



Damage to the instrument

Do not drop objects into the instrument when the plate tray is ejected.

WARNING



Risk of explosion

The QIAcuity is intended for use with reagents and substances supplied with QIAGEN kits or others that are outlined in respective Information for Use. Use of other reagents and substances may lead to fire or explosion.

CAUTION



Damage to the instrument

Do not stack instruments and do not place items on top of the QIAcuity.

CAUTION



Damage to the instrument

Do not lean against the touchscreen when it is pulled out.

2.2. Electrical safety

Note: Disconnect the line power cord from the power outlet before servicing.

WARNING



Electrical hazard

Any interruption of the protective conductor (earth/ground lead) inside or outside the instrument or disconnection of the protective conductor terminal is likely to make the instrument dangerous.

Intentional interruption is prohibited.

Lethal voltages inside the instrument

When the instrument is connected to line power, terminals may be live and opening covers or removing parts is likely to expose live parts.

WARNING



Damage to electronics

Before powering on the instrument, make sure that the correct supply voltage is used.

Use of incorrect supply voltage may damage the electronics.

To check the recommended supply voltage, refer to the specifications indicated in the type plate of the instrument.

WARNING**Risk of electric shock**

Do not open any panels on QIAcuity.

Risk of personal injury and material damage

Only perform maintenance that is specifically described in this user manual. Any other maintenance or repair may only be carried out by an authorized Field Service Specialist.

To ensure satisfactory and safe operation of the QIAcuity, follow these guidelines:

- The line power cord must be connected to a line power outlet that has a protective conductor (earth/ground).
- Do not adjust or replace the internal parts of the instrument.
- Do not operate the instrument with any covers or parts removed.
- If liquid has spilled inside the instrument, power off the instrument, disconnect it from the power outlet, and contact QIAGEN Technical Service.

If the instrument becomes electrically unsafe, prevent other personnel from operating it, and contact QIAGEN Technical Service.

The instrument may be electrically unsafe when:

- It or the line power cord appears to be damaged.
- It has been stored under unfavorable conditions for a prolonged period.
- It has been subjected to severe transport stress.
- Liquids come in contact directly with electrical components of the QIAcuity.

2.3. Environment

2.3.1. Operating conditions

WARNING**Explosive atmosphere**

QIAcuity is not designed for use in an explosive atmosphere.

CAUTION**Damage to the instrument**

Direct sunlight may bleach parts of the instrument and cause damage to plastic parts. The QIAcuity must be located out of direct sunlight.

CAUTION**Risk of overheating**

To ensure proper ventilation, maintain a minimum clearance of 10 cm at the sides and rear of the QIAcuity.

Slits and openings that ensure the ventilation of the QIAcuity must not be covered.

2.4. Biological safety

Specimens and reagents containing materials from humans should be treated as potentially infectious. Use safe laboratory procedures as outlined in publications such as Biosafety in Microbiological and Biomedical Laboratories, HHS (www.cdc.gov/labs/bmbl).

2.4.1. Samples

Samples may contain infectious agents. You should be aware of the health hazard presented by such agents and should use, store, and dispose of such samples according to the required safety regulations.

WARNING



Samples containing infectious agents

Some samples used with QIAcuity may contain infectious agents. Handle such samples with the greatest of care and in accordance with the required safety regulations.

Always wear safety glasses, gloves, and a lab coat.

The responsible body (e.g., a laboratory manager) must take the necessary precautions to ensure that the surrounding workplace is safe, and that the instrument operators are suitably trained and not exposed to hazardous levels of infectious agents as defined in the applicable Safety Data Sheets (SDSs) or the OSHA,* ACGIH,[†] or COSHH[‡] documents.

Venting for fumes and disposal of waste must be in accordance with all national, state, and local health and safety regulations and laws.

* OSHA — Occupational Safety and Health Organization (United States of America)

[†] ACGIH — American Conference of Government Industrial Hygienists (United States of America)

[‡] COSHH — Control of Substances Hazardous to Health (United Kingdom)

2.5. Chemicals

WARNING



Hazardous chemicals

Some chemicals used with QIAcuity may be hazardous or may become hazardous after completion of purification.

Always wear safety glasses, gloves, and a lab coat.

The responsible body (e.g., a laboratory manager) must take the necessary precautions to ensure that the surrounding workplace is safe, and that the instrument operators are suitably trained and not exposed to hazardous levels of infectious agents as defined in the applicable Safety Data Sheets (SDSs) or the OSHA,* ACGIH,[†] or COSHH[‡] documents.

Venting for fumes and disposal of waste must be in accordance with all national, state, and local health and safety regulations and laws.

* OSHA — Occupational Safety and Health Organization (United States of America)

[†] ACGIH — American Conference of Government Industrial Hygienists (United States of America)

[‡] COSHH — Control of Substances Hazardous to Health (United Kingdom)

2.6. Maintenance safety

WARNING/ CAUTION



Risk of personal injury and material damage

Only perform maintenance that is specifically described in this user manual.

WARNING



Risk of fire

Do not allow cleaning fluid or decontamination agents to come into contact with the electrical parts of the QIAcuity.

CAUTION



Damage to the instrument

Do not use bleach, solvents, or reagents containing acids, alkalis, or abrasives to clean the QIAcuity.

CAUTION



Damage to the instrument

Do not use spray bottles containing alcohol or disinfectants to clean surfaces of the QIAcuity.

2.7. Radiation safety

WARNING



Risk of personal injury

Hazard Level 2 laser light: Do not stare into the light beam when using handheld barcode scanner.

2.8. Symbols on the QIAcuity

Symbol	Location	Description
	Type plate on the back of the instrument	CE mark for European Conformity
	Type plate on the back of the instrument	UKCA mark for UK Conformity
	Type plate at the back of the instrument	CSA listing mark for Canada and the USA
	Type plate on the back of the instrument	RCM mark for Australia and New Zealand
	Type plate on the back of the instrument	RoHS mark for China (the restriction of the use of certain hazardous substances in electrical and electronic equipment)
	Type plate on the back of the instrument	Waste Electrical and Electronic Equipment (WEEE) mark for Europe
	Type plate on the back of the instrument	Legal manufacturer
	Type plate on the back of the instrument	Consult instructions for use
	Type plate on the back of the instrument	See Section 2 Safety Information for risks
	Type plate on the back of the instrument	Date of manufacture
	On the drawer	Biological hazard – some samples used with this instrument may contain infectious agents and must be handled with gloves.

3. General Description

After manually loading and sealing the QIAcuity Nanoplate, the QIAcuity performs a fully automated processing of the QIAcuity Nanoplates, including all necessary steps of plate priming, sealing of partitions, thermocycling, and image analysis. Depending on the plate type, up to 8, 24, or 96 samples per plate can be analyzed. For high sensitivity applications, the QIAcuity Nanoplate 26K 8- or 24-well is available. The number of in-parallel processable plates depends on the instrument configuration (One, Four, Eight). The QIAcuity controls all integrated modules, including a robotic gripper for plate handling, a partitioning module, a PCR thermocycler, and a fluorescence imaging module.


Setting up experiments and the analysis of results is done in the stand-alone QIAcuity Software Suite. The Software Suite and instrument software are able to communicate with each other over a direct connection or a network connection. Setting up an experiment is possible with the QIAcuity Software Suite as well as the instrument.

3.1. QIAcuity principle


The QIAcuity is designed as a walk-away instrument that integrates and automates all plate processing steps. Only plate preparation must be done manually before starting the run. This includes the pipetting of the target reagents and master mix in the input wells of the plate and the closing of the wells with the top seal. Once this preparation is complete, the plate is placed in a free plate slot of the instrument tray. By reading the barcode of the plate, the instrument links the plate to the experiment previously defined in the software, and after pressing the **Play** button, all further steps are performed fully automated by the instrument.

The following process steps are done sequentially:

Partitioning: In the first module, the microchannels and partitions of the plate are filled with the target reagents and master mix previously pipetted into the wells. This is done by plunging the pins against the elastic top seal and the input wells, which creates a peristaltic pressure that pumps the input well liquid into the microchannels and partitions. The connecting channels between the partitions are closed simultaneously by a pressure-controlled rolling process (see the following images).




Scheme of filling and partitioning of a well.



Principle of priming and rolling to allow partitioning of the wells.

Thermocycling: In the second step, the module is a high-accuracy plate thermocycler that performs the polymerase chain reaction. The cycling profile can be set in the QIAcuity Software Suite or the instrument software. For more details on the thermal cycler specification, see Section 10 Technical Specifications.

Imaging: The final process step is the image acquisition of all wells. The user can select the detection channels in the experiment setup. The partitions that contain a target molecule inside emit fluorescence and are brighter than the ones without a target molecule (see the following images). For more details and specifications on the imaging system, see Section 10 Technical Specifications.



Scheme of positive (green) and negative (blue) partitions after imaging.

3.2. External features of QIAcuity

3.2.1. Touchscreen

The QIAcuity is controlled using a swivel-mounted touchscreen. To adjust the angle of the touchscreen, pull gently at the bottom edge. The touchscreen enables the user to see an overview of all plate slots and the corresponding process steps and remaining times. Additionally, it can be used to extend the plate tray, start/stop plate runs, set up experiments, etc. For all functions and instructions of the instrument software, see Section 5 Operating Plates.



Pulled out touchscreen.

3.2.1.1. Power switch

The main power switch is located at the back of the QIAcuity. To power on the QIAcuity, turn the power switch to **I** and press the blue soft-switch button at the front of the instrument. The startup screen appears, and the instrument automatically performs initialization tests.

To conserve energy, the QIAcuity can be powered off when not in use. To power off the QIAcuity, press the blue front soft-switch button.

Important: After powering off the QIAcuity, wait for a few seconds before switching **ON** the instrument again. The system might fail to start if you do not allow the QIAcuity to rest for a few seconds before powering on.

3.2.1.2. RJ-45 ethernet port

The RJ-45 ethernet port is located at the back of the instrument beside the power cord socket. It is used to connect the QIAcuity to a local area network via cable or to connect directly to the Software Suite computer, depending on the network configuration chosen.

3.2.1.3. USB ports

The QIAcuity has two USB ports that are located at the front of the instrument in the upper left corner. For the QIAcuity Four and Eight, a third slot for accessories is available behind the touchscreen in the upper right corner. To access this slot, extend the touchscreen as far as possible.

The USB ports allow a connection of the QIAcuity to a USB stick. Data files, such as support packages, can be transferred via the USB port from the QIAcuity to the USB stick. The USB ports can also be used to plug in an external barcode reader or a keyboard.

Important: We recommend using QIAGEN USB sticks only to ensure full compatibility. If QIAGEN USB stick is not available, use an FAT32- or exFAT-formatted USB stick.

Important: Do not remove the USB stick while downloading or transferring data or software to or from the instrument.

3.2.1.4. Power cord socket

The power cord socket is located at the rear right of the QIAcuity and allows connection of the QIAcuity to a power outlet via the supplied power cord.

WARNING



Electrical hazard

Any interruption of the protective conductor (earth/ground lead) inside or outside the instrument or disconnection of the protective conductor terminal is likely to make the instrument dangerous.

Intentional interruption is prohibited.

Lethal voltages inside the instrument

When the instrument is connected to line power, terminals may be live and opening covers or removing parts is likely to expose live parts.

WARNING



Damage to electronics

Before powering on the instrument, make sure that the correct supply voltage is used.

Use of incorrect supply voltage may damage the electronics.

To check the recommended supply voltage, refer to the specifications indicated in the type plate of the instrument.

WARNING



Risk of electric shock

Do not open any panels on QIAcuity.

Risk of personal injury and material damage

Only perform maintenance that is specifically described in this user manual. Any other maintenance or repair may only be carried out by an authorized Field Service Specialist.

3.2.1.5. Cooling air outlet


Cooling air outlets are located at the rear side of the QIAcuity and allow cooling of the internal components of QIAcuity.

CAUTION

Risk of overheating



To ensure proper ventilation, maintain a minimum clearance of 10 cm at the sides and rear of the QIAcuity. Slits and openings that ensure the ventilation of the QIAcuity must not be covered.



Back view of the QIAcuity Four and Eight.

3.2.1.6. External hand scanner

The QIAcuity Four and Eight instruments are equipped with a barcode scanner, which enables the user to scan the plate ID before loading. For QIAcuity One, a barcode scanner is available as accessory.

WARNING

Risk of personal injury



Hazard Level 2 laser light: Do not stare into the light beam when using handheld barcode scanner.

3.3. Thermal cycler


The thermal cycler of the QIAcuity is a plate thermocycler that features high speed and precision temperature control of the temperature cycling steps. Several Peltier elements are used for the temperature generation and control. For an optimal thermal contact between plate and thermal cycler, the plate is clamped on the heating surface during cycling. The QIAcuity Eight features two thermal cyclers that are operated in parallel.

The thermal cycler has the following specifications:

Process temperature:	35–99°C
Ramp rate:	approx. 3.0°C/s
Accuracy:	±1°C
Homogeneity:	±1°C

3.4. Optical system

The optical system of QIAcuity is a camera-based fluorescence microscopy system. The excitation source for the fluorescence dyes is a high-power white LED. This source in combination with a specific excitation filter is used to illuminate a whole well at a time. The fluorophores in the single partitions absorb that light and emit light that is being filtered by a detection filter, and collected and imaged through an objective lens on a CMOS-camera chip (see image below for a detailed overview of the components). The QIAcuity Software version 3.0 supports dPCR assays up to 8 plex by using six optical channels for six standard dyes, and the additional use of two hybrid channels for LSS (Long Stokes Shift) dyes, which can be selected from five different hybrid channels. As of QIAcuity Software version 3.1, the amplitude multiplexing option is available, enabling duplex assays using two amplicons in one channel (see Section 7.6.11 Amplitude multiplexing) supporting dPCR assays up to 12 plex. The QIAcuity One 2 plex offers only two detection channels. In addition to the target detection, channels are also used to detect the base fluorescence of the master mix, to determine the exact number of filled partitions and normalization of fluorescence data.



Scheme of the imaging module.

3.4.1. Available channels

Table 2. Available channels in QIAcuity

Channel	Excitation (nm)	Emission (nm)	Example fluorophores
Green	463–503	519–549	FAM™, EvaGreen®
Yellow	513–534	551–565	HEX™, VIC®
Orange	541–563	582–608	TAMRA™, Atto 550
Red	568–594	613–655	ROX™, Texas Red®
Crimson	588–638	656–694	Cy5®, Quasar 680
Far red	651–690	709–759	Cy5.5. Atto 680, Atto 700
Green / Yellow	463–503	551–565	DY-482XL (LSS G/Y)*
Orange / Red	541–563	613–655	DY-540XL (LSS O/R)*

* For Long Stokes Shift (LSS) dyes, the software provides generic dye names called “LSS” followed by the abbreviation of the used channel combination denoted by the first channel letters. For example, channel combination Green/Yellow is abbreviated as “LSS G/Y”.

4. Installation Procedures

This section provides instructions on unpacking, packing, and installing the QIAcuity.

The installation procedure of the product is recommended to be carried out by a certified QIAGEN Field Service Specialist. A person who is familiar with the laboratory and computer equipment should be present during the installation.

4.0.1. Site requirements

The QIAcuity must be located away from direct sunlight, away from heat sources, and away from sources of vibration and excessive electrical interference. Placing a QIAgility® instrument or an orbital shaker next to the instrument does not exceed this value. Refer to Section 10 Technical Specifications for the operating conditions (temperature and humidity). Be aware that ambient temperatures of below 17°C (63°F) require an equilibration phase of approximately 30–60 min at the location where the instrument will be used before the instrument is powered on. The site of installation should be free of excessive drafts, excessive moisture, and excessive dust, and should not be subject to large temperature fluctuations.

Use a level workbench that is large enough and strong enough to accommodate the QIAcuity. Refer to Section 10 Technical Specifications for the weight and dimensions of the QIAcuity. Allow at least 10 cm (5.9 in.) of free space behind and on the sides of the instrument for cooling and cabling.

Ensure that the workbench is dry, clean, and vibration-proof, and has additional space for accessories.

The QIAcuity must be placed within approximately 1.5 m of a properly grounded (earthed) AC power outlet. The power line to the instrument should be voltage regulated and surge protected. Ensure that the QIAcuity is positioned where it is easy to access the power connector and the power switch at the back of the instrument at all times and that it is easy to power the instrument off and disconnect it.

Note: We recommend plugging the instrument directly into its own power outlet and not to share the power outlet with other laboratory equipment. Do not place the QIAcuity on a vibrating surface or near vibrating objects.

WARNING



Explosive atmosphere

QIAcuity is not designed for use in an explosive atmosphere.

CAUTION



Risk of overheating

To ensure proper ventilation, maintain a minimum clearance of 10 cm at the sides and rear of the QIAcuity.

Slits and openings that ensure the ventilation of the QIAcuity must not be covered.

WARNING



Risk of personal injury and material damage

The QIAcuity is too heavy to be lifted by one person. To avoid personal injury or damage to the instrument, do not lift the instrument alone. The bottom plane shall be used for lifting. Do not lift at the touchscreen.

CAUTION



Damage to the instrument

Direct sunlight may bleach parts of the instrument and cause damage to plastic parts. The QIAcuity must be located out of direct sunlight.

4.0.2. Power requirements

The QIAcuity operates at 100–240 V AC, 50/60 Hz, 1500 VA (max.).

Ensure that the voltage rating of the QIAcuity is compatible with the AC voltage available at the installation site. Main supply voltage fluctuations should not exceed 10% of nominal supply voltages.

WARNING



Damage to electronics

Before powering on the instrument, make sure that the correct supply voltage is used.

Use of incorrect supply voltage may damage the electronics.

To check the recommended supply voltage, refer to the specifications indicated in the type plate of the instrument.

WARNING



Electrical hazard

Any interruption of the protective conductor (earth/ground lead) inside or outside the instrument or disconnection of the protective conductor terminal is likely to make the instrument dangerous.

Intentional interruption is prohibited.

Lethal voltages inside the instrument

When the instrument is connected to line power, terminals may be live and opening covers or removing parts is likely to expose live parts.

4.0.3. Grounding requirements

To protect operating personnel, the National Electrical Manufacturers' Association (NEMA) recommends that the QIAcuity be correctly grounded (earthed). The instrument is equipped with a three-conductor AC power cord that, when connected to an appropriate AC power outlet, grounds (earths) the instrument. To preserve this protection feature, do not operate the instrument from an AC power outlet that has no ground (earth) connection.

WARNING



Electrical hazard

Any interruption of the protective conductor (earth/ground lead) inside or outside the instrument or disconnection of the protective conductor terminal is likely to make the instrument dangerous.

Intentional interruption is prohibited.

Lethal voltages inside the instrument

When the instrument is connected to line power, terminals may be live and opening covers or removing parts is likely to expose live parts.

4.1. Installation of AC power cord

The AC power cord connects to the socket located at the rear of the QIAcuity, and the other end to the AC power outlet.

4.2. Unpacking the QIAcuity

WARNING



Risk of personal injury and material damage

The QIAcuity is too heavy to be lifted by one person. To avoid personal injury or damage to the instrument, do not lift the instrument alone. The bottom plane shall be used for lifting. Do not lift at the touchscreen.

Note: Before unpacking the QIAcuity, move the package to the installation site and check that the arrows on the package point upward. In addition, check whether the package is damaged. In case of damage, stop here and contact QIAGEN Technical Service.

1. Cut the straps securing the packaging into the shipping pallet.
2. Open the top of the transportation box to remove the accessories set before lifting the box.
3. Remove the top and side protective black foam.
4. After the QIAcuity has been unpacked, a minimum of two people must lift the instrument. Lift the instrument by sliding your hands under both sides of the workstation and keeping your back straight.
5. **Important:** Do not hold the touchscreen display while unpacking or lifting the QIAcuity as it might damage the instrument.
6. Check if the packing list document is included after unpacking the QIAcuity.
7. Read the packing list to check that you have received all items. If anything is missing, contact QIAGEN Technical Service.
8. Check that the QIAcuity is not damaged and that there are no loose parts. If anything is damaged, contact QIAGEN Technical Service. Make sure that the QIAcuity has equilibrated to ambient temperature before operating it.
9. Retain the package in case you need to transport the QIAcuity in the future. Refer to Section 4.3 Packing the QIAcuity for more details. Using the original package minimizes the possibility of damage during transportation of the QIAcuity.

4.3. Packing the QIAcuity

WARNING



Risk of personal injury and material damage

The QIAcuity is too heavy to be lifted by one person. To avoid personal injury or damage to the instrument, do not lift the instrument alone. The bottom plane shall be used for lifting. Do not lift at the touchscreen.

Note: Before transporting the QIAcuity, the instrument must first be decontaminated. Refer to Section 8 Maintenance Procedures for more details. Then, prepare the instrument as follows:

1. Turn off the instrument and unplug the power cord.
2. Re-install the shipping fixation screw.
3. Prepare the packing material. Materials required are the cardboard carton, the pallet with foam blocks, and the foam lid.
4. Place the QIAcuity onto the pallet and put the black foam lid over the top of the instrument. Place the box onto the instrument.

Important: When lifting the QIAcuity, slide your hands under both sides of the instrument and keep your back straight.

Important: Do not hold the touchscreen display while lifting the QIAcuity, as this might damage the instrument.

WARNING **Risk of personal injury and material damage**



The QIAcuity is too heavy to be lifted by one person. To avoid personal injury or damage to the instrument, do not lift the instrument alone. The bottom plane shall be used for lifting. Do not lift at the touchscreen.

Place the accessories into the black foam lid.

Important: The power cord must be packed in an air cushion bags.

5. Seal the outside edges of the carton with tape to protect against moisture.

Note: Using the original package minimizes potential damage during transportation of the QIAcuity.

4.4. Installing the QIAcuity

This section describes important actions that must be performed before operating the QIAcuity. These actions include:

- Removal of the protective film from the QIAcuity touchscreen
- Removal of the shipping fixation screw
- Connection of the power cord to the back of the QIAcuity
- Powering on the QIAcuity
- Removal of protective foam block of the drawer

4.4.1. Removing the protective film from the QIAcuity touchscreen

Carefully peel off the protective film from the QIAcuity touchscreen.

4.4.2. Removing the shipping fixation screw

Access the back of the instrument and remove the shipping fixation screw using a 4 mm hex wrench. Store the fixation screw in a safe place in case it is needed at a later time. The hole in the housing for the fixation screw shall be closed with the dust cap that is provided with the accessories of the instrument (cat. no. 9026772).



Back of QIAcuity.

4.4.3. Connecting the power cord to the back of the QIAcuity

1. Remove the power cord from the foam packing material on top of the QIAcuity.

Note: Only use the power cord that is supplied with the QIAcuity.

2. Check that the voltage rating on the label found at the back of the QIAcuity matches the voltage available at the installation site.
3. Connect the power cord to the power inlet of the instrument and connect the cable to the wall power outlet.
4. Turn on the power switch at the back of the instrument.

WARNING

Damage to electronics



Before powering on the instrument, make sure that the correct supply voltage is used.

Use of incorrect supply voltage may damage the electronics.

To check the recommended supply voltage, refer to the specifications indicated in the type plate of the instrument.

WARNING

Electrical hazard



Any interruption of the protective conductor (earth/ground lead) inside or outside the instrument or disconnection of the protective conductor terminal is likely to make the instrument dangerous.

Intentional interruption is prohibited.

Lethal voltages inside the instrument

When the instrument is connected to line power, terminals may be live and opening covers or removing parts is likely to expose live parts.

4.4.4. Powering on the QIAcuity

Check that the QIAcuity operates properly:

1. Ensure that the drawer of the QIAcuity is closed.
2. Power on the QIAcuity using the blue front power switch.
3. The startup screen appears. The instrument automatically performs initialization tests.

Note: The main power switch in the back must be switched on for the front power switch to work.

Note: If ambient temperature is below 17°C (63°F), an equilibration phase of 30–60 min might be required. After the equilibration phase, the error can be cleared and the instrument is operational after restart.

4. If there is an initialization error, retry the initialization process by turning the instrument off and on again using the front power switch. If the problem persists, see Section 9.7 Troubleshooting the instrument and software or contact QIAGEN Technical Service.

Note: The instrument must be turned off at least once a week using the front power switch.

4.4.5. Removal of protective foam block of the drawer

Open the drawer of the QIAcuity instrument by pressing the physical button on the instrument or tapping **Eject Tray** on the instrument, and remove the protective foam. For QIAcuity Eight instrument, remove the foam of both drawers.

4.4.6. Installing a fresh copy of the QIAcuity Software Suite

Visit www.qiagen.com and go to the **Operating Software** section of the QIAcuity product page to check if an updated software version is available for download.

The QIAcuity Software Suite is designed to work with Windows® 11 operating systems. The following browsers were tested in the QIAcuity Software Suite:

- Mozilla® Firefox®: version 149.0.2*
- Microsoft Edge®: version 146.0.3856.109*
- Google Chrome®: version 147.0.7727.56*

The QIAcuity Four and QIAcuity Eight instruments are supplied with a notebook; the QIAcuity One instrument is optionally supplied with a notebook. See the following table for the recommended notebook requirements.

Table 3. Recommended notebook requirements

Description	Recommended requirement
Operating system	Microsoft® Windows 11 Professional Edition 64-bit version
Processor	x64 compatible processor with 4 physical cores and 2.5 GHz
Main memory	16 GB RAM
Hard disk	SSD at least 500 GB, minimal speed: 500 MB/s
Graphics interface	At least 1920 x 1080 pixels

*Patch versions of the browsers are released very frequently that mainly contain bug fixes; therefore, any of patch versions are compatible with the QIAcuity Software Suite.

Compatibility of Windows 11 security updates and browser updates are being monitored with the QIAcuity Software Suite application on a regular basis. These updates have not led to failures of the Software Suite Application Service; therefore, upgrading the Windows operating system to the latest available build version from Microsoft is recommended. We will continue to monitor security updates and will inform of any issue we might see in the future.

The firewall settings are handled by the Software Suite installer to ensure the proper function of the software. It is recommended to not change any firewall settings after Software Suite installation.

The QIAcuity Software Suite was tested with enabled Microsoft Windows Defender Antivirus.

The **QIAcuitySoftwareSuite.exe** package needed for the installation of the QIAcuity Software Suite is available for download from www.qiagen.com/QIAcuity.

Before starting the installation process and after an update of the Windows operating system using the QIAcuity Setup Wizard, note the following important setup information:

1. Ensure that the system data and time of the laptop to be used are up to date.
2. Turn off the standby/hibernation settings in the Windows 11 configuration.
 - a. Right-click **Windows start menu**, and select **Settings**.
 - b. Click **System**, and select **Power & battery**.
 - c. Open **Screen, sleep & hibernate timeouts**.
 - d. Set the relevant "Make my device sleep after" options to **Never**.
 - e. If available, set the relevant "Hibernate after" options to **Never** as well.
 - f. If additional power options are required, open **Control Panel > Power Options > Change plan settings > Change advanced power settings**, and expand **Sleep**.
 - g. Set "Allow hybrid sleep" to **Off** if this option is visible.
 - h. Click **Apply**, and then click **OK**.
 - i. Attach the computer via cable to the local network or connect it to the QIAcuity directly, depending on your preferred setup.

Important: If choosing a direct setup, it is recommended to set the Network adapter settings described in Section 4.8 Establishing a connection between the QIAcuity instrument and the QIAcuity Software Suite before continuing with Software Suite installation.


Note: Do not use any USB network adapter in addition to the ethernet cable connected to the instrument or to the laptop.

Note the following before installing QIAcuity Software Suite:


- QIAcuity Software Suite can be installed as a stand-alone application without a network or direct connection to the instruments. After successful installation of the Software Suite, the software can be used without an Ethernet connection.
- Copy the Software Suite installer from the USB stick to the hard drive prior to launching the Software Suite installer. Do not launch the installer directly from the USB stick.

To install the QIAcuity Software Suite on the notebook, follow the steps below. The installation of the QIAcuity Software Suite is performed by a Windows administrator user.

1. Locate the **QIAcuitySoftwareSuite.exe** file on the hard drive and double-click it. The installation process starts.
2. Read the license terms and conditions. These need to be agreed to by checking the box in the End-User License Agreement window and clicking **Install**.




3. When the installation is completed, click **Close**.




4. In the local host site that says the site is not secure, click **Advanced** and then **Continue to localhost (unsafe)**.

Note: If the local host is not accessible after the software installation, wait for 2–3 min and open it again.



5. Click **Continue** to local host on to the webpage.

You are directed to the QIAcuity Software Suite login screen.



4.5. Upgrading the QIAcuity Software Suite to a newer version

Note the following important information, which is valid for all Software Suite version upgrades:

1. Before upgrading the QIAcuity Software Suite, ensure that no run activity is in progress.
2. The upgrade of the QIAcuity Software Suite should be performed by a Windows administrator user.
3. It is strongly recommended to upgrade the Software Suite before proceeding with the Control Software upgrade.
4. Upgrading to the QIAcuity Software Suite version 3.5 should be performed without uninstallation of the previously installed QIAcuity Software Suite version.
5. Before upgrading the QIAcuity Software Suite, make sure that the system date and time of the laptop to be used are up to date. Be sure to set the Time Zone in Windows first, and then adjust the date and time, if needed. If an adjustment is required, restart the QIAcuity Software Suite application followed by the Control Software before proceeding with the software upgrade.

The latest QIAcuity Software Suite version 3.5 is only compatible with the QIAcuity Control Software version 3.5. If only one software component is upgraded, no connection between the Software Suite and the Control Software can be established.

In terms of existing plates upgrade, refer to Section 7.6.2 Plates after QIAcuity Software Suite version upgrade.


The following two direct upgrade scenarios are supported:

- From version 3.2 to version 3.5
- From version 3.1 to version 3.5

All Software Suite versions older than version 3.1 are not supported for a direct upgrade to version 3.5. Refer to the corresponding sections for upgrade instructions:

- Upgrading QIAcuity Software Suite from versions 3.1–3.2 (direct upgrade)
- Upgrading QIAcuity Software Suite from version 3.0 to version 3.1
- Upgrading QIAcuity Software Suite from version 2.5 to version 3.0
- Upgrading QIAcuity Software Suite from version 2.2 to version 2.5
- Upgrading QIAcuity Software Suite from version 2.0 to version 2.2
- Upgrading QIAcuity Software Suite from version 1.2.18 to version 2.0
- Upgrading QIAcuity Software Suite from version 1.1.3 to version 1.2.18


Note: In case user is trying to upgrade the software directly to version 3.5 and the upgrade scenario is not supported (e.g., from version 1.2.18), user is informed in the following way:



4.5.1. Upgrading QIAcuity Software Suite from versions 3.1–3.2 (direct upgrade)


To upgrade the QIAcuity Software Suite from versions 3.1–3.2, follow the steps below.

1. Locate the **QIAcuitySuite.exe** file on the hard drive and double-click it. The installation process starts.
2. Check the "I accept the terms in the License Agreement" box in the End-User License Agreement window, and click **Install**.




3. In the prompt window asking you if you want to allow changes to your device, click **Yes**.
4. The system then automatically upgrades the existing installation.


5. When the installation is completed, click **Finish**.



6. Note that the computer must be restarted after a successful QIAcuity Software Suite upgrade. You receive the following message:



7. Click **OK**.
8. Then click **Restart**, and the computer restarts.




4.5.2. Upgrading QIAcuity Software Suite from version 3.0 to version 3.1


This section describes the QIAcuity Software Suite upgrade from version 3.0. The Software Suite version 3.0 cannot be upgraded directly to version 3.5 but must be upgraded to version 3.1 first.

To upgrade the QIAcuity Software Suite version 3.0 to 3.1, follow the steps below.


1. Locate the **QIAcuitySuite.exe** file on the hard drive and double-click it. The installation process starts.
2. Check the "I accept the terms in the License Agreement" box in the End-User License Agreement window, and click **Install**.




3. In the prompt window asking you if you want to allow changes to your device, click **Yes**.
4. The system then automatically upgrades the existing installation.
5. When the installation is completed, click **Finish**.



6. Note that the computer must be restarted after a successful QIAcuity Software Suite upgrade. You receive the following message:



7. Click **OK**.
8. Then click **Restart**, and the computer restarts.




4.5.3. Upgrading QIAcuity Software Suite from version 2.5 to version 3.0


This section describes the QIAcuity Software Suite upgrade from version 2.5. The Software Suite version 2.5 cannot be upgraded directly to version 3.5 but must be upgraded to version 3.0 first.

To upgrade the QIAcuity Software Suite version 2.5 to version 3.0, follow the steps below.


1. Locate the **QIAcuitySuite.exe** file on the hard drive and double-click it. The installation process starts. Click **Next**.
2. Check the "I accept the terms in the License Agreement" box in the End-User License Agreement window, and click **Install**.




3. In the prompt window asking you if you want to allow changes to your device, click **Yes**.
4. The system then automatically upgrades the existing installation.
5. When the installation is completed, click **Finish**.



6. Note that because the computer must be restarted after successful Software Suite upgrade. The following message is prompted:



7. Click **OK**.
8. Then click **Restart**, and the computer restarts.




4.5.4. Upgrading QIAcuity Software Suite from version 2.2 to version 2.5


This section describes the QIAcuity Software Suite upgrade from version 2.2. The Software Suite version 2.2 cannot be upgraded directly to version 3.5 but must be upgraded to version 2.5 first.

To upgrade the QIAcuity Software Suite version 2.2 to version 2.5, follow the steps below.


1. Locate the **QIAcuitySuite.exe** file on the hard drive and double-click it. The installation process starts. Click **Next**.
2. Check the "I accept the terms in the License Agreement" box in the End-User License Agreement window, and click **Install**.



3. In the prompt window asking you if you want to allow changes to your device, click **Yes**.
4. The system then automatically upgrades the existing installation.
5. When the installation is completed, click **Finish**.




6. Note that because the computer must be restarted after successful Software Suite upgrade. The following message is prompted:



7. Click **OK**.

8. Then click **Restart**, and the computer restarts.




4.5.5. Upgrading QIAcuity Software Suite from version 2.0 to version 2.2


This section describes the QIAcuity Software Suite upgrade from version 2.0. The Software Suite version 2.0 cannot be upgraded directly to version 3.5 but must be upgraded to version 2.2 first.

To upgrade the QIAcuity Software Suite version 2.0 to version 2.2, follow the steps below.

1. Locate the **QIAcuitySuite.exe** file on the hard drive and double-click it. The installation process starts. Click **Next**.
2. Check the "I accept the terms in the License Agreement" box in the End-User License Agreement window, and click **Install**.



3. In the prompt window asking you if you want to allow changes to your device, click **Yes**.
4. The system then automatically upgrades the existing installation.
5. When the installation is completed, click **Finish**.
6. Note that because the computer must be restarted after successful Software Suite upgrade, click **Restart**.




4.5.6. Upgrading QIAcuity Software Suite from version 1.2.18 to version 2.0


This section describes the QIAcuity Software Suite upgrade from version 1.2.18 to 2.0. The Software Suite version 1.2.18 cannot be upgraded directly to version 3.5 but has to be upgraded to version 2.0 first, followed by upgrading to version 2.2.

To upgrade the QIAcuity Software Suite version 1.2.18 to version 2.0, follow the steps below.


1. Locate the **QIAcuitySoftwareSuite.exe** file on the hard drive and double-click it. The installation process starts. Click **Next**.




2. Check the "I accept the terms in the License Agreement" box in the End-User License Agreement window, and click **Next**.




3. Click **Next** in the Destination Folder window.




4. Click **Install** to start the installation.




5. In the prompt window asking you if you want to allow changes to your device, click **Yes**.




Note: During installation, some command line windows may appear in the foreground. Do not close any of them.



6. When the installation is completed, click **Finish**.




7. Note that the computer must be restarted after a successful QIAcuity Software Suite upgrade. You receive the following message:



8. Click **OK**.

Then, click **Restart** and the computer restarts.



9. Your QIAcuity Software Suite is now upgraded to version 2.0. Next, continue with Section 4.5.5 Upgrading QIAcuity Software Suite from version 2.0 to version 2.2.

4.5.7. Upgrading QIAcuity Software Suite from version 1.1.3 to version 1.2.18

The QIAcuity Software Suite version 1.1.3 cannot be upgraded directly to version 3.5. It must be updated to version 1.2.18, then sequentially through the intermediate versions described above, before reaching the latest version 3.5.


To upgrade the QIAcuity Software Suite version 1.1.3 to the version 1.2.18, follow the steps below:

1. Import all plates from QIAcuity Software Suite 1.1.3, and ensure they are visible in the Plates overview.


Note: Plates from the QIAcuity Software Suite 1.1.3 need to be upgraded together with the Software Suite upgrade. Plates created with the QIAcuity Software Suite 1.1.3 cannot be imported later into the QIAcuity Software Suite 1.2.18 or newer versions at all.

2. Ensure that a direct connection or a connection via network is already established and that the instrument and the PC running the QIAcuity Software Suite 1.1.3 are connected.


3. Locate the **QIAcuitySuite.msi** file on the hard drive and double-click it. The installation process starts. Click **Next**.




4. Check the "I accept the terms in the License Agreement" box in the End-User License Agreement window and click **Next**.




5. Make sure that the Destination Folder points to the existing installation of the QIAcuity Software Suite. Click **Next** in the Destination Folder window.



6. Click **Install** to start the installation.




7. In the prompt window asking if you want to allow changes to the device, click **Yes**.



The system then automatically upgrades the existing installation.

8. When the installation is completed, click **Finish**.




9. Continue with the QIAcuity Software Suite upgrade from version 1.2.18 to version 2.0. Refer to Section 4.5.6 Upgrading QIAcuity Software Suite from version 1.2.18 to version 2.0.

4.5.8. Backup QIAcuity Software Suite

Note: The integrated backup functionality is only available during upgrading of the software; during installation and uninstallation, there is no such option. In case a backup is required after the installation or upgrade of the software, an offline script for QIAcuity Software Suite version 3.5 can be downloaded from www.qiagen.com. This script may be used manually or automatically as part of a regular task. Please see the dedicated *QIAcuity Software Suite Backup and Restore Scripts User Manual* for further information. Please always ensure that the correct QIAcuity Software Suite Backup and Restore Scripts version is used for version 3.5: QIAcuity Software Suite Backup and Restore Scripts for version 3.5.


4.5.8.1. Creating backup

The QIAcuity Software Suite version 3.5 automatically creates a data backup during the upgrade process, unless this option was deselected by the user during the upgrade (click **Options**):



By default, the backup is created on drive **C:\qiacuity_backup_<ddMMyyyyHHmmss>**. The last part of this file name is a timestamp that will allow the user to differentiate backups. Backup location can be specified by the user; the installer will show available disc space for the selected path. The available and required space for backup is displayed. Ensure that required disc space for backup is available.



When there is not enough disc space during upgrade, an unidentified error occurs – refer to Section 9.7 Troubleshooting the instrument and software for more details.



4.5.8.2. Restore from backup

To restore application from backup:

1. Uninstall the currently installed Software Suite version that is causing the problem (see Section 4.6 Uninstalling the QIAcuity Software Suite).
2. Manually remove folders **C:\ProgramData\Qiagen**, **C:\Program Files (x86)\QIAcuity Software Suite**, and **C:\Program Files\Qiagen.CommonInterfaces.QIAidentity** if these folders exist. Be aware that **\ProgramData** might be hidden and you might need to change the view settings of Windows Explorer to view it.
3. Install the previously working Software Suite version for which backup was created.
4. Make sure that the browser accessing the Software Suite is closed.
5. Navigate to the folder with the backup and run **flash-rollback.exe**, then follow instructions from the pop-up window. It is recommended to run this program as Administrator.




4.6. Uninstalling the QIAcuity Software Suite


To uninstall the QIAcuity Software Suite from your system, follow the steps below. The uninstallation of the QIAcuity Software Suite is performed by a Windows administrator user.

Note: Uninstallation leads to loss of all data including plate runs.


1. Go to the **Control Panel** app.



2. Select **Uninstall a program** from the **Programs** menu.




3. Select QIAcuity Software Suite from the list, and click **Uninstall**.




4. In the opened uninstallation wizard, click the **Uninstall** button, and the QIAcuity Software Suite uninstallation process begins.

Note: The uninstall process will result in database deletion; all plate data will be lost.



5. After uninstallation, click **Restart** in the window asking to restart the device.



Note: After uninstalling the Software Suite, check the following locations and, if they exist, remove them manually:

- **C:\ProgramData\Qiagen** — Be aware that folder “ProgramData” might be hidden, and the view settings may be needed to be changed in Windows Explorer to see it.
- **C:\Program Files (x86)\QIAcuity Software Suite**
- **C:\Program Files\Qiagen.CommonInterfaces.QIAidentity**

4.7. Upgrading the instrument software to a newer version

Note: The latest QIAcuity Software Suite version 3.5 is only compatible with the latest QIAcuity Control Software version 3.5. If only one software component is updated, the connection between the Software Suite and Control Software cannot be established.

Important: It is strongly recommended to update the Software Suite first before proceeding with the Control Software.

Note: Only users with an Administrator and Lab Leader role or SetupUser can perform instrument control software updates.

An overview of all available CSW versions with their corresponding Software Suite versions is presented in the table below:

Instrument Control Software version	Compatible Software Suite version
3.5.0.2329	3.5.0.0
3.2.0.49	3.2.0.0
3.1.3.6	3.1.3.0
3.0.0.27	3.0.0.0
2.5.0.24	2.5.0.1
2.2.0.8	2.2.0.26
2.1.8.30	2.1.8.23
2.1.0.41	2.1.7.182
2.0.0.144	2.0.20
1.0.0.84	1.2.18
0.5.2.18	1.1.3

We support the following direct upgrade scenarios:

- From QIAcuity Control Software version 3.2.0.49
- From QIAcuity Control Software version 3.1.3.6

All older CSW software versions other than 3.0.0.27 are not supported for a direct upgrade to version 3.5. An upgrade to the QIAcuity Control Software version 3.1 or version 3.2 first is required.

The following intermediate updates of older versions must be followed:

- Upgrading the QIAcuity Control Software from version 3.1 or 3.2 to version 3.5.
Upgrading the QIAcuity Control Software from version 2.5 to version 3.0.0.27 or version 3.1.
- Upgrading the QIAcuity Control Software from version 2.0, 2.1, or 2.2 to version 2.5.
- Upgrading the QIAcuity Control Software from version 0.5 or 1.0 to version 2.0.

Visit www.qiagen.com and go to the **Operating Software** section of the QIAcuity product page to check if an updated software version is available for download.

4.7.1. Upgrading QIAcuity Control Software to version 3.5

On a computer running Microsoft Windows, download the software update from www.qiagen.com. Once the download is complete, extract the folder.

Prepare the USB drive provided with the QIAcuity and ensure that the following USB drive requirements are met:

- The USB drive must have a minimum capacity of 8 GB.
- When performing a Control Software update on multiple instruments using the same USB drive, allocate an additional 2 GB of capacity per instrument (e.g., one instrument, 8 GB; two instruments, 10 GB; three instrument, 12 GB).


Note: If the USB drive is not empty prior to preparation, the tool erases the data on it before proceeding.

4.7.1.1. USB drive preparation on the PC


1. Insert the USB drive that meets the above requirement mentioned above into a computer and do not remove it until the whole upgrade process is complete.
2. Launch the QIAcuity USB Drive Preparation Tool, which is located in the extracted folder on a computer.

Note: The tool automatically detects all connected USB drives.


3. Confirm reading and agreeing to the legal disclaimers.



4. Select the USB drive intended for preparation.



5. Click **Prepare USB Drive**, confirm this action, and wait until the process is completed.
6. After the preparation procedure has finished successfully, the USB drive can be safely removed from the PC.



4.7.1.2. Control Software update on the QIAcuity instrument

Note: The backup of the Control Software version installed on the instrument on which you are trying to upgrade is done automatically during the upgrade procedure.

Important: Do not remove the USB drive until the entire upgrade process is completed.


1. Log in to the instrument as a user with the sufficient permissions to perform the software upgrades.
2. Insert the USB drive into an instrument you would like to upgrade to version 3.5.
3. Go to **Configuration and System** tab.

Note: Information that the USB drive was connected is presented. The version prepared on the USB drive is displayed on the Update Info panel.

4. Click **Update software** button and wait until the copying process is completed.

5. Click **Reboot**, confirm this action, and wait until the upgrade process is completed.

Note: During the upgrade process, a progress bar is displayed along with an information on which step of the upgrade procedure is performed.



6. Once the QIAcuity Control Software is completed, the Log In page and the version of the currently installed software are displayed in the bottom-right corner. After the Network icon is tapped, the network status and Software Suite should be displayed in green. You can then log in using the administrator credentials previously defined in QIAcuity Software Suite.
 - a. If Software Suite is not yet connected, log in with the SetupUser credentials.
 - b. Check the Software Suite settings. If all settings are configured correctly, select **Test Connection** and **Save**.
 - c. Once the Software Suite is detected, a pop-up indicates that a new Software Suite was detected and a restart is needed.
 - d. Restart the instrument.
 - e. After restarting the instrument, the connection between the instrument and the Software Suite is established, and you can log in with the administrator credentials previously defined in the QIAcuity Software Suite.

4.7.2. Upgrading QIAcuity Control Software to version 3.2 or lower

On a computer running Microsoft Windows, download the software update from www.qiagen.com. Insert the USB drive provided with the QIAcuity, create a new folder named update, and extract the update software into this folder.

It is recommended to clear the data on the instrument first by clicking **Force clear** in **Data Management** under **Tools** before the update.

1. On the Home screen, tap **Configuration**.
2. Select the **System** tab.

Note: The current software and firmware versions are located in the Device Info pane.

3. Connect the USB drive to the instrument.
4. The software version of the update package on the USB is displayed in the Update Info (USB) panel.

Note: If the USB drive is empty, no information is displayed in the Device Info (USB) panel.

Note: Only update to higher versions is possible; updating to identical or lower versions will be prevented.

5. Tap **Update software** to proceed.

6. The Update Flash Controller Software and Firmware window is shown.
7. Tap **Start** to begin the software update or tap **Cancel** to return to the previous window.
8. The update files are copied from the USB drive to the instrument's internal drive. The status of the file copying process is shown on the screen.

Note: If an error occurs when the files are being copied, an error message is shown on the screen. Tap **Cancel** to stop the process. Remove the USB drive and tap **Reboot** to restart the instrument. If QIAcuity does not function after an unsuccessful software update, contact QIAGEN Technical Service.
9. After the software update files are copied, tap **Reboot** to restart the instrument.
10. The QIAcuity restarts and installs the software and firmware updates, which can take up to 1 hour.
11. **Important:** Valid only for update to versions older than 3.0: When the Control Software was updated before the Software Suite, a restart is required to be able to log in.
12. After the final restart of the instrument, the Network icon and Software Suite icon should be displayed in green. You can log in using the administrator credentials previously defined in QIAcuity Software Suite.
 - a. If Software Suite is not yet connected, log in using the SetupUser credentials.
 - b. Check the Software Suite settings. If all settings are configured correctly, select **Test Connection** and **Save**.
 - c. Once Software Suite is detected, a pop-up indicates that a new Software Suite was detected and a restart is needed.
 - d. Restart the instrument.
 - e. After restarting the instrument, the connection between the instrument and Software Suite is established, and you can log in using the administrator credentials previously defined in QIAcuity Software Suite.
13. Repeat steps 1–12, if additional update is necessary.

4.8. Establishing a connection between the QIAcuity instrument and the QIAcuity Software Suite

The QIAcuity instrument needs to be connected to the QIAcuity Software Suite to enable the exchange of data for the analysis and configuration of the instrument. An established connection enables the QIAcuity Software Suite to set up plates, analyze results, and monitor the status of runs in real time. Depending on the customer requirements, the connection can be realized in different configurations, as shown in the following sections.

4.8.1. Private LAN direct connection of one instrument to a co-located Software Suite computer

For this, the QIAcuity instrument and the QIAcuity Software Suite may be connected via an ethernet cable between the QIAcuity and the notebook where the QIAcuity Software Suite is running.




Figure 1. The QIAcuity instrument and QIAcuity Software Suite are directly connected via Ethernet cable.

4.8.2. Instrument and Software Suite computer connection via LAN

Alternatively, both the QIAcuity instrument and the computer running the QIAcuity Software Suite can be connected to a local area network (LAN). This configuration allows the QIAcuity notebook or a separate computer to work as a server to which multiple clients can be connected.




Figure 2. The QIAcuity instrument(s) and QIAcuity Software Suite are installed to a network, allowing multiple clients to access the QIAcuity instrument(s) via a single QIAcuity Software Suite server.

For connection to the Software Suite server, use the IP address of the Software Suite server.

4.8.3. Private LAN with multiple instruments connected to a Software Suite computer

Using a switch between the instrument and the Software Suite instance allows connection of multiple instruments to one Software Suite server in a private LAN environment.

4.8.4. Instrument in dedicated subnet with computer also connected to corporate LAN

A connection of the instrument in an isolated network via a direct ethernet cable connection to QIAcuity Software Suite server while the QIAcuity Software Suite server itself is connected via another interface (ethernet or wireless LAN) to customer's LAN (Intranet) allows the client workstations to access the QIAcuity Software Suite via the respective LAN (Intranet).

For the instrument connection to the QIAcuity Software Suite server, the explicit IP address configuration for the QIAcuity Software Suite server ethernet adapter has to be used. The client workstations use the IP address of the QIAcuity Software Suite server of either the WLAN or second ethernet adapter.




Figure 3. The QIAcuity instrument and the QIAcuity Software Suite can also be operated in two separate networks, allowing multiple clients to access the QIAcuity instrument via a single QIAcuity Software Suite server, while maintaining instrument network isolation.

4.8.5. Configuring an ethernet connection between the QIAcuity instrument and the QIAcuity Software Suite

Important: Only users with an Administrator role can modify the network configuration. Consulting your network administrator when configuring the network is recommended.

To establish a connection, the instrument and the notebook must be connected to the LAN. For 10 users accessing the system in parallel, the requirement is a minimum data connection speed of 10 Mbit/s for a setup via network. For the time synchronization between the instrument and the notebook, Windows Time Service (NTP) is used. Please make sure that the above service is enabled in the notebook or contact your administrator.

Note: Make sure that the QIAcuity instrument is connected to the LAN. Any other configurations are not supported by QIAGEN.

For communication with the QIAcuity Software Suite, the following ports are used and should be always opened in the correct direction:

- The inbound TCP port 44321
- The inbound TCP port 8687
- The inbound UDP port 123


After any changes are applied to the ports above, the QIAcuity instrument must be restarted.

Pinging the network is also supported.


Note: If the connection with the instrument from direct to LAN or from LAN to direct has been changed or the IP was reassigned, refer to point (d) under the “Installation and maintenance” subsection of Section 9.7 Troubleshooting the instrument and software.

Follow the steps below to configure the notebook running the QIAcuity Software Suite in Windows 11.


1. Go to the **Control Panel** app.




2. Click **Network and Internet** (if not available, proceed to the next step).



3. Click **Network and Sharing Center**.




4. On the left pane, click **Change adapter settings**.




5. Right-click the ethernet network adapter and select **Properties**.

6. Select **Internet Protocol Version 4 (TCP/IPv4)** and click **Properties**.



7. Select **Obtain an IP address automatically**. If your organization does not provide DNS details, select **Obtain DNS server address automatically as well**. Click **OK**, then **Close**.



Optional: You can check if the addresses have been assigned properly by following the steps below.

- From your Home screen, click the **Search** icon. Enter "cmd" and press the **Enter** key.
- Wait for the command line window to open. Enter "ipconfig".
- The address should be visible under the ethernet interface name for which modifications were made.

In Windows 11, refer to Microsoft support page – [Change TCP/IP settings - Microsoft Support](#) – to get guidance for the recent version.

Follow the steps below to configure the QIAcuity instrument network settings.

1. Log into the instrument using the following credentials:
 - **Login:** SetupUser
 - **Password:** 2#ConnectSuite
2. On the toolbar, tap **Configuration**.
3. Select the **Ethernet** tab.

QIAGEN

Running Status Tools Configuration Disk Monitor Network Alarm

Ethernet Software Suite

Device Network Settings

☐ DHCP Enabled

IP address: 192.168.1.2 Subnet mask: 255.255.255.0

Gateway: 192.168.1.1

Save

Hand: Idle Scanner: Idle Prime/Roller: Idle Cycler 1: Idle Cycler 2: Idle Imager: Idle SetupUser

4. Check the “DHCP Enabled” box. If this box is ticked, the “IP address” and “MAC address” fields are disabled. The assigned IP and MAC addresses of device are displayed in the “IP address” and “MAC address” fields. Alternatively, the customer’s IT may configure a fixed IP address for the instrument.

QIAGEN

Running Status Tools Configuration Disk Monitor Network Alarm

Ethernet Software Suite

Device Network Settings

☒ DHCP Enabled

IP address: 192.168.1.2 MAC address: 10-3D-1C-3F-44-27

Save

jan - QIAGEN (Rennickean.Maijan@qiagen.com) is signed in

Hand: Idle Scanner: Idle Prime/Roller: Idle Cycler 1: Idle Cycler 2: Idle Imager: Idle SetupUser


5. Tap **Save**.

4.8.6. Configuring a direct cable connection between the QIAcuity instrument and the QIAcuity Software Suite


Note: Before you start, ensure that the QIAcuity instrument and the notebook are connected with an Ethernet cable.

Follow the steps below to configure the notebook running the QIAcuity Software Suite in Windows 11.


1. Go to the **Control Panel** app.




2. Click **Network and Internet** (if not available, proceed to the next step).



3. Click **Network and Sharing Center**.




4. On the left pane, click **Change adapter settings**.



5. Right-click the ethernet network adapter, and select the **Properties** option.

6. Select **Internet Protocol Version 4 (TCP/IPv4)**, and click **Properties**:




7. Use the following IP address. Enter the following information:

- **IP address:** Enter "192.168.1.1".
- **Subnet mask:** Enter "255.255.255.0".
- **Default gateway:** Enter "192.168.1.254".
- **Preferred DNS server:** Enter the DNS server address.
- **Alternative DNS server:** Enter the alternative DNS server address.

Note: If the "Preferred DNS server" and "Alternative DNS server" fields are left blank, the connected is showed as unknown.

- Click **OK**, then click **Close**.



Optional: You can check if the addresses have been assigned properly by following the steps below.


- From your Home screen, click the **Search** icon. Enter "cmd" and press the **Enter** key.
- Wait for the command line window to open. Enter "ipconfig".

The address should be visible under the ethernet interface name for which modifications were made.

In Windows 11, refer to Microsoft support page – [Change TCP/IP settings - Microsoft Support](#) – to get guidance for the recent version.

Follow the steps below to configure the QIAcuity instrument.

- On the toolbar, tap **Configuration**.
- Select the **Ethernet** tab.



3. Ensure that the "DHCP Enabled" box is not checked. Enter the following information:

- **IP address:** Enter "192.168.1.2".
- **Subnet mask:** Enter "255.255.255.0".
- **Gateway:** Enter "192.168.1.1".

The screenshot shows the QIAGEN Configuration interface. At the top, there is a navigation bar with icons for Running Status, Tools, Configuration (selected), Disk Monitor, Network, and Alarm. Below this, there are tabs for Ethernet and Software Suite. The main section is titled "Device Network Settings" and contains a form with the following fields: "DHCP Enabled" (unchecked), "IP address" (192.168.1.2), "Subnet mask" (255.255.255.0), and "Gateway" (192.168.1.1). A "Save" button is located at the bottom right of the form. At the very bottom of the screen, a status bar shows the status of various components: Hand: Idle, Scanner: Idle, PrimeRoller: Idle, Cycler 1: Idle, Cycler 2: Idle, Imager: Idle, and SetupUser.

4. Tap **Save**.

4.8.7. Configuring the connection to the QIAcuity Software Suite in the QIAcuity instrument software

The QIAcuity instrument needs to be connected to the QIAcuity Software Suite to enable the exchange of data. To establish a connection, the instrument and the device in which the QIAcuity Software Suite is running must be connected to the same network.

Note: A plate run can only be performed if the QIAcuity Software Suite is connected to the instrument through a network or direct cable connection to the QIAcuity Software Suite server.

To connect the instrument to the QIAcuity Software Suite:

1. The **Network** icon represents the connection between the QIAcuity Software Suite and the instrument. When the icon is red, the connection is not established.
2. Log into the Instrument using the following credentials:
 - **Login:** SetupUser
 - **Password:** 2#ConnectSuite

Note: SetupUser is only allowed to log into the instrument when connection with the Software Suite is not established. Once established, login with SetupUser is no longer possible.

3. On the Home screen, tap **Configuration**.

4. Tap the **Software Suite** tab.

QIAGEN Running Status Tools Configuration Disk Monitor Network Alarm

Ethernet Software Suite

Software Suite URL

Address *

10.136.12.182

Port number *

8087

Test Connection

Save

Hand: Idle Scanner: Idle Prime/Roller: Idle Cyclor: Idle Imager: Idle SetupUser

5. Enter the IP address in the address field of the **Software Suite URL** section.

QIAGEN Running Status Tools Configuration Disk Monitor Network Alarm

Ethernet Software Suite

Software Suite URL

Address *

10.136.12.193

Port number *

8087

Test Connection

Save

Hand: Idle Scanner: Idle Prime/Roller: Idle Cyclor 1: Idle Cyclor 2: Idle Imager: Idle SetupUser

Note: To obtain the IP address of the Software Suite server, the instrument must be connected to the Software Suite server. From the home screen on the Suite PC, click the **Windows** icon and navigate to Command Prompt, or enter "cmd" in the search field. A command line window appears. Enter "ipconfig" to view the network settings.

Due to technical limitations, Suite Server IP address shall not contain the full IP of the instrument (e.g., instrument IP set to xxx.xxx.xxx.12 will not work correctly with Suite Server IP xxx.xxx.xxx.123; in that case the latter value should be changed, e.g., to xxx.xxx.xxx.13). This requires a new IP address assignment for the Software Suite laptop/network. Afterwards, the new IP address needs to be entered in the address field of the **Software Suite URL** section.

Note: An error message displays if the address and port number you entered are invalid. Tap **OK** to close the error message, and then re-enter the correct address and port number in the address field in the Software Suite URL area.

6. Tap **Save**.

4.9. Getting started with the QIAcuity


4.9.1. Configuration of the QIAcuity

If you are using QIAcuity for the first time, we recommend that you define the required settings. Other settings can be changed later, when needed.

For more information about using the touchscreen and software, refer to Section 6 Operating the QIAcuity Instrument.

4.9.2. Procedure

1. Make sure that the rear power switch is set to "I". Press the front power button to turn on the instrument.
2. The startup screen appears on the touchscreen. Wait until the initialization tests are finished.




3. Enter the following initial login information on the Login page. Tap the field to begin typing.
 - **User ID:** admin
 - **Password:** admin

Note: The default admin user account is available once connection to the Software Suite is established following the steps described in Section 4.8.7 Configuring the connection to the QIAcuity Software Suite in the QIAcuity instrument software.

4. Tap **Login** to continue.

5. The Home screen appears.



Note: To return to the Home screen from another screen, tap **Running Status**.

4.9.3. Setting basic system data


This section describes how to set the preferred name for the instrument.

4.9.3.1. To set the preferred QIAcuity name

1. On the Home screen, tap **Configuration**.
2. Select the **System** tab.
3. Specify your preferred instrument name in the "Device Name" field. If this field is left blank, a default name is automatically generated for each QIAcuity instrument.

Note: Names can have up to 24 characters: letters A–Z, a–z, 0–9, and a hyphen (-). Do not start the instrument name with a digit or a hyphen. Instrument names also cannot end with a hyphen.

4. The default device name uses the following naming convention: QIAcuity-<serial number of the instrument>.




4.9.4. Managing users

QIAcuity requires users to log in before accessing instrument functionalities. Each user must have a user account with an appropriate role assigned to it. QIAcuity supports various pre-designed user roles and customer-created user roles. Each role has different access rights to QIAcuity functions described in Section 7.2.1 Log-in screen.

4.9.5. Access policy

4.9.5.1. Password expiration


Since version 2.1 onwards, by default, after 30 days, passwords expire and every user (including default admin account) is prompted for password change. Starting with version 3.5, the password expiration can be specified or disabled. Refer to Section 7.2.19 Account security for further details. After the software update, during the first attempt to log in into an instrument, the user is informed about the need to update the password in the Software Suite. Once at least an additional user with administrator rights has been created, it is recommended to deactivate the initial default admin user.



4.9.5.2. Automatic log-off and blocking user account

QIAcuity Software Suite automatic log-off and user account blocking:

- After three unsuccessful login attempts, a user is temporarily blocked and needs to wait 10 minutes to unblock the account.



- In case of 15 minutes of inactivity, users are automatically logged off. Activity consists of mouse clicks, mouse scrolling, and pressing buttons on the keyboard (mouse movement without clicks nor scrolling is not considered as activity). This behavior applies even when user operates the application on multiple browser tabs– the aforementioned activities are registered on any of the opened windows. Automatic log off happens on all opened tabs in the application, and user is redirected to the default login page. When users log in again, the application will automatically redirect the user to the last page where log-off occurred.

Automatic log off does not interrupt plate operations such as, for example, plate upgrade. When some plate operations are triggered and automatic log-off occurs in the meantime, the operation will be continued in the background and results will be available after the next log-in.

4.9.6. Synchronizing labware with the QIAcuity Software Suite

The QIAcuity Control Software and the QIAcuity Software Suite use labware files that include information about the Nanoplate formats available. A labware file defines dimensional specifications and default processing parameters for each Nanoplate. Information about the labware used by QIAcuity can be downloaded from the Software Suite. The labware data are synchronized automatically when the instrument is turned on and the connection to the Software Suite is established. You can also synchronize it manually by clicking **Tools** and selecting **Labware Sync**. The labware is then downloaded and updated.


Note: Only users with appropriate rights are allowed to synchronize labware.

Note: Make sure that, after the first successful Software Suite connection, the instrument is restarted to allow automatic synchronization of labware files.


Note: The connection between the QIAcuity and the Software Suite must be configured before starting this procedure. For more information on how to set up the connection, refer to Section 4.8 Establishing a connection between the QIAcuity instrument and the QIAcuity Software Suite.

To download labware information from the Software Suite, follow the steps below.

1. On the toolbar, tap **Tools** and then proceed to the **Labware Synchronization** tab.



2. Tap **Labware sync**. The Labware synchronization dialog box appears.
3. The progress of the download is shown in the dialog box. Once the synchronization is complete, tap **OK** to finish the process.



5. Operating Plates

In the QIAcuity plate-based system, one reaction mix per well is partitioned into a large number of individual partitions prior to the amplification step, resulting in one or very few templates being present in each partition. QIAGEN offers different plate types according to specific user needs.

Table 4. Plate types according to user needs

Plate type	Frame color	No. of wells	Input volume/well (µL)	No. of partitions	Partition volume (nL)
Nanoplate 26K 24-well	Blue	24	40	Approx. 26,000	Approx. 0.82
Nanoplate 26K 8-well	Light blue	8	40	Approx. 26,000	Approx. 0.82
Nanoplate 8.5K 24-well	White	24	12	Approx. 8500	Approx. 0.34
Nanoplate 8.5K 96-well	Gray	96	12	Approx. 8500	Approx. 0.34

Note that the QIAcuity Software Suite calculates with a partition volume of 0.82 or 0.34 nL, depending on Nanoplate type, in cases where the VPF (volume precision factor) has not been applied. If the VPF has been loaded to the software, the volume of each well is Nanoplate batch-specific calibrated and used for concentration calculation. Thus, the concentration calculated by the QIAcuity Software Suite will differ to concentration values calculated manually.




Image of Nanoplate 26K 24-well, Nanoplate 8.5K 24-well, and Nanoplate 8.5K 96-well.

5.1. QIAcuity Nanoplate 26K 24-well

For applications requiring high sensitivity, QIAGEN offers the 26K nanoplate. In this plate, one reaction mix is distributed over 4 wells and separated into approximately 26,000 partitions. The plate may be used for up to 24 samples and has a blue frame as distinction from the other plates.

The key applications of the 26K nanoplate are:

- Rare mutation detection
- Liquid biopsy

5.2. QIAcuity Nanoplate 26K 8-well

For applications requiring high sensitivity, QIAGEN offers the 26K nanoplate. In this plate, one reaction mix is distributed over 4 wells and separated into approximately 26,000 partitions. The plate may be used for up to 8 samples and has a light blue frame as distinction from the other plates.

The key applications of the 26K nanoplate are:

- Rare mutation detection
- Liquid biopsy

5.3. QIAcuity Nanoplate 8.5K 24-well

In this plate, one reaction mix is distributed in 1 well and separated into approximately 8500 partitions. The plate is recommended for applications using low input volumes and a small number of samples. The plate may be used for up to 24 samples and has a white frame as distinction from the other plates.

The key applications of the 8.5K nanoplate are:

- CNV detection
- NGS library quantification

5.4. QIAcuity Nanoplate 8.5K 96-well

In this plate, one reaction mix is distributed in 1 well and separated into approximately 8500 partitions. This plate is recommended for applications using low input volumes and a large number of samples. The plate may be used for up to 96 samples and has a gray frame as distinction from the other plates.

The key applications of this nanoplate are:

- CNV detection
- NGS library quantification

5.5. Reaction setup

Note: The QIAcuity reads fluorescence from the bottom of the nanoplate, which is covered with a seal. For best results, keep the foil clean and avoid damage such as scratches. Also, keep the barcode on the side of the nanoplate clean and intact. Ensure that you wear gloves when working with a nanoplate and do not apply force to it.

For better handling of the nanoplate, you can place it into the nanoplate tray that can be ordered as an accessory, see Appendix B — QIAcuity Accessories or the QIAcuity webpage on www.qiagen.com

To set up a plate, follow these steps:

1. Prepare your master mix according to your reaction setup. To prepare the reaction mix without sample, the QIAcuity PCR master mix has to be mixed with primers, RNase-free water, and optionally restriction enzyme and probes according to the kit manual. The final volume depends on the QIAcuity Nanoplate that is used (refer to Table 4).

Note: To prevent non-homogeneous reaction mixes, set up in a standard PCR pre-plate is required. The calculated reagent volumes must be pipetted into the PCR pre-plate, and then the sample added accordingly. For homogenous mixing of reaction mix, the pre-plate must be sealed, shortly vortexed, and briefly centrifuged.

Note: Enzymatic fragmentation of DNA larger than 20 kb ensures even distribution of template throughout the QIAcuity Nanoplate, which in turn leads to accurate and precise quantification. Therefore, adding a restriction enzyme depends on the template used. In case of enzymatic fragmentation using the recommended restriction enzymes, the pre-plate has to be incubated at room temperature (RT) for 10 min. Longer incubation does not lead to unspecific restriction and therefore has no impact on the result. Refer to the Application Guide on www.qiagen.com for the recommended restriction enzymes.

Important: Do not pipet master mix and sample separately into the nanoplate as this will lead to insufficient mixing.

2. Pipet each reaction mix from the pre-plate into a well of the nanoplate. If possible, use an electric one-channel pipette. To ensure bubble-free pipetting, we recommend pipetting 39 μ L for Nanoplate 26K 8/24-well, and 11 μ L for Nanoplate 8.5K 96/24-well of your prepared reaction mix to the bottom of the respective input well of the nanoplate. Ensure not to pipet into the output well instead of the input well.

Note: To avoid damaging the optical surface and to reduce dust that will interfere with the imaging and analysis of results, we recommend placing the nanoplate into a nanoplate tray before pipetting the reaction mix into the nanoplate.

Note: Do not centrifuge the nanoplate as this will lead to pre-priming and insufficient filling of the wells.

Note: Do not vortex the nanoplate as this will lead to insufficient filling of the wells.

3. Apply the plate seal that comes with the nanoplates as follows to ensure good filling of the wells and to prevent evaporation and contamination:
 - a. The stiff plate seal consists of a plate seal and two protective sheets. The three-layered seal should not be folded. Remove the bottom white protective sheet carefully, and then center and align the plate seal (still containing the upper protective sheet) with the lower edge of the colored frame of row H. The seal should not overlap on any side more than 1 mm; otherwise, the nanoplate might not be processed by the instrument. In case the plate seal is incorrectly placed or the seal does not cover some parts of the nanoplate, carefully remove this seal and repeat the entire sealing step with a new one. Correct sealing of the nanoplate prevents samples from not being fully processed.

Note: It is recommended to cover the plate with the top seal within 30 min after pipetting to prevent subsequent filling issues.

Note: Keep the plate seals stored in a dry, darkened, and air-free environment by always completely closing them inside the provided storage bag in which they came, and storing them in the Nanoplate box.

- b. After correct placement, the plate seal must be fixed with the Nanoplate roller in both horizontal and vertical directions.
- c. Afterwards, the upper protective sheet is removed from the bottom left corner. Hold the rubber seal in place on the plate corner with one finger while the upper transparent sheet is being pulled off. If the upper sheet is removed in another direction, the plate seal might loosen.
- d. Use the Nanoplate roller with high force to fix the plate seal on the nanoplate by rolling at least three times forwards and backwards in a horizontal direction, and then three times forwards and backwards in the vertical direction over the edge of the plate. Roll over the plate seal covering the Nanoplate frame. The proper fixing of the plate seal is important for a good filling of the wells.

Note: For a properly sealed plate, the plate seal covers the whole structure, and no bubbles or strong depressions are visible, as this can also lead to poor filling.

4. The plate frame gives the option to mark the plate with a marker pen. Use the lane between the plate edge and the printed letters (next to column 1) as well as the mirrored portion (from column 12 to the plate edge) only. Marking the plate seal directly on top of each well is not recommended as it might lead to poor filling.

Important: Do not mark the bottom side of the plate, as it is used to read fluorescence signals.

Note: Ensure that overlapping parts of the plate seal are turned down and attached to the plate frame and that the barcode is not covered. Do not apply pressure to either upper or lower plate seal.

5. For the transport of the Nanoplate to the QIAcuity instrument, the plate should be held at the side edges or on the tray horizontally. Make sure that the plate is transported to the QIAcuity smoothly without shaking or turning over the plate to ensure that the reaction mix remains at the bottom of the input well.
6. The plate can now be used to start a run. For more information about starting a run on the QIAcuity, see Section 7 Operating the QIAcuity Software Suite.

Note: Do not store the plate for more than 2 hours before the start of a run as this may lead to pre-priming of the reaction mix resulting in a reduced number of analyzable partitions.

7. If the plate is kept in the dark, avoiding exposure to moving air (e.g., storage in a dark box), you can store the plate after the run for up to 1 week at room temperature or at 4°C.

Note: Storage time may be reduced from 1 week to shorter durations due to various factors, such as dye/probe stability, master mix, and previous imaging step/settings.


Dispose the plates after 7 days at the latest. A plate can be re-imaged up to six times (seven total imaging steps); see Section 7.3 Setting up an experiment for more information on how to re-cycle and re-image a plate.

Note: For improperly stored plates, the fluorescence intensity and plate seal integrity can be affected, which could lead to contamination of the laboratory. Store processed plates according to these guidelines or dispose of them properly after the process.

6. Operating the QIAcuity Instrument

The QIAcuity is operated through a touchscreen. Elements of the QIAcuity user interface are shown in the following table.

Table 5. QIAcuity interface elements

Button/Icon	Function
	Starts the run
	Stops the run
	Starts runs on all loaded plates
	Stops all runs
	Closes an open tray
	Ejects selected tray
	Displays an additional menu
	Enables the user to edit plate parameters
	Enables the user to create a new plate and specify its parameters
Text field	Enables to enter or edit a value using the on-screen keyboard
	Logs the user out
	Indicates whether the instrument is connected to a network
	Landing page with status of runs
	Configuration
	Tools

6.1. Entering text and numbers

To enter text or numbers, tap the corresponding field. An on-screen keyboard is displayed on the touchscreen.

Enter Plate Name

Plate 123

1234567890

qwertyuiop

↑

asdfghjkl

↑

zxcvbnm.,

#+=

Cancel

OK

Input Temperature

350

Valid range is between 40-99 °C.
One decimal point is allowed.

789

456

123

0.

Cancel

OK

In some cases, the value required in a text field must meet a specific criterion. If required, the criteria are specified in the corresponding input window.

Note: For all text fields, a handheld scanner plugged into one of the USB ports can be used to scan 1D barcodes. Buttons and icons related to the on-screen keyboards are shown in the following table. An external keyboard can also be attached via USB port for data entry, if desired.

Table 6. On-screen keypad buttons and icons

Button/Icon	Function
	Removes one character to the left of the cursor
	Clears the field
	Enables the user to type one uppercase letter. After the letter is typed, the keyboard will show lowercase letters again.
	Switches to uppercase letters. Allows the user to type multiple uppercase letters. To return to lowercase letters, press the symbol again.
	Shows special characters
	Shows alphanumeric characters
	Confirms the input and closes the window
	Discards the input and closes the window

If the entered value is not correct, the border of the textbox changes to red and additional information about the field’s requirements is shown. The input cannot be confirmed until the value entered in the box meets the requirements.

6.2. Turning on the instrument and logging in

To turn on the instrument and log into the software, follow these steps:


1. Press the power button to turn on the QIAcuity.
2. The startup screen appears on the touchscreen, and the instrument automatically performs initialization tests. After the initialization setup, the Login window appears.
3. Enter your credentials in the "Username" and "Password" fields.

Note: The "Username" field is case sensitive.

Note: When connection to the Software Suite has not been established yet, log into the instrument using the following credentials:

- **Login:** SetupUser
- **Password:** 2#ConnectSuite

For further information, refer to Section 4.8.7 Configuring the connection to the QIAcuity Software Suite in the QIAcuity instrument software.



4. Tap **Login**.
5. The Home screen displays.

Note: If the username does not match the password or if the username does not exist, an error message is displayed on the screen. Re-enter the correct credentials in the "Username" and "Password" fields.

6.3. Setting up a run

Before starting a run, at least one plate must be created, and its name, plate type, and dPCR parameters must be defined. We recommend that you define plates and their specific parameters (e.g., the run profile) using the QIAcuity Software Suite. For more information about setting up a plate using the QIAcuity Software Suite, refer to Section 7 Operating the QIAcuity Software Suite. For creating a plate using the plate configurator of the instrument software, refer to Section 6.4.3 Plate configuration procedure.

6.4. Setting up an experiment


Note: A plate run can only be performed if the instrument is connected to the QIAcuity Software Suite through either a network or a direct cable connection to the QIAcuity Software Suite server.

Note: It is recommended to cover the plate with the top seal within 30 minutes after pipetting to prevent subsequent filling issues.

6.4.1. Loading the trays and starting a run

The Home/Running status screen shows the current status of the trays and the slots inside them. If there are no plates loaded in the instrument, the screen displays empty panes and each pane displays the **Plate is not loaded** label. You can load up to eight plates at one time with QIAcuity Eight, up to four plates at one time with QIAcuity Four, and one plate with QIAcuity One.

Note: Loading and unloading plates during a run is supported by QIAcuity Eight and QIAcuity Four. To learn more about continuous loading and unloading, refer to Section 6.6 Continuous loading and unloading of plates.




To load a tray and to start a run, follow these steps:


1. To eject a tray, press the physical button on the instrument or tap **Eject Tray** on the touchscreen.

Note: In QIAcuity Eight, you can select to eject either the upper or the lower tray from the list located below the panes.

2. Place a plate in one of the slots of the ejected tray. Ensure that the plate is placed in the correct orientation, facing the barcode toward the instrument and the QIAGEN lettering toward you. Also, ensure that the plate seal of the plate is intact and not overlapping any of the sides more than 1 mm. Repeat this step until all plates are loaded to the tray.



3. Tap **Close Tray** or press the physical button on the instrument to close the tray. Do not push the tray itself.
4. The instrument scans the barcodes on the plates. The instrument detects the availability of the plate and the label of the corresponding pane changes to **Plate is detected**. If the barcode matches an existing experiment in the Software Suite, the loaded plate pane displays the defined run setup and can be started.



Note: In case the barcode does not match an existing plate in the Software Suite (e.g., if no barcode has been defined in the experiment setup), the plate can be assigned manually from the list of pre-defined plates without barcodes.

Note: If the plate is expired, a warning message displays, indicating the expiration date. User may continue with this plate at your own risk.

5. To view the details of the plate, tap **Show details** in the corresponding plate's pane.
6. When all plates are correctly labelled and the corresponding data are received from the QIAcuity Software Suite, start the run.
 - To start the run on all plates simultaneously without making any changes, tap **Run all**.
 - To start the run of an individual plate without making any changes, tap the **Run**  icon on the plate's pane.
 - To edit the parameters of a plate before starting a run, follow the steps described in Section 6.4.2 Configuring a plate and starting a run.

Note: A run can only be started if the current user logged in has the appropriate rights.

Note: After a plate is loaded into the instrument, QIAcuity sends a request to the Software Suite to lock the plate. This ensures that the plate is not modified by another user in the Software Suite while the plate is loaded and operated by an instrument. The plate is unlocked after it is unloaded from the instrument.


6.4.2. Configuring a plate and starting a run

User can configure a plate (in the Software Suite) before or after it has been loaded to the instrument.

Note: For configured plates loaded into instrument, only dPCR parameters can be changed; General Data cannot be edited. Changes are not allowed during the run.


To start the configuration of a plate that has been loaded into the instrument, follow these steps:

1. On the plate's pane, tap **More**.



2. Tap **Edit plate** or **Create a new plate** to proceed to the plate configurator.

Note: The **Edit plate** button becomes available when a plate is loaded and the instrument successfully received the data from the Software Suite. The **Create a new plate** button is available when the plate's barcode is not found in the Software Suite database or when the QIAcuity cannot connect to the Software Suite.



3. Proceed to Section 6.4.3 Plate configuration procedure.

To start the configuration of a plate that has not been loaded into the instrument, follow these steps:

1. On the Home (Running status) screen, tap **New Plate**.

Note: The **New Plate** button is not available for single-plate instruments.

2. To input the barcode manually, tap the "Barcode" field. To scan the barcode using the external USB scanner, tap **Scan**.
3. Proceed to Section 6.4.3 Plate configuration procedure.

6.4.3. Plate configuration procedure

To configure a plate and start the run, follow these steps:

1. In the **General Data** section, enter the following information:

- **Plate Name:** Enter the name of the plate.


Note: The plate type is automatically selected based on the scanned barcode.

- **Description (optional):** Provide a description for the plate.

Note: If you are editing an existing plate, you can only change the values in the **dPCR Parameters** section. The fields in the **General Data** section are disabled.

A screenshot of the 'NEW PLATE CONFIGURATOR' interface for 'Plate 123'. The interface has a top bar with 'NEW PLATE CONFIGURATOR' and 'Plate 123'. Below this is a tabbed interface with 'General Data' selected. The 'General Data' section contains: 'Plate Name' (text field with 'Plate 123' and 'Characters left: 91'), 'Plate Type' (dropdown menu showing '96 Wells (12x8)'), 'Description (optional)' (text area with 'Characters left: 200'), and 'Barcode' (text field with 'AABB_96'). Below the barcode field is a note: 'Recommended next step: dPCR parameters'. At the bottom of the screen are two buttons: 'Back to Running Status overview' and 'Save' (with a document icon) and 'Done' (with a checkmark icon).

Note: If you are creating a plate, you are automatically assigned as an owner of a plate. Owners are displayed under plate name on running status page. Modifying owners of the plate is only possible by editing the plate in the Software Suite.



2. Tap **dPCR Parameters** to proceed with the next step.

Note: Each step in dPCR parameters has its own tab. The **Priming**, **Cycling**, and **Imaging** tabs are mandatory.


3. In the **Priming** tab, select the applicable priming profile. Starting with the QIAcuity software version 3.0:

- To improve overall filling of all Nanoplate types: Two priming profiles are available for selection for probe-based and EvaGreen-based (RT-) reaction mixes.


Important: Nanoplates for those profiles must be sealed with the Nanoplate Seals.

- To omit filling in the Priming process for all nanoplate types: One priming profile is dedicated to the plates sealed in an Automatic Plate Sealer called “No Priming” – available after pressing **More**.

Important: Nanoplates sealed with the automatic plate sealing solution are already filled during that process.




4. Perform the following steps in the **Cycling** tab:
 - a. Enter your desired temperature in the "Temperature" field.
 - b. In the "Duration" field, enter the cycling duration for the plate.
 - c. Tap **Add temperature step**.




Note: The gradient cycling option can only be defined in the Software Suite.

5. If you want to modify the temperature steps, refer to these steps:
 - To edit or delete a temperature step, tap the **More**  icon, then tap **Edit** or **Delete**.



- To group the temperature steps, check the corresponding boxes of more than one temperature step, then tap **Group**.
- To ungroup a group of temperature steps, tap the **More**  icon, then tap **Ungroup**.



6. Perform the following steps in the **Imaging** tab:
 - a. In the **Imaging** tab, select the applicable channel, then enter the exposure duration and gain in the "Exposure duration" and "Gain" fields.
 - b. On all QIAcuity instruments (excluding QIAcuity One, 2 plex), high multiplex experiments, up to 8-plex analysis, can be performed. Channels 6–8 (Far Red and the combinations of Green/Yellow, Yellow/Orange, Orange/Red, Red/Crimson, Crimson/Far Red) require the High-Multiplexing Reference channel of the new QIAcuity High Multiplex Kit. If any of the above channels is selected on the **Imaging** tab, the system will automatically enable the required High-Multiplexing Reference channel and the user cannot disable it. It is also possible to activate the High-Multiplexing Reference channel for standard channel usage.

c. To include more steps in the run, tap the **Add**  icon, then select the applicable step. Provide the required information for the step. Repeat this step if more steps are needed for the run. In total, nine steps can be performed per plate.

d. Tap **Save** to save your progress or tap **Done** to save the run and go back to the Running Status window.

Note: If any required field is not completed, an error message is displayed, pointing out the missing information required in each field.

NEW PLATE CONFIGURATOR
TEST_PLATE

General Data

Priming
 Cycling
 Imaging

dPCR Parameters

HM-Ref

Channel	Exposure duration	Gain
GREEN	300 ms	6
YELLOW	250 ms	4
ORANGE	150 ms	3
RED	150 ms	3
CRIMSON	300 ms	4
FAR RED	600 ms	8
GREEN / YELLOW	1,000 ms	6
YELLOW / ORANGE	1,000 ms	6

[Back to Running Status overview](#)
[Done](#)

7. Start the run in the Running Status window:

- To start the run on all plates simultaneously without making any changes, tap **Run all**.
- To start the run of an individual plate without making any changes, tap the corresponding **Run**  icon located on the plate's pane.

6.4.4. Linking a plate to a pre-defined plate without existing barcode

If the instrument cannot match the barcode on a loaded plate to a barcode that already exists in the Software Suite, the plate can be linked manually. Alternatively, a new plate can be created by following the steps in Section 6.4.2 Configuring a plate and starting a run.

Barcode not found

96

The barcode does not match any plate in the Software Suite. You can either link the barcode to a saved plate, or you can use it to create a new plate.

To link the barcode to a defined plate in the Software Suite that has no defined barcode, follow these steps:

1. Tap the **Link**  icon.
2. In the Select Plate dialog box, select the plate that you want to link to the barcode of the loaded plate.

Note: Only plates with a “Defined” status without a barcode assigned can be linked.

Select plate

Select the plate from the list below to be associated with the barcode: 03026632123456000000000005

Updated 05.08.2024 14:55

Nanoplate 8.5K 96-well 

Plate_20240804_1530

Barcode: -

Updated 05.08.2024 14:54

Nanoplate 8.5K 96-well 

Plate_20240805_1230

Barcode: -

Updated 05.08.2024 14:54

Nanoplate 8.5K 96-well 

Plate_20240805_1130

Barcode: 03026632123456000000000005 

Updated 05.08.2024 14:53

Nanoplate 8.5K 96-well 

Plate_20240805_1020

Barcode: -

Cancel

Apply


3. Tap **Apply**.

6.5. Tracking the run status


Once the run has started, the status of the run can be tracked. The plate that the QIAcuity is currently working with is distinguishable through the following elements:

- The Running status is displayed in the pane.
- The **Stop Run**  button is available.
- A status bar with the remaining time is displayed.

The panel also shows all the steps within the run. The font color of the steps that are completed is black. When a step is in progress, its font color is blue. Pending steps are shown in light gray.



To view more details about the run, tap **Show details**. The dialog box appears containing information about the plate (in the **General Data** tab), as well as each step of the run (in the **dPCR Parameters** tab).



To view information about the individual steps of the run, tap **dPCR Parameters**, then tap the step that contains the details you want to view. The instrument shows the status of each step of the run and the remaining time of the current step. You can also view the parameters defined for each step.





Table 7 shows the meaning of each status icon that is shown in the dPCR parameters step.

Table 7. dPCR step status icon

Icon	Status
	The step is successfully finished.
	The step is being executed.
	The step is pending, and its execution will start after the current step is done.
	The step failed.

When the run is finished, the status of the run changes to **Done** and the **Eject**  button becomes available. To view the details about the run, tap **Show details**. To eject the plate, tap the **Eject**  button.



6.6. Continuous loading and unloading of plates

Note: The **Continuous loading and unloading of plates** function is only available on the QIAcuity Eight and QIAcuity Four instruments. To unload a plate that is currently running in the QIAcuity One instrument, you need to abort the run. For more information, see Section 6.7 Aborting a run.


On multi-plate instruments, user can load and unload plates while the instrument is running. User can load new plates, unload finished ones, or remove plates that are still in progress. To eject a tray, press the physical button on the instrument or tap **Eject tray** on the touchscreen. If any of the running plates are in the Imaging step, this process is paused. Once the changes in the tray are done, tap **Close tray** or press the physical button on the device to close the tray. The software checks the plates and displays the plate information on the screen. If any of the plates that were running before the tray was opened are missing, an error message appears and the run is stopped.

Note: If the slot where the new plate is placed is also used by a plate that is in a different module, an error message is shown on the screen and the new plate must be moved to a free slot. The drawer opens automatically, which can take up to 2 minutes. Move the plate and close the drawer to proceed.

Note: Depending on the time frame for unloading/loading of plates, the drawer opening might be delayed some time to finalize current movement steps.

6.7. Aborting a run


- If needed, a run can be stopped at any time. User can either abort all running plates or only a single running plate. To abort all runs on all plates, tap **Stop all**. Tap **OK** in the confirmation dialog box to proceed.
- To abort a single plate, tap the **Stop Run**  icon on its pane. All aborted plates return to their loading position on the tray.
- To unload the plates from the instrument, tap the **Eject**  button.



Aborting a plate during the priming/rolling step renders it unusable and the plate cannot be used and run again. A plate that has been aborted during the Thermocycling or Imaging step can be used again. To rerun the plate, configure a run with only the remaining steps. See Section 6.10 Rerunning a plate for more information.

Note: A run cannot be stopped during barcode scanning or when one or more trays are ejected.

Note: If the **Eject**  button is tapped or the physical eject button on the instrument is pressed before the plate is returned to the tray, a warning message is displayed on the screen and the tray is ejected after the plate is transported to drawer.




6.8. Error clearing


The Control Software provides an error-handling functionality to ensure that the software is in a defined state. It is designed to provide a streamlined and efficient way to manage potential system faults.

If an error appears on a specific module during the run, a notification will display under the “Alarm” notification box, for logged in users with appropriate permissions.


If the instrument was restarted after the error appeared during the run, a gray screen will display the list of errors that appeared and a **Clear errors** button to provide manual clearing of the errors without a need for instrument restart.




For a separate way to clear module-related errors, go to the **Tools > System status** panel and press the **Clear errors** button.




Confirmation is required after pressing the **Clear errors** button, as the process requires the affected modules to be reinitialized and the Control Software is blocked while this task occurs.



While the error clearing process occurs, information about the clearing status is displayed:



After the errors are cleared, an information message appears at the top of the screen, informing the user that the errors have cleared successfully. The errors no longer appear on the **System status** tab and under the “Alarm” notification box.



6.9. Automatic error clearing during the run

Multiple mechanisms have been introduced in the system to reduce interruptions and enhance workflow continuity. In case the system encounters an issue with gripping the plate, it will attempt automatic hand positioning to retrieve the plate without interrupting the run. Additionally, if the system comes across issues related to plate transportation, it will attempt to proceed with processing plates as far as possible. It will try to automatically resolve the issue and, if necessary, temporarily exclude the affected module from processing, reschedule the plate for later processing, and continue with other plates. Once the other plates are completed, the system will retry the failed plate. If the issue still occurs three times, a relevant error will be displayed on the “Alarm” notification list in the user interface (UI).

6.10. Rerunning a plate

If a plate failed or was aborted during the Thermocycling or Imaging step, it can be run again after adding new cycling or imaging steps. User can add the steps either through the instrument’s plate configurator or in the Software Suite. To add steps using the built-in plate configurator, follow the steps in Section 6.4.3 Plate configuration procedure. To use the Software Suite, refer to Section 6.4 Setting up an experiment.

Note: To modify a plate that was already used, you must remove it from the instrument. This ensures that the plate is unlocked and ready for modifications in the QIAcuity Software Suite. If modifications are desired using the plate configurator on the instrument, load the plate again.

6.11. Editing the run schedule

Note: Editing the run schedule is only possible on QIAcuity Eight and QIAcuity Four and for those users having the appropriate permissions (see Table 10).

When a run starts, it is added to the run schedule and the **Edit schedule** button is shown on the screen. If the runs are started individually, they will be added to the schedule in the order which they were started by tapping the **Run**  icon on their respective panes. If all the runs are started at the same time, using the **Run All** button, there is a default order in which the plates are run.

In QIAcuity Eight, the run starts with the first slot in the upper tray and ends with the last slot in the lower tray. The slot numbers are presented in Table 8.

Table 8. Slot numbers of the QIAcuity Eight

Tray	Slot numbers			
Upper	1	2	3	4
Lower	5	6	7	8

In QIAcuity Four, the run starts with slot number 1 and ends with slot number 4. The slot numbers are presented in Table 9.


Table 9. Slot numbers of the QIAcuity Four

Slot numbers			
1	2	3	4

To edit the run schedule, follow these steps:

Note: Only runs that are not started yet (with Pending Run status) can be rearranged.

1. On the Running Status screen, tap **Edit run schedule**.



2. Tap the row corresponding to the plate to be moved.


3. Perform one of the following actions:

- Tap **Move up** to move the plate run to an earlier position.
- Tap **Move down** to move the plate run to a later position.
- Tap **Remove** to cancel the plate run. Tap **Back to running status overview** to go back to the Running status window.

6.12. Viewing notifications

If the QIAcuity detects an error that affects the workflow of the instrument that the user can resolve, a notification displays on the screen.


To view a list of all notifications and possible solutions to the errors, tap the **Alarm**  icon. The last three errors are shown. If there are more than three errors, tap **View all** to view the full list of errors.




6.13. Disk monitoring

The **Disk Monitor** icon located in the header shows the real-time usage of the disk (free space and usage percentage). Depending on the space left, the information is shown in different colors. The **Disk Monitor** icon can appear as follows:


- **Blue** – When the disk occupation percentage is below 75% of the entire disk space



- **Yellow** – When the usage of the disk occupation rises above 75%



- **Red** – when the remaining free disk space is less than 4 GB (approx. 14%)



In case of Yellow and Red scenarios, additional information is shown to inform user about the actions that should be taken to regain disk space: forcing the clearing of images which have not been transferred to the Software Suite or setting up a connection with the Software Suite.

6.14. Logging out


Note: If a run is processing, you can still access its status, even if you log out of the instrument. For more information, refer to Section 6.14.1 Automatic logout.

To log out of the instrument, follow these steps:

1. Tap the **Logout**  icon located at the bottom right of the touchscreen.


Note: The **Logout**  button is disabled when the instrument is being calibrated or when a tray is ejected. However, you can log out when a plate is running.

2. In the Confirmation dialog box, tap **OK** to confirm or tap **Cancel** to go back.



6.14.1. Automatic logout


Users are automatically logged off after a default setting of a 15 minute period of inactivity. Time delay between user inactivity and log off can be configured manually or disabled under **Configuration > Automatic log off**. The maximum value that can be applied is 7 hours 59 minutes.



Note: For unsaved data, for example, during plate creation, an automatic log out will lead to loss of entries.

6.14.2. Accessing the run status when you are logged out

After logging out, the Login screen is displayed on the QIAcuity display. To view the run status of an ongoing run, tap **Running status**. The Running status screen is displayed in view-only mode. All functions are disabled. To perform any actions related to the run and the plates that are being processed, log into the instrument.



7. Operating the QIAcuity Software Suite

7.1. Getting started

This section describes the workspace within the QIAcuity Software Suite, its basic concepts, and the general software use.

Note: If the network connection was set up, the Software Suite can be accessed via another laptop using the IP address of the Software Suite server. Up to 10 users can access the system in parallel.

7.1.1. Software workspace

7.1.1.1. Main toolbar

The main toolbar shows navigation items. Clicking the icon navigates to the overview of the selected area. Depending on your role, not all navigation areas might be visible. An active icon becomes highlighted.



Environment area contains the **Plates**, **Templates**, **Disk monitor**, and **Archive** icons. **Tools**, **Configuration**, and **Login settings** are in the Configuration area.

7.1.1.2. Navigation areas



A plate describes each experiment and contains all information regarding the experiment such as run setup, plate layout, and analysis results. See Sections 7.3 Setting up an experiment and 7.4.14 Managing your plates for more information.



To perform an experiment multiple times, user can create templates to enable a faster setup of plates. See Sections 6.4 Setting up an experiment and 7.5.4 Creating a new reaction mix template for more information.



To operate the QIAcuity Software Suite, free disk space is needed. See Section 8.3 Regular maintenance procedure of QIAcuity for more information.



To archive plates on an external drive, user can configure the archive. See Section 7.8 Archive for more information.



Tools

The **Tools** tab contains the Troubleshooting sub-page that allows user to generate a password-protected software support package described in Section 9.5.3 Problem during the Software Suite runtime.



Configuration

In the **Configuration** tab, user can access configuration features such as Instrument name, Archive Management, User Management, and Audit Trail. Only Administrator, Supervisor, Quality Assurance, and Lab leader roles have access to this panel. See Section 7 Operating the QIAcuity Software Suite.



admin ▾

The logged-in user is shown in the main toolbar. For more information, see Section 7.2 Concepts of the QIAcuity Software Suite.

7.1.1.3. Information bar

The information bar located at the bottom of the screen displays the software version.

ON Audit trail enabled
Tracking activities

QIAcuity Software Suite 3.5.0.0 ⓘ

When the user's mouse hovers over the ⓘ icon, additional information is presented: unique Software Suite ID and build version.


Suite ID d2707bf4-11be-49ac-a9e3-c89d42af00be
Build 120.0.0.621

QIAcuity Software Suite 3.5.0.0 ⓘ

7.2. Concepts of the QlAcuity Software Suite

7.2.1. Log-in screen

The main toolbar shows which user is currently logged in. To view more information about the user, click the icon. The user can change the password, edit the user profile, and log out.



Note: Log in to QlAcuity Software Suite is independent of log in to the instrument.

1. To change the password, click **Change password**. The Change user password dialog box appears.

Change user password

Current password *

New password *

The password should contain between 8 and 100 characters, at least one lower case letter, one upper case letter, one number and one symbol (e.g. - ! \$ % ^ & * { } _ + | ~ = ' " , < > ? , / #).

Confirm password *

Cancel

Save

2. Enter the current password in the “Current password” field and the new password in the “New password” field. In the “Confirm password” field, enter the same password specified in the “New password” field. Click **Save** to change the password.
3. To edit the user profile, click **Edit profile**. The Edit User profile dialog box appears.

Edit user profile

Name *

admin

Surname *

admin


Cancel

Save

4. Enter a new name in the “Name” field and surname in the “Surname” field. Click **Save**.
5. To log out, click **Logout** to return to the home screen of the QIAcuity Software Suite.

7.2.2. User management

The QIAcuity Software Suite requires users to log in before accessing instrument functionalities. Each user must have a user account with an appropriate role assigned to it.



From QIAcuity Software Suite 2.0 and QIAcuity Control Software 2.0 onwards, the QIAcuity system offers an advanced user management that supports users meeting Good Manufacturing Practice (GMP)/Good Laboratory (GLP) regulations. The user management is centralized and controlled by the QIAcuity Software Suite only. In contrast to older software versions, users can no longer be created and edited by the instrument Control Software. All users, their roles, and their permissions are created and edited in Software Suite and are automatically transferred to the instrument Control Software, facilitating unique and synchronized user management information. From version 2.1 onwards, users can either select predefined roles or create their own by selecting proper permission.

As a consequence, all users created with older versions than SW 2.0 will be overwritten by the Software Suite user management. After completing the update to Software Suite 2.2 and CSW 2.2, users might have to be created again in Software Suite 2.2. All users created with SW 2.0 and user roles created with SW 2.1 are not affected and will remain after upgrade to later versions.

Important: For updates starting from the Software Suite 2.0 and instrument Control Software 2.0, users will be migrated and forced to change their password during the first login attempt (except the initial administrator user with login name “admin” provided by QIAGEN during the initial installation). When working with Good Manufacturing Practice (GMP)/Good Laboratory (GLP) regulations, deactivate this initial admin user (for which the password does not expire) once at least one additional user with administrator rights has been created.

The advanced User Management allows one to create, edit, activate, and deactivate the user and provide a unique login and one password for both the instrument and the Software Suite (PC). Login is entered only once and cannot be changed. In addition, each user is assigned to a specific user role (see Section 7.2.15 Default roles).

A user role is a set of permissions to features relating to the instrument or the Software Suite (PC). Each user is assigned to one role only.


The centralized user management enables independent use of the instrument Control Software and Software Suite. Regardless of which user is logged in with which role on the Software Suite, another user can log in with a different role on the instrument. Both logins are completely independent from each other.

7.2.3. Navigating in the User Management panel

1. Click the **Configuration** tab on the top bar menu.



2. Choose and click the **User Management** tab on the left-hand side menu, then select **Users view**.



7.2.4. New user creation

All activities related to creating/editing/deactivating users can be found within the **User Management** tab in the Users view.

Note: To read **Users list**, the permission to “Read users and roles” is required. To create or edit users, the permission “Create and Edit Users and Roles” is required as well.

1. If you want to create a new user, click the **New User** button.



2. Fill out the form: Name (first name), Surname, Login, and Password.

Note: There is an already existing login “System” that is reserved for special users. It cannot be selected by the Administrator when the new user is created. A warning message is shown when the Administrator tries to create a user with a reserved login.

The screenshot shows the 'NEW USER CREATION' interface for a user named 'John Doe'. The interface has a top navigation bar with icons for Photos, Templates, Disk Space, and Archive. On the right, there are icons for Tools, Configuration, and Admin. The main content area has a progress bar with two steps: '1 User information' (active) and '2 Permissions'. Below the progress bar is a form titled 'Complete user information' with the following fields: Name * (John), Surname * (Doe), Login * (johnd), and Password * (masked with dots and a toggle icon). At the bottom left is a link '← Back to Users List' and at the bottom right is a 'Next' button.

Remember that user can enter any particular user login name only once, and after user creation, it cannot be changed or used again. To create a unique login, use letters, numbers, and symbols. The minimum number of characters for the user login is 5.

3. When all information is filled out properly, click **Next** or **Permissions** to move to the next step.

This screenshot is similar to the previous one, showing the 'NEW USER CREATION' interface for 'John Doe'. The 'Login *' field now contains 'jdoe123' and the 'Password *' field is still masked. The 'Next' button is visible at the bottom right.

4. In the Permissions (second) step, one role is chosen and assigned to the user. Description of all Roles can be found below. For detailed information about roles and permissions, refer to the table “Default role permissions” or the descriptions displayed on screen in the Software Suite during the user creation process.

The screenshot shows the 'NEW USER CREATION' interface for 'John Doe'. The 'Permissions' step is active. The 'Complete user permissions' dialog is open, showing the 'Administrator' role selected. The description for the Administrator role is displayed: 'The administrator is the role outside of the laboratory being responsible to configure the system and provide individual user access and rights. Users with this role will have extensive access to the QIAcuity instrument control software and QIAcuity Software Suite including the user management and audit trail access rights.' A dropdown menu shows 'show all permissions 46/46'. Navigation buttons at the bottom include 'Back to Users List', 'Back to User information', and 'Save'.

5. Click the selected role button. Read the description and choose the desired user role.

The screenshot shows the 'NEW USER CREATION' interface for 'John Doe'. The 'Permissions' step is active. The 'Complete user permissions' dialog is open, showing the 'Operator' role selected. The description for the Operator role is displayed: 'The operator is the role inside the laboratory and is designed for Life Science projects. Users with this role will have access to all general QIAcuity instrument control software and QIAcuity Software Suite functionalities required to process plates and analyze results. Deleting plates and access to the user management are restricted for these users.' A dropdown menu shows 'show all permissions 27/46'. Navigation buttons at the bottom include 'Back to Users List', 'Back to User information', and 'Save'.

6. Show/hide the permissions list assigned to each role by clicking the **show/hide all permissions** button below the role's description.

NEW USER CREATION
John Doe

Permissions

Complete user permissions

Select role

Administrator Operator Lab leader Technician Group leader
Supervisor Quality Assurance Custom_role

Description: Operator

The operator is the role inside the laboratory and is designed for Life Science projects. Users with this role will have access to all general QIAcuity instrument control software and QIAcuity Software Suite functionalities required to process plates and analyze results. Deleting plates and access to the user management are restricted for these users.

hide all permissions 27/42

show all descriptions

Log in [Instrument and PC software] 2/2

show descriptions

Instrument

Suite Software

Instrument accesses [Instrument software] 2/3

show descriptions

Back to Users List Back to User information Save

7. Show/hide descriptions of the permissions related to particular permissions group or for all permissions at once by using the **show/hide all descriptions** button.

NEW USER CREATION
John Doe

Permissions

Complete user permissions

Select role

Administrator Operator Lab leader Technician Group leader
Supervisor Quality Assurance

Description: Operator

The operator is the role inside the laboratory and is designed for Life Science projects. Users with this role will have access to all general QIAcuity instrument control software and QIAcuity Software Suite functionalities required to process plates and analyze results. Deleting plates and access to the user management are restricted for these users.

hide all permissions 27/46

show all descriptions

Log in [Instrument and PC software] 2/2

show descriptions

Instrument

Suite Software

Back to Users List Back to User information Save

8. To go back and check or change user information, click the **Back to User information** button or the User information step in the navigation on the top of screen.

Back to Users List Back to User information Save

9. Click the **Save** button to confirm and create the user.

Save

It is possible to start with the user creation process from the Permissions step, but entries in the User information step are mandatory and will be highlighted by the software (see the next screenshot).

1. If Permissions are defined prior to User information, a yellow warning icon is displayed and the new user cannot be created until all mandatory information is entered.

1 User information — 2 Permissions

Complete user permissions

Select role

Administrator **Operator** Lab leader Technician Group leader

Supervisor Quality Assurance

Description: Operator

The operator is the role inside the laboratory and is designed for Life Science projects. Users with this role will have access to all general QIAcuity instrument control software and QIAcuity Software Suite functionalities required to process plates and analyze results. Deleting plates and access to the user management are restricted for these users.

show all permissions 27/46

2. Upon return to the User information section, all mandatory input fields will be displayed in red and must be completed so that the new user can be created and information saved.

1 User information — 2 Permissions

Complete user information

Name *
Required

Surname *
Required

Login *
Required

Password *
Required

3. If all input fields are filled out, click the **Next** button.

QIAGEN

NEW USER CREATION
John Doe

1 User information — 2 Permissions

Complete user information

Name *
John

Surname *
Doe

Login *
jdoe123

Password *

← Back to Users List

Next

4. To create the user, click the **Save** button.

NEW USER CREATION
John Doe

User information | **Permissions**

Complete user permissions

Select role

Administrator | **Operator** | Lab leader | Technician | Group leader

Supervisor | Quality Assurance

Description: Operator

The operator is the role inside the laboratory and is designed for Life Science projects. Users with this role will have access to all general QIAcuity instrument control software and QIAcuity Software Suite functionalities required to process plates and analyze results. Deleting plates and access to the user management are restricted for these users.

show all permissions 27/46

← Back to Users List

Back to User information | **Save**

At any time during user creation, it is possible to return to the Users information section by clicking the **Back to User information** button, but all data entered will be lost.

7.2.5. Editing an existing user

To edit user data, follow the instructions below:

1. Find the desired user in the Users List.

Configuration

Instrument name

Archive

User Management | **Users list**

New User

Search for users

Search

Show: Active users (2)

Login	Name	Role	Status	
admin	admin admin	Administrator	Active	
jdoe	John Doe	Operator	Active	

2. Click the **edit user** icon.



3. Three tabs related to editing user personal data and permissions are presented at the left-hand side of the screen.

The screenshot shows the 'QIAGEN' logo in the top left corner. Below it, a navigation bar contains icons for 'Photos', 'Templates', 'Disk Space', and 'Archive'. On the right side of the navigation bar, there are icons for 'Tools', 'Configuration', and 'Admin'. The main content area is titled 'USER EDITION' and 'John Doe | Operator'. On the left, there are three tabs: 'User information' (selected), 'User permissions', and 'User password'. The 'User information' tab displays the following fields: 'Name *' with the value 'John', 'Surname *' with the value 'Doe', and 'Login' with the value 'jdoe'. At the bottom left, there is a link '← Back to Users List'. At the bottom right, there is a 'Save' button.

a. **User information** tab

Click the input field and type in the new name/surname. User login name cannot be changed.

This screenshot is identical to the one above, but the 'Name *' input field, which contains the text 'John', is highlighted with a blue selection bar, indicating it is the active field for editing.

b. **User permissions** tab

Click the new desired role, and click the **Save** button.

QIAGEN

Plates

Templates

Data Space

Archive

Tools

Configuration

Admin

USER EDITION

John Doe | Operator

User information

User permissions

User password

User permissions

Select role:

Administrator

Operator

Lab leader

Technician

Group leader

Supervisor

Quality Assurance

Description: Operator

The operator is the role inside the laboratory and is designed for Life Science projects. Users with this role will have access to all general QIAcuity instrument control software and QIAcuity Software Suite functionalities required to process plates and analyze results. Deleting plates and access to the user management are restricted for these users.

show all permissions 27/46

← Back to Users List

Save

c. **User password** tab

Change the user's password.

QIAGEN

Plates

Templates

Data Space

Archive

Tools

Configuration

Admin

USER EDITION

John Doe | Lab leader

User information

User permissions

User password

User password

To change the user password, please fill out the following form:

New password *

Confirm new password *

← Back to Users List

Save

- d. In the “New password” field, enter the new password. In the “Confirm new password” field, re-enter the same password as in the “New password” field. Those passwords should be the same. If the passwords entered matched, click the **Save** button.

The screenshot shows the QIAGEN User Edition interface. The top navigation bar includes icons for Files, Templates, Disk Space, and Archive. The main header displays 'USER EDITION' and 'John Doe | Lab leader'. On the left, a sidebar menu has 'User password' selected. The main content area is titled 'User password' and contains the instruction: 'To change the user password, please fill out the following form:'. Below this are two password fields: 'New password *' and 'Confirm new password *', both masked with asterisks and featuring an eye icon to toggle visibility. At the bottom left is a 'Back to Users List' link, and at the bottom right is a 'Save' button.


- e. Finally, click the **OK** button to save the changes.

This screenshot shows the same QIAGEN User Edition interface as the previous one, but with a modal dialog box open in the center. The dialog is titled 'Save changes?' and contains the question 'Are you sure you want to edit user and save changes?'. At the bottom of the dialog are two buttons: 'Cancel' and 'OK'. The background interface is dimmed, showing the 'User password' form and the 'Save' button at the bottom right.


7.2.6. User activation

Deactivated users may be activated by users with “Activate and Deactivate User” permissions to restore their access to the system.

1. In the Users list tab, find the **Show** button. Change the option to **Deactivated users**. The Users list table shows all deactivated users.



2. Find the user to activate and click the **Activate user** icon.




3. When the **Activate** button is clicked, the user is moved to the “Active” and “All” Users list.

7.2.7. User deactivation


Users with Administrator role are able to deactivate other users to restrict access to the system.

Note: It is not possible to delete users.

1. Find the user to deactivate.
2. Click the **Deactivate user** icon.



3. Read the information in the pop-up window, and click **Yes** to confirm.



4. After the user is deactivated, all Plates assigned to this user still exhibits the user as plate owner registered, but marked as deactivated. If the user is activated again, Plate Ownership is reassigned.
5. Click the **Yes** button to deactivate the user.

7.2.8. Log in (Instrument and PC software)

1. **Instrument** — User can log in to the instrument (login and password is needed).
 - Log into the Instrument by providing credentials.
2. **Software Suite** — User can log in to the Software Suite (PC software) (login and password is needed).
 - Log into the Software Suite by providing credentials
 - Change own password
 - Modify own user data
 - name
 - surname
 - If the user does not have access to log in but provides the correct login and password, then he/she is presented with the following message: "Insufficient permissions. Please contact administrator".

7.2.9. Instrument access (Instrument software)

1. **Instrument Maintenance** — User can update the instrument, change instrument connectivity settings, and configure the auto log-off time for the instrument. User can also access system area, which includes support, testing, status, and labware synchronization.
2. **Experiment Schedule** — User can change or set the order of plates processing.
3. **Create Support Package** — User can download a support package to a USB drive and upload a support package.

7.2.10. Plates (Instrument and PC software)

Create Plate — User can set up dPCR parameters (priming, cycling, and imaging), reaction mixes (reagents), samples (control, non-control), and create a Plate layout.

- Create a new Plate (fill out General Data and scan barcode).
- Set up dPCR parameters.
- Set up a Plate layout (add/remove [before experiment run] reaction mixes, samples, and controls).

7.2.10.1. All plates

1. **Run Experiment** — User can run/stop an experiment and eject Plate(s) from instrument.

Note: "Read all Plate" required to have fully available permissions.

 - Start an experiment in the instrument.
2. **Edit Plate Data** — User can check and edit parameters of existing Plates (dPCR parameters, Plate layout (samples, reaction mixes (reagents), controls) and mark it as primed.

Note: The "Read all Plate" permission is required to have the fully available permissions.

3. **Edit Analysis Data** — User can change the threshold and use the polygon selection on the Analysis page of all Plates to verify the accuracy of the results.

Note: The “Read all Plate” permission is required to have the fully available permissions.

4. **Read Plate** — User can search for a specific Plate, see all created Plates, analyze a Plate, check details about a Plate [dPCR parameters, plate layout (samples, reaction mixes, controls)], and export results to CSV.
5. **Delete Plate** — User can delete any Plate.

Note: The “Read all Plate” permission is required to have the fully available permissions.

7.2.10.2. Owned plates

Applies only to plates for which the user is listed as Plate owner.

1. **Run Experiment** — User can run/stop an experiment and eject owned Plates from the instrument.
Note: The “Read owned Plate” or “Read all Plate” permission is required to have the fully available permissions.
2. **Edit Plate Data** — User can check and edit parameters of owned Plates (dPCR parameters, plate layout (samples, reaction mixes (reagents), controls), and mark it as primed.
Note: The “Read owned Plate” permission is required to have the fully available permissions.
3. **Edit Analysis Data** — User can change the threshold and use the polygon selection on the Analysis page of the owned Plates to verify the accuracy of the results.
4. **Read Plate** — User can search the Plate, analyze the Plate, see all created Plates, check details about owned Plates (dPCR parameters, plate layout (samples, reaction mixes, controls)], and export results to CSV.
5. **Delete Plate** — User can delete owned Plates.

Note: The “Read owned Plate” permission is required to have the fully available permissions.

7.2.10.3. Other permissions

1. **Import Plate** — User can import a Plate as a password-protected ZIP file.
Note: The “Read owned Plate” or “Read all Plate” permission is required to have the fully available permissions.
 - Import plate
 - The **Import Plate** button is visible in the Plates overview.
2. **Export Plate** — User can export a Plate as a password-protected ZIP file.
Note: The “Read owned Plate” or “Read all Plate” permission is required to have the fully available permissions.
 - Export plate
 - The **Export Plate** button is visible after clicking the three dots (...) on a plate.
 - The **Export Plate** button is visible in the Plate details view.
3. **Unlock Plate** — User can unlock locked Plates.
Note: The “Read owned Plate” or “Read all Plate” permission is required to have the fully available permissions.

- **Unlock plate**

- When a Plate is in locked status, the **Unlock Plate** button is visible in the Plate details.
- **Note:** Avoid use of the **Unlock Plate** button. If the **Unlock Plate** button is tapped during a run, the run will stop and the data will be lost. Instead, always attempt to properly unlock plate by ejecting the drawer, removing the plate, and closing the drawer. Only tap the **Unlock Plate** button in the rare situation where the plate continues to display a locked status despite being properly removed from the instrument. This can occur in situations where the run is stopped due to an instrument error.

4. **Set Plate Ownership** — User can assign owners to a plate.

Note: The “Read owned Plate” or “Read all Plate” permission and the “Edit owned Plate” or “Edit all Plate” permission are required to have the fully available permissions.

- **Set plate ownership**
 - The “plate ownership” field in plate general data is active.

5. **Upload VPF** — User can upload the Volume Precision Factor.

- **Upload VPF**
 - The **Upload VPF** button is visible in the Plates overview.
 - The **Upload VPF** button is visible in the Plate details.
- If the user does not have access rights to upload the VPF, the information displayed is changed as follows:

“The volumes of some nanoplates are not yet optimized. You can work with these results; however, to get the most accurate results, please contact your administrator”.

6. **Upgrade Plate** — User can upgrade the Plate.

Note: The “Read owned Plate” or “Read all Plate” permission is required to have the fully available permissions.

- **Upgrade plate**
 - The **Upgrade** button is visible on the plate.
 - The **Upgrade** button is visible in the Plate details view.

7. **Create Support Package** — The user can download a support package for the Plate.

Note: The “Read owned Plate” or “Read all Plate” permission is required to have the fully available permissions.

- **Create support package**
 - The **Support Package** button is visible in the Plate details.

8. **Create Report for Analysis** — User can create and generate a report using the charts and data from the Analysis of the Plate.

Note: The “Read owned Plate” or “Read all Plate” permission is required to have the fully available permissions.

- Add charts to a report.
- Check selected items for a report.
- Create a report (add report name, select or change report elements).
- Generate a report

9. **Sign Report** — User can add a signature to the report.

Note: The “Read owned Plate” or “Read all Plate” permission is required to have the fully available permissions.

- Add a signature and the reason for signing a report.

10. **Delete Report** — User can delete a report.

Note: The “Read owned Plate” or “Read all Plate” permission is required to have the fully available permissions.

- The **Delete report** button is visible in the report list section (only unsigned reports can be deleted)

7.2.11. Templates (Instrument and PC software)

If the user has any of the rights regarding templates, the following requirements apply.

The user can go to **Template** (top-bar menu). If the user does not have “Read templates” permissions, the following information is displayed:

To view templates, you need to have “Read templates” permission. Please contact the administrator to get access rights.

1. **Create Template** — User can create a new template.

Note: The “Read Plate” permission is required to be able to create a template from a plate.

- Create a new Plate template.
- Create a new Reaction mix template.
- Create a Plate Template from a plate.
- Create a Reaction mix template from a reaction mix (from the Plate level).

2. **Edit Template** — User can edit an existing template.

Note: The “Read Template” permission is required to be able to edit a template.

- Modify templates (and their parameters) – Modify Plate templates and Reaction mix templates

3. **Read Template** — The user can read information about existing Templates and use them while creating and editing plates and reaction mixes (if the user also has appropriate plate permissions). This permission provides access to all available templates.

- Go to a Template.
- Read all Templates.

- See all created Templates.
- Search Templates (and sort them).
- Create a Plate from a Template.
 - If the user also has the “create plate” permission
- Import a Template while creating a new plate or reaction mix.
 - If the user also has the “create plate” permission
- Import a Template while editing a plate or reaction mix.
 - If the user also has the “edit plate” permission

4. **Delete Template** — A user can delete existing templates.

Note: The “Read Template” permission is required to be able to delete templates.

- Delete templates
 - The **Delete** button is visible after clicking the three dots (...) on a Template.

5. **Manage Analysis rules** — User can create, edit, or delete Analysis rules.

Note: Select **Edit Template** to edit the templates and **Edit Plate Data (Owned and All)** to edit Reaction Mix.

Refer to Section 7.4.7 Analysis rules for more details.

6. **Create Custom Cross Talk Matrix** — User can create a new Custom Cross Talk Matrix and save it in a Reaction Mix Template. Please refer to Section 7.6.4 Custom cross talk matrix.

Note: The “Read Plate” and “Create Template” permission is required to be able to create a Custom Cross Talk Matrix.

7.2.12. Archive (PC software)

1. **Plate Archiving** — The user can archive a Plate.

Note: The “Read owned Plate” or “Read all Plate” permission is required to have the fully available permissions.

- a. Go to **Plates** (top-bar menu).
 - If the user does not have the “Read plates” permission, then the following information is displayed:
 “In order to view plates, you need to have “Read plates” permission. Please contact administrator to get access rights”.
- b. Archive the Plate (all/owned).
 - The **Archive** button is visible after clicking the three dots (...) on a plate.
 - The **Archive** button is visible in the Plate details.

2. **Archive Overview** — The user has access to the list of archived Plates. The user can see all archived Plates, search for archived Plates, and check general information about the archived Plate and disk space usage for the Archive in the Disk Space monitor.

- a. Go to the **Archive** and the Disk Space monitor.
- b. See the archive disk space (in the Disk space monitor).

- c. See the archived plate.
- d. Search the archived Plate (sort by Archived date, Plate name, Plate statuses, time frame, and change view).
- e. See the archived plate general data.

3. **Restore a Plate from the Archive** — User can restore archived Plates.

Note: The “Archive Overview” permission is required to have the fully available permissions.

- a. Go to the **Archive** and the **Disk Monitor**.
 - If the user does not have the “Archive overview” permission, the following information is displayed:
In order to view archived plates, you need to have “Archive overview” permission. Please contact administrator to get access rights.
- b. Restore a plate from the archive.
 - The **Restore** button is visible after clicking the three dots (...) on a plate.
 - The **Restore** button is visible in the Plate details.

4. **Delete Plate from Archive** — The user can delete any plate from the Archive.

Note: The “Archive Overview” permission is required to have the fully available permission.

- a. Go to the **Archive**.
 - If the user does not have the “Archive overview” permissions, the following information is displayed:
To view archived plates, you need to have “Archive overview” permission. Please contact administrator to get access rights.
- b. Delete a plate from the archive.
 - The **Delete** button is visible after clicking the three dots (...) on a plate.
 - The **Delete** button is visible in the Plate details.

7.2.13. User management (PC software)

1. **Read Users and Roles** — The user can see the list of users and the list of roles in the system.

- a. Go to the **Configuration** panel.
- b. Go to the **User Management** tab.
- c. Go to the **Users** tab in the **User Management** tab.
- d. See the list of users.
- e. Search users.
- f. Go to the **Roles** tab in the **User Management** tab.
- g. See the list of roles.

2. **Create and Edit Users and Roles** — User can create and edit a user and create and edit a role.

Note: The “Read user and roles” permission is required to have the fully available permission, otherwise the following information is displayed:

To view users/roles list, you need to have “Read users and roles” permission. Please contact administrator to get access rights.

- a. Go to the **Configuration** panel.
- b. Go to the **User Management** tab.
- c. Go to the **Users** tab in the **User Management** and create new users or edit exiting users.
- d. Go to the **Roles** tab in the **User Management** and create new roles, see permissions list or see users list that are assigned to role and edit existing roles.

Note: The roles designed for GMP/GLP (Administrator, Operator, Lab leader, Technician, Group Leader, Supervisor, and Quality Assurance) cannot be edited.

3. **Activate and Deactivate User** — The user can activate and deactivate a user.

Note: The “Read users and roles” permission is required to have the fully available permissions, otherwise the following information is displayed: “In order to view users, you need to have “Read users and roles” permission. Please contact administrator to get access rights.”

- a. Go to the **Configuration** panel.
- b. Go to the **User Management** tab.
- c. Go to the **Users** tab in the **User Management** and can deactivate user and activate (again) deactivated user.

4. **Delete Role** — User can delete existing roles in the system.

Note: The “Read users and roles” permission is required to have the fully available permission, otherwise the following information is displayed: “In order to view users, you need to have “Read users and roles” permission. Please contact administrator to get access rights.”

- a. Go to the **Configuration** panel.
- b. Go to the **User Management** tab.
- c. Go to the **Roles** tab in the **User Management** and can delete a particular role if no users are assigned to it.

Note: Roles designed for GMP/GLP (Administrator, Operator, Lab leader, Technician, Group Leader, Supervisor, and Quality Assurance) cannot be deleted.

If some users are assigned to a role the deletion of the role is not possible.

5. **Manage password expiration** — User can change password expiration timeframe.

- a. Go to the Configuration panel.
- b. Go to the **User management** tab.
- c. Go to the **Account Security** tab.
- d. Set password expiration time from 1 to 365 days, or disable the feature completely so that passwords never expire.

7.2.14. System configuration (PC software)

1. **Registered Instrument** — The user can see a list of the registered instruments.
 - a. Go to the **Configuration** panel.
 - b. Go to the **Instrument names** tab.
 - c. See the list of registered instruments.
2. **Manage Archive** — The user can edit the Archive location, detach the Archive, turn on/off, and configure the automatic archiving.
 - a. Go to the **Configuration** panel.
 - b. Go to the **Archive** tab.
 - c. Edit the archive location.
 - d. Detach the archive.
 - e. Set automatic archiving and its parameters.
3. **Manage Lab Automation** — The user can manage Lab Automation. For more details, refer to the dedicated *QIAcuity Lab Automation Service User Guide*.
 - a. Go to the **Configuration** panel.
 - b. Go to the **Lab Automation** tab.
 - c. Switch **ON** the Lab Automation API.
 - Download/Copy the generated Lab Automation API key.
 - Generate a new key.
4. **Audit Trail configuration**
 - a. **View Audit Trail** — The user can see the list of the Audit Trail events, search for specific events, check details of an event, and export it to PDF.
 - Go to the **Configuration** panel.
 - Go to the **Audit trail** tab in the configuration panel.
 - Go to the events list.
 - See audit trail data.
 - Filter audit trail data.
 - Export audit trail data.
4. **Turn Audit Trail on and off** — The user can turn on/off the Audit Trail (events tracker).
 - a. Go to the **Configuration** panel.
 - b. Go to the **Audit trail** tab in the **Configuration** panel.
 - c. Go to the Audit trail tracker settings.
 - Turn audit trail on and off.

7.2.15. Default roles

This section describes roles available in the QIAcuity Software Suite and QIAcuity Control Software. Roles may be viewed as the set of permissions and are designed in a way to suit laboratories that need to fulfill Good Manufacturing Practice (GMP)/Good Laboratory (GLP) regulations and Research Use Only (RUO) laboratories as well.

Admin, Supervisor, Group leader, Technician, and Quality Assurance are predefined roles designed for GMP/GLP laboratories, whereas Admin, Lab leader, and Operator are designed for RUO laboratories.

Note: All predefined roles cannot be edited or deleted.

1. Administrator

The administrator is the role of the laboratory responsible for configuring the system and providing individual user access and rights. Users with this role have extensive access to the QIAcuity Control Software and QIAcuity Software Suite including the user management and audit trail access rights.

2. Supervisor

The supervisor has extensive access to QIAcuity Control Software and QIAcuity Software Suite functionalities required to process plates and analyze results. Users with this role cannot delete plates and templates, cannot unlock or archive plates, and cannot access the user management. The audit trail functionality is limited to viewing the list of events and providing event details.

3. Group leader

The group leader has access to QIAcuity Control Software and QIAcuity Software Suite functionalities required to process plates, analyze results, and manage archived plates but only for the plates the group leader owns. Users with this role cannot delete plates and templates, cannot unlock plates, and cannot access the user management and audit trail.

4. Technician

The technician has limited access to the QIAcuity Control Software and QIAcuity Software Suite. Users with this role can process (create, run) their own plates and use existing templates to run an experiment.

5. Quality Assurance

The quality assurance role has the rights to check all information about the plate, can import plates, and can create and sign reports. Users with this role have audit trail read access, consisting of viewing and searching events, and showing event details. They can also export audit trail for external review.

6. Lab leader

The lab leader role is designed for RUO labs. Users with this role have extensive access to all QIAcuity Control Software and QIAcuity Software Suite functionalities required to process plates and analyze results. This role also allows for basic user management functionalities to read user descriptions and their permissions.

7. Operator

The operator role is designed for RUO. Users with this role have access to all general QIAcuity Control Software and QIAcuity Software Suite functionalities required to process plates and analyze results. This role cannot delete plates and does not have access to the User management.

Table 10. Default role permissions

	Administrator	Supervisor	Group leader	Technician	Quality Assurance	Lab leader	Operator
Log in							
Instrument	X	X	X	X	X	X	X
Suite Software	X	X	X	X	X	X	X
Instrument accesses							
Instrument Maintenance	X					X	
Experiment Schedule	X	X	X	X		X	X
Create Support Package	X	X	X	X		X	X
Plates							
Create Plate	X	X	X			X	X
All Plates							
Run Experiment	X	X				X	X
Edit Plate Data	X	X				X	X
Edit Analysis Data	X	X				X	X
Read Plate	X	X			X	X	X
Delete Plate	X					X	
Owned Plates							
Run Experiment	X	X	X	X		X	X
Edit Plate Data	X	X	X	X		X	X
Edit Analysis Data	X	X	X	X		X	X
Read Plate	X	X	X	X		X	X
Delete Plate	X					X	
Other permissions							
Import Plate	X	X	X		X	X	X
Export Plate	X	X	X			X	X
Unlock Plate	X					X	
Set Plate Ownership	X	X	X			X	X
Upload VPF	X	X				X	
Upgrade Plate	X	X	X			X	X
Create Support Package	X	X	X	X		X	X
Create Report for Analysis	X	X	X		X	X	X
Sign Report	X	X	X		X	X	X
Delete Report	X					X	X
Templates							
Create Template	X	X	X			X	X
Edit Template	X	X	X			X	X

Table 10. Default role permissions (continued)

	Administrator	Supervisor	Group leader	Technician	Quality Assurance	Lab leader	Operator
Read Template	X	X	X	X	X	X	X
Delete Template	X	X				X	
Manage Analysis rules	X		X			X	
Create Custom Cross Talk Matrix	X		X			X	
Archive							
Plate Archiving	X	X	X			X	X
Archive Overview	X	X	X		X	X	X
Restore Plate from Archive	X	X	X		X	X	X
Delete Plate from Archive	X					X	
User Management							
Read Users and Roles	X				X	X	
Create and Edit Users and Roles	X						
Activate and Deactivate User	X						
Delete Role	X						
Manage password expiration	X						
System Configuration							
Registered Instruments	X					X	
Manage Archive	X					X	
Manage Lab Automation	X						
Audit Trail Configuration							
View Audit Trail	X	X			X	X	
Audit Trail Toggle	X						

X – role has access to this permission


This section describes how the functionalities in the application are impacted by permissions, which are assigned to user roles. Pay special attention to notes, because some permissions require other ones to work – notes become visible after checking checkbox.

7.2.16. New role creation

All activities related to creating/editing/deleting roles and a list of existing roles can be found within the **User Management** tab in the Roles view.

Note: To read the roles list, the “Read users and roles” permission is required. To create or edit users, the “Create and Edit Users and Roles” permission is required as well.


1. To create a new role, click the **New Role** button.



The screenshot shows the QIAGEN User Management interface. The top navigation bar includes icons for Files, Templates, Disk Space, and Archive, along with Tools, Configuration, and a user profile icon. The left sidebar shows the Configuration menu with options for Instrument name, Archive, User Management (selected), Account Security, Audit Trail, and Lab Automation. The main content area is titled 'Roles list' and features a 'New Role' button. Below the button is a table listing predefined roles.

Role name	Created by	Creation date and time	Assigned users
Quality Assurance	Predefined	17/04/2026, 14:38:47 UTC+02:00	0
Supervisor	Predefined	17/04/2026, 14:38:46 UTC+02:00	0
Group leader	Predefined	17/04/2026, 14:38:46 UTC+02:00	0
Technician	Predefined	17/04/2026, 14:38:45 UTC+02:00	0
Lab leader	Predefined	17/04/2026, 14:38:45 UTC+02:00	1
Operator	Predefined	17/04/2026, 14:38:43 UTC+02:00	0
Administrator	Predefined	17/04/2026, 14:38:41 UTC+02:00	1

2. Fill out the form: role name and role description.



The screenshot shows the 'ROLE EDITION' form for 'custom_role'. The left sidebar has 'Role information' selected. The main form area is titled 'Role information' and contains two input fields: 'Role name' (with a character count of 29) and 'Role description' (with a character count of 489). At the bottom, there is a 'Back to Roles List' link and a 'Save' button.

3. When all information is filled out properly, click **Next** or **Permissions** to move to the next step.

4. In the Permissions (second) step, user needs to choose the permissions that will be assigned to the role. To speed up selection, use predefined roles as templates and adjust permissions to your needs, then save as new role. Every permission has its own description that can be shown or hidden similarly as when creating or editing users. Some permissions display useful notes, for example, which permissions should be selected together.

NEW ROLE CREATION
custom_role

1. Role name 2. Permissions

Complete role's permissions

To speed up selection you can use predefined roles:

Administrator Operator Lab leader Technician Group leader
Supervisor Quality Assurance

hide all permissions 26/46
show all descriptions

☐ Log in [Instrument and PC software] 1/2
show descriptions
☐ Instrument
☒ Suite Software

☐ Instrument accesses [Instrument software] 2/3
show descriptions

← Back to Roles list Back to Role name Save

5. To go back and check or change the role name, click the **Back to Role name** button or click the Role name step in the stepper.

← Back to Roles list

Back to Role name

Save

6. Click the **Save** button to confirm and create the role.

Note: All entries need to be completed under Role name before moving to the Permissions step. The software will indicate any missing information in the Role name step. If any information under Permissions has been entered before having completed all required entries under Role name, all entries will be lost when you hit the **Back to Role name** button.

Note: Creation of a new role needs to be completed by pressing the **Save** button. Otherwise, all changes will be lost in case the **Back to Roles list** is pressed.

From the Roles list, check permissions by pushing the **Permissions list** button.



Permissions list - custom_role

hide all permissions 26/46

show all descriptions

Log in [Instrument and PC software] 1/2

show descriptions

Instrument

☒ Suite Software

Instrument accesses [Instrument software] 2/3

show descriptions

Instrument Maintenance

☒ Experiment Schedule

☒ Create Support Package

Plates [Instrument and PC software] 17/21

show descriptions

☒ Create Plate

Close

Pressing the **Users list** button directs user to the list of all users and their status.



custom_role - Users list

User name	User login	Status	
1. John Doe	jodoe	Active	

Close

7.2.17. Editing existing role

Note: Editing a role requires the “Create and Edit Roles” permissions. Only roles created by users can be edited. Predefined roles cannot be edited.

To edit a role, follow the instructions below:

1. On the roles list, find the role for editing and click the **Edit role** button.

The screenshot shows the QIAcuity Configuration page. On the left, there is a sidebar with navigation options: Instrument name, Archive, User Management (selected), Account Security, Audit Trail, and Lab Automation. Under User Management, there are tabs for Users and Roles (selected). The main area displays the 'Roles list' with a 'New Role' button and a table of roles.

Role name	Created by	Creation date and time	Assigned users	Edit role
custom_role	User	20/04/2026, 15:53:21 UTC+02:00	1	
Quality Assurance	Predefined	17/04/2026, 14:38:47 UTC+02:00	0	
Supervisor	Predefined	17/04/2026, 14:38:46 UTC+02:00	0	
Group leader	Predefined	17/04/2026, 14:38:46 UTC+02:00	0	
Technician	Predefined	17/04/2026, 14:38:45 UTC+02:00	0	
Lab leader	Predefined	17/04/2026, 14:38:45 UTC+02:00	0	
Operator	Predefined	17/04/2026, 14:38:43 UTC+02:00	0	
Administrator	Predefined	17/04/2026, 14:38:41 UTC+02:00	1	

2. Two tabs related to role information and role permissions are on the left-hand side.


The screenshot shows the 'ROLE EDITION' page for 'custom_role'. On the left, there are two tabs: 'Role information' (selected) and 'Role permissions'. The 'Role information' tab contains two input fields: 'Role name *' with a character count of 29, and 'Role description *' with a character count of 489. At the bottom left, there is a 'Back to Roles List' link, and at the bottom right, there is a 'Save' button.

a. Role information tab


Change role name and description. To edit a user name or surname, click the input field and type the new value.

b. **Role permissions** tab

Change permissions assigned to a role. Select permissions using checkboxes, then click the **Save** button.



- c. When there are users assigned to the role being modified, a pop-up window appears after the **Save** button is pressed, showing a list of users that will be impacted by the change.



- d. To confirm changes, click the **Yes, edit role** button.

If no users are assigned to the role being modified, the confirmation window will not appear.

7.2.18. Role deletion

Note: Deleting a Role requires the “Delete role” permission. Only roles created by users with no users assigned can be deleted. Predefined roles cannot be deleted.

To delete a role, find the role for deletion on the roles list and click the **Delete role** button.

The screenshot shows the QIAGEN Configuration interface. On the left is a sidebar with navigation links: Instrument name, Archive, User Management (selected), Account Security, Audit Trail, and Lab Automation. The main content area is titled 'Configuration' and has tabs for 'Users' and 'Roles' (selected). Under 'Roles', there is a 'New Role' button and a table titled 'Roles list'.

Role name	Created by	Creation date and time	Assigned users	Delete role
custom_role	User	20/04/2026, 15:53:21 UTC+02:00	0	
Quality Assurance	Predefined	17/04/2026, 14:38:47 UTC+02:00	0	
Supervisor	Predefined	17/04/2026, 14:38:46 UTC+02:00	0	
Group leader	Predefined	17/04/2026, 14:38:46 UTC+02:00	0	
Technician	Predefined	17/04/2026, 14:38:45 UTC+02:00	0	
Lab leader	Predefined	17/04/2026, 14:38:45 UTC+02:00	0	
Operator	Predefined	17/04/2026, 14:38:43 UTC+02:00	0	
Administrator	Predefined	17/04/2026, 14:38:41 UTC+02:00	2	

Note: If users are assigned to the role, the **Delete role** button becomes inactive (gray) and a tooltip is presented indicating that the role cannot be deleted.

This screenshot is similar to the previous one, but the 'custom_role' now has 1 assigned user. The 'Delete role' button is now gray and inactive. A tooltip is visible over the button with the text: 'The role cannot be deleted because it is assigned to some users.'

Role name	Created by	Creation date and time	Assigned users	Delete role
custom_role	User	20/04/2026, 15:53:21 UTC+02:00	1	
Quality Assurance	Predefined	17/04/2026, 14:38:47 UTC+02:00	0	
Supervisor	Predefined	17/04/2026, 14:38:46 UTC+02:00	0	
Group leader	Predefined	17/04/2026, 14:38:46 UTC+02:00	0	
Technician	Predefined	17/04/2026, 14:38:45 UTC+02:00	0	
Lab leader	Predefined	17/04/2026, 14:38:45 UTC+02:00	0	
Operator	Predefined	17/04/2026, 14:38:43 UTC+02:00	0	
Administrator	Predefined	17/04/2026, 14:38:41 UTC+02:00	1	


7.2.19. Account security

From QIAcuity Software Suite version 3.5, it is possible to configure a password expiration timeframe. Modifying these settings requires the dedicated permission “Manage password expiration.” For more information, refer to Section 7.2.2 User management. By default, this permission is assigned only to the Administrator role but can be added to any customized role.

Note: The password expiration is a general Software Suite setting and is valid for all users.


To change password expiration settings, follow the instructions below:

1. Log in to the application.
2. From the top application bar, select **Configuration**.
3. Navigate to the **Account Security** tab.
 - a. When the toggle is disabled, password expiration is turned off and users’ passwords never expire.



- b. When the toggle is enabled, a password expiration period must be defined. A value between 1 and 365 days can be set. After this period, all users are prompted by the system during login to change their password.

Note: By default password expiration is enabled and set to 30 days.




4. After saving the changes, the settings take effect immediately and an Audit Trail event is generated.

7.3. Setting up an experiment

This section provides information about the steps required to set up a new experiment.

7.3.1. Creating a new plate

1. Click **Plates** in the main toolbar to enter the plates environment.



2. Click **New Plate**.



3. Refer to Table 11 to provide the following information in each tab:

General Data
dPCR parameters
Reaction mixes
Samples & controls
Plate layout
Report template

Table 11. Steps in creating a plate

Tab	Steps
General data	Enter the basic information about the plate: • Plate name • Plate type • Description • Labels • Plate ownership • Barcode
dPCR parameters	Specify the following information: • Priming profile • Cycling • Imaging

Table 11. Steps in creating a plate (continued)

Tab	Steps
Reaction mixes	Provide the following information for a new reaction mixes: • Reaction mix name • Color • Target Name • Dye • Channel • Amplitude multiplexing • Analysis rules
Samples & Controls	Specify the following information for a new sample: • Sample name • Labels • Concentration factor • Template volume • Conversion factor • Unit • Amount • Description Specify the following information for a new control: • Control name • Concentration factor • Template volume • Conversion factor • Unit Specify the following information for a new non-template control • Non Template Control name • Concentration factor • Template volume • Conversion factor • Unit
Plate layout	Provide the following information: • Add reaction mix • Add sample • Add control • Add NTC • Mark as blank
Report template	• Report name • Reaction mixes • General report settings • Analysis • Report file(s)

7.4. Plate configurator

7.4.1. Defining general data

In the **General Data** tab, specify the basic information about the plate. Mandatory input fields are marked with an asterisk. The plate name is required to save a plate.

Note: Make sure that the selected plate type corresponds with the entered barcode, if manually entered. If they do not match, it will lead to an error on the instrument (error 205).

Table 12. General Data tab

Field	Field Help
Plate name	Specify the name of the plate.
Plate type	Select the plate type from the list. You can select Nanoplate 26K 8-well, Nanoplate 26K 24-well, Nanoplate 8.5K 24-well, or Nanoplate 8.5K 96-well.
Description	Enter a descriptive information about your experiment.
Labels	Add labels to your plate to help you categorize your experiments.
Plate ownership	Enter users that should be allowed to view and edit the plate according to their permissions. More than one user can be a Plate owner.
Barcode	Enter the barcode that is located on the side of the plate. Barcodes are unique to each plate and can only be used once.

7.4.2. Plate ownership

The Plate Ownership allows users to assign one or more users to a specific plate. A user who creates a new plate, imports a plate, or restores a plate from the archive is assigned automatically as an owner of the plate.

Note: For imported or restored plates, the operating user will automatically be added as the plate owner if no plate owner is already assigned to the plate or if the assigned plate owner is deactivated. For upgraded plates, owners from the original plate will be preserved if they exist in the current QIAcuity Software Suite; otherwise, the operating user will be set as the plate owner.

7.4.3. Assigning the owner of the plate

1. On the **Plates** tab (Plates Overview), find the plate to which ownership must be assigned.
2. In the **General Data** tab, the “Plate Ownership” field is displayed (below “Labels”).

The screenshot shows the 'PLATE CONFIGURATOR' interface for a plate named 'plate'. The 'General Data' tab is active. The left sidebar contains a menu with options: General Data, qPCR parameters, Reaction mixes, Samples & controls, Plate layout, Report template, Reports, Export, Support package, Delete, and Plate Audit Trail. The main area displays the 'General Data' form. It includes a warning about VPF (Volume Precision Factor) file, fields for Plate name, Plate type (set to 'Nonplate 9.5K 96-well'), Description, Labels, and Plate Ownership. The Plate Ownership field currently shows 'admin admin (admin)' with an 'add user' button. A 'Barcode' field is also present at the bottom. Navigation buttons at the bottom include 'Back to plates', 'Save changes', and 'Done'.

3. Click the “Plate Ownership” input field.

This close-up shows the 'Plate Ownership *' input field. It contains the text 'admin admin (admin)' followed by an 'add user' button. Below the input field, a hint reads: 'Type user name, surname or login to add user'. A close button (X) is visible on the right side of the input field.

4. Start writing the name/surname/login.

This close-up shows the 'Plate Ownership *' input field with a dropdown list. The input field contains 'admin admin (admin)'. The dropdown list is open, showing a search bar and a list of users, with 'John Doe (jodoe)' visible at the bottom.

5. Choose the user from the drop-down list by clicking the chosen name.

This close-up shows the 'Plate Ownership *' input field with the dropdown list closed. The input field contains 'admin admin (admin)'. The dropdown list is open, showing a search bar and a list of users, with 'John Doe (jodoe)' visible at the bottom.

6. User has been added.

Plate Ownership *

admin admin (admin) [close]

John Doe (jodoe) [close]

add user

Type user name, surname or login to add user

7. To add another user, begin typing the name/surname/login; user will appear in the drop-down list and can be chosen as desired.
8. Click the **Done** button to save changes.

7.4.4. Removing an owner of the plate

1. To remove one owner of a plate, click the **close** button placed within the user name tag.

John Doe (jodoe) [close]

2. To remove all owners, click the **clear** button on the end of the input field.

Plate Ownership *

admin admin (admin) [close]

John Doe (jodoe) [close]

add user

Type user name, surname or login to add user

Clear

3. Click the **Done** button to save changes.


7.4.5. Defining the dPCR parameters

The run profile of each experiment is configured in the **dPCR parameters** tab. This tab is divided into three subtabs: **Priming**, **Cycling**, and **Imaging**.

The screenshot displays the QIAcuity Plate Configurator interface. The top navigation bar includes icons for Plates, Templates, Data Space, and Archive. The main header shows 'PLATE CONFIGURATOR plate' and a 'Drafted' status with a 'Plate ID: 51e8091b-a077-4d89-ab17-29975e0a7831'. The left sidebar contains a list of tabs: General Data, dPCR parameters (selected), Reaction mixes, Samples & controls, Plate layout, Report template, Reports, Export, Support package, Delete, and Plate Audit Trail. The main content area is divided into three subtabs: Priming (selected), Cycling, and Imaging. Under the Priming subtab, there are two radio button options: 'QIAcuity Priming Profile Probe (RT-) PCR specific priming for QIAcuity Probe based (RT-) PCR Kits' and 'QIAcuity Priming Profile EvaGreen (RT-) PCR specific priming for QIAcuity EvaGreen based (RT-) PCR Kits'. A 'Recommended next step: Cycling' is indicated. At the bottom, there are buttons for 'Back to plates', 'Save changes', and 'Done'.

7.4.5.1. Priming tab


Select the priming profile applicable for the plate and your type of experiment in the **Priming** tab.



Alternatively, click **More** to expand the section and select the “No priming” option. Use this option if priming has already been performed outside the instrument.



7.4.5.2. Cycling tab



Define the temperature profile of each experiment in the **Cycling** tab. To do this, follow these steps:

1. In the "Temperature" field, specify the temperature of the step, then specify the duration of the temperature step in the "Duration" field.
2. Click **Add Temperature Step**.
3. The temperature step is added to your cycling profile.
4. Repeat steps 1–2 for all temperature steps.

Note: Use the up and down arrows to arrange the order of the temperature steps.

5. Check the box corresponding to the desired temperature steps for the repeated cycling. Then, click **Group**.
6. In the first column of the grouped temperature steps, add the number of cycles.

Note: To separate the grouped temperature steps, check the box corresponding to the group, then click **Ungroup**. To delete a temperature step, check the box corresponding to the step, then click **Delete**. The three-dotted icon in each temperature step enables you to edit or delete the step.

Important: Temperature values between 40°C and 99°C can be entered.

7.4.5.3. Gradient cycling



Working with non-optimized annealing temperatures in PCR can influence the sensitivity or specificity of the amplification reaction. On the one hand, low annealing temperatures can lead to unspecific binding and amplification of unwanted products; on the other hand, too high annealing temperatures could cause the exclusion of the desired product.

The essential temperature gradient function allows for cycling at different temperatures across the columns of a QIAcuity Nanoplate. This feature shall support assay development to easily identify optimal temperature in a single plate run.

The temperature gradient functionality can be used with every QIAcuity instrument type running with QIAcuity Software Suite version 2.5 or higher. The temperature gradient functionality has been developed based on the integrated cycler included in all QIAcuity instruments, allowing users of older instruments to also take advantage of this new feature. The QIAcuity Software Suite offers a functionality to run a temperature gradient on a QIAcuity Nanoplate 8.5K 96-well, only. However, the optimal temperature defined for a QIAcuity Nanoplate 8.5K 96-well can be transferred to all other QIAcuity Nanoplate formats.


Two pre-defined temperature ranges are available. A temperature range from 55°C to 42°C is for RT-PCR related applications and a range from 64°C to 52°C is for standard PCR-related applications. The temperature distribution per well (based on the selected gradient can be previewed and provided in the Plate layout within the QIAcuity Software Suite.

Note that the two different gradient cycling profiles cannot be combined within one plate. Furthermore, the pre-defined temperature ranges cannot be modified and no custom temperature profiles can be created.



Selection of optimum temperature can be based on multiple criteria. The most common criteria are the signal-to-noise ratio (S/N), the presence or absence of rain, and concentration results. The selected optimum temperature should allow the highest signal-to-noise ratio, minor to no rain, and that the obtained concentration reflects the expected results. Finding the optimum temperature is also important to minimize primer mismatch, which could lead to cross-hybridization issues in a multiplex reaction mix.

The selected optimal condition can be verified by a new plate run using the standard cycling program with the optimum temperature found after using the gradient cycling functionality.



Example of gradient temperature cycling results.

The first and last rows (rows A & H) of a QIAcuity Nanoplate 8.5K 96-well are not available for the gradient functionality. There is no possibility within the QIAcuity Software Suite to add reaction mixes and samples/controls to the disabled wells.

7.4.5.4. Imaging tab

The **Imaging** tab enables user to set the respective exposure duration and gain value for each channel. The channel options depend on the connected instrument. The QIAcuity multiplex instruments support dPCR assays up to 8-plex by using six optical channels for six standard dyes and the additional use of two channel combinations for LSS (Long Stokes Shift), which can be selected from five different channel combinations. The QIAcuity One, 2 plex, offers only two detection channels. The following table shows the available channels provided for each instrument.

Note: The instruments offer an exposure duration from 1 to 4000 ms and a gain value of 0–40 dB.

QIAAGEN

Plates

Templates

Disk Space

Archive

Tools

Configuration

Admin

PLATE CONFIGURATOR

plate

Drafted Plate ID: 51e8091b-a077-4d89-ab17-29975e0a7831

Plate templates...

General Data

dPCR parameters

Reaction mixes

Samples & controls

Plate layout

Report template

Reports

Export

Support package

Delete

Plate Audit Trail

Priming

Cycling

Imaging

Enable High-Multiplexing-Reference channel

Channel

Exposure duration

Gain

Green

300

ms

6

Yellow

250

ms

4

Channels available for high multiplex instruments only

Orange

150

ms

3

Red

150

ms

3

Crimson

300

ms

4

Far red

ms

Select channel

ms

Select channel

ms

Recommended next step: Reaction mixes

QIAcuity User Manual | 07/2026

145

Table 13. QIAcuity instruments and their available channels

Instrument	Available channels
QIAcuity One, 2plex	Green Yellow
QIAcuity One	Green Yellow Orange Red Crimson Far red + two combinations: Green/Yellow, Yellow/Orange, Orange/Red, Red/Crimson, Crimson/Far red
QIAcuity Four	Green Yellow Orange Red Crimson Far red + two combinations: Green/Yellow, Yellow/Orange, Orange/Red, Red/Crimson, Crimson/Far red
QIAcuity Eight	Green Yellow Orange Red Crimson Far red + two combinations: Green/Yellow, Yellow/Orange, Orange/Red, Red/Crimson, Crimson/Far red

7.4.5.5. High multiplexing

On all QIAcuity instruments (excluding QIAcuity One, 2 plex), high multiplex experiments, up to 8-plex analysis can be performed by using six optical channels for six standard dyes and the additional use of two channel combinations for LSS (Long Stokes Shift) dyes. Two out of five different LSS channel combinations (Green/Yellow, Yellow/Orange, Orange/Red, Red/Crimson, Crimson/Far red) require the High-Multiplexing Reference channel. If any of the above channels is selected on the **Imaging** tab, the system will automatically enable the required reference channel and the user cannot disable it. It is also possible to activate the High-Multiplexing Reference channel for standard channel usage.

Using High-Multiplexing Reference channel allows to perform additional multiplexing type – Amplitude multiplexing on each type of optical channel and channel combinations. Refer to Section 7.6.11 Amplitude multiplexing and 7.6.15 Absolute quantification for more details.

Note: Enabling the High-Multiplexing Reference channel requires using the QIAcuity High Multiplex Kit, which includes a reference dye dedicated for high multiplexing purposes.

The following actions can be performed when each run is finished:

1. To reimage the plate with different settings, click **+**, then select **Imaging**.
2. To rerun the plate with additional cycles, click **+**, then select **Cycling + Imaging**.
 - a. **Important:** After a run is finished, remove the plate from the instrument before adding a new imaging or cycling + imaging step.




Note: For QIAcuity Software Suite v2.0 or higher, dust detected in one channel is used for identifying dust in other channels as well. If required, to improve dust detection, always image in all channels even when they are not used by the assay(s).


7.4.6. Reaction mixes tab

Create a new reaction mix or import a reaction mix from a template for each experiment (plate) on the **Reaction mixes** tab.

The **General View** tab displays the name of all reaction mixes used in the plate.



The **Detailed List** view tab displays detailed information about the reaction mixes assigned to a plate.



Note: For each reaction mix,  icon is indicating that the reaction mix is not assigned to any well on the **Plate layout** tab (described in the next section); otherwise,  icon is displayed.

7.4.6.1. Creating new reaction mix

To create a new reaction mix:

1. Click **New Reaction Mix**.
2. The New Reaction Mix window appears.

New Reaction Mix

Reaction mix creation Add Analysis Rules

Reaction mix name * Characters left: 100 Total volume µL Change color

Amplitude multiplexing

Color	Target Name *	Dye	Channel(s) *	Internal control	
☐	Name	Select	Select channel	☐	
☐	Name	Select	Select channel	☐	
☐	Name	Select	Select channel	☐	
☐	Name	Select	Select channel	☐	
☐	Name	Select	Select channel	☐	
☐	Name	Select	Select channel	☐	
☐	Name	Select	Select channel	☐	
☐	Name	Select	Select channel	☐	

Cancel Create

3. Enter the name of the reaction mix in the “Reaction mix name” field. The name must be unique and must not contain any special characters. Up to 100 characters can be entered in this field.
4. Click the **Change color** button to select a color for the reaction mix.
5. **Optional:** To use the dilution calculation function during the analysis, enter the value in the “Total volume” field. Refer to Section 7.6.14.7 Dilution calculation option for further details.

Enter a target name in the “Target Name” field. The name must be unique and must not contain any special characters. Up to 40 characters can be entered in this field.

Note: The “Color box” shows the color of the single target in the reaction mix.

6. **Optional:** For amplitude multiplexing target definition, expand Section 7.6.11 Amplitude multiplexing and use checkboxes to select the channel/s for which amplitude multiplexing target option should be applied or use the option **select all**. The selected channel/s will be subdivided into High and Low for dedicated target definition.

Note: Amplitude multiplexing requires the use of the High-Multiplexing Reference channel. If this option is selected, a warning is displayed to ensure that the High-Multiplexing Reference channel is enabled in the imaging settings.

7. Select the channel from the channel list where each target is detected.
 8. **Optional:** Select the dye of the target from the dye list. Selecting a dye automatically sets the associated channel in the Channel list. Recommended dyes for particular channels are collected and presented in Table 2 in this user manual.
 9. If the target is an internal control, check the “Internal control” box.
- Note:** Clicking the trash icon deletes all entries in the corresponding row.
10. Click **Create**.
 11. The reaction mix is added to the database and can be used for the experiment.

7.4.7. Analysis rules

From QIAcuity Software Suite version 3.5 onward, analysis of a dPCR run can be automated through analysis rules assigned to individual reaction mixes. This allows different reaction mixes within the same experiment to use different analysis rules. The primary purpose of the analysis is to define threshold settings and ensure quality control of the results.

Note: Analysis rules can be configured for both reaction mixes and reaction mix templates using the **Analysis Rules** tab. To create, edit, or delete analysis rules, the “Manage Analysis Rules” permission is required.

Important: To ensure the correct application of analysis rules, a properly configured plate layout is required. The sample type (unknown sample or control type for each channel: positive, negative, or NTC) defined for a reaction mix must be consistent between the analysis rules and the plate layout. Otherwise, the rules will not be applied.


7.4.7.1. Adding analysis rules

To add analysis rules for existing reaction mix:

1. Navigate to the **Reaction mixes** tab.
2. For the selected reaction mix, click ... button and select the **Details/Edit** option.
3. In the window that opens, click the **Add Analysis Rules** tab.




A new tab is added, and a pop-up notification is displayed.



To add analysis rules during creation of a new reaction mix:

1. Navigate to the **Reaction mixes** tab.
2. Click the **New Reaction Mix** button.
3. In the **Reaction mix xreation** tab of the window that opens, at least one target with corresponding channel must be configured.
4. Click the **Add Analysis Rules** tab.

Note: The analysis rules are only available for the channels that were previously created in the **Reaction mix creation** tab.



7.4.7.2. Configuring analysis rules

The **Analysis Rules** tab consists of three expandable, interconnected panels:

- Amplitude multiplexing
- Thresholds
- Quality Control (QC) rules

1. **Amplitude multiplexing** – allows configuration of amplitude multiplexing for specific channels.

Important: Enabling amplitude multiplexing mode in the **Analysis Rules** tab does not automatically enable it in the **Reaction mix creation** tab and must be configured there manually. When the amplitude multiplexing mode is enabled in the **Reaction mix creation** tab, the setting is automatically preselected in the **Analysis Rules** tab.



Amplitude multiplexing

Channel	Green	Yellow	Orange
Amplitude multiplexing	☒ Certain QC rules and thresholding methods are not supported in Amplitude Multiplexing mode.	☒ Certain QC rules and thresholding methods are not supported in Amplitude Multiplexing mode.	☐

Note: Activating amplitude multiplexing mode restricts the availability of quality control rules and threshold methods:

- The “No Propagation” mode is selected automatically. Threshold propagation from controls is not possible.
- Only the Auto threshold and the Numeric threshold methods are selectable.

Thresholds * ⓘ

Control based thresholding ⓘ

No propagation or Propagation from with the appropriate Control type must be selected for this setting.

Control propagation *

No propagation

Propagation is unavailable when Amplitude Multiplexing is enabled for this channel.

No propagation

Propagation is unavailable when Amplitude Multiplexing is enabled for this channel.

Select

Required.

Unknown Samples ⓘ

Threshold selection

Auto threshold

Auto threshold

Positive Controls ⓘ

Threshold selection

Auto threshold

Auto threshold

Negative Controls ⓘ

Threshold selection

Threshold selection is unavailable when Amplitude Multiplexing is enabled for this channel.

Threshold selection is unavailable when Amplitude Multiplexing is enabled for this channel.

NTC ⓘ

Threshold selection

Auto threshold

Auto threshold

- The following quality control rules are not available:
 - Expected conc. for Positive Controls in dPCR reactions - Min. Range or Max. [cp/μL]
 - Max. expected number of positive partitions in negative controls and NTC

Controls			
Min. valid partitions % for Controls 	25 %		
☐ Different values for each channel			
Expected conc. for Positive Controls in dPCR reaction - Min. or Range or Max. [cp/μL] 	Min. conc.	Min. conc.	Min. conc.
	cp/μL	cp/μL	0.5 cp/μL
	Max. conc.	Max. conc.	Max. conc.
	cp/μL	cp/μL	15000 cp/μL
Max. expected number of positive partitions in Negative Controls and NTC 	Max.	Max.	Max.
			10
Unknown Samples			
Min. valid partitions % for Samples 	25 %		
☐ Different values for each channel			

2. Thresholds – allows to specify thresholding methods for specific channels.

The first mandatory step in this section is to select a control propagation method.

- No propagation** — In this thresholding mode, a thresholding method must be defined separately for each sample type: Unknown Samples, Positive Controls, Negative Controls, and NTC. Each sample type supports a specific set of thresholding methods.

Amplitude multiplexing

Channel	Green	Yellow	Orange
Amplitude multiplexing	☐	☐	☐

Thresholds *

Control based thresholding			
No propagation or Propagation from with the appropriate Control type must be selected for this setting.			
Control propagation *	No propagation	No propagation	No propagation

Unknown Samples

Important: The thresholding methods described below for Unknown Samples apply to wells to which a user-defined sample is assigned, as well as to wells with reaction mix only.

Auto Threshold – The standard automatic thresholding method is pre-defined by default.

Unknown Samples ⓘ			
Threshold selection	Auto threshold ▾	Auto threshold ▾	Auto threshold ▾


Numeric Threshold – Allows the user to define a fix numeric threshold value manually. The mandatory Threshold field accepts values from 0 to 255 RFU, with up to two decimal places.

Unknown Samples ⓘ			
Threshold selection	Numeric threshold ▾	Auto threshold ▾	Auto threshold ▾
Numeric threshold ⓘ	Threshold * 100.55		

DMM (Delta Min.–Max.-Based Threshold) – Allows positions the threshold at a user-defined ratio between the negative and positive bands. Delta is defined as the distance between the lowest (sampled minimum) RFU value of the negative band and the highest (sampled maximum) RFU value of the positive band.

The DMM method is recommended for poorly separated (rainy) assays. In case of replicated, the average threshold value is applied.

Note: This thresholding method is not available in Amplitude Multiplexing mode.



A fallback threshold based on the average values of the negative and positive bands must also be defined for cases in which the bands cannot be reliably identified. The following fields are required:


- **Ratio** – Accepts values in the range of 0–100%.
- **Fallback Min.** – Accepts values in the range of 0–255 RFU, with up to two decimal places. The value must be lower than Fallback Max.
- **Fallback Max.** – Accepts values in the range of 0–255 RFU, with up to two decimal places. The value must be higher than Fallback Min.

Unknown Samples ⓘ			
Threshold selection	DMM (Delta Min. Max. based ... ▼	Auto threshold ▼	Auto threshold ▼
DMM (Delta Min. Max. based Threshold) ⓘ	Ratio *		
	60 ▲▼ %		
	Fallback Min. *		
	50 ▲▼		
	Max. *		
	150 ▲▼		

DBA (Delta Bandwidth Average-Based Threshold) – Allows positioning the threshold at a user-defined ratio within the Delta between the negative and positive bands. Delta is defined as the distance between the average RFU values of the positive and negative bands.

The DBA thresholding method is recommended for well-separated assays. In case of replicates, the average threshold value is applied.

Note: DBA thresholding method is not available for the amplitude multiplexing mode.



A fallback threshold based on the average values of the negative and positive bands must also be defined for cases in which the bands cannot be reliably identified. The following fields are required:

- **Ratio** – Accepts values in the range of 0–100%.
- **Fallback Avg. Negative Band** – Accepts values in the range of 0–255 RFU, with up to two decimal places. The value must be lower than Fallback Avg. Positive Band.
- **Fallback Avg. Positive Band** – Accepts values in the range of 0–255 RFU, with up to two decimal places. The value must be higher than Fallback Avg. Negative Band.

Unknown Samples ⓘ			
Threshold selection	DBA (Delta Bandwidth Avera... ▼	Auto threshold ▼	Auto threshold ▼
DBA (Delta Bandwidth Average based Threshold) ⓘ	Ratio * 60 %		
	Fallback Avg. negative band * 70		
	Avg. positive band * 140		

Unknown Samples ⓘ			
Threshold selection	DBA (Delta Bandwidth Avera... ▼	Auto threshold ▼	Auto threshold ▼
DBA (Delta Bandwidth Average based Threshold) ⓘ	Ratio * %		
	Fallback Avg. negative band * 		
	Avg. positive band * 		

Positive Controls

Auto threshold – The standard automatic thresholding method. An Auto threshold offset (positive or negative) needs to be defined by which the threshold line should be adjusted. A positive offset value (e.g., 10 RFU) increases the threshold value, whereas a negative offset value (e.g., –10 RFU) decreases it. The default offset value is 0 RFU (no adjustment). This method is selected by default.

The Offset field accepts values from –255 to 255 RFU, with up to two decimal places.


Positive Controls ⓘ			
Threshold selection	Auto threshold ▼	Auto threshold ▼	Auto threshold ▼
Auto threshold offset ⓘ	Offset * 0	Offset * 0	Offset * 0

Numeric Threshold – Functions in the same manner as for Unknown Samples.

DMM (Delta Min.-Max.-Based Threshold) – Functions in the same manner as for Unknown Samples.

DBA (Delta Bandwidth Average-Based Threshold) – Functions in the same manner as for Unknown Samples.

PCT (Positive Control-Based Threshold) – Available only for Positive Controls. This method positions the threshold close to the edge of the positive band. An Auto Threshold Offset (positive or negative) must also be defined to adjust the threshold, as described for Auto Threshold.




Positive Controls ⓘ	
Threshold selection	PCT (Positive Control based ... ▼
PCT (Positive Control based Threshold) ⓘ	Offset * 5 ▲▼

Negative Controls

Auto threshold – Functions in the same manner as for Positive Controls.

Numeric Threshold – Functions in the same manner as for Positive Controls.

NCT (Negative Control-Based Threshold) – Positions the threshold close to the edge of the negative band. An Auto Threshold Offset (positive or negative) must also be defined to adjust the threshold, as described for Auto threshold method. The default offset value is 5 RFU.



Negative Controls ⓘ	
Threshold selection	NCT (Negative Control based... ▼
NCT (Negative Control based Threshold) ⓘ	Offset * 5 ▲▼

NTC

The same thresholding methods available for Negative Controls can be selected here.

NTC ⓘ	
Threshold selection	NCT (Negative Control based... ▲
NCT (Negative Control based Threshold) ⓘ	Auto threshold Numeric threshold NCT (Negative Control based Threshold)

Quality Control (QC) rules ⓘ

- b. **Propagation from Positive Control, Negative Control, or NTC** — In this thresholding mode, the user selects a control type and a thresholding method to be applied to matching wells. The resulting threshold values are then propagated to unknown samples exhibiting the identical reaction mix.

Thresholds * ⓘ

Control based thresholding ⓘ

No propagation or Propagation from with the appropriate Control type must be selected for this setting.

Control propagation * Positive control ▼

Positive Controls ⓘ

Threshold selection PCT (Positive Control based ... ▲

PCT (Positive Control based Threshold) ⓘ

Auto threshold

Numeric threshold

DMM (Delta Min. Max. based Threshold)

DBA (Delta Bandwidth Average based Threshold)

PCT (Positive Control based Threshold)

Quality Control (QC) rules ⓘ

Configuration

Select QC rules Select

For example, when propagation from a Positive Control using the PCT method is selected, the threshold is first calculated for all matching wells using the PCT method. The resulting threshold value is then propagated to the remaining wells that use the configured reaction mix.

The same thresholding methods available in No Propagation mode are available for the respective control types.

Important: If multiple wells contain the selected control type, the mean threshold value is calculated and propagated.: Wells that fail the quality control rules described below are excluded from threshold propagation.

3. **Quality control (QC) rules** – allows automatic quality control (QC) rules to be applied to the obtained results based on the selected thresholds. Wells or channels that do not meet the defined criteria can either be excluded from further analysis calculations or flagged according to the configured **Severity level** settings. The **Scope of application** settings define how a QC failure is propagated to other wells.

- a. **QC rule selection** – The drop-down list allows users to select QC rules applicable to controls and QC rules applicable to unknown samples.

Rules for controls

- **Min. valid partitions % for Controls** – Allows users to specify the expected percentage of valid partitions. The recommended default value is 25%. The rule fails if the calculated percentage of valid partitions falls below the specified value. The total number of partitions depends on the Nanoplate type. When the Different values for each channel toggle is enabled, separate values can be defined for each channel. Otherwise, a single value is applied to all channels.

Controls		
Min. valid partitions % for Controls <i>i</i> ☒ Different values for each channel	25 <i>↕</i> %	30 <i>↕</i> %

Controls	
Min. valid partitions % for Controls <i>i</i> ☐ Different values for each channel	25 <i>↕</i> %

- Expected conc. for Positive Controls in dPCR reaction – Min. or Range or Max. [cp/μL]** – Allows users to specify the expected concentration for wells with Positive Controls assigned. Three concentration options are available:
 - Defining only Min. conc. causes the rule to fail if the calculated concentration is lower than the specified minimum value.
 - Defining only Max. conc. causes the rule to fail if the calculated concentration is higher than the specified maximum value.
 - Defining both Min. conc. and Max. conc. causes the rule to fail if the calculated concentration falls outside the specified concentration range.

Expected conc. for Positive Controls in dPCR reaction - Min. or Range or Max. [cp/μL] <i>i</i>	Min. conc.	Min. conc.	Min. conc.
	0.5 <i>↕</i> cp/μL	<i>↕</i> cp/μL	0.5 <i>↕</i> cp/μL
	<i>↕</i> cp/μL	15000 <i>↕</i> cp/μL	15000 <i>↕</i> cp/μL

- Max. expected number of positive partitions in Negative Controls and NTC** – Allows users to specify the expected amount of positive partitions in wells with Negative Controls or NTCs assigned. The rule fails if the calculated amount of positive partitions exceeds the specified maximum value.

Max. expected number of positive partitions in Negative Controls and NTC <i>i</i>	Max.	Max.	Max.
	10 <i>↕</i>	15 <i>↕</i>	20 <i>↕</i>

Rules for samples

- Min. valid partitions % for Samples** – Functions in the same way as Min. valid partitions % for Controls but applies to wells with samples and wells with only reaction mix assigned.

Unknown Samples	
Min. valid partitions % for Samples <i>i</i> ☐ Different values for each channel	25 <i>↕</i> %

b. **QC result processing**

Severity level – One of the following options must be selected:

- **Invalidate Results (Fail)** – If any selected and configured QC rule fails, the results are invalidated and excluded from further analysis calculations, including control-based thresholding and second-level analysis.
- **Flag only (Warning)** – Results that fail QC are flagged with a warning but remain included in the calculations described above.

Scope of application – One of the following options must be selected:

- **Well level** – A QC failure in any channel causes all channels within the well to be marked as failed.
- **Channel level** – A QC failure is channel specific and does not affect other channels within the well.

In the event of QC failures:

- A QC failure in any channel within a well containing a control causes the failure to be propagated to other channels or wells (depending on the selected scope of application) that share the same reaction mix.
- A QC failure in one well is propagated to its replicates. This rule applies to both Unknown Samples and Controls.

Quality Control (QC) rules ⓘ

Configuration Hide details ▲ Current configuration Flagged only at well level

Select QC rules 4 rules selected ▼

QC Results Processing ⓘ

Severity level


- ☐ Invalidate Result (Fail)
QC failed results are marked with invalidation and excluded from further calculation (Control based thresholding and Second Level Analysis).
- ☒ Flag only (Warning)
QC failed results are clearly flagged with a warning but included in further calculation.

Scope of application

- ☒ Well level
QC failure in at least one channel will impact all other channels within the well.
- ☐ Channel level
QC failure is channel specific, without impacting other channels within the well.

To save the analysis rule configuration in a reaction mix (or reaction mix template), click **Create** when creating a new reaction mix with analysis rules or **Update** when adding analysis rules to an existing reaction mix.

After the configuration is saved, an additional tag is displayed in the Reaction Mixes view to indicate that analysis rules have been applied to the reaction mix.




This tag is also displayed on the plate overview, in the well information dialog on the plate layout, and in the List view on analysis.

For reaction mix templates, the tick indicator displayed in the Analysis rules column is selected.

Template name	Reaction mix name	ID	Analysis rules	CXTM	Modified by	Last modification
tmp1	Reaction mix 1	b5cc2240-92ab-4f2d-9c55-7bd51624b8e	-	-	admin	21/04/2026, 11:58:24 UTC+02:00
tmp2	Reaction mix 2	4b0b83ac-6a24-49bc-b312-783a36a0759e	✓ Yes	-	admin	27/04/2026, 09:14:42 UTC+02:00

7.4.8. Editing, deleting, and saving reaction mixes as template

To edit, delete, or save the reaction mix as template, click the three-dotted icon and select one of available options:



- **Details / Edit** allows to preview a reaction mix.
- **Delete** allows to completely remove a reaction mix from the plate. This option is disabled when a reaction mix is assigned on a plate layout.
- **Save as template** allows to save a reaction mix as template for further usage in different experiments. To save an existing reaction mix as a Reaction mix template, follow the instructions below:


1. After selecting **Save as template** from the context menu, the Save as reaction mix template window appears:

2. Enter the name of the template in the "Template name" field and the name of the reaction mix in the "Reaction mix name" field. The template name must be unique and both fields must not contain any special characters. Up to 100 characters can be entered in those fields.
3. Click **Save**.
4. The reaction mix template is added to the system database and can be imported in other experiments.


7.4.9. Importing reaction mixes from templates

Reaction mixes saved as templates can be imported to another experiment:

1. Click the **Import from template** button.



2. Import reaction mix template window appears.



3. Select which reaction mix template should be imported.

Note: Reaction mix templates defined in the system can be searched by their names or reaction mix names defined inside the templates using the search field and sorted by template name, reaction mix name, modification and creation dates using the drop-down menu.

4. Click **Import**.

- Reaction mix template is imported to a plate.

Note: In case a reaction mix name is already defined in a plate and the template with the same reaction mix name will be imported, the system will automatically add the suffix "Copy" for first copy and "Copy X" for the next copies, where X is the number of copies.




7.4.10. Defining samples, controls, and non-template controls

7.4.10.1. Samples

To add a new sample:

- In the **Samples & control** tab, under the **Samples** subtab, click **New Samples**.
- The New Samples window appears.



- Enter the following information in the fields:
 - In the Name field, enter the sample name. The name cannot contain any special characters. Up to 80 characters can be entered in this field.

Note: The Sample ID is automatically generated. This ID is unique for each sample created.
 - Labels can be added to samples to assist in categorizing experiments.

- c. **Optional:** To use the dilution calculation function during analysis, enter the template volume and, if applicable, a concentration factor. Refer to Section 7.6.14.7 Dilution calculation option for further details.

Note: To calculate a sample pre-dilution calculation factor, the template volume must be defined. Otherwise, sample cannot be saved.

- d. **Optional:** To use the conversion function during analysis, enter the conversion factor and a corresponding unit. Select a default unit or define a customized unit. Refer to Section 7.6.14.9 Conversion factor for further details.
- e. **Optional:** In the “Amount” field, enter the number of samples that shall have the same parameters. They will be numbered automatically behind the sample name by adding suffixes 01, 02, 03, etc.
- f. **Optional:** In the “Description” field, enter a description for your sample.

4. Click **Create**. The sample(s) is/are added to the plate.

PLATE CONFIGURATOR
plate

General Data
dPCR parameters
Reaction mixes
Samples & controls
Plate layout
Report template

Reports
Export
Support package
Delete
Plate Audit Trail

Samples & controls

Samples Controls Non Template Controls

New Samples

Set dilution Set conversion factor



	Name	Concentration factor	Template vol. [µL]	Conversion factor	Unit	
☐	S1	1	10	2	cp/mL	☐
☐	S2	2	20	4	ng/µL	☐
☐	S3	3	30	4	vg/mL	☐
☐	S401	2	40	5	vg/mL	☐
☐	S402	2	40	5	vg/mL	☐

Recommended next step: Samples & controls - Controls

Back to plates

Save changes Done

Note: A user can change the sample dilution or the conversion parameters for several samples at once by selecting the samples with the checkbox and using the “Set sample dilution” and “Set Conversion factor” fields. In modal window, enter new value(s) and click the **Update** button to apply changes.



7.4.10.2. Controls

Adding positive, negative, or mixed controls to your experiments is possible. To add controls:

1. In the **Samples & controls** tab, under **Controls** subtab, Click **New control**.
2. The New control window appears.


The screenshot shows the QIAcuity Plate Configurator software interface. The main window is titled 'plate CONFIGURATOR' and has a sidebar with various tabs: General Data, qPCR parameters, Reaction mixes, Samples & controls (selected), Plate layout, Report template, Reports, Export, Support package, Delete, and Plate Audit Trail. The 'Samples & controls' tab is active, and the 'Controls' subtab is selected. A 'New control' dialog box is open in the center of the screen. The dialog box has a title bar with a close button (X). It contains the following fields and options: 'Name *' with a character count of 80; 'Concentration factor' and 'Template volume' (with a unit dropdown set to µL); 'Conversion factor' and 'Unit' (with a character count of 8 and a 'Choose add new' button); and 'Cancel' and 'Create' buttons at the bottom. The background interface shows a 'Recommended next step' section and buttons for 'Set dilution' and 'Set conversion factor'.

3. Enter the following information in the fields:
 - a. In the Name field, enter a control name. The name cannot contain special characters. Up to 80 characters can be entered.
 - b. **Optional:** To use the dilution calculation function during analysis, enter the template volume and, if applicable, the concentration factor. Refer to Section 7.6.14.7 Dilution calculation option for additional information.
Note: To calculate a control pre-dilution using the concentration factor, template volume must be defined. Otherwise, the control cannot be saved.
 - c. **Optional:** To use the conversion function during analysis, enter the conversion factor and the corresponding unit. Select a default unit or define a custom unit. Refer to Section 7.6.14.9 Conversion factor for additional information.
4. Click **Create**. The control is added to the plate.

7.4.10.3. Non Template Controls

To add Non Template Controls (NTC):

1. In the **Samples & controls** tab, under **Non Template Controls** subtab, Click **New NTC**.
2. The New NTC window appears.




3. Enter the following information in the fields:
 - a. In the Name field, enter the NTC name. The name cannot contain special characters. Up to 80 characters can be entered.
 - b. **Optional:** To use the dilution calculation function during analysis, enter the template volume and, if applicable, the concentration factor. Refer to Section 7.6.14.7 Dilution calculation option for additional information.
Note: To calculate a control pre-dilution using the concentration factor, template volume must be defined. Otherwise, the NTC cannot be saved.
 - c. **Optional:** To use the conversion function during analysis, enter the conversion factor and the corresponding unit. Select a default unit or define a custom unit. Refer to Section 7.6.14.9 Conversion factor for additional information.
4. Click **Create**. The NTC is added to the plate.

7.4.11. Defining plate layouts


7.4.11.1. Plate view

To define the plate layout, you must add reaction mix, samples, and controls to your plate.

7.4.11.1.1. Adding a reaction mix to the plate




1. Left-click the desired well(s).
2. Left-click the **+** icon, then select **Add reaction mix** or **Mark as blank**. The Add reaction mix window appears.



3. Select the reaction mix you want to add to the plate. To create a new reaction mix, click the **Create new** tab. See Section 7.4.6.1 Creating new reaction mix for information about creating a new reaction mix.

- Click **Assign to well** to add the reaction mix to the well.

Note: To edit or remove the reaction mix from the well, right-click the well and select **Edit reaction mix** or **Remove reaction mix**. User can also remove the reaction mix from the well by clicking the ... icon in the bottom right corner of well and select **Remove reaction mix**.



Note: After a reaction mix is assigned to a well, it is moved from the Available section to the Added section in the Reaction Mixes panel next to the Plate Layout. As shown above, the indicator on the reaction mix tile in the Reaction Mixes tab is also updated accordingly.

7.4.11.1.2. Adding samples to the plate

- On a marked well, click the ... icon in the bottom right corner of a well or right-click the well.

Note: User can also mark more than one well if assigning a sample to multiple wells is desired.

- Click **Add sample**.
- The Add Sample window appears.


- Select a sample to add to the plate. To create a new sample, click the **Create new** tab. See Defining samples, controls, and non-template controls for information about creating new samples.
- Click **Assign**.

7. The control is added and the well is marked with "C".



Note: To edit or remove the control from the well, right-click the well and select **Edit control** or **Remove control**. User can also remove the control from the well by clicking the ... icon and selecting **Remove control**. To remove the control and the reaction mix from the well, select **Clear well**.

7.4.11.1.4. Adding NTCs to the plate




1. On a marked well, click the ... icon in bottom right corner of the well or right-click the well.

Note: User can also mark more than one well if assigning a non template control to multiple wells is desired.

2. Click **Add NTC**.
3. The Add NTC window appears.


4. Select an existing non template control from the Non Template Control name list or enter a new name.
5. Click **Assign**.
6. The non template control is added and the well is marked with "NTC".



Note: To edit or remove the non template control from the well, right-click the well and select **Edit NTC** or **Remove NTC**. User can also remove the non template control from the well by clicking the ... icon and selecting **Remove NTC**. To remove the non template control and the reaction mix from the well, select **Clear well**.


7.4.11.1.5. Help

User can click the **Help** icon in the upper right corner of plate layout area to display a legend and check the meaning of all icons and descriptions used on a plate layout.



7.4.11.1.6. Plate layout with skipped analysis rules


In case of configured Analysis Rules requiring a specific sample type that is not assigned in the plate layout, the following warning is displayed on the **Plate layout** tab:




7.4.11.1.7. Plate layout with defined gradient cycling

In case a gradient cycling is defined, the plate layout looks slightly different:

- 1. Due to technical reasons and thermal cycler design, the first and last rows of the plate (rows A & H) are disabled from usage and analysis. There is no possibility of adding reaction mixes and samples or controls to wells from these rows.
- 2. The assigned temperature gradient is displayed below the plate layout. The purpose of the temperature map is to present the temperatures applied in the wells.



- 3. With the help of the **View details** button, a temperature map is presented. By clicking **Download PNG**, the temperature map can be downloaded in *.png format.



7.4.11.1.8. List view

The list view in the **Plate layout** tab displays a detailed overview of your plate setup.

Plate layout

PlateList

Help

Sort by: Plate rowsFilter: NoneVisible columns: AllCSV import/export


Well	Sample/NTC/Control	Reaction mix	Target	Dye	Channel	IC
A1	-	-	-	-	-	-
A2	01 1ng gDNA	DPH218 ERBB2 + DPH186 TERT	DPH218 ERBB2	FAM	Green	-
			DPH186 TERT	HEX	Yellow	-
A3	01 1ng gDNA	DPH218 ERBB2 + DPH186 TERT	DPH218 ERBB2	FAM	Green	-
			DPH186 TERT	HEX	Yellow	-
A4	01 1ng gDNA	DPH218 ERBB2 + DPH186 TERT	DPH218 ERBB2	FAM	Green	-
			DPH186 TERT	HEX	Yellow	-
A5	01 1ng gDNA	DPH218 ERBB2 + DPH186 TERT + DPH464 SPIN4	DPH218 ERBB2	FAM	Green	-
			DPH186 TERT	HEX	Yellow	-
			DPH464 SPIN4	ROX	Red	-
A6	01 1ng gDNA	DPH218 ERBB2 + DPH186 TERT + DPH464 SPIN4	DPH218 ERBB2	FAM	Green	-
			DPH186 TERT	HEX	Yellow	-
			DPH464 SPIN4	ROX	Red	-
A7	01 1ng gDNA	DPH218 ERBB2 + DPH186 TERT + DPH464 SPIN4	DPH218 ERBB2	FAM	Green	-
			DPH186 TERT	HEX	Yellow	-
			DPH464 SPIN4	ROX	Red	-
			DPH43 AR	FAM	Green	-

You can modify this view by sorting and filtering:


- 1. Sort by rows or columns
- 2. Filter by existing reaction mixes
- 3. Hide specific columns

7.4.12. Plate layout: CSV import/export

It is possible to export plate data as CSV file. Click **CSV import/export**, then click **Export to CSV** to export the data.



An import of the whole plate data from a CSV file is possible to define the plate layout. The file structure for import and export is identical. First, make sure that the plate was saved and shows Plate status: Defined before importing a CSV file. Click **CSV import/export** then click **Import from CSV**. A new window appears where you can upload the CSV file from the operating system.



Note: All exported CSV files use a comma (",") as list separator and dot (".") as decimal separator and identical format is required for successful import of CSV files to QIAcuity Software Suite. Modification of CSV files with other software can overwrite separators due to regional settings, which can cause error. To fix the problem, change the regional settings of your system.

7.4.12.1. CSV structure

From QIAcuity Software Suite version 3.5 onward, CSV export and import files use a new structure.

Important: Information about CXTM, analysis rules, and report templates is stored in encrypted, non-human-readable format. When using CXTM, analysis rules, or report templates, a plate must be defined manually. QIAGEN recommends exporting the CSV plate layout file and using it as a template for future plate layout creation.

The files are divided into several sections that contain different parameters.


7.4.12.1.1. ### PLATE TEMPLATE

- **TemplateID** – If this field contains a Plate Template ID that exists in the system, the values in the General Data and dPCR Parameters sections of the plate are overwritten during CSV import with the data from the referenced plate template.

Note: The Plate Template ID can be copied from the URL displayed in the web browser address bar.



Validation: The system displays an error if the specified Plate Template ID does not exist.



7.4.12.1.2. ### REACTION MIXES

- **ID** – Ordinal number of the reaction mix.
- **Name** – Name of the reaction mix.
- **Total reaction volume** – Total reaction mix volume per well defined during reaction mix creation. If a template volume is specified, this field is mandatory.
- **Channel 1–16** – Up to 16 selected channels.

Note: Pay attention to the exact channel name notation. Channel names must be written in uppercase letters (e.g., GREEN, YELLOW, FAR RED, or for combinations, GREEN/YELLOW, etc.). When amplitude multiplexing is used, the suffixes "(High)" and "(Low)" must be used (e.g., ORANGE/RED (High)).

- **Target 1–16** – Up to 16 targets assigned to the selected channels.
- **Dye 1–16** – Up to 16 dyes assigned to targets and channels.

Note: Pay attention to the exact dye name notation. Only dyes available in QIAcuity Software Suite can be used (see Table 2). When amplitude multiplexing is enabled, the same dye must be used for both the (High) and (Low) channel assignments.

- **Internal control 1–16** – Up to 16 internal controls. If a target or channel is defined as an internal control in the reaction mix, set the value to TRUE; otherwise, set it to FALSE.

Note: Use the exact notation TRUE or FALSE. This field is mandatory when defining a reaction mix.

- **CXTM** – Contains encrypted, non-human-readable information about the Custom Cross Talk Matrix (CXTM) settings and metadata assigned to the reaction mix. A blank value indicates that no CXTM is assigned. If a CXTM is assigned to the reaction mix, this field is automatically populated during CSV export.

Note: If a discrepancy exists between the CXTM and the reaction mix targets, the CXTM is detached as described in Section 7.6.4.3 Usage of custom cross talk matrix.

Validation: The system displays an error if the encrypted information has been modified and can no longer be processed.

7.4.12.1.3. ### SAMPLES

- **ID** – Ordinal number of the sample.
- **Name** – Name of the sample.
- **Label** – Sample description entered by the user during creation.
- **Description** – Comma-separated labels assigned to the sample during creation.
- **Concentration factor** – Concentration factor assigned to the sample. If a concentration factor is specified, the Template volume field is mandatory.
- **Template volume [µL]** – Sample template volume.
- **Conversion factor** – Conversion factor value.
- **Conversion unit** – Conversion factor unit. If a conversion factor is specified, this field is mandatory.

7.4.12.1.4. ### CONTROLS

- **ID** – Ordinal number of the control.
- **Name** – Name of the control.
- **Concentration factor** – Concentration factor assigned to the control. If a concentration factor is specified, the Template volume field is mandatory.
- **Template volume [µL]** – Control template volume.
- **Conversion factor** – Conversion factor value.
- **Conversion unit** – Conversion factor unit. If a conversion factor is specified, this field is mandatory.

7.4.12.1.5. ### NTCs

- **ID** – Ordinal number of the NTC.
- **Name** – Name of the NTC.
- **Concentration factor** – Concentration factor assigned to the NTC. If a concentration factor is specified, the Template volume field is mandatory.
- **Template volume [µL]** – NTC template volume.

7.4.12.1.6. ### WELLS

- **Well** – Well identifier (A1, B1, etc.).
- **Sample ID** – ID of the sample defined in Section 7.4.12.1.3 ### SAMPLES and assigned to the well.
- **Reaction mix ID** – ID of the reaction mix defined in Section 7.4.12.1.2 ### REACTION MIXES and assigned to the well.
- **Control ID** – ID of the control defined in Section 7.4.12.1.4 ### CONTROLS and assigned to the well.
- **NTC ID** – ID of the NTC defined in Section 7.4.12.1.5 ### NTCs section and assigned to the well.
- **Control type for target 1–16** – Up to 16 control types can be defined. For each target in the assigned reaction mix, either a positive or negative control type must be specified. For example, if the reaction mix contains three targets, control types must be assigned for targets 1, 2 and 3.

Note: Pay attention to the exact notation – only lowercase letters are valid here. The value is specified when adding a control to a well in the plate layout. This field is mandatory for controls.

7.4.12.1.7. ### ANALYSIS RULES

- **Reaction mix ID** – Ordinal number of the reaction mix to which analysis rules are assigned.
- **Analysis rules** – Contains encrypted, non-human-readable information about the analysis template assigned to a specific reaction mix. During CSV import, the analysis template is recreated and assigned to the reaction mix using this information. If analysis template is assigned to a reaction mix, this field is automatically populated during CSV export.

126	### ANALYSIS TEMPLATE	
127	Reaction Mix ID	Analysis template
128		iRTedfrcOIEYKsCjV8p5lMX+eMP+dAIDV1rDy5h7ASHJsz5KcCjSbNlnunEkxhrolSWppBg9s6vfhQ8pghbNL+FOQ5n4kcd9e3SOH7m4WcOUln+TdM5cwg9+e/0AnHKGLg1R9NdffqH+uL2/8QDOy SMcBmsd8Mt7mg/700UDaVIT4wXgECCh83HJ9kcd5u5lnMfsm4/GbRnQ2/34XGwpNzMh7ccKf5/7gagYgWVC52:83C7+TPXn02UO/sEm37GVZusEJub8/esi+TQ99VfT+eAS2fBbQ8T7YomKzf 8pKaFWoWSZw78KVOZDIRLspVW4ePGAd4FTeU5a91HfQo949/57pZXkweIDLZuvTmLZd2pX0T0hgq70J5AAKFin06zd3CKYUjJq3nJnp0KQOACccuY86Y8Wss5V6Xh1FKYw cisTID7H88MLhaT6b7F+UMICGidwexUocNU+IQ9yS2io7cn0HrggSG2khWw-Ts5Zz+ipTAPFR0VYIOH24BOFVhghvclUesfMYDQ5enMeAUsQURFR3IT+g8c8dsDEYFSQWA+luOIQny1ROCBvQyJvP daWXXbRNGdg7dovYUuHj4U1mgdKdNENV2W5d5m0V6mQ775V9WwcbuWB+UsutLg5dUw+SDohu9eE5c3w9gpa7g4E99sgADNL-dk40YUWIN16Qy9KcaDHRB8hnd03T46MUNLzmrfcoJ 4E8hsNm3uG35uVZLuhov8B8RT3QU4M4SP4huv97d6dN0Nw996g03jCQ9B8G3CqgIDAP258K0YfMewfsmO0hDKVKEj3pdlpJ/0owkE7XcofauU9f9f9pBWAq9G7TMuuzc0dsHavQzQ FaZULh3Zf3MX4+2z3IwFNqeqBauNjmkbbWecpPmeDm7s6/5iGC234ANVjDPThRjMnRmYQJ3nNuss8h8R6A/ubazTKBWOCBdahlKH7b9yQ2wP2yocf+uabAB3NanXlvO54W19huw3D3 1J6RKWov0/kyQngP3ZDNFUZQ6A1KQ02gNgodZUM5aRMXZMJEavaQUL3rQ5cJredgmN17vncWaa+BlngQ0jdME559HJGfmgis87rwlSkBFAW9y21Bn7UPz2BpRLEOR68G0K0fa21JNnw8Aa6B GLLUBM2b10EPY229o1Nin0USUkaIQOWpaB+dEUK+mbmmCnRi+OIMuZAV5s6sG2Pwds2Q4QMMO4psP9uop+3g8O7G7jvnrH8XiofN8e07ugsTdrzHov+9wElB8YORIE+8R5GCRN0UuELXG 0/SMWU21g7YdDvKYbWUQROJqC8mdJLnkznfamaHauQh5G96gQmHdzg+ROVs12Z9y5q7eV7ZdhtspK6GHZnYQpbb8M0czU1W8vHwRmrlLzaXkHn87/IBL54QyQrUw24h28LoCS8nYU U6yM20XTT8u+8u45CfHgaZJu4e45277K9RHM2uWnhk9pjs2nSE8PwKOVTO125huhuf77arasp8p9uKXk8h9g6u7475ZnTB+u6GPKSFGLS9H4yEgP2+Z3VY6U04eent791uQ 1n5G4M4VZTEYH8ONZ6EhLqkylndInY+aw752huzpwy7QBT7g2om0uLm1D4sNEKxaZLOccz2km8lq7v8bN0Q+sdw0pQOnhuDZQ83DVH2R1ahnrTRH8J6JHnTIW1DXt9uAAn0b3Ebw68Z9X/P4p JlInmpMwT/rH6opp8RGY1urBZ5cVR3zYISCYWRcWu5BLHw7Q85EFGEdG4Yoo3MEB4Y+OOnKlKasoGpY/avQ7QZVhyCmle/entNZ7BPmNpZy8Jj0BQ5uuzK2epApsPaRuHtGZDn1NFNGeoMLZC wZQg8RqGp/NK9FPQED6obUugREtoZMFLD6B86y9sMXPINI+sz+5rM8D0KTYqoSaun84NT4uWcEodddA0yU7QFM8sdcK+7P8R0KqgWZnZc8Chg6SRKZKdW3zqgbYnMiibQ4sAvVU03Q

Validation:

- The system displays an error during import if the encrypted information has been modified and can no longer be processed.
- * The system displays an error if the IDs in Section 7.4.12.1.2 ### REACTION MIXES do not match the IDs in Section 7.4.12.1.7 ### ANALYSIS RULES.

7.4.12.1.8. ### REPORT TEMPLATE

- **Report template general settings** – Contains encrypted, non-human-readable information about the “General Report settings” section of the report template assigned to the plate. During CSV import, these settings are recreated and assigned to the plate using this information. If a report template is assigned to the plate, this field is automatically populated during CSV export.

Validation: The system displays an error during import if the encrypted information has been modified and can no longer be processed.

7.4.12.1.9. ### REPORT TEMPLATE FOR REACTION MIXES

- **Reaction mix ID** – Ordinal number of the reaction mix to which the report template is assigned.
- **Report template** – Contains encrypted, non-human-readable information about the report template assigned to a specific reaction mix. During CSV import, the report template is recreated and assigned to the reaction mix using this information. If a report template is assigned to the plate, this field is automatically populated during CSV export.

130	### REPORT TEMPLATE		
131	Report template general settings		
132	+D5G5OzE6gALD6gBSGGeB8lJCuHHDw6E6NXO+25DhB8+EH6dJbGh8lW0raOWMlgHnd5yQ362QzGqH2mli vvp4YNcEW5NfP1S2M1LTPVNEYLHATYPVJ4Ds/2JukagglTdxVinh+prIXTRdDEWc7mio0VVICfhvly9fZ59rjnp		
133			
134	### REPORT TEMPLATE FOR REACTION		
135	Reaction Mix ID	Report template	
136		MwI5dclca3K4cZmKleKp2f2n5aUkbEnv/LJGaOB6rIJeAylc3RechCJeaUVunmXw5vaWmVik/V50efjPmrsnwreq1MR1vAWqBDgQOf0AdpXKOSLMVDSbYD5yGSUgPw00iP4IMcdt1IOTUEFH3VBnd3FL U01Qo3t479V2Zr+ZcRhQXWd3W3V0YHIEELXFD80Y1RW0aX4SfuvrnbqlT1QbSvmKJQcSgS6Udo+J6b+nGfH6QYqe+KxH5e2p7wICWEGeHKAjGm2RlHgg0SUA6AWOD6kU1TOVDcnr+v62U1Zr/KHYL15 184CYNN2dCz+H65E5c253r3H3yCNCX8bpg+P9fYd4Z+U3gga1uXn61JH5+wy56V+qIVNlmm6PwR6j8BNA4E3k6c49cab1XW46D+Qz9d6J3G53V1VpW6gYtHw666E+gN6PwH4z2wjdA6w T4H9YbYd6khu1Bf8ag7m1UjRjKyp+3u6ow2M44T2HwQ6Q3Dn6c6bw76E0E5Kj+So+K6E3LQm6aKOCJTNu4P636d6emrUJXWd8JwY9H9f9yQ6bUHMZQY65CQm3S5uwb7F7m+OB44 21NSFG5NNV+nHEDJAdGenFOV2mdX1+sCDcNp/HKRDAnJ1EHK0uMaKvsc+K2cMjSnBaPNX1TczrH8B0a+YdNuuoW0D7ZnOmU4RwYCMHf6eVWVW6Hewegw4FFJ1J13D63JLQ8YHbHQN6z6sPAny n/zowhpgBk4XduelNw0a9mymblUveqooX0hL+V6H5jG83n5pBayW6jXLLAqWmK6BQdmH5p1VTP7HmmsrdF0T38nQap132w6w6LDZey6yB6K0g6zQvkw6frikmGj306HkzwTpf8kbsytwn4 0AljHqINybSGCZOTYpPw+MXNv6T490+OluT4cKDeNig7Lghu07VWh+QKcrtMjds+Y6Ab6oBXv8S07mLNUm1MRHf6cJ2ysRt6YL/KUQ0c+1hpbNnjpw+JiVVEU4LZu6pJ8BdLKV6pmxLHE+2+diaO5 2 wvR2F4qH6g8bLlMwQHNNW3KpczhnIX7yVFX9B+78Pps45/ZnuvZZHq26cokSLCm9d6R1QgagV8T13b21s48PqgBLDpnagG8Bel6y89/UdtUvUAH6gD6cWU5JYKRD1TLoD4m6aFwU6D6Kw6w x06u3wNqQy9aH+KGmC2529M4d4y1m6E4q3NThg57FL2uXVQ3MpsV6JL2E6mDCC1PVO6UjE2B3Pp8C9PUn6d6um39b1B8gpnWn6d6pU68k6E24F59Z6j6m6d0h7C6g6R6B6w Z+JRY2YQD6t6aAFJQEHSK8Nqejd8Eugwrcd6uBM0Imf1fg6aHw6a6cc6c073Imd590U6kP33dm/Yv6K53Ac6gV62P6p6q6y24BmX1TVg/2+6um4Q7Q9YfJEK0c6gZLH6t6UXH5y2y6IY2W IKW2X21VPPT+1z0GmouPij6y6w6S4u7m923Ak25mdU3fKjGFYAdB3N6Zs5SOX/3HPK6ZCW64ca/NIDQ3T12M65agKLib6c66S6S6y6BYuQom6k4A6d63+44y7h6+JNU0X1PijVud54Y6 MNGR6B6mFh3H2Hq4004aJfYKba1mG6K6NKBG73Al6B6k60U1++vAlq6m6B6ZL7U69U6ab+K2gb63s71+YE4F6C7gm0gUJ1X4Q6C6281J1J0k3p7yHwC6COW6c1h2u1d6H6eX6oPNS21V82J6a7K 3 I4ZQV7Lsc6dU6gU6R+NeR607bup/M6N6B6H6A6U6s6FLUR73N5qZ6gH6aU6R6dV6g6p6M6Y6B6r6p6mZ6q69+ZP506G6H6F+y4KpV6w3XGQ6P6wWZAT6b6u6k6T6R69Q6h6p601H6eB6H656S6B6E K7v6C6w6P6g6R6DZ6V0R6N+K6m6Q6s602+6FZL6B6V6H6A6X6U6A6E6C6k6T6L6G6U6S6F6B6X6Z6h6P2y6H6W6U6FT6B1M6q6u67Z6K6c6r6f6J1R6Q6u679696B66c6e6Q6Y6f6AC6W6U6K d6c6K6C6B6S656N67P6g637P6c6nc2L6N6c6N6G6S6y6K6u6w6B656g7L6K6s746Z6w6P6Y6f6Y6Q6J6N6c6S6B6E6H6EQ66+N6P6S6Y6C6P+R6X6O6Z6B6D6S6B66c60Q6Y6F6d6S6c60J6y6C6P6P6q6d6K6A6B6W6Q34aJ6J UJVP6B6h6S6W6m6d6Yp6T6Ar6D4m6jv9111B4y6J5J1JyoM6N6I6t6a266Y4u6MW6B6b6h6m6tp7XJ6h6N6czt6w6H6D/VuU6D36X6q6q2Nym626b/wNTR6a6m6d6Y7F7Yq6aQ6V6C6S6G6C6P6y63A6u6e6K6J1N6g6K6Q26w61Y1 P26p6Q6O7W6W6u6Z6H+H6E6G6P6AT6Nq+p3X6J6w6m6M6F6p6CL6Na6G6U6H6Q6R6V6Q3N6c6A6q6T6TH6c6U6c6L6B6Z6H6em6N6X6M6V6U6G1c6J6a6J60N6u6B6D6B6626de6Q6U9I6S6Q6Z6u656G6W6Ng6d6k6L6U6T6ym6m6L6Xa 4 VdLp6S6S6N6K6h60H6W6S6w6MU6L6B6SM6W7In6R6C6H6N6p7T7X6B6e6Z6W6V6b6X679C6J6j6Vz6s6M75B6Y6O6Z6N6A6p6k6u66M696d6S6H6Z6d6V6e6A6D6W6n6p6n6C6Y6d6m6KQ+6e6Y6D6m6b6J6R69H63Y6M62Z6Y6N6B6p6 8Hu6m6nz6P6B6Z6o6N6U6R6Z6V6W6H6m6K01K6H6V6b61X6L6a6S6H6S6H656Z6p6q6U6s6d6T6D6H6L6S6H6C6V6b6p6Vz60p6u6p6q6a6n6f6X6P6Y6e6S6y6Z6Y6P6Z6N6B6Z6N6C6S626B6e6S6m6R6G6H6M6Z6d6J1H6H6Z6U6 e6w6S6Z6W621J6H6d6n6U6Z6Z66u6d6Ok6m6U6a6U6H6b6r6U6E6I6S6XW6S6F6g6h6Y6L6Q6O65+V6W6Z6J1R6W6U6c6D6K6S6y6C6Q6Y6H6d6P6b6A6H6u6d6S9N6L6o6G6Z6T6R6B6L6S6b6N6T6U6D6d6H6r U6KL6Y6d6U6p6m6U6c6B6Z6C6Z6E6i6u6K6P6A6H6S6h6S6o1v4C6B6e629U6K6Z6G6V6D6VTE6M6X6Y696B6R67K6b6q6P6z6N6P6S6q6I1T6H6K6b6e6o6u6p6v6H6B6u686c6W6G6F6H6d6S9N6L6o6G6Z6T6R6B6L6S6b6N6T6U6D6d6H6r q6h6N6F6n6q6B6Z6P6Q6P6C6Z6F6S6B6E6Y6A6B6T6Q6Z6s176T1Q25u6P6n6I24U6c6q6B6E6Z6629w6Lm6M6S6V68B6Z6Y6Z6P6P6M6y6U6P6N6K6J6k6H6463g7Z6W6N6R6q6t6m6D6F6Z6XW6D6P6R6Q6Z6Y6C4q6S6U6A6r6d6I6p6K64Q6P+ 6w6d6T624q6H6Y6D6X6K6Z6Q6P6G6m6sz693150Nw6m6v6I6b6b6E6u6q6c6Y6s16A6C6Z66D64Y6G6d6N6B6M6J6B6CL6HF6W63Yw6L6P6Y6Y6R6e6u6Z6N6G6Y6E6X6Z6U6a6w6o6s6J6w6K3p6T6M6B6G6Z6F6B6+6W6T6r6Q6H6p616S6Z68 1w6V6o71K6S6Y6L6D6L6c1Z6P6Y61X6u6X76c6c6Q6a6P6e6n6I6u6g6m6W6Q6B6k6T6c6S6L64Y6W6R6f6m6K6a6D6B6G6D6F6G6H6T6U6G6S6M6N6S6w6R6AT6w6X6f6m6t+Z6H6Z6T6U6A6E6H6B6E6S6g6H6Q6P6X6S6D	
137			
138			
139			
140			

Validation:


- The system displays an error during import if the encrypted information has been modified and can no longer be processed.
- The system displays an error if the IDs in Section 7.4.12.1.2 ### REACTION MIXES do not match the IDs in Section 7.4.12.1.9 ### REPORT TEMPLATE FOR REACTION MIXES.

7.4.12.2. Import plate layout from CSV


Important: All data related to previously created plate layout elements, such as reaction mixes, samples, controls, etc.) will be overwritten after a CSV import.

A user can specify all plate parameters that are accessible via user interface in applications. The software validates the input data and only data that exists in the application can be entered via the CSV file (e.g., only existing dyes can be entered).

Note: If a plate has defined a gradient cycling in the dPCR parameters, the application will display the warning pop-up window describing that rows A and H of the imported plate layout are to be disabled.




In case of successful CSV import (there are no errors nor warnings in file), all data from the CSV file will be imported to the plate and the user will be notified by a message “CSV successfully imported” in bottom right corner:




7.4.12.3. When will the CSV import function fail?

If there are some errors in the CSV file, there are two possible scenarios:


1. Data will be imported showing the warning that current plate data will be overwritten, and the user will receive a notification with a list of issues:



User can expand the “Show warnings” section to show more details.



2. Data will not be imported, current data will not be overwritten, and the user will receive a notification with the error:



7.4.12.4. Possible errors and warnings

Possible errors and warning related to reaction mixes, samples, and control in the CSV file are listed below:

1. Reaction mix (### REACTION MIXES section):
 - a. Warning— Import skips such reaction mix:
 - Reaction mix name is null or empty.
 - Reaction mix ID is left blank but other columns are filled.
 - b. Errors:
 - Reaction mix name exceeds the limit of 100 characters or contain any special characters.
 - Target name exceeds the limit of 40 characters or contains any special characters.
 - Defined channel does not exist in the application.
 - Defined dye does not exist in the application.

2. Samples (### SAMPLES section):

a. Warning — Import skips such sample:

- Sample ID is left blank but other columns are filled.
- Sample ID and sample name are left blank but other columns are filled.
- Sample ID is filled, sample name is left blank, but other columns are filled.

b. Errors:

- Sample name exceeds the limit of 80 characters.
- The template volume is empty while the concentration factor is filled.
- The template volume value is below 0.1 or exceeds 1000.
- The concentration factor value is below 1 or exceeds 1,000,000,000,000.
- The conversion factor value is below 0.000000001 or exceeds 1,000,000,000.0.
- The conversion unit exceeds the limit of 8 characters.
- The amount of labels exceeds 10.
- The description exceeds the limit of 1000 characters.

3. Controls (### CONTROLS section)

a. Warning — Import skips such control:

- Control ID is left, but other columns are filled.
- Control ID and control name are left blank, but other columns are filled.
- Control ID is filled, control name is left blank, but other columns regarding controls are filled.

b. Errors:

- Control name exceeds the limit of 80 characters.
- The template volume is empty while the concentration factor is filled.
- The template volume value is below 0.1 or exceeds 1000.
- The concentration factor value is below 1 or exceeds 1,000,000,000,000.
- The conversion factor value is below 0.000000001 or exceeds 1,000,000,000.0.
- The conversion unit exceeds the limit of 8 characters.

4. NTC (### NTCs section)

a. Warning — Import skips such control:

- NTC ID is left, but other columns are filled.
- NTC ID and NTC name are left blank, but other columns are filled.
- NTC ID is filled, NTC name is left blank, but other columns regarding NTC are filled.

b. Errors:

- NTC name exceeds the limit of 80 characters.
- The template volume is empty while the concentration factor is filled.
- The template volume value is below 0.1 or exceeds 1000.
- The concentration factor value is below 1 or exceeds 1,000,000,000,000.
- The conversion factor value is below 0.000000001 or exceeds 1,000,000,000.0.
- The conversion unit exceeds the limit of 8 characters.

5. Wells (### WELLS section)

a. Warning:

- If the Reaction Mix and Control IDs are filled, but the sample and NTC IDs are not filled, and the number of channels in the reaction is lower than the number of filled control types, only the controls associated with the Reaction Mix channels are imported. All other controls are omitted.

b. Errors:

- The number of wells does not match the selected plate type (e.g., a 96-well plate requires 96 rows in the CSV file).
- One or more sample, reaction mix, control, or NTC IDs do not exist in the corresponding sections.
- More than one sample, control, or NTC ID is specified for the same well.
- An NTC ID is specified while one or more Control Type fields (1–16) are filled.
- One or more Control Type fields (1–16) contain a value other than "Positive" or "Negative".
- A Control ID is specified, but the number of RM channels exceeds the number of filled Control Type fields.

Additional warnings and errors related to particular features usage:

1. Long Stokes Shift (LSS) dyes and channels are used:

a. Errors:

- Reaction mix with more than 2 LSS is defined in CSV.
- Defined LSS channel does not exist in QIAcuity Software Suite.

2. Amplitude multiplexing (AM) is applied.

a. Warning:

- CXTM is removed and a warning is added, when AM split is done (in CSV file) for different channels than standard ones used for CXTM.

b. Errors:

- Some of the amplitude multiplexing channels are used more than once in CSV (e.g., GREEN (High) twice).
- Standard channels are mixed with AM channels within one channel (e.g., GREEN and GREEN (High) will result in error).

7.4.13. Saving plate

After configuring the plate in the Plate configurator using the General Data, dPCR parameters, Reaction mixes, Samples & controls, Plate layout, and Report template plate tabs, save the plate using the bottom panel.

← Back to plates


Save changes

Done

The **Save Changes** option saves all changes made by the user and keeps the user on the current screen. The **Done** option saves all changes made by the user and redirects the user to the Plate Overview screen.

After the plate is saved, a unique Plate ID is displayed in the upper-right corner of the screen. This ID serves as the reference for the created plate. The user can click the **Copy** button to copy the Plate ID to the Windows clipboard.

The same Plate ID is also displayed in the Analysis view and in the browser address bar.



7.4.14. Managing your plates

To enter the Plates environment, click **Plates** in the main toolbar. Existing plates are shown in the Plates Overview window. Plates can be presented in grid view and list view accordingly.




Plate Overview – grid view.





Plate Overview – list view.

As of the QIAcuity Software Suite version 2.5, instead of “ – Upgraded” suffix in the plate name after an upgrade of a read-only plate, the color of bar and dedicated icons inform users if a plate is up to date or if an upgrade is required:


1. A blue bar is used to denote up-to-date plates, while a gray bar is used for read-only plates.
2. Plates that have been imported from older QIAcuity Software Suite version and are already upgraded display the following icon and tooltip message:



3. Plates that have been imported from older QIAcuity Software Suite version are not upgraded yet and remain in read-only mode display the following icon and tooltip message.



4. Plates created in the current QIAcuity Software Suite version do not display any of the above icons and tooltip:




On the bar, information about the last update of a plate is shown. When a plate was updated less than an hour ago, minutes or seconds are shown. When the plate was modified more than 24 hours ago, the date of the last modification is indicated.

The checkbox in the corner may be used to select or deselect plates manually. In addition, the **Select all** option can be used for bulk operations as described in Section 7.8.3 Bulk plate archiving.

Under the three dots menu (...) in the upper right corner, all actions that can be performed on a plate are listed. This includes upgrade, analyze, details, reports, export, archive/restore, and delete. Note that some actions are permissions dependent and not visible to users who do not have the relevant permissions.

7.4.14.0.1. Information icons

1. **Plate type icon** — The number 8, 24, or 96 indicates the plate type.
2. **Plate size icon** — This icon indicates the plate size on the hard drive.
3. **Plate status indicator** — On mouse hover, a tooltip message indicates if the plate is up to date or read only.
4. **VPF icon** — On mouse hover, a tooltip message indicates the status of the volume precision factor. Details can be found in Section 7.6.3 Volume Precision Factor (VPF).
5. **Lock icon** — On mouse hover, a tooltip message shows the instrument ID and if a plate is locked by the instrument.



Example of up-to date plate (after upgrade) with VPF.




Example of read-only date plate without VPF.

7.4.14.1. Sorting

User can sort the Plates Overview window by Last updated, Plate name, or Plate status.

1. Click the symbol for tile or list view to switch views within the Plates Overview window.


Note: Both views provide information regarding the plate name, plate status, modified date, type of plate, and used disk space.



2. On a specific plate, click the ... button. The context menu provides options to edit, delete, or analyze the plate. It also points to the existing reports and enables the export of plates. When the selected plate is currently running, the run status and the respective plate details are visible.

7.4.14.2. Search


The plates overview screen provides search options for plates by providing the plate name or a barcode as search criteria.



Clicking the empty input field displays up to five recent searches.



As the user types, the system displays plate suggestions that match the entered text.




Use a combination of letters and enter it as a search string in the input field and click  or click suggestion. The plates overview page is filtered, and only plate names including the given letter combination are shown. The search functionality is not case sensitive. To get back from the Search view to the General Plates overview, either empty the search field and click  or press **Esc** on a keyboard while the text field is active.


When searching for two keywords within a plate name, the search function can be simplified by using the % symbol in between search terms as a wild card. For example, the following plate name “Name_ID123456789_StudyABC_2023” can be found with the search function “Name%2023”.

7.4.14.3. Filtering

Click the calendar symbol beside Time Frame to limit the overview results to plates modified within a specific time.



A window appears and enables selection or entry of a specific time frame. Click **Apply** to filter the results.



7.4.14.4. Export and import plate data

To archive data and free-up disk space, plates can be exported as password-protected zip files. Click the respective plate in the plates overview. On the left side of the screen, click **Export plate**. The plate is exported as a password protected zip file.

After exporting and saving the password-protected zip file, the plate can be deleted by clicking **Delete** on the left side of the screen. For more information about disk space, see Section 8 Maintenance Procedures.

The screenshot shows the QIAGEN Plate Configurator interface. The top navigation bar includes 'Plates', 'Templates', 'Disk Space', and 'Archive'. The left sidebar lists various actions: 'General Data', 'dPCR parameters', 'Reaction mixes', 'Samples & controls', 'Plate layout', 'Report template', 'Analyze', 'Reports', 'Export', 'Archive', 'Support package', 'Delete', and 'Plate Audit Trail'. The main area displays the 'General Data' tab for a specific plate. The 'Plate name' field contains '20220322_JA_ProbeCNV_Marketing_Exp15_P3'. The 'Plate type' is set to 'Nanoplate 8.5K 96-well'. The 'Description' field is empty. The 'Labels' field contains 'Confirm each label with "Enter" button'. The 'Plate Ownership' field shows 'admin admin (admin)' with an 'add user' button. The 'Barcode' field contains '0302666210024800000000064'. The 'Recommended next step' is 'dPCR parameters'.

To import a plate, click **Import Plate** in the plates overview.



A new window appears for upload of the password-protected zip file. Click **Import**, and the plate is added to the plates overview.

Note: A plate that already exists cannot be imported again.

Note: If a plate from a previous version is imported to a newer QIAcuity Software Suite version, it will be visible in read-only mode and must be upgraded before it can be edited. There is no possibility for importing a plate from QIAcuity Software Suite versions earlier than 1.2.18. Exported plates from version 1.1.3 cannot be imported directly; therefore, import these plates into QIAcuity Software Suite version 1.2.18 prior to software update if the plate data are required for further analysis.

A dialog box titled 'Import plate from ZIP file' with a close button (X) in the top right corner. The main area contains a dashed blue box with the text 'Drag and drop file here' and 'or' below it. A 'Browse file' button is centered within the dashed box. At the bottom right of the dialog are 'Cancel' and 'Import' buttons.


7.5. Setting up templates

There are two types of templates that can be used to set up experiments: plate template and reaction mix template. In both cases, user can create a new template of plate or reaction mix or use an existing plate or reaction mix and save it as template.


Note: Template creation is permission dependent.

7.5.1. Creating a new plate template

1. In the Main toolbar, click **Templates**, then select the **Plates** tab and click **New template**.



2. The Create New Plate Template window appears.
3. Enter the name for the template in the "Template name" field. User can enter up to 100 characters in this field. Click **Next**.
4. Follow the steps as described in Section 6.4 Setting up an experiment.
5. After entering all required information, click **Done** at the bottom of screen.
6. The template is stored in the database and can be used for future experiments.




7.5.2. Saving existing plate as a plate template

Follow the steps to set up a new plate as described in Section 7.3 Setting up an experiment. After entering all required information, user can save the information as a template to use for future plates.

1. Click **Plate templates...** in the upper right corner of the screen.




2. Click **Save as template**.



3. The Save as Plate Template window appears.
4. Enter the name of the template in the "Template name" field.

Note: Click **Already existing Plate Templates** to display an overview of the existing plate templates.

A window titled "Save as Plate Template" with a close button (X) in the top right corner. It contains a text input field labeled "Template name *" with a character count "Characters left: 100". Below the input field is a section titled "Already existing Plate Templates" with a dropdown arrow. This section contains a list of existing templates, each with a plate icon and a label: "T1" and "T2". At the bottom right of the window are "Cancel" and "Save" buttons.

7.5.3. Using a plate template to create a new plate

Existing templates can be used to create a new plate in two ways – from **New Plate** level and from the **Templates** level.

To use a plate template from the **New Plate** level:

1. In the Main toolbar, click **Plates**, then click **New Plate**.



2. Click **Plate templates**, then click **Import template**.

The screenshot shows the "NEW PLATE CONFIGURATOR" interface for a plate named "my_plate". On the left is a sidebar with a menu: "General Data" (selected), "dPCR parameters", "Reaction mixes", "Samples & controls", "Plate layout", and "Report template". The main area is titled "General Data" and contains several form fields: "Plate name *" with the value "my_plate" and a character count of 117; "Plate type" with a dropdown menu labeled "Choose plate type"; "Description" with a large text area and a character count of 2000; "Labels" with a text area and a character count of 10; "Plate Ownership *" with a dropdown menu showing "admin admin (admin)" and an "add user" button; and "Barcode" with a text area and a note: "You may scan it using USB scanner, enter it now or scan it later, by the instrument". At the bottom, it says "Recommended next step: dPCR parameters". On the right side, there are buttons for "Import template" and "Save as template". At the bottom of the interface, there are buttons for "Back to plates", "Save changes", and "Done".


3. The Import Plate Template window appears with all existing templates.

The screenshot shows the "Import Plate Template" dialog box. It has a title bar with a close button (X). Below the title bar, it says "Select the plate template". There is a search bar with a magnifying glass icon and the text "Search...". Below the search bar, there are two list items: "T1" and "T2", each with a small icon to its left. At the bottom of the dialog box, there is a note: "By importing a template, you are going to replace all the data that is currently entered for this plate." Below the note are two buttons: "Cancel" and "Import".

4. Select an existing template, then click **Import**.
5. All information in the selected template is automatically transferred to the new plate setup.

To use a plate template from the **Templates** level:


1. Go to **Templates**, then select the **Plates** tab.
2. Find the template to be used on the list then click the three-dot icon and select the **Use in a new plate** option.



3. All information in the selected template is automatically transferred to the new plate setup.

7.5.4. Creating a new reaction mix template

1. In the Main toolbar, click **Templates**, then select the **Reaction mixes** tab and click **New template**.



2. The New reaction mix template window appears.

The screenshot shows the 'New reaction mix template' window. It contains the following fields and controls:

- Reaction mix creation** tab with a sub-tab **Add Analysis Rules**.
- Template name *** text field with a character count of 100.
- Reaction mix name *** text field with a character count of 100.
- Total volume** text field with a unit selector (µL) and a **Change color** button.
- Amplitude multiplexing** dropdown menu.
- Table for defining reaction mix components:**

Color	Target Name *	Dye	Channel(s) *	Internal control
☐	Name	Select	Select channel	☐
☐	Name	Select	Select channel	☐
☐	Name	Select	Select channel	☐
☐	Name	Select	Select channel	☐
☐	Name	Select	Select channel	☐
☐	Name	Select	Select channel	☐
☐	Name	Select	Select channel	☐
☐	Name	Select	Select channel	☐

At the bottom right, there are **Cancel** and **Create** buttons.

3. Enter the name for the template in the "Template name" field. Up to 100 characters are possible.
4. Follow the steps as described in Section 7.4.6 Reaction mixes tab to set targets.

5. **Optional:** Follow the steps described in Section 7.4.7 Analysis rules to set up analysis rules.
6. After entering all required information, click the **Create** button.

Example of template with 8-plex:

New reaction mix template

Reaction mix creation ⊕ Add Analysis Rules

Template name * Characters left: 89
RM_template

Reaction mix name * Characters left: 97 Total volume
RM1 100 μL Change color

Amplitude multiplexing ▾

Color	Target Name *	Dye	Channel(s) *	☐ Internal control
11		FAM	Green	☐
12		VIC	Yellow	☐
13		TAMRA	Orange	☐
14		ROX	Red	☐
15		Cy5	Crimson	☐
16		Cy 5.5	Far red	☐
17		LSS GY	Green / Yellow	☐
18		LSS YO	Yellow / Orange	☐

Cancel Create

Example of template with 8-plex and activated amplitude multiplexing for Green channel:

New reaction mix template

Reaction mix creation ⊕ Add Analysis Rules

Template name * Characters left: 89
RM_template

Warning (1)
When selecting Amplitude Multiplexing, please ensure that High-Multiplexing-Reference channel in imaging parameters is enabled.

Reaction mix name * Characters left: 97 Total volume
RM1 100 μL Change color

Amplitude multiplexing ▾
☐ Select all ☒ Green ☐ Yellow ☐ Orange ☐ Red ☐ Crimson ☐ Far red ☐ Green / Yellow ☐ Yellow / Orange ☐ Orange / Red ☐ Red / Crimson ☐ Crimson / Far red

Color	Target Name *	Dye	Channel(s) *	☐ Internal control
11l		FAM	Green (Low)	☐
11h		FAM	Green (High)	☐
12		VIC	Yellow	☐
13		TAMRA	Orange	☐
14		ROX	Red	☐
15		Cy5	Crimson	☐
16		Cy 5.5	Far red	☐
17		LSS GY	Green / Yellow	☐

Cancel Create

7. The template is stored in the database and can be used for future experiments.

Note: Creating reaction mix templates from an existing reaction mix or from reaction mix templates is described in Section 7.4.8 Editing, deleting, and saving reaction mixes as template and 7.4.9 Importing reaction mixes from templates, accordingly.



Template name	Reaction mix name	ID	Analysis rules	CXTM	Modified by	Last modification
RM_template	RM1	84c37a11-53ab-44d4-a13d-e82b-b9006c8a	-	-	admin	28/04/2026, 14:16:22 UTC+02:00


Note: The CXTM (Custom Cross Talk Matrix) column indicates whether reaction mix template has a custom cross talk matrix assigned to it. If CXTM is assigned, the CXTM column displays **Yes** with a check mark icon. Please refer to Section 7.6.4 Custom cross talk matrix for more details.



Template name	Reaction mix name	ID	Analysis rules	CXTM	Modified by	Last modification
TMPL_CXTM	RM_CXTM	36f6a296-85e6-4f83-9299-7f727-780a3c6	-	✓ Yes	admin	28/04/2026, 14:55:36 UTC+02:00

7.5.5. Managing your templates

To enter the Templates environment, click **Templates** from the Main toolbar. The overview screen lists all existing templates for plates and reaction mixes on separate tabs.



Template name	Modified
T2	28/04/2026, 13:18:29 UTC+02:00
T1	21/04/2026, 15:24:44 UTC+02:00

On the desired template, click the ... button to open a context menu that provides the following options:

- Edit, delete, or use the template in a new plate – for any of the Plates templates
- View details/edit or delete the template – or any of the Reaction mixes templates

Note: There is no possibility to download or export a plate template. However, it is possible to export a plate, import it into another Software Suite instance and generate a new plate template from this plate.

7.5.5.1. Sorting

User can sort the Templates Overview window by modification date or name. Sorting the templates by the modification date enables user to view the recently modified entries.

The template list can be sorted by:

- Modification date (ascending or descending) or template name (ascending or descending) – for plate templates
- Template name (A–Z), reaction mix name (A–Z), reaction mix name (A–Z) with CXTM first, modification date (descending), creation date (ascending or descending) – for reaction mixes templates

7.5.5.2. Searching

Searching for specific templates can be done by entering the template name (or reaction mix name for reaction mixes templates) in the Search field.

7.5.5.3. New template

See Section 7.5 Setting up templates to create a new templates.

7.6. Analysis

The QIAcuity Software Suite analysis of plates that have been processed by the instrument. The following analysis options are available in the software:

1. Absolute Quantification
2. Mutation Detection
3. Genome Editing
4. Copy Number Variation
5. Gene Expression


7.6.1. Accessing the analysis environment

To access the Plate Analysis environment:


1. On the Plates Overview page of the Plates environment, search for the plate for analysis. Alternatively, you can open the Plate Analysis environment. Click the plate name in the Plates overview, then select **Analyze** from the context menu.

Note: The plate run must be completed.

2. Click the ... icon in the upper right corner of the plate tile.



3. Select **Analyze** from the context menu.



7.6.2. Plates after QIAcuity Software Suite version upgrade

After upgrading the QIAcuity Software Suite (see Sections 4 Installation Procedures and 4.5 Upgrading the QIAcuity Software Suite to a newer version), the status of all plates will be changed to read only until the plates are upgraded to the new software version. The same applies to plates that are imported from a previous Software Suite version. Read-only plates can be recognized by gray bar on top of the plate tile and a dedicated icon with a tooltip displaying "Read-only plate":




Note: After upgrade, the original plate becomes read only. This means that the results of the experiment are in read-only mode and user is not able to change the threshold anymore (threshold can be changed only on an up-to-date plate, upgraded, or created in current software version).


To upgrade a plate, go to the plate tile in the plates overview and click the ... menu, then select the **Upgrade** option from the drop-down menu. Alternatively, click the plate name in the tile to enter the Plate Configurator view, then click **Upgrade** in the context menu.

Note: If upgrading an older version of QIAcuity Software Suite using indirect scenarios (e.g., upgrade from version 1.2.18), it is not recommended to upgrade plates in intermediate versions – one final upgrade in the desired version (e.g., 3.0) is adequate.

During the plate upgrade, a blue pulse indicator is shown on the plate tiles, indicating that the upgrade process is taking place. During the upgrade process, both plates are blocked and cannot be accessed and changed to avoid inconsistent data or loss of data.



If the plate has been upgraded successfully, two plates will be displayed: the original (read-only) plate that includes the previously performed analysis, and the upgraded version of the plate. Up-to-date plate (the upgraded version of the original one) can be recognized by: the same name, a blue bar on top of the plate tile, and a dedicated icon with a tooltip displaying “Upgraded”:



User can redirect from the read-only plate to the general data section of the upgraded plate by clicking ... menu and selecting the **Go to upgraded plate** option or from the analysis level (of Read-only plate) using the **Go to upgraded plate** button on dedicated communicate:



7.6.3. Volume Precision Factor (VPF)

The Volume Precision Factor (VPF) offers a unique feature to secure consistency in precision of concentration results obtained from a QIAcuity dPCR run. In general, nanoplates provide partitions of fixed sizes that enable a very precise calculation of sample concentration. Potential variation of partition sizes in nanoplate batches, caused by different stampers (molding form for microstructures), can be addressed by applying the stamper-specific VPF. The VPF specifies the exact cycled volume of a well within a nanoplate and therefore further increases precision of concentration calculation in each well. If a VPF is not available for a particular nanoplate batch, concentrations are calculated using an average cycled volume per plate until the VPF is imported. The microstructure molding form is defined by the first two digits of the plate barcode.

Note: Multiple plate batches can come from one microstructure molding form.

New sets of VPFs will be published during production of the nanoplate batches and can be downloaded from the QIAGEN website.

7.6.3.1. Identification of VPF status on plates


In general, there are three possible states of the VPF on a plate:

- 1. **VPF applied** — VPF is already applied to plate, and it will be taken into account during concentration calculation.
- 2. **VPF not applied** — VPF is not applied to plate, and it will not be taken into account during concentration calculation. Plates without VPF will be analyzed using an average volume per plate.
- 3. **VPF unknown** — This is reserved for read-only plates originating from older versions of the Software Suite, where software cannot deduct if VPF was applied or not. During plate upgrade, described in Section 7.6.2 Plates after QIAcuity Software Suite version upgrade, the system assigns VPF, if available. VPF status and plate status display the following icon combinations on the plate overview:


Plate status/VPF status	Applied	Not applied	Unknown
Up to date (from current Software Suite version)			N/A
Read-only	N/A		
Upgraded			N/A

In addition, information about missing VPF is available on:

- 1. Plates Overview screen



- 2. Analysis screen



3. Plate Configuration screen



PlatesTemplatesData SpaceArchive

PLATE CONFIGURATOR
Generic_Plate_96well_8.5K

Run completedPlate ID: f1ba09bc-7ba5-406c-a4e1-f6279db7c27

ToolsConfigurationadmin

Plate templates...

General Data

dPCR parameters

Reaction mixes

General Data

ⓘ

Volume of wells is not optimized. Results may differ. We recommend you to upload the newest version of VPF (Volume Precision Factor) file and do recalculation.

Upload VPF

4. Report (on Plate general data page)



Generic_Plate_96well_8.5K

Plate general data

Plate nameGeneric_Plate_96well_8.5K

Plate typeNanoplate 9.5K 96-well

Barcode-

Labels-

VPFNot applied

Descriptionsome description

Plate Owners

User name	User login	Status
admin admin	admin	Active

Sample to Insight

3/34

Generated by admin admin (admin) on 28/04/2026, 15:08:54 UTC+02:00
via QIAculty Software Suite 3.5.0.0 | Report ID: fdc6878a-e91e-404b-a316-5b6a78466d77

7.6.3.2. Loading VPF

All existing VPFs to all used microstructure negative forms are bundled together in one zip file to allow the user to always download the most recent version. After uploading the file, the QIAcuity Software Suite automatically chooses which VPFs are missing and applies them. To load the most recent VPF, user can either click the **VPF** icon of the plate or directly click the **Upload VPF** button on the Plates Overview screen, Analysis screen, or on the Plate Configuration screen.

After uploading the file, the QIAcuity Software Suite automatically chooses which VPFs are missing and applies them. To load the most recent VPF, click the **Upload VPF** button on the Plates Overview screen, Analysis screen, or on the Plate Configuration screen. Once clicked, a new pop-up window will appear with detailed instructions. Follow the steps to properly load the most recent VPF file:

Upload Volume Precision Factor (VPF) ✕

The Volume Precision Factor (VPF) specifies the exact volume of a nanoplate of a specific batch providing most accurate concentration results. If a VPF is not available for a new nanoplate batch, concentrations are calculated using an average volume per plate until the VPF is downloaded.

- Go to <https://resources.qiagen.com/qiacuity-vpf> or as alternative go to www.qiagen.com and select:
Products > Instruments & Automation > PCR Instruments > QIAcuity Digital PCR System > Product Resources > Operating Software
- Download VPF file to your desktop or external disk
- Upload the downloaded zip file here

Drag and drop file here

or

Browse file

Cancel

Save

Note: The structure of the VPF file is a password-protected zip file. IT should be loaded in its zip form and should not be unzipped.

Note: New VPFs are valid for the whole system. When loaded, the QIAcuity Software Suite will refresh all plates and align concentrations using the newly loaded well-based volumes. The notifications about missing VPF for applicable plates will no longer be shown. All new imported plates and plates restored from the Archive will automatically receive the VPF assignment.

7.6.4. Custom cross talk matrix

To compensate for the spectral overlap between the fluorescent dyes called cross talk, a correction algorithm is implemented for the six standard channels (Green, Yellow, Orange, Red, Crimson, Far red) in the QIAcuity Software Suite. This standard cross talk matrix is automatically applied to experiments using abovementioned standard channels and no additional actions are required from the users.

In experiments, where any of the high multiplex channel combinations are activated for imaging, a dedicated custom cross talk matrix (CXTM) could be prepared for result optimization. The following five channel combinations are available for multiplexing:

- Green/Yellow
- Yellow/Orange
- Orange/Red
- Red/Crimson
- Crimson/Far red

A notification is provided about the required custom cross talk matrix when additional multiplex channel combinations are configured during imaging settings for a plate.

Channel	Exposure duration	Gain
Green	300 ms	6
Yellow	250 ms	4
Channels available for high multiplex instruments only		
Orange	150 ms	3
Red	150 ms	3
Crimson	300 ms	4
Far red	600 ms	8
Green / Yellow	1000 ms	6
Select channel		

The creation of a custom cross talk matrix is not limited to the multiplex channel combinations only but can be created for any desired channel usage. If, for example, the default matrix is creating artifacts affecting setting threshold, a custom cross talk matrix can be also created for any standard channel/s.

Custom cross talk matrix can be created from two channels up to eight channels. There is no limit to the number of custom cross talk matrixes that can be generated.

For using amplitude multiplexing mode, the custom cross talk matrix needs to be created for the standard channels and/or channel combinations, and afterwards, the reaction mix needs to be edited to enable amplitude multiplexing.

7.6.4.1. Preparing custom cross talk matrix (CXTM)

For creation of a custom cross talk matrix (CXTM), a dedicated training plate needs to be created. This plate must exhibit all targets of interest (from one up to eight targets) as individual simplexes. For example, if a custom cross talk matrix is desired for a triplex reaction mix, all three individual targets must be available as simplexes on one dedicated plate. Wells containing no template controls (reaction mix only) are also required on the same plate. The plate used to create the CXTM can also contain the desired multiplex reaction so that the results can be checked directly. The dedicated CXTM plate should be processed as usual and afterwards the CXTM configurator can be opened.

Note: While setting imaging on the plate, the reference channel must also be taken into consideration. To use the High-Multiplexing Reference channel in experiments along with the custom cross talk matrix, the High-Multiplex reference channel should be enabled for the training plate. In addition, all simplexes should exhibit identical High-Multiplex reference. In general, all simplexes and the reference wells (exhibiting reaction mix only without template) should exhibit identical reference. There is no mixture of standard and High-Multiplex reference allowed.

Important: Preparing a custom cross talk matrix is permission dependent. The following permissions are required to trigger the CXTM configurator: Create Custom Cross Talk Matrix, Create template, Read all/owned plates.

Important: To trigger the CXTM configurator on a training plate, the following conditions must be met:

- The plate has to be up to date (read-only plates should be upgraded).

Note: Plates coming from versions older than 3.0 exhibit different default imaging settings for the channels. They can give sub-optimal results in final experiments, if different Imaging settings are used. To obtain optimal cross talk correction in final experiment where reaction mix template with CXTM is used, make sure that Imaging settings are the same as in training plate (expand and check the CXTM details section in the reaction mix template) and adapt the plate template according, if required.

- The plate layout needs to be defined, with at least one well per target exhibiting a simplex reaction mix for the desired target and at least one well that exhibits reaction mix only without any target.

Note: Amplitude multiplexing usage is not feasible for custom cross talk matrix creation. The targets need to be assigned to normal channels or channel combinations, without enabling amplitude multiplexing mode.


- Plate must have results (experiment in status "finished") for all dedicated reaction mixes.

Note: Optimal results for the custom cross talk matrix will strongly depend on the quality of experimental results in the CXTM training plate. The user who prepares the CXTM training plate should:


1. Minimize the number of invalid partitions for each channel.
2. Assure that there are no warnings (e.g., saturation problems) on the training plate.
3. Assure there are approximately 25–75% of positive partitions per Nanoplate well per simplex reaction.
4. Ensure that the same assays are used in actual experiments as were used on the CXTM plate.

To finally prepare custom cross talk matrix user should follow the procedure below:

1. The CXTM configurator can be triggered from any dedicated plate in the plate overview or during analysis. In the plates overview environment, plates that fulfil the pre-requisites for CXTM creation, exhibit the **Create CXTM** function under the three-dot menu:




To start the CXTM creation during analysis, click **More** and select **Create CXTM**.



2. After selecting the **Create CXTM** option, user is guided to the CXTM configurator automatically. The configurator consists of four steps.

Note: For plates that are up to date but the rest of the conditions described above are not met, the option is not active:




Important: While working with the CXTM configurator, do not log out manually nor let automatic system log off occur to avoid lost progress. User must always start over in the configurator if logged out mid-session.


- a. **Step 1: Reference channel** – This is the first step, where NTC reaction mix-only wells are selected within the chosen imaging step in the plate layout and are then assigned to CXTM.

Under plate layout, a list with detected reference channels for the selected wells is displayed. In case of mixed scenarios, user should select the appropriate one, depending on the desired CXTM. High-Multiplexing Reference not only is always required for more than 6-plex experiments but also can be used optionally for other user scenarios, as described in Section 7.4.5.4 Imaging tab. At least one well exhibiting reference channel must be selected.

At this step, all wells that are not suitable for selection are automatically disabled. This includes wells containing targets, wells without images, wells with missing reference channels, and wells with different type of references than the one already selected.



After selecting wells with the proper reference channel type, click the **Add to CXTM** button.



After adding wells to the custom cross talk matrix, an information table containing Channel, Target, Wells, and reference type selected is presented.


Select imaging step
1 2

Green (300ms / 6) Red (150ms / 3) Green / Yellow (1000ms / 6)
Yellow (250ms / 4) Crimson (300ms / 4) Orange / Red (1000ms / 6)
Orange (150ms / 3) Far red (600ms / 8)

Custom cross talk matrix

Channel	Target	Wells
Reference	-	E4-E5, F4-F5 HM-Ref

In case of wrong selection, user can remove it using the **trash** icon.




After reference channel is added correctly to CXTM, click the **Next** button at the bottom of screen.

- b. **Step 2: Target channels** – In this step, select and assign wells exhibiting the targets/channels that should be used for CXTM creation. Click appropriate well/s and then on **Add to CXT matrix**.

Wells that are not suitable to be selected are automatically disabled. This includes blank and empty wells, wells with multiple targets, wells without images, wells with missing reference channels, and wells with different type of reference than selected in the first step of the configurator.

Add all desired channels/targets in this step as there is no possibility of adding them later nor to of updating the custom cross talk matrix. While adding one simplex, wells with other simplexes remain inactive. Hover with the mouse over the wells to view a tooltip with information about Sample, NTC, or Control. Up to 8 channels can be selected on this step. After selecting well(s), a panel on the right side presents information about well(s) and selected target and channel.



When all desired targets/channel of interest are added, click **Next** to continue.

CXTM CONFIGURATOR
Plate_for_CXTM_wizard_8_plex

Reference channel — Target channels — Review & correction — Create new reaction mix

Unselect all

One or more wells are not suitable for CXTM configuration and have been disabled.

Custom cross talk matrix

Channel	Target	Wells
Reference	-	E4-E5, F4-F5 HM-Ref
Yellow	T2	C2-C3
Green	T1	B2
Far red	T6	B4-B5
Green / Yellow	T7	C4
Orange	T3	D2
Orange / Red	T8	D4
Red	T4	E2
Crimson	T5	F2-F3

Back Next


- c. **Step 3: Review & correction** – In this step, the thresholds for particular well exhibit that the simplex reactions can be adjusted, if it is required. The plots do not exhibit any cross talk correction that is usually visible on regular 1D Scatterplots during Analysis (exhibiting default cross talk matrix for the standard channels).

Note: Generating 1D Scatterplots in this step may take a while. Do not refresh the page until all plots are generated. When this operation is ongoing, the following information and spinner are presented:



Preparing the data, this may take a while... Don't refresh the page.

When all plots are generated, user can make thresholds corrections in similar way like on regular 1D Scatterplot on Absolute Quantification analysis.



After all threshold corrections are done, press the **Next** button at the bottom of the screen to go to the last step.

- d. **Step 4: Create new reaction mix** – In this step, user saves created custom cross talk matrix along with new reaction mix template. Similar for regular reaction mix template, it is mandatory for user to input Template name and Reaction mix name (see further detail under Section 7.5.4 Creating a new reaction mix template). Optionally, user can define Total volume parameter and change the color. In the section below, there is a list of targets that user defined in step 2 of configurator. User can change the names of the targets, select used dyes, and assign internal control for each channel. To save CXTM along with reaction mix template, press the **Save** button at the bottom of screen.

Note: User cannot apply Amplitude multiplexing here; it can be applied later after saving template.

Important: Calculated cross talk strictly depends on dyes; thus, dyes selected here cannot be changed later from reaction mix template edition level.

QIAGEN CXTM CONFIGURATOR
Plate_for_CXTM_wizard_8_plex

Reference channel — Target channels — Review & correction — **Create new reaction mix**


Template name * Characters left: 96
TMPL

Reaction mix name * Characters left: 98 Total volume
RM µL Change color

Color	Target Name *	Dye	Channel(s) *	Internal control
■	T2	VIC	Yellow	☐
■	T1	FAM	Green	☐
■	T6	Cy 5.5	Far red	☐
■	T7	LSS GY	Green / Yellow	☐
■	T3	TAMRA	Orange	☐
■	T8	LSS QR	Orange / Red	☐
■	T4	RDX	Red	☐

← Back Save

After successful saving of CXTM, an information message at the top of screen appears and the plate configurator is closed.



7.6.4.2. Saturation detection

While creating a new reaction mix template (Step 4: Create new reaction mix, described above), the system calculates whether the current gain and exposure settings in the training plate can cause a problem with saturation on a given channel in final experiments on any plates where this reaction mix template with CXTM will be used. If the system detects a potential problem, user is presented with an appropriate warning in CXTM Configurator.

Due to the impact of different targets on one partition in the final reaction mix, following channels listed below may reach saturation. If the nanoplate used is still available and has been stored according to the recommended conditions, please try re-exposing the nanoplate with the recommended exposure duration and gain listed below.

Channel	Imaging parameters (exposure duration / gain)
● Orange	120/3
● Orange / Red	920/5

Important: This warning will be presented even when a given channel with potential saturation is not added to the reaction mix template at the last step; if a given channel is physically oversaturated, it already has a negative impact on neighboring channels and experimental results.

If user saves the reaction mix template with CXTM despite the above warning, additional information is presented across the application:

- On **Templates** tab in Reaction mixes template list

Templates

Plates | Reaction mixes

Sort by:
Modification date [descendin...]

The applied custom cross talk matrix exhibits saturation for some channels, which might lead to inaccurate results. For more information, please see CXTM details of the Reaction mix.

Search by template or reaction mix name Search

Template name	Reaction mix name	CXTM	nd by	Last modification
TMP_L_CXTM	RM_CXTM	✓ Yes	admin	10/03/2025, 13:22:50 UTC+01:00

- In reaction mix template details

Reaction mix creation

Add Analysis Rules

Template name *

TMPL_CXTM

Characters left: 91

Reaction mix name *

RM

μL

Change color

Amplitude multiplexing

CXTM applied

Details

Base plate name:

Plate_for_CXTM_wizard_8_plate

Base plate ID:

3e4e4154-d876-482b-a045-e51d826513b5

Reaction mix template name:

TMPL

Reaction mix template ID:

5a05b85f-e09f-4373-9a73-00ac03907299

Created:

28/04/2026, 15:59:04 UTC+02:00

Created with:

QIAcuity Software Suite 3.5.0.0 (Suite ID: 18b883bf-79fb-4888-bc3d-3bed744acd)

Channel

Imaging parameters

Wells

	(ref. channel)	E4-E5, F4-F5
● HM: Ref		
● Green	300M	B2
● Yellow	250M	C2-C3
● Orange	150J	D2
● Red	150J	E2
● Crimson	300M	F2-F3
● Far red	600R	B4-B5
● Green / Yellow	1000R	C4
● Orange / Red	1000R	D4

The applied custom cross talk matrix exhibits saturation for channels Orange, Orange / Red which might lead to inaccurate results.

Color

Target Name *

T1

T2

Dye

FAM

Green

Internal control

VIC

Yellow


Internal control

Channel(s) *

Green


Yellow

- While importing reaction mix template



- After importing into the Reaction mixes section on Plate Configurator (General View and Detailed List)

Reaction mixes



Reaction mixes

Reaction mixes				
General View Detailed List				
New Reaction Mix Import from template				
RM_CXTM CXTM	Target	Dye	Channel	IC
	T1	FAM	Green	-
	T2	VIC	Yellow	-
	T3	TAMRA	Orange	-
	T4	ROX	Red	-
	T5	Cy5	Crimson	-
	T6	Cy 5.5	Far red	-
	T7	LSS G/Y	Green / Yellow	-
	T8	LSS Q/R	Orange / Red	-

- Add Reaction Mix (B6)

Assign existing
Create new

Reaction mixes

RM_OXTM
OXTM

Target	Dye	Channel	Total volume
T1	FAM	Green	-
T2	VIC	Yellow	-
T3	TAMRA	Orange	-
T4	ROX	Red	-
T5	Cy5	Cyan	-
T6	Cy 5.5	Far red	-
T7	LS5 GY	Green / Yellow	-
T8	LS5 GR	Orange / Red	-

- During analysis on List view

QIAcuity User Manual | 07/2026

- In PDF report



Plate_for_CXTM_wizard_8_plex

Reaction Mixes

Reaction Mix	Target name	Dye	Channel	IC
RM_CXTM CXTM	T1	FAM	Green	-
	T2	VIC	Yellow	-
	T3	TAMRA	Orange	-
	T4	ROX	Red	-
	T5	Cy5	Crimson	-
	T6	Cy 5.5	Far red	-
	T7	LSS G/Y	Green / Yellow	-
	T8	LSS O/R	Orange / Red	-
RM1	T1	FAM	Green	-
RM2	T2	VIC	Yellow	-
RM3	T3	TAMRA	Orange	-
RM4	T4	ROX	Red	-
RM5	T5	Cy5	Crimson	-
RM6	T6	Cy 5.5	Far red	-
RM7	T7	LSS G/Y	Green / Yellow	-
RM8	T8	LSS O/R	Orange / Red	-

Sample to Insight

12/16

Generated by admin admin (admin) on 29/04/2026, 13:23:03 UTC+02:00
via QIAcuity Software Suite 3.5.0.0 | Report ID: 96bda3e2-5e36-4961-aeac-4946735f9ec1



Plate_for_CXTM_wizard_8_plex

CXTM 1

Reaction Mix	RM_CXTM
Base plate name	Plate_for_CXTM_wizard_8_plex
Base plate ID	1f34f28e-637a-4895-b7c8-7d1fb8e5efb6
Reaction mix template name	TMPL_CXTM
Reaction mix template ID	36fd6a96-85e6-4f83-9299-7f727780a3c6
Created	28/04/2026, 14:55:36 UTC+02:00
Created with	QIAcuity Software Suite 3.5.0.0 (Suite ID: 18b883bf-7bfb-4688-8c9b-69eb6744cee8)

Channel	Imaging parameters	Wells
HM-Ref	(ref. channel)	B6, B7
Green	300/6	B2
Yellow	250/4	C2
Orange	150/3	D2
Red	150/3	E2
Crimson	300/4	F2
Far red	600/8	B5
Green / Yellow	1000/6	C5
Orange / Red	1000/6	D5

Sample to Insight

13/16

Generated by admin admin (admin) on 29/04/2026, 13:23:03 UTC+02:00
via QIAcuity Software Suite 3.5.0.0 | Report ID: 96bda3e2-5e36-4961-aeac-4946735f9ec1

Absolute Quantification (Imaging step 1)

Well	Sample / NTC / Control	Reaction Mix	Channel			Concentration ¹⁾		Partitions	Valid Positive Negative	Threshold
			Channel	IC	Control	dPCR reaction cp/μL	CI (95%)			
B6	-	RM_CXTM CXTM Ref. channel: HM-Ref	Green	-	-	0.000	-	8246 0 8246		10.46
			Yellow	-	-	0.000	-	8246 0 8246		7.91
			Orange	-	-	0.000	-	8246 0 8246		21.93
			Red	-	-	178.5	8.9%	8230 484 7746		35.06
			Crimson	-	-	0.000	-	8246 0 8246		16.83
			Far red	-	-	0.000	-	8246 0 8246		6.63
			Green / Yellow	-	-	0.000	-	8246 0 8246		11.73
			Orange / Red	-	-	0.000	-	8246 0 8246		10.46

¹⁾ Presented results do not include the Volume Precision Factor

Sample to Insight

15/16

Generated by admin admin (admin) on 29/04/2026, 13:23:03 UTC+02:00
via QIAcuity Software Suite 3.5.0.0 | Report ID: 96bda3e2-5e36-4961-aeac-4946735f9ec1

7.6.4.3. Usage of custom cross talk matrix

7.6.4.3.1. Template level

All available reaction mixes templates are listed template list. When the reaction mix exhibits custom cross talk matrix, it is marked in CXTM column.

Plates Templates Disk Space Archive Tools Configuration admin					
Templates					
Plates Reaction mixes Sort by: Modification date (descendin...) Search by template or reaction mix name Search New template					
Template name	Reaction mix name	ID	Analysis rules	CXTM ⓘ	Modified by
TMPL_CXTM	RM	5b058c5f-ee9f-43f7-9e73-00ac03907299	-	✓ Yes ⓘ	admin
TMPL_CXTM_8PLEX	RM_CXTM	36f6a96-85e6-4f83-9299-71727780a3c6	-	✓ Yes	admin

Note: When CXTM exhibits saturation in a specific channel, this information is displayed as a tooltip for the “i” icon.

Plates Templates Disk Space Archive Tools Configuration admin					
Templates					
Plates Reaction mixes Sort by: Modification date (descendin...) Search by template or reaction mix name Search New template					
Templ	The applied custom cross talk matrix exhibits saturation for some channels, which might lead to inaccurate results. For more information, please see CXTM details of the Reaction mix.				
Template name	Reaction mix name	ID	Analysis rules	CXTM ⓘ	Modified by
TMPL_CXTM	RM	5b058c5f-ee9f-43f7-9e73-00ac03907299	-	✓ Yes ⓘ	admin
TMPL_CXTM_8PLEX	RM_CXTM	36f6a96-85e6-4f83-9299-71727780a3c6	-	✓ Yes	admin
RM_template	RM1	84c37a11-53ab-44d4-a13d-eb2bb9006cda	-	-	admin

When a user with sufficient permissions clicks the three-dot icon and selects the **Details/Edit** option, the “Edit reaction mix template” window is presented.

An additional CXTM section applied with expandable details is presented. After expanding user is presented with details of cross talk matrix:

- **Base plate name** – name of the plate that was used to prepare matrix in CXTM configurator
- **Base plate ID** – UUID of above plate
- **Reaction mix template name** – name of reaction mix template given in CXTM configurator
- **Reaction mix template ID** – UUID of above reaction mix template
- **Created** – date of creation of reaction mix template
- **Created with** – QIAcuity Software Suite version and UUID used for creation of above reaction mix template
- **Channel – Imaging parameters – Wells** – set of wells and their parameters used to prepare matrix in CXTM configurator

CXTM applied Details		
Base plate name:	Plate_for_CXTM_wizard_8_plex	
Base plate ID:	1f3428e-637a-4895-b7c8-7d1fb8e5eb6	
Reaction mix template name:	TMPL_CXTM	
Reaction mix template ID:	36f6da96-85e6-4ff3-9299-7f727780a3c6	
Created:	28/04/2026, 14:55:36 UTC+02:00	
Created with:	QIAcuity Software Suite 3.5.0.0 (Suite ID: 18b883bf-7bf8-4688-8c9b-69eb6744cee8)	
Channel	Imaging parameters	Wells
☐ HM-Ref		(ref. channel) B6-B7
☒ Green		300/6 B2
☐ Yellow		250/4 C2
☐ Orange		150/3 D2
☐ Red		150/3 E2
☐ Crimson		300/4 F2
☐ Far red		600/8 B5
☐ Green / Yellow		1000/6 C5
☐ Orange / Red		1000/6 D5

Note: When CXTM exhibits saturation in a specific channel, this information is visible as additional information section.

CXTM applied Details		
Base plate name:	Plate_for_CXTM_wizard_8_plex	
Base plate ID:	3b4e4154-d876-4dcb-a545-ed1d82e513b5	
Reaction mix template name:	TMPL	
Reaction mix template ID:	5b058c5f-ee9f-43f7-9e73-00ac03907299	
Created:	28/04/2026, 15:59:04 UTC+02:00	
Created with:	QIAcuity Software Suite 3.5.0.0 (Suite ID: 18b883bf-7bf8-4688-8c9b-69eb6744cee8)	
Channel	Imaging parameters	Wells
☐ HM-Ref		(ref. channel) E4-E5, F4-F5
☒ Green		300/6 B2
☐ Yellow		250/4 C2-C3
☐ Orange		150/3 D2
☐ Red		150/3 E2
☐ Crimson		300/4 F2-F3
☐ Far red		600/8 B4-B5
☐ Green / Yellow		1000/6 C4
☐ Orange / Red		1000/6 D4

 The applied custom cross talk matrix exhibits saturation for channels Orange, Orange / Red which might lead to inaccurate results.

While editing reaction mix template, user can modify the following content:

- Change Template name
- Change Reaction mix name
- Change Total volume
- Change Color
- Change Targets names
- Apply the **Amplitude multiplexing** option for any channel/s included in the custom cross talk matrix

Other modifications are blocked to ensure that CXTM is always consistent with reaction mix template and will not be detached. Changes are applied directly after clicking the **Update** button on modal.

7.6.4.3.2. Plate level

During plate creation, user can import reaction mix template along with CXTM, like already described in Section 7.4.9 Importing reaction mixes from templates. To ease identification, they have special **CXTM** icon.

CXTM icon () , informing that reaction mix consists of CXTM, is presented on Reaction mix General View and Detailed List, during assigning of reaction mix to wells, and on well information modal.

After importing, user can review reaction mix and CXTM parameters and edit the Reaction mix name, the Target name, Internal control option, Total volume parameter, or color. In addition, the amplitude multiplexing function can be activated. Depending on modification, the CXTM can be kept or will be detached.

The following edits that do not affect the CXTM can be performed:

- Change reaction mix name
- Change total volume
- Change color
- Change targets names
- Remove some of targets/channels (whole rows using trash icon), but at least one of channels from prepared CXTM (visible in details windows above) needs to be remained.

When amplitude multiplexing is applied, one part of channel (Low or High) is sufficient.

- Apply Amplitude multiplexing split for any channel(s).

After applying AM split, both parts (High and Low) need to have the same dye, and this dye must be the same as set in CXTM. For example, if CXTM consists of Green channel with FAM dye and user decides to apply AM split on Green channel, then Green (Low) and Green (High) parts must have FAM set as a dye to keep that CXTM.

- Enable Internal control option

Reaction mix creation [Add Analysis Rules](#)

Information (1)

This modification is going to change this reaction mix everywhere it's used. If you'd like to assign another reaction mix, remove this one from the well first.

Warning (1)

When selecting Amplitude Multiplexing, please ensure that High-Multiplexing-Reference channel in imaging parameters is enabled.

Reaction mix name * Characters left: 93 Total volume

RM_CXTM

Amplitude multiplexing ☐ Green ☐ Yellow ☐ Orange ☐ Red ☐ Crimson ☐ Far red ☐ Green / Yellow ☐ Yellow / Orange ☐ Orange / Red ☐ Red / Crimson ☐ Crimson / Far red

CXTM CXTM applied Details

Color	Target Name *	Dye	Channel(s) *	Internal control	
☐	T1L	FAM	Green (Low)	☐	Internal control
☐	T1H	FAM	Green (High)	☐	Internal control
☐	T2	VIC	Yellow	☐	Internal control
☐	T3	TAMRA	Orange	☐	Internal control
☐	T4	ROX	Red	☐	Internal control
☐	T5	Cy5	Crimson	☐	Internal control

Changes made in reaction mix that will keep CXTM.

Performing one of the following changes results in the loss of the CXTM:

- Dye change
- Addition of channel that was not included for CXTM creation

The following warning is shown in case of dye change and/or channel addition:

Reaction mix creation [Add Analysis Rules](#)

Information (1)

This modification is going to change this reaction mix everywhere it's used. If you'd like to assign another reaction mix, remove this one from the well first.

Warning (1)

Your modifications (adding channel/s and/or changing dye/s) have caused inconsistencies with the currently assigned custom cross talk matrix of this reaction mix, resulting in the loss of your custom cross talk matrix. Please review the changes to ensure they are intentional.

Reaction mix name * Characters left: 93 Total volume


RM_CXTM

Amplitude multiplexing ☐ Green ☐ Yellow ☐ Orange ☐ Red ☐ Crimson ☐ Far red ☐ Green / Yellow ☐ Yellow / Orange ☐ Orange / Red ☐ Red / Crimson ☐ Crimson / Far red

Color	Target Name *	Dye	Channel(s) *	Internal control	
☐	T1	SYBR Green	Green	☐	Internal control
☐	T2	VIC	Yellow	☐	Internal control
☐	T3	TAMRA	Orange	☐	Internal control
☐	T4	ROX	Red	☐	Internal control
☐	T5	Cy5	Crimson	☐	Internal control
☐	T6	Cy 5.5	Far red	☐	Internal control
☐	T7	LSS G/Y	Green / Yellow	☐	Internal control

To save the changes, click the **Update** button and **Save**.

For experiments where high multiplexing channel combinations are activated, the user is warned during reaction mix creation that preparation of CXTM is recommended to obtain accurate results.



Similar warnings (exclamation mark) are presented on Detailed List.

This reaction mix uses new channel combinations and does not exhibit a custom cross talk matrix (CXTM) resulting in not accurate results.	I6	Ly 5.5	Far red	-
	T7	LSS G/Y	Green / Yellow	-
	T8	LSS O/R	Orange / Red	-

And later on Analysis:

Warning (1)

Channel cross talk notice

Reaction mixes: "RM8", "RM7" use new channel combinations and do not exhibit a custom cross talk matrix (CXTM). This might result in incorrectly set thresholds which may lead to inaccurate results. Create a custom cross talk matrix according to the user manual or assign an existing reaction mix template which includes a custom cross talk matrix.

ListSignalmapHeatmapHistogram1D Scatterplot2D ScatterplotConcentration diagram

☐ Add to report☐ Show mean values for replicatesExport to CSV...

Well	Sample/NTC/Control	Reaction Mix	Channel			Concentration		Partitions			Threshold
			Name	IC	Control	dPCR Reaction	C (95%)	Valid	Positive	Negative	
C5	-	RM7 Ref channel: HM-Ref	Green	-	-	361.4	9.4%	8121	433	7688	13.39
			Yellow	-	-	0.000	-	8129	0	8129	11.73
			Orange	-	-	0.000	-	8129	0	8129	18.11
			Red	-	-	0.000	-	8129	0	8129	13.01
			Crimson	-	-	0.000	-	8129	0	8129	7.91
			Far red	-	-	0.000	-	8129	0	8129	6.63
			Green / Yellow	-	-	360.3	9.5%	8121	430	7691	24.86
			Orange / Red	-	-	0.000	-	8129	0	8129	52.53
			Green	-	-	0.000	-	8172	0	8172	13.01
			Yellow	-	-	0.000	-	8172	0	8172	10.46
D5	-	RM8	Orange	-	-	0.360	147.5%	8172	1	8171	27.03
			Red	-	-	0.000	-	8172	0	8172	25.76


Back to plate configurator

0 items selectedCreate report

1. Channel cross talk notice (third on warning list above) warns which reaction mixes are missing CXTM. (If no reaction mixes are assigned to plate layout, warning is very similar but does not point reaction mixes names.)
2. Exclamation mark on List View – similar like on **Reaction mixes** tab.
3. Additionally, when Imaging settings (channels, exposure, and duration) on plate are different from the one used in reaction mix imported from template with CXTM, another warning (second on warning list above), listing reaction mixes with that issue, is presented.

7.6.5. Images

1. The Software Suite also enables user to view the images. After a run is completed, user can view the images in the Plate Analysis environment. For more information about how to access the Plate Analysis, see Section 7.6.1 Accessing the analysis environment. To access the images, click **Check source images** icon.
2. To select a channel, click the corresponding button next to the relevant channel. Only channels where imaging took place are available.
3. To zoom in and out, click the image.
4. To download, click the image to open it on a new window. Then, click the  icon located at the top left corner of the image.
5. To copy the image to Windows clipboard, click  **Copy** icon located at the top left corner of the image.



Note: Errors affecting single wells or empty wells are indicated by a  symbol in the affected well. Try reimaging the plate with different exposure and/or gain settings. If the error persists, create a support package and contact QIAGEN Technical Service.

7.6.5.1. Image quality control


The fluorescence signal in the reference channel is measured to determine the number of valid partitions in a well. Differences in the signal intensities between partitions are normalized, and the fluorescence signals in the target channels are corrected accordingly.

If the fluorescence signal is saturated in too many partitions of a well in a target channel, a warning message will be shown to the customer. Furthermore, saturated signals are marked with  in the Results overview. Saturated signals lower the signal-to-noise ratio and can lead to improper analysis results; for example, the cross talk correction algorithm might be affected. The recommendation is to re-image the plate with 30% less exposure time in the respective channel.

Note: The optimal RFU range of your positives is between 80 and 120 to avoid saturation and proper functioning of image analysis algorithms. Use exposure time changes (linear dependency) to optimize the RFU level. For RFU values below 60, it is recommended to increase the exposure time of the corresponding channel/s, and for RFU values above 150, it is recommended to decrease the exposure time of corresponding channel/s.



In case more than one imaging step has been done, the imaging step where the saturation occurred is marked in yellow and the warning message is shown when moving the mouse over the **camera** icon.




7.6.6. Invalidation of images

In rare cases, the image quality can be too low and the image cannot be used for further analysis. A message is shown to the customer that some wells have been invalidated. Those wells are grayed out in the plate layout and cannot be used for the result analysis.

Note: This message also appears if not all wells were used in the run. For that situation, ignore the message.



In case more than one imaging step has been done, the imaging step where the low signal quality occurred is marked in red and the message is shown when moving the mouse over the **camera** icon.



Reasons for the invalidation of an image are:

1. Lesser fluorescence signal, for example, when the nanoplate was re-imaged after a long storage period (see Section 5 Operating Plates for information about the storage of plates).
2. Vibration during the imaging process can lead to blurry images. If the image of the reference channel is affected, the number of valid partitions cannot be determined and the whole well is invalidated for analysis. If a target channel is affected, only the image of the respective channel is invalidated for analysis.
3. Incomplete filling of a well can lead to too few valid partitions in the reference channel needed for analysis. In this case, the whole well is invalidated.


7.6.7. Image corrective measures

To ensure proper analysis based on valid partitions, artifacts that could influence the result analysis are removed from the images. The corrections are done automatically by the QIAcuity Software Suite and do not require any user action. The partitions that are affected by artifacts are blacked out and are invalidated for further analysis. Artifacts can be:


1. Dust and other particles
2. Low amplification areas
3. Areas of bad filling

7.6.8. Dust and other particles

Dust and other particles like hairs or strands are detected by the QIAcuity Software Suite and are removed from the images. This figure shows an example of a well before and after dust/other particles correction.



Raw image of a well showing dust particles (marked with red circles).




Signal map of the dust-corrected image.

In case the images still show dust particles or other particles after the correction, the recommendation is to unload the plate, wipe the plate with a lint-free tissue, and re-image the plate.

Note: For QIAcuity Software Suite version 2.0 or higher, dust detected in one channel is used for finding dust in other channels as well. If required, to improve dust detection, always image all channels even not used by assay(s).


The QIAcuity Software Suite version 2.1 exhibits an improvement for dust detection for dust causing light infections of neighbor partitions. This figure shows an example of a well before and after smear dust correction.



Improved dust detection for dust causing light infections of neighbor partitions: left, not sufficient dust removal; right, sufficient dust removal with QIAcuity Software Suite version 2.1. Affected area is removed from analysis and therefore partitions are invalidated.

7.6.9. Low amplification areas


In case of low amplification areas, the fluorescence signal in the target channels is less pronounced or not detectable in certain areas of the well. The signal in the reference channel is not affected. If an equal amplification does not take place in the well, the area of low amplification does not meet the requirements for Poisson distribution. Therefore, the partitions in those areas are blacked out in the image and are not included in the analysis.



Signal map of an image with blacked-out low amplification areas.

7.6.10. Areas of bad filling

Incorrect pipetting or sealing can lead to areas of the well which are not filled with reaction mix. Those areas affect the reference channel as well as the target channels and reduce the number of valid partitions. See Section 5 Operating Plates for instructions on how to pipet and seal the nanoplates properly.



Signal map of an image showing areas of bad filling.

7.6.11. Amplitude multiplexing

Starting with the QIAcuity Software version 3.1, the amplitude multiplexing option is available next to the optical channel multiplexing. Amplitude multiplexing utilizes the differences of amplitude in fluorescence intensity of partitions. By setting the appropriate three thresholds, four bands of partitions can be clustered: double positives, high target positives, low target positives, and low target negatives.



For amplitude multiplexing usage, each channel is divided into a High and a Low part. Up to 16 channels (including High and Low) can be defined in total. Refer to Section 7.4.6 Reaction mixes tab for more details on how to prepare reaction mix with amplitude multiplexing usage. Refer to Section 7.6.15 Absolute quantification for more details about how to enable and use amplitude multiplexing during analysis.

7.6.12. Cross talk correction

Depending on the optical configuration of the QIAcuity instrument, user can detect up to two or eight fluorescent channels. To compensate for the spectral overlap between the fluorescent dyes, a cross talk correction algorithm is implemented in the QIAcuity Software Suite.

When up to six standard channels are used in experiment, the correction is done automatically by the software by a default cross talk matrix and does not require any user action. The bleed-through signals are removed from the images and are not taken into account in the result analysis. The cross talk correction is correcting an absolute value based on the RFU level of the neighboring channel.

For multiplex channel combination usage, a dedicated custom cross talk matrix needs to be prepared upfront and the reaction mix template should be applied in the experiment.

Refer to Section 7.6.4 Custom cross talk matrix for more details on how to prepare custom cross talk matrix to apply above correction.

The bleed-through signals are removed from the images and are not taken into account in the result analysis. The cross talk correction is correcting an absolute value based on the RFU level of the neighboring channel.

Note: In case insufficient compensation or overcompensation is seen (e.g., as double negative bands), check the RFU level of positive signals of neighboring channels if saturated or very bright. By lowering the RFU level of positive signals, insufficient compensation or overcompensation might be reduced.

7.6.13. Reference channel discrepancies

When different reference channels have been assigned to wells with the same reaction mix (reference channel discrepancies), it can lead to the situation that user will obtain inaccurate results. Such situation may happen in case of human error, for example, when pipetting reaction mix to well or reference channel has been wrongly recognized (e.g., due to image quality).

Important: In case of reference channel discrepancy, well cannot be grouped into hyperwells.

Software version 3.0 informs the user about reference channel discrepancies.

In the following example, despite the same reaction mix has been assigned to wells A1 and B1, different reference channels have been detected: Std-Ref in well A1 and HM-REF in well B1.

Well Information (A1)

Reaction mix nameRM1_3plex

Total volume per well-

Ref. channel:

1:

Std-Ref

Target	Control	Dye	Channel	IC
T1	-	-	Green	-
T2	-	-	Yellow	-
T3	-	-	Far red	-

Close

Well Information (B1)

Reaction mix nameRM1_3plex

Total volume per well-

Ref. channel:

1:

HM-Ref

Target	Control	Dye	Channel	IC
T1	-	-	Green	-
T2	-	-	Yellow	-
T3	-	-	Far red	-

Close

In such case, user is warned about discrepancy in:

- **Plate layout** – Indicator is presented if discrepancy exists on any of Imaging step.

Different reference dyes were detected for the following wells, which do not match the pre-settings of the reaction mix. Please check whether the reaction mix assignment was carried out correctly and adjust the plate layout if necessary.


B

QIAcuity User Manual | 07/2026

227

- **Analysis**

- **Warning** – User can go back to plate configurator and do needed adjustments.



- **Exclamation mark** on List view next to wells with reference discrepancies.

<

- **CSV export – Current results** – “REF” if particular wells have different reference channel assigned.


- **Reports**

- The “Warnings” section presents Reaction mix, Imaging step, and Wells with reference channel discrepancy issue.
- List View – when added contains exclamation marks next to wells informing which wells have issue.

7.6.14. General analysis options

7.6.14.1. Selecting wells for analysis

1. To select multiple wells at the same time, click the individual wells or click one well then drag your mouse until all wells are selected.
2. To select all wells, click **Select all**.
3. To remove a selected well, click the well.
4. To remove all selected wells, click **Unselect all**.



To view more information about an individual well, double-click the well in the plate layout. The Well Information dialog box appears. Click **OK** to close the dialog box.

Well Information (A2)

Reaction mix name

DPH218 ERBB2 + DPH186 TERT

Total volume per well

-

Sample ID

01

Sample name

1ng gDNA

Ref. channel:

1

Std-Ref

Concentration factor

-

Template volume per well

-

Conversion factor

-

Conversion unit

-

Target

IC

Dye

Channel

1

DPH218 ERBB2

-

FAM

Green

2

DPH186 TERT

-

HEX

Yellow



Close

7.6.14.2. Hyperwells

To achieve higher accuracy, multiple wells can be grouped together and analyzed as a single well. To define a hyperwell, select multiple wells with the same reaction mix and same sample name.



By clicking **Group as hyperwells**, the software automatically groups all selected samples exhibiting the identical reaction mix and sample to hyperwells. User can get the same result by right-clicking and selecting **Group as hyperwell** from the context menu for previous selected wells.



To ungroup the hyperwell, select the hyperwell and click **Ungroup hyperwell** from the menu below or from the context menu.

For the analysis, hyperwells are treated as a single well but with a larger number of partitions. This may be helpful for rare event detection if the sample volume to be analyzed exceeds the volume that can be loaded into a single well. Results from all wells coupled into a hyperwell will be aggregated and presented as a result from a single well.

Details about CI calculation and concentration determination in hyperwells are described in the *QIAcuity User Manual Extension: QIAcuity Application Guide* available at www.qiagen.com.

Hyperwells can be selected for Absolute Quantification, Mutation Detection, and Genome Editing, Copy Number Variation, and Gene Expression analysis.

7.6.14.3. Using hyperwells in second-level analysis

Hyperwells can be also used in second-level analysis. In Copy Number Variation mode’s **CNV with reference sample** and **Gene Expression** analysis, hyperwells can be picked in the reference selection field. It allows the user to select if parameter calculations for unknown sample shall be performed comparing to concentrations from replicates or hyperwells, in reference sample.

7.6.14.3.1. Hyperwells in Gene Expression analysis

- 1. Select **Gene Expression** analysis.

Absolute Quantification	Mutation Detection	Genome Editing	Copy Number Variation	Gene Expression
-------------------------	--------------------	----------------	-----------------------	-----------------

- 2. Select wells from plate layout.

Select source of gene expression (4 wells, 1 hyperwell)

	1	2	3	4	5	6	7	8	9	10	11	12
A												
B												
C												
D												
E												
F												
G												
H												

Select all Unselect all Group as hyperwells Ungroup hyperwells

Select imaging step
 Imaging info

Reference sample *

Select

Reference selection

Select

Reference target(s) *

Select

Target of interest *

Select

Show results

3. Select one reference sample from the drop-down list.

Select source of gene expression (4 wells, 1 hyperwell)

	1	2	3	4	5	6	7	8	9	10	11	12
A	01	01	01	01	01	01	01	01	01	01		
B	02	02	02	02	02	02	02	02	02	02		
C	03	03	03	03	03	03	03	03	03	03		
D	04	04	04	04	04	04	04	04	04	04		
E	05	05	05	05	05	05	05	05	05	05		
F	06	06	06	06	06	06	06	06	06	06		
G	07	07	07	07	07	07	07	07	07	07		
H	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC		

Select all Unselect all Group as hyperwells Ungroup hyperwells

Select imaging step

The reference sample contains the target of interest and at least one reference target.

Reference sample * ⓘ

01 1ng gDNA

Reference selection ⓘ

Select

Reference target(s) * ⓘ

Select

Target of interest * ⓘ

Select

Show results

4. Select reference selection from the drop-down list – this option is active only if the selection contains both hyperwells and replicates within one selected reference sample (the same sample ID). User can choose which option should be taken as reference.

Select source of gene expression (4 wells, 1 hyperwell)

	1	2	3	4	5	6	7	8	9	10	11	12
A	01	01	01	01	01	01	01	01	01	01		
B	02	02	02	02	02	02	02	02	02	02		
C	03	03	03	03	03	03	03	03	03	03		
D	04	04	04	04	04	04	04	04	04	04		
E	05	05	05	05	05	05	05	05	05	05		
F	06	06	06	06	06	06	06	06	06	06		
G	07	07	07	07	07	07	07	07	07	07		
H	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC		

Select all Unselect all Group as hyperwells Ungroup hyperwells

Select imaging step

1 Imaging info

Reference sample * ⓘ

01 1ng gDNA

Reference selection ⓘ

Select

Hyperwell 1 (A2-A3)

Replicates (A4)

Target of interest * ⓘ

Select

Show results

- Select one or more reference target(s) using the checkboxes from the drop-down list.

Select source of gene expression (4 wells, 1 hyperwell)

	1	2	3	4	5	6	7	8	9	10	11	12
A	01	01	01	01	01	01	01	01	01	01		
B	02	02	02	02	02	02	02	02	02	02		
C	03	03	03	03	03	03	03	03	03	03		
D	04	04	04	04	04	04	04	04	04	04		
E	05	05	05	05	05	05	05	05	05	05		
F	06	06	06	06	06	06	06	06	06	06		
G	07	07	07	07	07	07	07	07	07	07		
H	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC		

Select all Unselect all Group as hyperwells Ungroup hyperwells

Select imaging step
 1 Imaging info ▼

Reference sample * ⓘ
 01 1ng gDNA ▼

Reference selection ⓘ
 Hyperwell 1 (A2-A3) ▼

The target of interest contains the gene region to be investigated regarding expression of the gene.

Target of interest * ⓘ
 DPH186 TERT Yellow ● ▼

Green ● ▼

Show results

- Select one target of interest from the drop-down list.
- Click the **Show results** button to get results.

7.6.14.3.2. Hyperwells in Copy Number Variation analysis

- Navigate to **Copy Number Variation** analysis.

Absolute Quantification	Mutation Detection	Genome Editing	Copy Number Variation	Gene Expression
-------------------------	--------------------	----------------	------------------------------	-----------------

- Select wells from plate layout.

Absolute Quantification	Mutation Detection	Genome Editing	Copy Number Variation	Gene Expression
-------------------------	--------------------	----------------	------------------------------	-----------------

Select source of copy number variation (4 wells, 1 hyperwell)

	1	2	3	4	5	6	7	8	9	10	11	12
A	01	01	01	01	01	01	01	01	01	01		
B	02	02	02	02	02	02	02	02	02	02		
C	03	03	03	03	03	03	03	03	03	03		
D	04	04	04	04	04	04	04	04	04	04		
E	05	05	05	05	05	05	05	05	05	05		
F	06	06	06	06	06	06	06	06	06	06		
G	07	07	07	07	07	07	07	07	07	07		
H	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC		

Select all Unselect all Group as hyperwells Ungroup hyperwells

Select imaging step
 1 Imaging info ▼

☒ CNV with reference sample
 ☐ CNV with reference target
 Hide details ▲

Copy Number Variation with reference sample
 CNV based on reference sample allows checking how the copy number of a target of interest varies from one sample to another in relation to the known copy number of the reference sample.

Selection requirements

- Please make sure that the plate layout including the reaction mix and samples is defined for the respective well(s).
- Please note that targets in Amplitude Multiplexing mode cannot be applied for CNV analysis.
- Please check for any warnings or errors in Absolute Quantification and Plate Configurator environment.

How to set up CNV with reference sample analysis:

- Select wells for analysis.
- Define hyperwells (optional).
- Specify reference sample.
- Specify target(s) of interest, copies per genome and reference target(s).
- Create up to 3 combinations, if required.

3. Select one reference sample from the drop-down list.

Select source of copy number variation (4 wells, 1 hyperwell)

	1	2	3	4	5	6	7	8	9	10	11	12
A		01	01	01	01	01	01	01	01	01		
B		02	02	02	02	02	02	02	02	02		
C		03	03	03	03	03	03	03	03	03		
D		04	04	04	04	04	04	04	04	04		
E		05	05	05	05	05	05	05	05	05		
F		06	06	06	06	06	06	06	06	06		
G		07	07	07	07	07	07	07	07	07		
H		NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC		

Select all Unselect all Group as hyperwells Ungroup hyperwells

Select imaging step

1 Imaging info

The reference sample contains the target of interest and at least one reference target. An input copies/genome value needs to be provided to be used as reference for calculating the copy number variation of the other sample in the selection. The value for "Copies/genome" has to be in the range of 1 to 99.

Reference sample *

01 1ng gDNA

Reference selection

Select

Reference target(s) *

Select

Copies / genome *

1 - 99

Target of interest *

Select

Show results

4. Select reference selection from the drop-down list – this option is active only if the selection contains both hyperwells and replicates within one selected reference sample (the same sample ID). User can choose which option should be taken as reference; otherwise, the option is inactive and you should skip it.

Select source of copy number variation (4 wells, 1 hyperwell)

	1	2	3	4	5	6	7	8	9	10	11	12
A		01	01	01	01	01	01	01	01	01		
B		02	02	02	02	02	02	02	02	02		
C		03	03	03	03	03	03	03	03	03		
D		04	04	04	04	04	04	04	04	04		
E		05	05	05	05	05	05	05	05	05		
F		06	06	06	06	06	06	06	06	06		
G		07	07	07	07	07	07	07	07	07		
H		NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC		

Select all Unselect all Group as hyperwells Ungroup hyperwells

Select imaging step

1 Imaging info

CNV with reference sample CNV with reference target See details

Combinations

+ Add

C1 Combination 1

The reference selection defines wells, hyperwells that have the same sample ID for the selected reference sample. Select one that you would like to analyze.

Reference selection

01 Hyperwell 1 (A2-A3)

Reference target(s) *

Select

Copies / genome *

1 - 99

Target of interest *

Select

Show results

- Select one or more Reference target(s) using checkboxes from the drop-down list.

Select source of copy number variation (4 wells, 1 hyperwell)

	1	2	3	4	5	6	7	8	9	10	11	12
A		01	01	01	01	01	01	01	01	01		
B		02	02	02	02	02	02	02	02	02		
C		03	03	03	03	03	03	03	03	03		
D		04	04	04	04	04	04	04	04	04		
E		05	05	05	05	05	05	05	05	05		
F		06	06	06	06	06	06	06	06	06		
G		07	07	07	07	07	07	07	07	07		
H		NT18	NT18	NT18	NT18	NT18	NT18	NT18	NT18	NT18		

Select all Unselect all Group as hyperwells Ungroup hyperwells

Select imaging step

1 Imaging info ▼

[See details ▼](#)

Combinations ⓘ [+ Add](#)

C1 Combination 1 ^

Reference sample * ⓘ

01 1ng gDNA ▼

The reference target(s) are used to normalize the copy number variation results of the selection.

Reference target(s) * ⓘ

DPH218 ERBB2 Green ● ▼

Copies / genome *

1 - 99 ⚙

Target of interest * ⓘ

Select ▼

[Show results](#)

- Input number of Copies/genome. Choose a value between 1 and 99.

Select source of copy number variation (4 wells, 1 hyperwell)

	1	2	3	4	5	6	7	8	9	10	11	12
A		01	01	01	01	01	01	01	01	01		
B		02	02	02	02	02	02	02	02	02		
C		03	03	03	03	03	03	03	03	03		
D		04	04	04	04	04	04	04	04	04		
E		05	05	05	05	05	05	05	05	05		
F		06	06	06	06	06	06	06	06	06		
G		07	07	07	07	07	07	07	07	07		
H		NT18	NT18	NT18	NT18	NT18	NT18	NT18	NT18	NT18		

Select all Unselect all Group as hyperwells Ungroup hyperwells

Select imaging step

1 Imaging info ▼

[See details ▼](#)

Combinations ⓘ [+ Add](#)

C1 Combination 1 ^

Reference sample * ⓘ

01 1ng gDNA ▼

Reference selection ⓘ

Hyperwell 1 (A2-A3) ▼

Reference target(s) * ⓘ

DPH218 ERBB2 Green ● ▼

Copies / genome *

5 ⚙

Target of interest * ⓘ

Select ▼

[Show results](#)

7. Select one target of interest from the drop-down list.

Select source of copy number variation (4 wells, 1 hyperwell)

Select source of copy number variation (4 wells, 1 hyperwell)

Select imaging step

Imaging info

CNV with reference sample

CNV with reference target

See details

Combinations

+ Add

C1 Combination 1

Reference sample *

01 1ng gDNA

Reference selection

Hyperwell 1 (A2-A3)

The target of interest contains the gene region(s) to be investigated regarding variation in copy number.

Target of interest *

DPH186 TERT

Copies / genome *

Green

5

Yellow

8. Repeat the above steps for every combination needed.

9. Click the **Show results** button to get results.

7.6.14.4. Multiple imaging steps

If the plate was configured with multiple imaging steps, user can select the one used for analysis. To select the imaging step, click one of the available boxes indicated by the **camera** icon.

Select imaging step

1 2 3 4 5

Imaging info

Green	500 ms / 6
Yellow	500 ms / 6
Crimson	400 ms / 8

The channels along with the duration and gain settings that were activated in the selected imaging step are shown after expanding **Imaging info** section.


Select imaging step

Imaging info

Green	300 ms / 6	Crimson	300 ms / 4
Yellow	250 ms / 4	Far red	600 ms / 8
Orange	150 ms / 3	Green / Yellow	1000 ms / 6
Red	150 ms / 3	Yellow / Orange	1000 ms / 6

Important: When switching imaging steps, the application will ask to ungroup existing hyperwells. All wells linked as hyperwells will be ungrouped as individual wells.

Note: If an imaging step fails during the run or images are of low quality, a message is shown by moving the mouse over the **camera** icon to indicate that the results might be incorrect. Furthermore, error messages are indicated with a red box around the image step icon, warnings with a yellow box.



7.6.14.5. Diagram options

There are several tools related to the diagrams and charts that enable user to adjust the view and download the chart that needs to be viewed. To access the tools, point to a diagram. Table 14 shows the toolbar buttons and their corresponding functions.


Table 14. Diagram toolbar buttons

Toolbar buttons	Icons	Functions
Pan		Changes the perspective of the graph Moves along the x-axis, y-axis, or both
Zoom		Enables you to select a part of the diagram to zoom into To reset the zoom, double-click the diagram.
Zoom in		Zooms in the diagram To reset the zoom, double-click the diagram.
Zoom out		Zooms out the diagram To reset the zoom, double-click the diagram.
Reset axes		Resets the axes after the view is panned
Polygon partitions assignments		Available only on 2D Scatterplot: Enables you to select a freehand part of diagram

Note: Each diagram type contains a different set of toolbar buttons.

7.6.14.6. Horizontal and vertical wells results presentation

From the Software Suite version 2.5 onwards for Absolute Quantification, before clicking **Show results**, user can select between Horizontal and Vertical wells results presentation:



Option Horizontal orders wells results row by row: A_1, A_2 to A_i , then B_1, B_2 to B_i , and so on. Option Vertical orders wells column by column: A_1, B_1 to H_1 , then A_i, B_i to H_i , and so on, where "i" in both cases is the number of column.

Selected wells results presentation (Horizontal or Vertical) affects List View, 1D Scatterplot, and Concentration diagram. It is also reflected in CSV exports (Current results, Multiple Occupancy, and RFU export) and reports.

7.6.14.7. Dilution calculation option

From QIAcuity Software Suite version 2.5 onwards, there is the possibility to calculate the concentration of the undiluted sample. Dilution calculations can be used in all type of analysis: Absolute quantification as well as in all second-level analysis (Mutation detection, Genome editing, Copy number variation, and Gene expression).

To calculate concentration in undiluted sample ($C_{undiluted}$) following information are required:

1. Total volume value (V_{rm}) of reaction mix per well: Allowed values are in range 1 to 1000 μL .
2. Corresponding sample template volume (V_t) defines the volume of template used during PCR reaction. Allowed values are in the range 0.1 to 1000 μL .

Optionally, for sample pre-dilutions: Concentration factor (C_f) of sample refers to the ratio of how sample was pre-diluted. The concentration factor is a multiplier. Allowed values are in range 1 to 1×10^{12} . If a sample was for example pre-diluted with a ratio of 1:100, a concentration factor of 100 needs to be defined.

The following formula is applied to reaction mix dilution (without sample pre-dilution and corresponding concentration factor):

$$C_{undiluted} = \frac{C}{\frac{V_t}{V_{rm}}}$$

Concentration in undiluted sample ($C_{undiluted}$) including sample pre-dilution (concentration factor) is calculated using formula:

$$C_{undiluted} = \frac{c}{\frac{V_t}{V_{rm}}} \times C_f$$

$$C_{undiluted} = \frac{c}{\frac{V_t}{V_{rm}}}$$

Note: The results for undiluted sample concentration is presented per default as cp/μL.

Example:

$$C = 120 \frac{cp}{\mu L}$$

$$V_t = 10 \mu L$$

$$V_{rm} = 100 \mu L$$

$$C_f = 1000$$

$$C_{undiluted} = \frac{120 \frac{cp}{\mu L}}{\frac{10 \mu L}{100 \mu L}} \times 1000 = 1,200,000 \frac{cp}{\mu L}$$

7.6.14.8. Usage of dilution calculation feature in analysis

Before using dilution calculation for data analysis, make sure all needed samples have dilution factor parameters filled accordingly (described in Sections 7.4.10 Defining samples, controls, and non-template controls and 7.4.6 Reaction mixes tab). User can use drop icons on plate layout for it.

Example:


	1	2	3	4	5	6	7	8	9	10	11	12
A		01	01	01	01	01	01	01	01	01		
B		02	02	02	02	02	02	02	02	02		
C		03	03	03	03	03	03	03	03	03		
D		04	04	04	04	04	04	04	04	04		
E		05	05	05	05	05	05	05	05	05		
F		06	06	06	06	06	06	06	06	06		
G		07	07	07	07	07	07	07	07	07		
H		NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC		

In the aforementioned example, the calculation of undiluted sample concentration will be possible for Sample 01 and 02, but not possible for Sample 03:


1. Sample 01 has total volume, template volume, and concentration factor filled, which is indicated with blue drop icon.



2. Sample 02 has total volume, template volume filled, but concentration factor is empty, which is indicated with empty drop icon.



3. Sample 03 has total volume filled but template volume and concentration factor are empty, which is indicated with red drop icon.



7.6.14.8.1. Dilution factor results visualization

1. List View


The list view column with results of concentration is divided into two sub-columns: dPCR reaction and undiluted sample (based on provided dilution information). When user enables the option to show the mean values for replicates, the mean concentration and standard deviation (SD) columns are additionally presented and divided in similar manner.

Sample/NTC/Control	Reaction Mix	Name	Channel		Conc. [cp/mL] ¹		CI (95%) dPCR reaction	Partitions			Threshold
			IC	Control	dPCR reaction	Undiluted sample		Valid	Positive	Negative	
A2	1ng gDNA Conc. factor: 5 Template volume: 50 µL	DPH218 ERBB2 + DPH186 TERT Ref. channel: Std-Ref	Green	-	26.51	-	23.4%	8240	70	8170	63.11
			Yellow	-	23.09	-	25.1%	8240	61	8179	78.41
			Red	-	0.000	-	-	8240	0	8240	14.28
A3	1ng gDNA Conc. factor: 5 Template volume: 50 µL	DPH218 ERBB2 + DPH186 TERT Ref. channel: Std-Ref	Green	-	28.82	-	22.5%	8255	76	8179	61.20
			Yellow	-	23.49	-	24.9%	8255	62	8193	91.16
			Red	-	0.000	-	-	8255	0	8255	15.56
A4	1ng gDNA Conc. factor: 5 Template volume: 50 µL	DPH218 ERBB2 + DPH186 TERT Ref. channel: Std-Ref	Green	-	24.44	-	24.5%	8210	64	8146	73.95
			Yellow	-	27.51	-	23.1%	8210	72	8138	89.89
			Red	-	0.000	-	-	8210	0	8210	13.01
A5	1ng gDNA Conc. factor: 5 Template volume: 50 µL	DPH218 ERBB2 + DPH186 TERT + DPH464 SPIN4 Ref. channel: Std-Ref	Green	-	32.24	-	21.3%	8269	85	8184	80.33
			Yellow	-	25.77	-	23.8%	8269	68	8201	92.44
			Red	-	14.75	-	31.4%	8269	39	8230	74.59
A6	1ng gDNA Conc. factor: 5 Template volume: 50 µL	DPH218 ERBB2 + DPH186 TERT + DPH464 SPIN4 Ref. channel: Std-Ref	Green	-	38.16	-	19.5%	8260	101	8159	77.78
			Yellow	-	30.56	-	21.8%	8260	81	8179	88.61
			Red	-	18.45	-	28.0%	8260	49	8211	80.33

Note: Similar column division is also used in CSV export: Current results and in report.


2. Heatmap

To display concentration for undiluted sample on Heatmap user needs to check the checkbox “Use sample dilution”:



3. Concentration diagram

On the concentration diagram, user needs to check the checkbox to display concentration for undiluted sample:



Note: Results visualization works the same on for absolute quantification and all second-level analysis (Mutation Detection, Genome Expression, Copy Number Variation, and Gene Expression).

7.6.14.9. Conversion factor

From the QIAcuity Software Suite version 2.5 onwards, there is possibility to convert concentration result by default given in copies per microliter, into another unit defined by the user. Conversion factor can be used in absolute quantification as well as in second-level analysis (Mutation detection, Genome editing, Copy number variation, and Gene expression). Result can be also combined with dilution factor so it allows user to obtain results of undiluted concentration in any custom unit.

Software provides following default units:

cp/mL, ng/μL, pg/μL, vg/mL, vg/μL.

On top of that, user can introduce custom units to the system.

To convert the unit, user needs to input two additional parameters during sample definition: conversion factor and unit. Concentration result is just multiplied by conversion factor and expressed in given unit.

Examples:

1. The single copy gene CDKN2A has been detected in genomic DNA isolated from human leukocytes. Knowing that the weight of the haploid human genome is approximately 3.3 pg per cell, 100 copies/ μL of the target corresponds to **(a)** 330 pg of DNA/ μL and **(b)** to 50 cell equivalents (with diploid genome)/ μL .

Conversion from copies/ μL into pg/ μL :

$$C_{\text{undiluted}} = 100 \frac{\text{cp}}{\mu\text{L}}$$

$$\text{conversion factor} = 3.3$$

$$\text{unit} = \frac{\text{pg}}{\mu\text{L}}$$

$$C_{\text{undiluted converted}} = 330 \frac{\text{pg}}{\mu\text{L}}$$

Conversion from copies/ μL into cell equivalents:

$$\text{conversion factor} = \frac{1}{2} = 0.5$$

$$\text{unit} = \frac{\text{cells}}{\mu\text{L}}$$

$$C_{\text{undiluted converted}} = 50 \text{ cells}/\mu\text{L}$$

2. The 16S rRNA gene has been detected in genomic DNA isolated from *E. coli* cells. The copy number of the 16S rRNA gene is 7 per one *E. coli* cell. The weight of one *E. coli* genome is approximately 5.1 fg. A total of 1000 copies of the target corresponds to **(a)** 729 fg of DNA and **(b)** to approximately 1423 cell equivalents.

Conversion from copies/ μL into fg/ μL :

$$C_{\text{undiluted}} = 1000 \frac{\text{cp}}{\mu\text{L}}$$

$$\text{conversion factor} = \frac{5.1}{7} = 0.729$$

$$\text{unit} = \frac{\text{fg}}{\mu\text{L}}$$

$$C_{\text{undiluted converted}} = 729 \text{ fg}/\mu\text{L}$$

Conversion from copies/ μL into *E. coli* equivalents:

$$C_{\text{undiluted}} = 1000 \frac{\text{cp}}{\mu\text{L}}$$

$$\text{conversion factor} = \frac{1}{7} = 0.143$$

$$\text{unit} = \frac{\text{E. coli}}{\mu\text{L}}$$

$$C_{\text{undiluted converted}} = 142.8 \text{ E. coli}/\mu\text{L}$$

7.6.14.9.1. Usage of conversion factor in analysis

To use conversion factor in analysis, make sure all needed samples have conversion factor and unit filled accordingly (described in Section 7.4.10 Defining samples, controls, and non-template controls).


Note: If the selected wells for analysis exhibit different defined conversion units, or a mixture of converted and non-converted wells is present, no converted data will be analyzed and displayed by the software.

Note: The conversion function is only available for samples, not for controls nor non template controls.

7.6.14.9.2. Conversion factor results visualization

1. List View

To display converted results on list view user needs to select wells for analysis exhibiting an identical conversion factor unit and enable checkbox "Use conversion factor". Otherwise, checkbox is disabled and following information is presented on tooltip:



When all selected wells for analysis exhibit identical conversion unit, the converted result concentration is displayed in addition to the default sample result concentration (copies/ μ L).

When all parameters were filled correctly, Concentration column is divided in following way:

- a. dPCR reaction has three sub-columns:
 - dPCR reaction concentration (cp/ μ L)
 - Converted dPCR concentration (custom unit)
 - CI (95%)
- b. If dilution factor was applied, then Undiluted sample is additionally presented with following columns:
 - Undiluted concentration (cp/ μ L)
 - Converted undiluted concentration (custom unit)

When user enables the option to show mean values for replicates, columns: mean concentration and standard deviation (SD) are additionally presented.

Note: Sample name and assigned reaction mix must be identical to enable the **replication calculation** option.

ListSignalmapHeatmapHistogram1D Scatterplot2D ScatterplotConcentration diagram

☐ Add to report

☐ Show mean values for replicates

☒ Use conversion factor

 Export to CSV...

Well	Sample/NTC/Control	Reaction Mix	Channel			Concentration				Partitions			Threshold	
			Name	IC	Control	dPCR Reaction			Undiluted sample		Valid	Positive		Negative
						cp/μL	cp/mL	CI (95%)	cp/μL	cp/mL				
A2	1ng gDNA Conc. factor: 5 Template volume: 10.0 μL Climo factor: 2 Conc. unit: cp/mL	DPH218 ERBB2 + DPH186 TE RT Total volume: 100.0 μL Ref. channel: 994-Ref	Green	-	-	26.51	53.01	23.4%	1325.3	2650.7	8240	70	8170	63.11
			Yellow	-	-	23.09	46.17	25.1%	1154.3	2308.6	8240	61	8179	78.41
A3	1ng gDNA Conc. factor: 5 Template volume: 10.0 μL Climo factor: 2 Conc. unit: cp/mL	DPH218 ERBB2 + DPH186 TE RT Total volume: 100.0 μL Ref. channel: 994-Ref	Green	-	-	28.83	57.66	22.5%	1441.4	2882.8	8253	76	8177	61.20
			Yellow	-	-	23.50	47.00	24.9%	1174.9	2349.8	8253	62	8191	91.16
A4	1ng gDNA Conc. factor: 5 Template volume: 10.0 μL Climo factor: 2 Conc. unit: cp/mL	DPH218 ERBB2 + DPH186 TE RT Total volume: 100.0 μL Ref. channel: 994-Ref	Green	-	-	24.44	48.88	24.5%	1222.0	2444.0	8210	64	8146	73.95
			Yellow	-	-	27.51	55.02	23.1%	1375.4	2750.8	8210	72	8138	89.89


Back to plate configurator

0 items selected

Create report


2. Heatmap

To display converted result concentration, user needs to enable checkbox "Use conversion factor". Results are displayed in custom unit. In addition, the result presentation of both diluted and converted concentration results can be selected by use of "Use sample dilution" and "Use conversion factor".



3. Concentration diagram


On the concentration diagram, user needs to check the same checkbox to display converted concentration that also can be combined with dilution factor.



Note: Results visualization for all second-level analysis (Mutation Detection, Genome Editing, Copy Number Variation, and Gene Expression) works the same as for the Absolute Quantification.

7.6.14.9.3. Range sliders

If more wells are selected for the analysis than how much can fit on a chart, some charts such as concentration diagrams or point diagrams offer the additional option of a range slider. This tool lets user view the data that do not fit on the diagram. User can also adjust the range of data that is shown to see more information at the same time.



Example of a range slider below a chart.

The highlighted area of the slider shows the portion of the chart that is currently displayed. The gray part of the slider is a preview of the rest of the chart.

To view another part of a diagram, click the highlighted area of the slider and drag to the part that user wants to view.

To adjust the range of the displayed data, click one of the handlebars on the left or right side of the highlighted area and drag until the preferred range is reached.

7.6.14.9.4. Ongoing background actions on plate


Every time there are some ongoing actions on plates processed on background, user is informed about it on analysis level via indicator as shown on example below:



Processing analysis results in background.

Important: While background operations are processed, user cannot change (recalculate) results of analysis – all elements of UI – that can influence the ongoing operation are disabled.

If more users are using the Software Suite at the same time, the user who has not triggered the action is additionally presented with notification with button to refresh the plate.



List of affected operations:

- Processing analysis results
- Processing images
- Processing reports
- Importing and exporting the plate
- Archiving and restoring the plate
- Upgrading the plate
- Deleting the plate
- Updating configuration (of the plate)
- Updating experiment progress

7.6.15. Absolute quantification

The **Absolute Quantification** (AQ) tab is the first tab in the Analysis environment. After selecting the wells to be analyzed, user can view lists, signal maps, heatmaps, histograms, 1D scatterplots, 2D scatterplots, and concentration diagrams in this tab.

7.6.15.1. Total number of copies

The total number of copies of the target molecule in all valid partitions of a well is calculated by multiplying the copies of the target molecule per partition with the number of valid partitions. We use an intermediary quantity, λ , interpreted as average number of target molecules in a single partition.

The estimation of λ is probabilistic in its nature, and the uncertainty of λ is described by the normal distribution centered around the following mean $\hat{\lambda}$:

$$\lambda = -\ln\left(\frac{\text{Number of valid partitions} - \text{Number of positive partitions}}{\text{Number of valid partitions}}\right)$$

The 95% confidence interval of this distribution is a range given by

$$CI_{\text{low}} = \lambda_{\text{low}} = -\ln\left(1 - p + 1.96\sqrt{\frac{p(1-p)}{\text{Number of partitions}}}\right)$$

$$CI_{\text{high}} = \lambda_{\text{high}} = -\ln\left(1 - p - 1.96\sqrt{\frac{p(1-p)}{\text{Number of partitions}}}\right)$$

Where

$$p = \frac{\text{Number of positive partitions}}{\text{Number of valid partitions}}$$

Example:

For simplicity, the assumption is that we have 8500 total partitions with 8000 partitions that are valid and from those 4000 partitions are positive. The estimated number of copies of the target molecule in a partition is

$$\lambda = -\ln\left(\frac{8000-4000}{8000}\right) = 0.6931471805599450...$$

By using the formula for the standard error of the uncertainty, this can be estimated:

$$CI_{\text{low}} = \lambda_{\text{low}} = -\ln\left(0.5 + 1.96\sqrt{\frac{0.5 \times 0.5}{8000}}\right) = 0.67147036342047...$$

$$CI_{\text{high}} = \lambda_{\text{high}} = -\ln\left(0.5 - 1.96\sqrt{\frac{0.5 \times 0.5}{8000}}\right) = 0.71530431303236...$$

The CI range is equal to $CI_{\text{high}} - CI_{\text{low}} = 0.04383...$. This range is used to determine how many digits of the result are significant.

The result is based on detecting 4000 positive partitions out of 8000 total valid, the λ parameter is distributed with around a value $\lambda = 0.693$ and there is 95% certainty that the true value lays between $\lambda \in 0.671...0.715$. This equals to a CI range of 6.32% compared to mean λ at 0.693...

Estimation of number of copies of the target molecule in the whole well:

$$8500 \times (0.671...0.693...0.715) = (5707...5892...6080)$$

7.6.15.2. Copies per microliter

Based on the known number of copies of the target molecule per partition (λ) and the partition volume, the copies per microliter can be calculated using the tripartite calculation.

$$\Lambda_{\text{volume}} = \frac{\lambda}{V[\mu\text{L}]}$$

Example:

The number of copies of the target molecule is $\lambda = 0.693$.

The estimated partition volume is $V = 0.34 \text{ nL}$.

The copies per microliter is:

$$\lambda_{\text{volume}} = \frac{0.693}{0.34} \times 1000 = 2038 \text{ copies}/\mu\text{L}$$

The 2038 copies/ μL is the concentration, which is the standard readout in the dPCR results. To calculate the copies of the target molecule in the reaction volume, you multiply by the input reaction volume. In case the input reaction volume is 12 μL , the copy number in the input reaction is $2038 \times 12 = 24,456$ copies.

7.6.15.3. Replicates

Replicates are analyzed as separate wells, but in addition, the mean concentration value and the CI value of the mean concentration are provided on demand.

On the right side above the table, there is a checkbox that allows the user to show mean values for replicates in addition. By default, the button is unchecked and results are displayed without mean values. When the button is checked, the list still shows independent rows for each selected well but replicates are grouped together. Replicates from the same group are next to each other in the list view.

☐ Add to report ☒ Show mean values for replicates [Export to CSV...](#)

Well	Sample/NTC/Control	Reaction Mix	Channel			Concentration		Mean concentration		SD	CV%	Partitions			Threshold
			Name	IC	Control	dPCR Reaction	CI (95%)	dPCR Reaction	CI (95%)	cp/μL		Valid	Positive	Negative	
A2	Inq gDNA	DPH218 ERBB2 + DPH186 T ERT	● Green	-	-	26.51	23.4%	26.60	20.5%	2.196	8.26%	8239	70	8169	61.84
			● Yellow	-	-	23.09	25.1%	24.70	24.6%	2.443	9.89%	8239	61	8178	78.41
A3	Inq gDNA	DPH218 ERBB2 + DPH186 T ERT	● Green	-	-	28.83	22.5%	26.60	20.5%	2.196	8.26%	8252	76	8176	59.93
			● Yellow	-	-	23.50	24.9%	24.70	24.6%	2.443	9.89%	8252	62	8190	91.16
A4	Inq gDNA	DPH218 ERBB2 + DPH186 T ERT	● Green	-	-	24.44	24.5%	26.60	20.5%	2.196	8.26%	8209	64	8145	73.31
			● Yellow	-	-	27.51	23.1%	24.70	24.6%	2.443	9.89%	8209	72	8137	89.25

Example screenshot taken from the QIAcuity Software Suite showing results for replicates with three wells: A2, A3, and A4.

7.6.15.3.1. Mean concentration

Mean concentration for replicates is calculated as a weighted average for concentrations for individual replicates. Weights are the well-specific volume of a single partition within a well, which can be calculated as a volume of the whole well divided by the total number of partitions.

$$\text{Formula for mean concentration (cp per } \mu\text{L) of 2 replicates} = \frac{c(1) \times v(1) + c(2) \times v(2)}{(v(1) + v(2))}$$

Example for mean concentration:

$$(\text{cp per } \mu\text{L) of 2 replicates} = \frac{(472.2 \times 0.757 + 505.1 \times 0.749 + 478.1 \times 0.749)}{0.757 + 0.749 + 0.749} = 485.09 \text{ cp}/\mu\text{L}$$

CI (95%) — CI of mean concentration assumes that error between individual results has normal distribution. t_{n-1} is defined as critical value of Student's t distribution for 95% and number of degrees of freedom equal number of replicates minus 1.

$$\text{CI for replicates} = \text{mean weighted by partition volume} \pm t_{n-1} \times \frac{\text{Standard deviation of the replicate set}}{\sqrt{n}}$$

n is the number of replicates, three in our example. The critical value for the appropriate t distribution is $t_{n-1} = t_2 = 4.303$. The factor $\frac{t_{n-1}}{\sqrt{n}}$ can be seen as a factor by which the standard error for the replicates is larger than the standard deviation of the concentrations in the observed set of replicates. The factor is fixed for a given number of replicates. In this example, with three replicates, the factor is $\frac{t_{n-1}}{\sqrt{n}} = \frac{4.303}{1.7320508} = 2.48434$. We calculate the standard deviation of the replicate set using the formula for sample:

$$\text{Standard deviation of the replicate set} = \sqrt{\frac{\sum(a_i - \bar{c})^2}{n-1}}$$

7.6.15.3.2. Standard deviation

$$\text{Example for the standard deviation} = \sqrt{\frac{(472.2-485.09)^2 + (505.1-485.09)^2 + (478.1-485.09)^2}{3-1}} = 17.5416$$

7.6.15.3.3. Coefficient of variation


Coefficient of variance is a ratio of Standard deviation to Mean concentration for replicates, expressed in %:

$$\text{Formula for coefficient of variation of 2 replicates} = \frac{\text{standard deviation}}{\text{mean concentration}} 100\%$$

$$\text{Example for coefficient of variation of 2 replicates} = \frac{17.5416}{485.0876} 100\% = 3.616\%$$

7.6.15.4. Setting up an absolute quantification analysis


1. Click the applicable wells in the plate layout. For more information, refer to Section 7.6.14.1 Selecting wells for analysis.



2. To select the analysis type, click **Target** or **Channel**.

Note: If there are no reaction mixes available on the plate, the **Target** button is disabled.

3. To analyze the plate by targets, select the targets from the Select Targets list. User can select one or more targets from the list. To select all targets, click **Select all**.



Note: If amplitude multiplexing is enabled, associated targets are disabled for a target-based analysis. Only a channel-based analysis is supported.

Analyze per

Target

Channel

Select targets *

Select targets for analysis

One or more targets have Amplitude Multiplexing applied and are not available for selection

Example of enabled amplitude multiplexing for the Green channel. Associated targets are disabled for a target based analysis.

4. Select **Horizontal** or **Vertical** wells results presentation.

Wells results presentation ⓘ

→ Horizontal

↓ Vertical

5. Click **Show results** to view the results of the analysis.
6. To analyze the plate by channels, check the boxes of the corresponding channel color to select the relevant channels. If images are not taken for a channel, the channel becomes disabled.

Note: In analysis per Channels, only channels selected during Imaging are available and channels assigned to selected wells are preselected by default (checkboxes checked).

12

1

2

3

4

5

6

7

8

9

10

11

A

B

C

D

E

F

G

H

Select all

Unselect all

Group as hyperwells

Ungroup hyperwells

Select imaging step

1

Imaging info

Analyze per

Target

Channel

Select channels

☒ Green

☐ Red

☒ Yellow

☐ Crimson

☐ Orange

Wells results presentation ⓘ

→ Horizontal

↓ Vertical

Show results

7. Select **Horizontal** or **Vertical** wells results presentation.
8. Click **Show results** to view the results of the analysis.
9. The results are divided into several tabs. To view the contents of the tab, click the tab title.

Note: For the result analysis at least one well and a target or channel must be selected.

7.6.15.5. List tab for absolute quantification

The **List** tab contains a table with an overview of the analyzed wells. The following columns are available in the table:

1. **Well ID** – Like A1, B2, when gradient cycling was selected, there is also temperature in the well (temperature range instead of single one, if hyperwells were selected).
2. **Sample/NTC/Control** – This column shows the sample, NTC, or control name with its corresponding icon that identifies the sample or indicates whether the entry is an NTC or control.
3. **Reaction mix** – This column contains the icon and the name of the reaction mix, and reference channel that has been detected (Std-Ref or HM-Ref).
4. **Target or Channel** – Depending on the settings defined when selecting a source, this column shows the target or channel names and its corresponding color.

Note: If amplitude multiplexing mode is enabled, the list view of the channel-based analysis is enlarged into Low and High results of associated channel/s.

5. **Conc. [copies/μL]** – This column shows the concentration assigned to each target or channel per well.
6. **CI (95%)** – This column shows the value of the confidence interval at a 95% confidence level for concentration.
 - a. When checkbox “Show mean values for replicates” is checked, additional columns are displayed:
 - **Mean conc. [copies/μL]** – This column shows the mean concentration assigned to each target or channel per well for replicates.
 - **CI (95%)** – This column shows the value of the confidence interval at a 95% confidence level for the mean concentration.
 - **SD** – This column contains standard deviation of concentration for replicates.
 - **CV%** – This column shows coefficient of variance in percentage of the concentration for replicates.

Note: Columns Conc., CI (95%), and columns related to Mean conc. CI will be additionally divided into several sub-columns, depending if dilution and/or conversion function (described in Sections 7.6.14.7 Dilution calculation option and 7.6.14.9 Conversion factor, accordingly) have been selected.

7. **Partitions (Valid, Positive, Negative)** – This column shows the number of valid, positive, and negative partitions per well and the target or channel.
8. **Threshold** – This column shows the current threshold.

Note: When polygon (for threshold setting) was used, “variable” is displayed instead of threshold value.

Note: When amplitude multiplexing is enabled, three threshold values are presented in following order: double positive, high threshold, and low threshold per each row.

Well	Sample/NTC/Control	Reaction Mix	Channel			Concentration		Partitions			Threshold
			Name	IC	Control	dPCR Reaction		Valid	Positive	Negative	
A10	Sample1	 CXTM_Suite_VER_TC1_96LV Ref. channel:  HM-Ref  CXTM	 Green (Low)	-	-	6.608	47.5%	8031	17	8014	36.72 29.62 21.04
			 Green (High)	-	-	191.4	9.0%	8031	478	7553	36.72 29.62 21.04

Example screenshot taken from the QIAcuity Software Suite showing how AM split on channel Green impacts List.


Note: Saturated signals are marked with a  symbol next to the concentration value in the list view. Furthermore, a dedicated information message is shown above the diagram. For more information regarding saturated signals, refer to Section 7.6.5.1 Image quality control.

Note: Reaction mixes without advised custom cross talk matrix are marked with  symbol in the list view. Furthermore, a dedicated information message is shown above the diagram. For more information, refer to Section 7.6.4 Custom cross talk matrix.


7.6.15.6. Analysis behavior when Analysis rules are applied

When analysis rules are applied to a reaction mix in the plate layout (see Section 7.4.7 Analysis rules), the Analysis and List views include additional columns that display information related to the applied analysis rules.


Before wells are selected for analysis, the user is informed that analysis rules are applied. The user can open the Reaction Mixes view by clicking **Details**.



When analysis rules are manually overridden by a user with the appropriate permissions (e.g., when a threshold is manually changed on a 1D Scatter Plot or 2D Scatter Plot for at least one reaction mix with analysis rules applied), the notification is updated. The user can restore the original analysis rules by clicking **Revert to Analysis Rules** button.



After clicking the **Revert to Analysis Rules** button, a dialog box is displayed. The user can select the reaction mixes to restore by selecting the corresponding checkboxes and clicking the **Revert to Analysis Rules** button.



In the List view, reaction mixes with analysis rules applied are identified by the **Analysis Rules** tag displayed in the Reaction Mix column.

7.6.15.6.1. Overall Quality Control Status

The “Overall Quality Control Status” column is a new column related to analysis rules. This column is displayed when the selected wells for analysis include reaction mixes with QC rules. The column displays the final QC validation result and can show one of the following values:

- —: QC rules are not applicable.
- **Passed:** QC rules are added to the reaction mix analysis and all rules passed the validation.
- **Failed:** QC rules are added to the reaction mix analysis and at least one rule failed validation. The status is displayed as “Failed” even when the QC rule severity level is configured as “Flag Only”.

7.6.15.6.2. QC failure visualization

Each QC rule that can be added to analysis rules behaves as described in Section 7.4.7 Analysis rules. QC rule failures can be identified in the List view in dedicated columns and in the “Overall Quality Control Status” column.

The validation results for the following QC rules are displayed as follows:

1. Min. valid partitions % for Controls and Min. valid partitions % for Samples

Validation results are displayed in the “Partitions” > “Valid” column for rows representing wells with assigned Controls and Samples.

2. Expected conc. for Positive Controls in dPCR reaction – Min., Range, or Max. [cp/μL]

Validation results are displayed in the “Concentration dPCR Reaction” > “cp/μL” column for rows representing wells with assigned Positive Controls.

3. Max. expected number of positive partitions in Negative Controls and NTC

Validation results are displayed in the “Partitions” > “Positive” column for rows representing wells with assigned Negative Controls and NTC.

Depending on the QC rule configuration, failures are displayed as follows:

Invalidated result at the channel level

A red indicator is displayed in the column corresponding to the failed QC rule. The affected channel row is highlighted in red.

Well	Sample/NTC/Control	Reaction Mix	Overall Quality Control Status	Channel			Concentration ⓘ		Partitions			Threshold
				Name	IC	Control	dPCR Reaction		Valid	Positive	Negative	
							cp/μL	CI (95%)				
A1	-	RM1 Ref. channel: ⓘ HM-Ref ⓘ Analysis rules	❌ Failed ✅ Green	-	-	2423.8	3.1%	❌ 7530	4223	3307	65.66	
			✅ Passed ⚠ Yellow	-	-	892.8	4.3%	8028	2099	5929	7.01	
			✅ Passed ⚠ Orange	-	-	2217.1	3.1%	7754	4101	3653	65.03	

Invalidated result at the well level

A red indicator is displayed in the column corresponding to the failed QC rule. All channel rows associated with the affected well are highlighted in red.

Well	Sample/NTC/Control	Reaction Mix	Overall Quality Control Status	Channel			Concentration 📊		Partitions			Threshold
				Name	IC	Control	dPCR Reaction		Valid	Positive	Negative	
							cp/L	CI (95%)				
B1	-	RM2 Ref. channel: 📄 HM-Ref 📄 Analysis rules	🔴 Failed	🟢 Green	-	-	2423.8	3.1%	🔴 7530	4223	3307	65.66
			🔴 Failed	🟡 Yellow	-	-	892.8	4.3%	8028	2099	5929	7.01
			🔴 Failed	🟠 Orange	-	-	2217.1	3.1%	7754	4101	3653	65.03

Flagged-only result at the channel level

A yellow indicator is displayed in the column corresponding to the failed QC rule. The affected channel row is highlighted in yellow.

Well	Sample/NTC/Control	Reaction Mix	Overall Quality Control Status	Channel			Concentration ⓘ		Partitions			Threshold
				Name	IC	Control	dPCR Reaction		Valid	Positive	Negative	
							cp/L	CI (95%)				
C1	-	RM3 Ref. channel: ⓘ HM-Ref Analysis rules	❌ Failed 🟢 Green	-	-	2423.8	3.1%	🟡 7530 4223 3307	65.66			
			✅ Passed 🟡 Yellow	-	-	892.8	4.3%	8028 2099 5929	7.01			
			✅ Passed 🟠 Orange	-	-	2217.1	3.1%	7754 4101 3653	65.03			

Flagged-only result at the well level

A yellow indicator is displayed in the column corresponding to the failed QC rule. All channel rows associated with the affected well are highlighted in yellow.

Well	Sample/NTC/Control	Reaction Mix	Overall Quality Control Status	Channel			Concentration 		Partitions			Threshold
				Name	IC	Control	dPCR Reaction		Valid	Positive	Negative	
							cp/L	CI (95%)				
D1	-	 RM4 Ref. channel:  HM-Ref  Analysis rules	 Failed	 Green	-	-	2423.8	3.1%	 7530	4223	3307	65.66
			 Failed	 Yellow	-	-	892.8	4.3%	8028	2099	5929	7.01
			 Failed	 Orange	-	-	2217.1	3.1%	7754	4101	3653	65.03

When the pointer is positioned over an indicator, a tooltip displays the failed rule and the expected value.

Well	Sample/NTC/Control	Reaction Mix	Overall Quality Control Status	Channel			Concentration 		Partitions			Threshold
				Name	IC	Control	dPCR Reaction		Valid	Positive	Negative	
							cp/L	CI (95%)				
D1	-	RM4 Ref. channel: HM-Ref Analysis rules	 Failed  Green	-	-	2423.8	3.1%	 7530	4223	3307	65.66	
			 Failed  Yellow	-	-	892.8	4.3%	 8028	2099	5929	7.01	
			 Failed  Orange	-	-	2217.1	3.1%	 7754	4101	3653	65.03	
D2	 S1	 RM4 Ref. channel:  HM-Ref  Analysis rules	 Failed  Green	-	-	2423.8	3.1%	 7530	4223	3307	65.66	
			 Failed  Yellow	-	-	892.8	4.3%	 8028	2099	5929	7.01	
			 Failed  Orange	-	-	2217.1	3.1%	 7754	4101	3653	65.03	

QC rule: Min. valid partitions %
Min. valid partitions defined level 90% has not been reached for Sample.

7.6.15.6.3. Overall Quality Control Status details

The “Overall Quality Control Status” column displays the final validation result (“Passed”, “Failed”, or “–”) and provides additional details when the pointer is positioned over the status value:

1. QC rules configuration

Displays information about the applied validation strategy, including the Scope of Application and Severity Level.

2. Well or channel failures due to QC rules

Lists the QC rules that directly caused a failure at the well or channel level. Affected channels are identified in parentheses when applicable (e.g., Channels: Yellow, Orange).

3. Controls

Displayed when controls associated with the assigned reaction mix fail QC validation. This section lists failures related to:

- Min. valid partitions % for Controls
- Expected conc. for Positive Controls in dPCR reaction – Min., Range, or Max. [cp/μL]
- Max. expected number of positive partitions in Negative Controls and NTC

4. Replicates

Displayed when replicate wells associated with the assigned reaction mix fail QC validation. This section lists failures related to:

- Min. valid partitions % for Samples

QC RULES CONFIGURATION

Invalidated results at channel level

Channel is excluded from further calculation (Control based thresholding and Second Level Analysis) because it fails one or more QC rules.

Channel failed due to QC rules:

Min. valid partitions % for Samples (Channel: Green)

Controls

Controls associated with assigned Reaction Mix failed QC rules:

Min. valid partitions % for Controls

Replicates

Replicates associated with assigned Reaction Mix failed QC rules:

Min. valid partitions % for Samples

Add to report

Show mean values for replicates

Export to CSV...

Well	Sample/NTC/Control	React	Channel	Concentration	Partitions			Threshold		
			IC	Control	dPCR Reaction	CI (95%)	Valid	Positive	Negative	
					cp/μL					
A1	-		-	-	2423.8	3.1%	7530	4223	3307	65.66
			-	-	892.8	4.3%	8028	2099	5929	7.01
			-	-	2217.1	3.1%	7754	4101	3653	65.03
A2	S1		-	-	2423.8	3.1%	7530	4223	3307	65.66
			-	-	892.8	4.3%	8028	2099	5929	7.01
			-	-	2217.1	3.1%	7754	4101	3653	65.03
A3	S1		-	-	2423.8	3.1%	7530	4223	3307	65.66
			-	-	892.8	4.3%	8028	2099	5929	7.01
			-	-	2217.1	3.1%	7754	4101	3653	65.03
A4	S2	RM1	-	-	2423.8	3.1%	7530	4223	3307	65.66
			-	-	892.8	4.3%	8028	2099	5929	7.01
			-	-	2217.1	3.1%	7754	4101	3653	65.03
A5	S2	RM1	-	-	2423.8	3.1%	7530	4223	3307	65.66
			-	-	892.8	4.3%	8028	2099	5929	7.01
			-	-	2217.1	3.1%	7754	4101	3653	65.03
A6	C1	RM1	-	POS	2423.8	3.1%	7530	4223	3307	65.66
			-	POS	892.8	4.3%	8028	2099	5929	7.01

Back to plate configurator

0 items selected

Generate Report from Template

Create report

7.6.15.6.4. QC validation messages

When QC validation fails and the invalidation strategy is configured, the following error message is displayed across the whole analysis.

Error (1)

Some wells or channels has/have been invalidated and excluded in RM1, RM2 due to Quality Control rule/s failure on channel/s. Please refer to the List view for detailed information.

When QC validation fails and the warning strategy is configured, a warning message is displayed:

Warning (1)

Some wells or channels has/have been highlighted in RM4, RM3 due to Quality Control rule/s failure on channel/s. Please refer to the List view for detailed information.

QC validation failures are also included in CSV exports. For more information, refer to Section 7.4.12 Plate layout: CSV import/export.

7.6.15.6.5. Threshold fallback

A threshold fallback occurs when user-configured threshold settings on Analysis rules cannot be applied. In such cases, a dedicated indicator is displayed in the List view that fallback method has been used.

List	Signalmap	Heatmap	Histogram	1D Scatterplot	2D Scatterplot	Concentration diagram	Analysis Rules applied Details					
☐ Add to report ☐ Show mean values for replicates  Export to CSV...												
Well	Sample/NTC/Control	Reaction Mix	Overall Quality Control Status	Channel			Concentration		Partitions		Threshold	
				Name	IC	Control	dPCR Reaction cp/L	CI (95%)	Valid	Positive	Fallback thresholding applied	
A1	-	RM1 Ref. channel: HM-Ref Analysis rules	Failed	Green	-	-	2430.1	3.1%	7530	4230	3300	50.12
			Passed	Yellow	-	-	892.8	4.3%	8028	2099	5929	7.01
			Passed	Orange	-	-	2217.1	3.1%	7754	4101	3653	65.03

7.6.15.7. Export to CSV

ListSignalmapHeatmapHistogram1D Scatterplot2D ScatterplotConcentration diagramAdd to reportShow mean values for replicatesExport to CSV...											
Well	Sample/NTC/Control	Reaction Mix	Channel			Concentration		Partitions			Threshold
			Name	IC	Control	cp/L	CI (95%)	Valid	Positive	Negative	
A9	Sample1	CXTM_Suite_VER_TC1_96LV Ref. channel: HM-Ref CXTM	Green (Low)	-	-	3.074	69.3%	8094	8	8086	36.30 27.53 11.67
			Green (High)	-	-	181.5	9.1%	8094	459	7635	36.30 27.53 11.67
			Yellow	-	-	228.4	8.2%	8100	574	7526	38.89
A10	Sample1	CXTM_Suite_VER_TC1_96LV Ref. channel: HM-Ref CXTM	Green (Low)	-	-	6.997	46.2%	8031	18	8013	36.30 27.53 11.67
			Green (High)	-	-	195.9	8.9%	8031	489	7542	36.30 27.53 11.67
			Yellow	-	-	227.5	8.2%	8031	565	7466	31.88

Besides displaying the table with results, there is an additional option in **List** tab to export results of analysis to CSV file.

ListSignalmapHeatmapHistogram1D Scatterplot2D ScatterplotConcentration diagramAdd to reportShow mean values for replicatesExport to CSV...											
Well	Sample/NTC/Control	Reaction Mix	Channel			Concentration		Partitions			Threshold
			Name	IC	Control	cp/L	CI (95%)	Valid	Positive	Neg	
A9	Sample1	CXTM_Suite_VER_TC1_96LV Ref. channel: HM-Ref CXTM	Green (Low)	-	-	3.074	69.3%	8094	8		36.30 27.53 11.67
			Green (High)	-	-	181.5	9.1%	8094	459	7635	
			Yellow	-	-	228.4	8.2%	8100	574	7526	
A10	Sample1	CXTM_Suite_VER_TC1_96LV Ref. channel: HM-Ref CXTM	Green (Low)	-	-	6.997	46.2%	8031	18	8013	36.30 27.53 11.67
			Green (High)	-	-	195.9	8.9%	8031	489	7542	
			Yellow	-	-	227.5	8.2%	8031	565	7466	

7.6.15.7.1. Current results

To export CSV file with the current results of analysis, follow the instruction below:

1. Select the wells that user wants to get results for.
2. Choose whether to analyze per target or per channel by clicking the proper tab, and select targets or channels that the user is interested in.
3. Select **Horizontal** or **Vertical** wells results presentation.
4. Click the **Show results** button.
5. In the **List** tab, above the table, on the right-hand side, the **Export to CSV...** option is available.
6. Click the **Export to CSV...** option and select the **Current results** option.
7. Remember that data in CSV reflect data from List view are structured as follows:

- Plate name – name of the plate
- Plate ID – unique identifier of the plate
- Plate type – type of the plate
- Well – identifier of well or hyperwell (if defined)
- Hyperwell – list of wells being part of hyperwell
- Sample ID – unique identifier of the sample
- Sample/NTC/Control – name of Sample/NTC/Control
- Type – Type (Sample/Control/Non Template Control)
- Reaction Mix – name of reaction mix
- Channel (name)/Target (name) – abbreviation of channel name or target name, respectively.

Note: When amplitude multiplexing is enabled, additional suffix “L” or “H” representing “Low” or “High” part of channel is added to channel abbreviation.

- Channel (IC)/Target (IC) – internal control (if selected)
- Channel (Control)/Target (Control) – type of control (if defined)
- Conc. [cp/μL] (dPCR reaction) – calculated concentration in dPCR reaction
- Conc. [unit] (dPCR reaction) – converted concentration in dPCR reaction, in user-defined unit
- CI (95%) (dPCR reaction) – confidence interval parameter in dPCR reaction
- Conc. [cp/μL] (undiluted sample) – calculated concentration in undiluted sample
- Conc. [unit] (undiluted sample) – converted concentration in undiluted sample and in user-defined unit
- Mean conc. [cp/μL] (dPCR reaction) – calculated mean concentration in dPCR reaction for replicates
- Mean conc. [unit] (dPCR reaction) – converted mean concentration in dPCR reaction in user-defined unit for replicates
- CI (95%) (dPCR reaction) – confidence interval parameter for mean concentration in dPCR reaction in custom unit for replicates

- Mean conc. [cp/μL] (undiluted sample) – calculated mean concentration in undiluted sample for replicates
- Mean conc. [unit] (undiluted sample) – converted mean concentration in undiluted sample and in custom unit for replicates
- SD [cp/μL] (dPCR reaction) – calculated standard deviation of concentration for replicates in dPCR reaction
- SD [unit] (dPCR reaction) – converted standard deviation of concentration for replicates in dPCR reaction in custom unit
- SD [cp/μL] (undiluted sample) – calculated standard deviation of concentration for replicates in undiluted sample
- SD [unit] (undiluted sample) – converted standard deviation of concentration for replicates in undiluted sample in user-defined unit
- CV% – calculated coefficient of variance of concentration for replicates
- Partitions (Valid) – number of valid partitions
- Partitions (Positive) – number of positive partitions
- Partitions (Negative) – number of negative partitions
- Threshold – value(s) of single threshold or three thresholds (double positives, high, and low) when amplitude multiplexing mode is enabled
- Volume per well [μL] – volume per well, includes VPF if applied
- Temperature gradient [°C] – temperature in well (range for hyperwells) if gradient cycling used
- Concentration factor – value of concentration factor given by user during sample creation
- Template volume [μL] – value of template volume given by user during sample creation
- Total volume [μL] – value of total volume given by user during reaction mix creation
- Conversion factor – value of conversion factor given by user during sample creation
- Conversion unit – conversion factor's unit given by user during sample creation
- REF – type of detected Reference channel. Standard Reference channel (Std-Ref) or High-Multiplexing Reference channel (HM-Ref)
- CXT matrix RM template name – if reaction mix with CXTM was assigned to this well, this column shows name of the reaction mix template on which that reaction mix was based.
- CXT matrix RM template ID – if a reaction mix with CXTM was assigned to well, this column shows the ID of the reaction mix template on which that reaction mix was based.
- Lambda – expected target copies per partition.
- Actual cycled vol/partition [nL] – actual (real) cycled volume per partition.
- Actual cycled vol/well [nL] – actual (real) cycled volume per partition.
- Mean RFU positives – arithmetic average of RFU of all positive partitions at certain threshold.
- Mean RFU negatives – arithmetic average of RFU of all negative partitions by certain threshold.
- Mean RFU positives for replicates – mean of arithmetic average of RFU of all positive partitions at certain threshold for replicates.

- Mean RFU negatives for replicates – mean of arithmetic average of RFU of all negative partitions at certain threshold for replicates.
- Threshold strategy – Represents the threshold strategy configured for the experiment. This may include a manual threshold, an automatic threshold, or threshold settings derived from Analysis rules, including the fallback mechanism. For more information, refer to the Section 7.4.7 Analysis rules.
- Overall Quality Control status – Represents the overall execution result (Passed or Failed) of all applied QC rules configured alongside Analysis rules, including the effects of rule propagation. For more information, refer to Section 7.4.7 Analysis rules.
- Apply to well? – Represents the scope of application of QC rules when a QC rule is added alongside Analysis rules. “Off” indicates that the rule is applied at the channel level, whereas “On” indicates that the rule is applied at the well level. For more information, refer to Section 7.4.7 Analysis rules.
- Warning only? – Represents the severity setting for QC rules when a QC rule is added alongside Analysis rules. When set to Off, a rule failure invalidates the experiment results. When set to On, failed results are flagged but not invalidated. For more information, refer to Section 7.4.7 Analysis rules.
- Min. valid partitions (%) for Controls – value – Specifies the configured value of the QC rule “Minimum valid partitions (%) for Controls” when the rule is added alongside Analysis rules.
- Min. valid partitions (%) for Controls – result – Represents the execution result (Passed or Failed) of the QC rule “Minimum valid partitions (%) for Controls” when the rule is applied alongside Analysis rules.
- • Min. valid partitions (%) for Samples – value – Specifies the configured value of the QC rule “Minimum valid partitions (%) for Samples” when the rule is added alongside Analysis rules.
- Min. valid partitions (%) for Samples – result – Represents the execution result (Passed or Failed) of the QC rule “Minimum valid partitions (%) for Samples” when the rule is applied alongside Analysis rules.
- Expected Min./Range/Max. conc. PC [cp/μL] – value – Specifies the configured value of the QC rule “Expected conc. for Positive Controls in dPCR reaction – Min., Range or Max. [cp/μL]” when the rule is added alongside Analysis rules. Depending on the configuration, this value represents the minimum concentration, maximum concentration or concentration range.
- Expected Min./Range/Max. conc. PC [cp/μL] – result – Represents the execution result (Passed or Failed) of the QC rule “Expected conc. for Positive Controls in dPCR reaction – Min., Range or Max. [cp/μL]” when the rule is applied alongside Analysis rules.
- Max. no. positive partitions NC_NTC – value – Specifies the configured value of the QQC rule “Max. expected number of positive partitions in Negative Controls and NTC” when the rule is added alongside Analysis rules.
- Max. no. positive partitions NC_NTC – result – Represents the execution result (Passed or Failed) of the QC rule “Max. expected number of positive partitions in Negative Controls and NTC” when the rule is applied alongside Analysis rules.

7.6.15.7.2. Multiple occupancy

To export CSV file with multiple occupancy for multiplex reaction, selected wells must meet the following criteria:

- Include at least two channels (Analysis per channel) or targets (Analysis per target) with a single threshold per well.
- The selection must not include more than 8 channels.
- All wells in the selection must contain the required channels or target channels.
- All selected wells must use the same reference channels.
- For Analysis per target, the selection must include the required channels in the reaction mix.

Then follow the instruction below:

1. Select the wells that need to get the results for.
2. Choose whether to analyze per target or per channel by clicking proper tab, and select targets or channels that the user is interested in.
3. Select **Horizontal** or **Vertical** wells results presentation.
4. Click the **Show results** button.
5. In the **List** tab, above the table, on the right-hand side, you can see the **Export to CSV...** option.
6. Click the **Export to CSV** option and select the **Multiple occupancy** option.
7. Use the checkboxes to specify group/s, that should be presented in CSV.

The number preceding the word “positives” determines the amount of positives (“+”) in all possible combinations in file. For example, in a 3-plex reaction mix, all possible combinations with only 1 positive are “+--”, “-+-”, and “--+”. The groups “All positives” and “All negatives” represent combinations with only positives (only “+”) and only negatives (only “-”). So in the 3-plex example, it is “+++” and “---”, accordingly.

Multiple occupancy

Select group/s you want to export.

☒ Select all

☒ Positives

- ☒ All positives
- ☒ 1 positive
- ☒ 2 positives
- ☒ 3 positives
- ☒ 4 positives
- ☒ 5 positives
- ☒ 6 positives
- ☒ 7 positives
- ☒ 8 positives

☒ All negatives

Cancel Export

8. When CSV file is generated successfully, the data are structured as follows:

- Plate name – name of the plate
- Plate ID – unique identifier of the plate
- Plate type – type of the plate
- Well – identifier of well
- Hyperwell – identifier of hyperwell if wells were grouped
- Reaction Mix name – name of reaction mix
- Sample ID – unique identifier of the sample
- Sample name – name of sample
- Target names – name of targets in reaction mix
- Categories – abbreviations of channel names associated with targets in reaction mix

Note: When amplitude multiplexing is applied in this CSV, "H" or "L" suffix is used for target High or target Low, respectively.

- Group – identifier of a specific combination of channels, represented as a sequence of either positive (+) or negative (–) symbols for each channel
- Valid partitions – total number of valid partitions in a well
- Volume per well [µL] – cycled volume per well (VPF file dependent)
- Count categories – number of valid partitions in a certain group
- Count random – the theoretical number of partition being positive in all selected channels ("++...+") in the well that statistically are related to random filling of molecules from groups not creating a signal in all selected channels ("++...+") but do not containing target molecules which are fully linked and thereby would create a signal in all selected channels anyway. For example, for fully linked target molecules, the count random value should therefore be rather small compared to the overall number of full positive partition ("++...+") and for none linked targets rather as many as the observed amount of full positive partition ("++...+") count.
- Random variation – standard error of count random
- Lambda – expected number of target molecules within a single partition per group
- Lambda error – standard error of the Lambda
- Conc. Per group [cp/µL] – expected number of target molecules per microliter per group
- Conc. Per group error – standard error of Conc. Per group [cp/µL]
- Concentration factor – value of concentration factor defined during sample creation
- Template volume [µL] – value of sample template volume defined during sample creation
- Total volume [µL] – value of total reaction mix volume per well defined during reaction mix creation
- Undiluted Conc. Per group [cp/µL] – value of concentration of certain group in undiluted sample taking concentration factor into account, if defined
- Undiluted Conc. Per group [cp/µL] error – standard error of Undiluted Conc. per group [cp/µL]
- Conversion factor – value of conversion factor defined during sample creation

- Conversion factor unit – conversion factor's unit defined during sample creation
- Conv. Undiluted Conc. Per group – converted value of concentration of certain group, in defined unit in undiluted sample taking concentration & conversion factor into account, if defined
- Conv. Undiluted Conc. Per group error – standard error of the Conv. Undiluted Conc. Per group
- % intact – % ratio of the concentration of target molecules for full positive group divided by concentration of all molecules from all groups
- % intact error – standard error of % intact
- Mean Random – mean value for Count random parameter for replicates
- Mean Lambda – mean value for Lambda value for replicates
- SE Mean Lambda – standard error for Mean Lambda
- Mean Clean Conc – mean value for Conc. Per group value for replicates
- SE Mean Clean Conc – standard error for Mean Clean Conc.
- Mean % intact – mean value for % intact value for replicates
- SE Mean % intact – standard error for Mean % intact
- Mean Undiluted Conc. – mean value for above Undiluted Conc. Per group parameter for replicates
- SE Mean Undiluted Conc. – standard error for Mean Undiluted Conc.
- Mean Conv. Undiluted Conc. – mean value for Conv. Undiluted Conc. Per group parameter for replicates
- SE Mean Conv. Undiluted Conc. – standard error for Mean Conv. Undiluted Conc.
- CXT matrix RM template name – if Reaction Mix with CXTM was assigned to well this column shows name of RM template on which that RM was based
- CXT matrix RM template ID – if Reaction Mix with CXTM was assigned to well this column shows ID of reaction mix template on which that reaction mix was based
- REF – type of detected Reference channel. Standard Reference channel (Std- Ref) or High- Multiplexing Reference channel (Std-Ref or HM-Ref)
- Overall Quality Control status – Represents the overall execution result (Passed or Failed) of all Quality Control (QC) rules applied alongside Analysis rules, including the effects of rule propagation. For more information, refer to Section 7.4.7 Analysis rules.


Note: To not duplicate the same data in CSV, same data in subsequent rows of one well are displayed only once.

Note: The algorithm calculates a balanced estimate within the sum of all λ for all groups in a range of 0.02 to 5. Please ensure that this value does not exceed a λ of 5 within a well.


7.6.15.7.3. Error handling

When any of the errors listed below are detected, CSV generation is aborted and user has to change source selection.


- For both analysis types (per channel and per target), the selected wells must contain at least 2 channels or targets. If fewer than 2 channels or targets are selected, the following error message is displayed:




- For both analysis types (per channel and per target), the maximum number of selected channels or targets is limited to 8. If this limit is exceeded, the following error message is displayed:



- For Analysis per channel, all selected wells must use the same reference channel set (Std-Ref or HM-Ref; see Sections 7.4.5 Defining the dPCR parameters and 7.6.13 Reference channel discrepancies for more information about reference channels). Otherwise, the following error message is displayed:



- All other issues trigger a generic error message:



7.6.15.7.4. RFU values

If you want to export CSV file with relative fluorescence units per partitions for selected wells, follow the instructions below:

1. Select the wells that user wants to get results for.
2. Click the **Channels** tab, and select channels you are interested in.
3. Click the **Show results** button.
4. In the List tab, above the table, on the right-hand side, the **Export to CSV...** option is available.
5. Click the **Export to CSV...** option and select the **RFU values** option.
6. Remember that the data in CSV are structured as follows:

- Plate name – name of the plate
- Plate ID – unique identifier of the plate
- Plate type – type of the plate
- Well – identifier of well
- Sample ID – unique identifier of the sample
- Sample – name of sample
- Channel – first letter of channel on which picture was taken

Note: When amplitude multiplexing is used, “H” or “L” suffix is added for High or Low target indicator, respectively.

- Cycled volume (µL) – well volume corrected by VPF
- Threshold – threshold value
- Partition – number by which a partition can be identified
- Is Invalid – code for invalidation reason (check mapping table code statuses, there can be a maximum three codes separated by a comma)

In case amplitude multiplexing is applied, the following columns are additionally available:

- Threshold low – replaces Threshold by threshold low value
- Threshold high – threshold high value
- Threshold double – threshold double value
- Classification – if partition is valid (RFU is filled), it shows whether partition is positive, negative, or double (positive); otherwise, N/A is presented:
 - In files with suffix “L”
 - If the partition’s RFU greater than the Threshold double value, the column displays “double”.
 - If the Threshold low value less than the partition’s RFU and the partition’s RFU is less than Threshold high value, the column displays “positive”.
 - If the partition’s RFU is less than the Threshold low value or the Threshold high value is less than the

partition's RFU and the partition's RFU is less than the Threshold double value, the column displays "negative".

- In files with suffix "H"
 - If the partition's RFU is greater than the Threshold double value, the column displays "double".
 - If the Threshold high value is less than the partition's RFU and the partition's RFU is less than the Threshold double value, the column displays "positive".
 - If the partition's RFU is less than the Threshold high value, the column displays "negative".

Status	Code
Poisson test – linear distribution issue Blistering (Poisson test)	1
Poisson test areas of too low/no positive partitions amplification)	2
Poisson test areas of too high positive partitions (Proportion test – over-amplification)	3 & 4
Reference partition not filled	5 & 9
Dust detected by different reasons	6, 7, 8
Artifacts founds	B & C

- IsPositive – information whenever a partition was marked as positive or double positive (1) or negative (0). For invalid partitions there is no information presented.
- RFU – RFU values associated with partition.
- REF – type of detected Reference channel (Std-Ref or HM-Ref)

7. The data will be exported to separate CSV files (one for each selected channel) and compressed into one zip file.

Note: When amplitude multiplexing is applied two separate files for Low (suffix "L") and High (suffix "H") part are created.


Note: Be informed that, due to some corrections provided by analysis models, sometimes there might be changes when comparing IsPositive column values with information obtained by comparing RFU values to threshold.

7.6.15.7.5. RFU values (compact)


This option is very similar to regular RFU report but redundant data in columns: Well, Sample, Channel, and Cycled volume in CSV file are removed to decrease the file size — same names or values in subsequent rows will only be shown once until the name of value has changed.

7.6.15.7.6. Importing of exported CSV file to Microsoft Excel

To correctly import previously exported CSV into Microsoft Excel without any data loss, it is strongly recommended to use the following option: from **Data** menu, select the **From Text/CSV** option, then browse for the correct file and click **Load** in newly opened window.



It is strongly recommended to check/adapt the column type for the result data to Decimal Number.



7.6.15.8. Signalmap tab for absolute quantification


The **Signalmap** tab provides the view that allows to differentiate positive partitions for target channels and valid partitions for the reference channel of selected wells. For each channel included in target or channel selection, one signal map view is created. The signal map views are sorted by channel position in imaging, separated by a horizontal line.

With this view, the user can visually check the influence of threshold settings on the partition distribution and consider the impact of artifacts that might have been discovered in the source image view.

Each signal map represents the plate layout for a selected channel where only the images of the selected wells are loaded. The remaining wells are displayed as gray squares. When the image of a well could not be calculated by the algorithm, a placeholder image is shown. On hovering the mouse over the well, the user is informed that the signal map for this well could not be created.

The title of a signal map shows the channel name and, in case more than one well is selected, the number of selected wells.

When the user hovers with the mouse over a well, a tooltip is shown informing about the label of the given well, detected reference channel, and, in analysis per target, the associated target. On hovering the well image, the image is highlighted and the cursor changes to the zoom icon – user can click and enlarge the well.




Signal map for a target channel.

When a well is clicked, a modal window opens and displays the well image. The following tools are available in the upper-right corner of the window:


1. Copy to Windows clipboard – Copies the signal map image to the Windows clipboard.
2. Download signalmap of this well as picture
3. Zoom in
4. Zoom out
5. Close zooming window

The Zoom-in and Zoom-out feature is also possible using the mouse wheel. On the upper left side, the well ID, channel name, and if defined the associated target name are shown. Below the signal map, there is a legend with color's description – positive partitions are always marked with green dots independently of channel.




Enlarged signal map for a target channel Yellow with assigned target.

When amplitude multiplexing split is enabled, on enlarged view of particular well, partitions that are positive for channel low, positive for channel high, double positives, or negatives can be distinguished. Below the signal map, there is a legend with the color's description.




Signal map for enlarged well when amplitude multiplexing is applied.

The Software Suite provides a signal map view for the reference channel, which is hidden by default. To view the signal map for the reference channel in addition, click **Show reference channel**. The functionality of the signal map view for the reference channel is analog to the signal map views of the target channels but shows partitions that are marked with blue dots.




Signal map for a reference channel.




Enlarged signal map for a reference channel.

To copy all signalmaps currently displayed on the screen to the Windows clipboard as a grid, click **Copy all**.



To copy the signal map for a specific channel, click **Copy**.



Note: Both options copy the image at high resolution. The application window must remain in focus during the copy operation; otherwise, the operation will fail.

7.6.15.9. Heatmap tab for absolute quantification

The **Heatmap** tab shows the concentration of the selected targets or channels in each well. The values of all selected wells are also displayed in this tab. Values for disabled wells are not displayed. One heatmap view is created for each selected target or channel. The heatmap views are sorted by channel position in imaging ("Green", "Yellow", "Orange", "Red", "Crimson"), separated by a horizontal line.

When amplitude multiplexing is applied, separate heatmaps are generated for "Low" and "High" part of the channel.

If the target or channel shown in a heatmap is not relevant to one or more wells, those wells do not have a value displayed and their background color is gray.

Move the pointer over a well getting further detailed information of the corresponding well.


To view an additional toolbar that enables downloading the plot, hold the pointer over the diagram.

There are two views of each heatmap – the concentration view and the partitions view (see the following images). To switch between the views, click **Concentration** or **Partitions**. There are several additional options that user can select:


1. **Use sample dilution** – as described in Section 7.6.14.7 Dilution calculation option, enables calculations related to dilution factor. Results in undiluted sample is additionally presented on well tiles. Option is available both on concentration view and partition view.
2. **Use conversion factor** – enables conversion of results into unit given by user (described in Section 7.6.14.9 Conversion factor). Results in converted unit replace standard ones on well tiles. Option is only available in the concentration view (not supported in the partition view).
3. **Show mean values for replicates** – showing the mean concentration values for replicates in the concentration view (not supported in the partition view).

To add any of the heatmaps to the report, click **Add to report** next to the relevant diagram. For more information on reports, see Section 7.7 Reports.


Additional options include **Copy** and **Copy all**, which copy images to the Windows clipboard and behave the same as the corresponding options in the Signalmap tab.



The concentration view for heatmap of a selected target (with selected mean values for replicates, conversion, and dilution factors).



The partitions view for heatmap of a selected target.



Heatmap with grouped hyperwells.


7.6.15.10. Histogram tab for absolute quantification

The **Histogram** tab displays graphs that visualize the fluorescence values of selected wells for the selected target or channel. One histogram view is created for each selected target or channel. The histograms are sorted by channel position in imaging ("Green", "Yellow", "Orange", "Red", "Crimson"), separated by a horizontal line.


Each histogram has two axes. The x-axis represents the relative fluorescence intensity. The y-axis represents the number of partitions having that fluorescence intensity. The values on the y-axis have two available scales that can be selected using one of the buttons located below each graph: **lin** for linear or **log10** for logarithmic scale.

The Threshold field shows the threshold value of the fluorescence intensity that is used to distinguish between positive and negative calls. If only one source well is selected, the value of the threshold is shown in the Threshold field and on the graph as a red line. If multiple source wells are defined and their automatically calculated threshold values are different, a threshold value is initially not shown in the histogram.

To add any of the histograms to the report, click **Add to report** next to the relevant diagram. For more information on reports, see Section 7.7 Reports.



For Amplitude Multiplexing, three threshold values are displayed instead of a single threshold value: “Double”, “High”, and “Low”.




7.6.15.10.1. Copy, Copy all, and Download functions

To copy all histograms currently displayed on the screen, click **Copy all**.

To copy a single histogram to the Windows clipboard, click **Copy**. To save a single histogram as an image file, click **Download**.

7.6.15.10.2. Reference channel on histogram

The Software Suite also provides a histogram for the reference channel, which is hidden by default. To view the histogram for the reference channel in addition, click **Show reference channel**. The title of this histogram indicates that the histogram is related to the reference channel.



7.6.15.11. 1D Scatterplot tab for absolute quantification

The **1D Scatterplot** tab shows one 1D Scatterplot view for each analyzed target or channel. If there are more than one scatterplot views, they are separated with a horizontal line. The 1D Scatterplot views are sorted by channel position in imaging (“Green”, “Yellow”, “Orange”, “Red”, “Crimson”, “Far red”).

The title of a 1D Scatterplot view shows the related channel name including the dot channel color indicator and, if defined, the target name. If more than one well is selected also the number of wells is shown.

Thus, a 1D Scatterplot view has two axes. The x-axis represents the analyzed partitions, while the y-axis represents the relative fluorescence intensity of each partition.


Note: For RFU values below 60, it is recommended to increase the exposure time of corresponding channel/s, and for RFU values above 150, it is recommended to decrease the exposure time of corresponding channel/s.

A 1D Scatterplot view concentrates the diagrams for each selected well in a horizontal way separated by a vertical line (column indicator). For each well diagram, a header shows the following information:

- The well coordination (well ID) on the plate
- Sample ID and name – if assigned to that well
- Reference channel detected by Algorithm (Std-Ref or HM-Ref)
- Temperature of this well – if temperature gradient cycling was used

A red line represents the current threshold fluorescence intensity value (decimal value) that is used to distinguish between positive and negative partitions. Fluorescence values below the threshold are shown in gray, above the threshold in blue color.

User is able to select how many wells are presented per row using drop-down menu – 8, 12, 16 (by default), 20, or 24. Width of each well will depend on selected option and screen resolution.




Example of 1D Scatterplot with enabled temperature gradient and 16 wells per row.




Example of 1D Scatterplot of hyperwells.

To open an individual plot, click the appropriate header of the 1D Scatterplot.




The user can change the range of the y-axis by adjusting the value in the field Max value for the y axis (RFU) and clicking **Save**. For resetting the y-axis to the default range, press the **Back to default** button. The view of the diagram is adapted accordingly.



7.6.15.11.1. Changing the thresholds for all selected wells (Common threshold)

Note: In the QIAcuity Software Suite version 3.2, for each user who has migrated from one of previous versions, during software upgrade process, additional information is presented one time, when **1D Scatterplot** tab is opened first time, to inform that recalculating results is reworked comparing to previous version.




The 1D Scatterplot view provides two options to set a common threshold value for all associated wells:


- Using the Common threshold input field, click the **Recalculate** button to trigger the re-analysis of data.



- Moving threshold line directly on plot – drag, move to the desired position and drop




Use the **Auto-threshold** button to reset the threshold to the values, which is calculated by the analysis algorithm for each well. Click the **Recalculate** button to trigger the re-analysis of data.



Note: Starting with QIAcuity Software Suite version 3.2 onward, user can adjust threshold for all desired targets or channels and click any **Recalculate** button once at the end – all thresholds will be applied accordingly.

All threshold changes will be discarded, if the **Recalculate** button is not pressed. An appropriate warning message appears:




To add any of the 1D Scatterplot to the report, click **Add to report** next to the relevant view. For more information on reports, see Section 7.7 Reports.

7.6.15.11.2. Changing the threshold individually per well

1. To change the threshold individually per well, click the appropriate header of the well in the 1D Scatterplot view. A window opens and the threshold can be changed by pointing over the chart, which triggers the appearance of a dotted line.
2. Once the dotted line is in the appropriate spot, click the chart. The line becomes solid, and the threshold value is updated and shown in the Threshold field.
3. To change the value again using this method, click the red line, and drag it to the appropriate spot. Alternatively, user can also directly edit the value in the Threshold field. Use the **Auto-threshold** (🔄) button to set the threshold to the value, which is calculated by the analysis algorithm.

Note: The Threshold field and the **Auto-threshold** (🔄) button become only visible by moving the pointer in the range of the well diagram.

4. Click **Recalculate** to trigger the re-analysis of data and to close the window. Click **Cancel** to close the window without any changes.



Note: To add a single well diagram to the report, click **Add to report**. For more information on reports, see Section 7.7 Reports.

7.6.15.11.3. Setting amplitude multiplexing on 1D Scatterplot

1D Scatterplot allows to enable amplitude multiplexing split for a particular well, on a particular channel (Reaction mix with amplitude multiplexing split is not required).

Important: Amplitude multiplexing can be applied only for wells processed with the High Multiplexing Reference channel; otherwise, when Standard Reference channel was used in particular Imaging step, this feature is not available.

Note: Amplitude multiplexing split cannot be applied for Reference channels: Standard Reference channel nor High Multiplexing Reference channel.

There are several methods to set amplitude multiplexing on a different level:


1. Amplitude multiplexing drop-down menu allows to set AM split for all wells for selected channels at once. After checking the appropriate checkboxes (or choosing the **Select all** option) and clicking the **Apply** button, changes are applied to all selected channels (auto-thresholds for Low, High, and Double positives are set) and there is no need to click the **Recalculate** button for each channel separately. Please note that this operation might take up to several minutes depending on selection.

Only channels selected in source selection are visible on the drop-down menu. When the checkbox for particular channel is ticked here, the checkbox in the particular channel section (described below) is ticked as well and vice versa – there is bi-directional interaction between them.




Example of 1D Scatterplot for channel Green with AM split applied via drop-down menu.

Note: When Std-Ref is used as a reference channel, amplitude multiplexing cannot be applied, then the **i** icon, next to drop-down menu, changes color from blue to yellow and, when user mouse hover it, appropriate information is displayed.




-

Each checkbox state is coupled with the aforementioned drop-down menu. If AM cannot be enabled, the following information is presented:



-


Also here, HM-Ref is required; otherwise, a warning is presented.



Please note that, after such operation, changed well becomes outlier comparing to the other selected wells on a particular channel. In such state, user cannot set common threshold nor apply AM for the rest of wells using checkbox nor via drop-down menu – the first well needs to be reverted to single threshold mode, following the opposite procedure as described above.




When amplitude multiplexing is applied, user can adjust threshold(s) in the same manner as for single thresholds but the difference is there are three text inputs and red lines instead of one. Moreover, recalculation is required at the end.



7.6.15.11.4. Reference channel on 1D Scatterplot

The Software Suite also provides a 1D Scatterplot view for the reference channel, which is hidden by default. To view the 1D Scatterplot for the reference channel in addition, click **Show reference channel**. The title of this 1D Scatterplot view indicates that the 1D Scatterplot is related to the particular reference channel – standard reference channel (Std-Ref) or high-multiplexing reference channel (HM-Ref). In case of mixed scenarios when two types of reference channels are detected by Algorithm, two separate plots are presented.

The graph for the reference channel provides the possibility to set a lower as well as an upper threshold to exclude partitions with too high/too low RFU. Setting the thresholds (individually per well or common lower and upper threshold for all selected wells) is analog to 1D Scatterplots for target channels. To apply the new threshold values for the analysis, click **Recalculate**. The 1D Scatterplot for the reference channel uses the same functions as the 1D Scatterplot views for non-reference channels.



7.6.15.11.5. Copy, Copy all, and Download functions

As with other plots, **Copy**, **Copy all**, and **Download** options are available for 1D Scatterplots.

Copy and **Download** apply to individual plots, including plots displayed per target or per channel. **Copy all** applies to all plots displayed in the current tab.

7.6.15.12. 2D Scatterplot tab for absolute quantification


The **2D Scatterplot** tab shows a 2D Scatterplot view that displays the fluorescence intensity from two selected channels or targets, allowing for a comparison and evaluation of the fluorescence from two sources.

To create a 2D Scatterplot, two different modes are available: the single pair mode and the selected pairs mode.

7.6.15.12.1. Single pair mode


The single pair mode allows a 2D Scatterplot analysis of just one pair of a channel or target combination by assigning desired targets/channels to the x-axis and the y-axis using the drop-down menus.

Note: If the reaction mix contains only two channels/targets, the assignment will be done automatically.



7.6.15.12.2. Selected pairs mode


This mode allows to select multiple pairs of targets/channels combination using the drop-down menu. The software provides all possible combinations of targets or channels automatically. After selection of desired pairs by checking appropriate checkboxes or choosing the **Select all** option, click the **Show** button to display 2D Scatterplots for all selected pairs. Targets or channels are assigned to axis automatically. Each selected pair is represented by separate, independent 2D scatterplots with its own set of features.



In both modes, the x- and y-axes represent the value of fluorescence intensity. The ranges of the axis are aligned with the maximal fluorescence intensity of each selected channel/target measured. The range of the x-axis and the y-axis can be changed by modifying the max value of the fluorescence intensity. For doing this, adjust the value in the field to Max value for the x-axis (RFU) or Max value for the y-axis (RFU) and press **Save**. Resetting the x-axis and the y-axis to the default range is provided by using the **Back to Default** buttons.

The application also presents the number of double positives (++) and double negatives (--), and the number of partitions that are positives on one channel and negative on the other (+-, -+). To view updated results after changing threshold, click the **Recalculate** button.

To view an additional toolbar enabling actions related to the 2D Scatterplot view, such as lasso mode, downloading the plot, pan, zooms, reset axis, hold the pointer over the diagram. For more details about the toolbar, refer to Section 7.6.14.5 Diagram options.



The Common threshold field for each axis shows the common threshold value for each selected well of the fluorescence intensity, which is used to distinguish between positive and negative partitions. If only one source well is selected, the values of the thresholds for the targets or channels on each axis are shown in the Common threshold fields and on the graph in the form of red lines. If multiple source wells are defined and their automatically calculated threshold values are different, a common threshold value is initially not shown.

7.6.15.12.3. Setting the common thresholds for all selected wells and each axis (channel)

The 2D Scatterplot view provides an option to set a common threshold value for the x-axis and y-axis for all associated wells. There are two ways to change the threshold. The first one involves pointing to the chart, which triggers the appearance of two perpendicular dotted lines. Once the dotted lines are in the appropriate spot, click the chart. The lines become solid, and the threshold value is updated and is shown in the Threshold field. To change the value again using this method, click one of the red lines and drag it to the appropriate spot. If needed, repeat this step with the second line. In addition to moving the lines, directly edit the value in the Common threshold field of the associated axis. Click the **Recalculate** button to trigger the re-analysis of data.

Note: Amplitude multiplexing is not available for 2D Scatterplot analysis, and channels that have this mode applied (via 1D Scatterplot) cannot be selected.

Single pairSelected pairs

X-axis channel

Common threshold

-

↺

Y-axis channel

Common threshold

-

↺

Recalculate


Some channels are unavailable because one or more of selected wells are in amplitude multiplexing "mode".

For each partition point the assignment to its group (++ , +-, -+, or --) is derived from the threshold values. The partition number of each group is displayed on the top right, next to the diagram. The color of the point that represents the partition fluorescence measurement is assigned according to the group. A legend is shown on the left side below the 2D Scatterplot view:

1. On the 2D Scatterplot, only valid partitions are shown.
2. **Dark blue:** Partition is assigned for x-axis and y-axis channel as positive (++).
3. **Orange:** Partition is assigned to x-axis channel as negative and for y-axis channel as positive (-+).
4. **Light blue:** Partition is assigned to x-axis channel as positive and for y-axis channel as negative (+-).
5. **Gray:** Partition is assigned for x-axis and y-axis channel as negative (--).
6. The number of invalid partitions is shown in the legend at the right-hand side.

Invalid partitions on X mean the number of invalid partitions assigned to the x-axis.

Invalid partitions on Y mean the number of invalid partitions assigned to the y-axis.




2D Scatterplot view with two common thresholds.


7.6.15.12.4. Assigning partitions to a group using free hand (Polygon mode)

The user can select Polygon partitions measurement dots with a free-hand mode, so that he can use a more precise way to assign partitions to the group they should belong to. The polygon selection is available in the menu above the diagram on hover.

- 1. When the **Polygon** icon () is clicked, the group (++, +-, --+, or ---) to which partitions should be assigned using the free-hand mode can be selected.



- 2. After selecting the group, the plot area become dimmed, and the legend is cleared, user can start drawing or exit polygon mode (click the **Cancel** button).




3. User need to create polygon by placing its vertex on by one, until polygon become the closed area. After placing each vertex, there is a possibility to undo the last move (remove last vertex) using  icon or totally clear the polygon using  icon from the toolbar. Note that during drawing polygon lines cannot cross – in such case, dashed line become red and next vertex cannot be placed.



Note: Toolbar can be moved within plotting area by using  icon. Clicks, hold, and drag the toolbar to a convenient place, ensure to not cover desired partitions.


4. When polygon is drawn and closed, user can pan (move) the polygon over plot area if needed.
5. Finally, user should click the **Apply** icon (this icon become active) to apply the changes. Partitions on plot will change the color, but polygon is not reflected in results until user presses **Recalculate**. Until that moment, legend is cleared and appropriate communication is presented.



6. After selecting points by polygon, the user can set thresholds only by clicking the **Auto-threshold** icon. Clicking this icon reactivates the threshold behavior. The user can use either the polygon mode or the threshold setting. A combination of both is not possible. When thresholds are changed and not confirmed by clicking the **Recalculate** button, and if some partitions are selected through polygon mode and recalculated, the threshold values are ignored. User can discard changes using **Auto-threshold** button, which become common for both axes.

Note: The points selection in polygon mode is additive. User can add points to the selected group or create new groups until **Recalculate** button is pressed.

7. After pressing the **Recalculate** button, user gets the results – legend is filled with results. Polygon selection in 2D Scatterplot also affects histogram and 1D Scatterplots views. For details, refer to Sections 7.6.15.10 Histogram tab for absolute quantification and 7.6.15.11 1D Scatterplot tab for absolute quantification.



To adjust axis to ease drawing user can change values of x and y-axis using panel below the plot:

Max. value for X-axis [RFU]

Max. value for Y-axis [RFU]

To add the 2D scatterplot to the report, click **Add to report**. For more information on reports, see Section 7.7 Reports.

7.6.15.12.5. 2D Scatterplot Custom analysis

The user can click **Custom analysis** below the main 2D Scatterplot graph to expand two modes of 2D Scatterplot analysis: All selected wells and Sample modes.

All selected wells mode


In the All selected wells mode, each well selected on source selection is represented by separate mini 2D Scatterplot. Merging of above mini plots creates main 2D Scatterplot described in above paragraphs – it means that any change (e.g., threshold change) introduced on main 2D Scatterplot will directly influence the mini plots and in opposite way – changes made on particular mini plot will impact main plot.



Each mini 2D Scatterplot title bar contains the following information:


- Well ID
- Hyperwell ID (if wells has been grouped into hyperwell on source selection)
- Sample name (if assigned to well)
- Detected reference channel (Std-Ref or HM-Ref)
- Temperature in well (if gradient was applied)

Each mini 2D Scatterplot can be enlarged by clicking the gray title bar with above information. Then a new Well details window appears. In the new window, on enlarged mini plot, user can perform similar actions like on main 2D Scatterplot and additionally use navigation buttons to switch between mini plots particular wells presented on overview.



Important: In case of threshold changes – line threshold and lasso(polygon) or using auto-threshold function, changes on plot are automatically recalculated (and there is no need to additionally click any button).

In case user created some hyperwells in source selection, on analysis per target, mini 2D Scatterplots representing wells being part of hyperwells have colorful bar and hyperwell ID indicating particular hyperwells.



In this scenario, when user clicks the colorful bar to enlarge particular mini 2D Scatterplot instead of Well details, other modal window – **Hyperwell details** – is presented. This modal represents merged 2D Scatterplot of all wells being part of selected hyperwell; user operates on group of wells instead of single one. Rest of behaviors of this window remains the same as for Well details.




Samples mode

In the Samples mode, user additionally selects samples that will be presented:



Note: If no samples are assigned to selected wells, mode Samples will be inactive.

After selecting samples, the overview of Custom analysis is divided into horizontal sections – each section represents replicates of particular Samples of one reaction mix. Each section consists of grouped: 2D Scatterplot (merged one of particular mini 2D Scatterplots) and those mini plots itself.




Any change, for example, threshold change introduced on mini 2D Scatterplot of particular sample, will affect grouped 2D Scatterplot of that sample and main 2D Scatterplot.

Each individual mini plot can be enlarged by clicking gray bar, but here, the Replicate details window appears and user navigates between particular replicates (mini 2D Scatterplots from particular sections).




Grouped plot can be also enlarged by clicking the title bar and then Sample details modal window appears. Here, the user navigates between grouped plots (if several Samples have been selected in Custom analysis).




Important: In case of threshold changes done on one Replicates window or Sample, data are automatically recalculated immediately.

In case user created some hyperwells in source selection, on analysis per target, mini 2D Scatterplots representing replicates being part of hyperwells have colorful bar and hyperwell ID indicating particular hyperwells.




Clicking the bar enlarges the particular mini 2D Scatterplot. Hyperwell details is presented. This modal represents merged 2D Scatterplot of all wells being part of selected hyperwell – user operates on group of wells instead of single one.



7.6.15.12.6. Unifying axis values of 2D Scatterplot for download and report purposes

The user can expand the Settings section and specify max values for the x- and y-axes [RFU] by inputting each value (255 is the maximum value). After entering desired values, the following buttons can be selected: **Save** applies the changes and **Clear changes** rejects current changes and clears inputs. For all types of plots (including Custom analysis plots after enlarging), specified values will overwrite the values visible on the plots in the user interface and will be applied to plots downloaded by the user, or added to reports.



7.6.15.12.7. Copy, Copy all, and Download functions

Copy, **Copy all**, and **Download** functions are available for 2D Scatterplots.

Copy and **Download** can be used for the main 2D Scatterplot and for enlarged plots. **Copy all** is available in the Custom Analysis and applies to all plots displayed in the current tab.

7.6.15.13. Concentration diagram tab for absolute quantification

The **Concentration Diagram** tab shows the diagrams that display the distribution of concentration values and confidence intervals. One diagram is created for each selected target or channel. A concentration diagram has two axes. The x-axis shows the analyzed wells, and the y-axis represents the concentration values for the selected targets or channels of each well. The values on the y-axis have two available scales – linear and logarithmic.


When amplitude multiplexing is applied, separate concentration diagrams are generated for “Low” and “High” part of the channel.

To view an additional toolbar that enables user to perform actions related to the diagram, such as downloading the plot, hold the pointer over the diagram. For more details about the toolbar, refer to Section 7.6.14.5 Diagram options.

The y-axis scale can be modified using the buttons located below each graph. The buttons are visible when you hold the pointer over a graph. To view the values on a linear scale, click **lin**. To view the values on a logarithmic scale, click **log10**.

Each diagram presents two values for each well – the concentration value, displayed as a bar, and the confidence interval, displayed as an error bar. To view the exact values, point to one of the bars. After a concentration diagram loads, the first 32 wells are shown in the diagram. To view other wells, use the slider located below the diagram.

To view the mean values for replicates on the diagram, click **Show mean values for replicates**. In this case, one bar is shown for a replicate group showing the mean concentration value and the mean CI value of the replicate group. To view exact values and a list of wells belonging to the replicate group point to the associated bar.



To display values scaled by dilution and conversion factors, select **Use dilution factor** (applies to the entire tab) and **Use conversion factor** (applies to plots displayed per target or per channel), respectively.



As with other plots, **Copy**, **Copy all**, and **Download** options are available for Concentration diagrams. **Copy** and **Download** apply to individual plots displayed per target or per channel, whereas **Copy all** applies to all plots displayed in the current tab.

To add any of the concentration diagrams to the report, click **Add to report** next to the relevant diagram. For more information on reports, see Section 7.7 Reports.

7.6.16. Mutation detection

The Plate Analysis environment of the Software Suite includes the **Mutation Detection** tab. Mutation Detection analysis is based on the concentrations (see Section 7.6.15 Absolute quantification). To use mutation detection, targets must be defined in the reaction mixes, samples must be defined, and then reaction mixes and samples must be assigned in plate layout. For more information, see Section 6.4 Setting up an experiment.

Wild type target *

1

Select

Mutant target *

Select

One or more targets are not available for selection because Amplitude Multiplexing is applied, they are excluded by Quality Control rules, or there is an issue with Imaging. Make sure you meet selection requirements described in details. [See details](#)

Reset all
 Add pair

The **Mutation Detection** tab is used to show the results of analyzing plate contents to detect mutations in the samples. The analysis results are put into list views, heatmaps, point diagrams, and concentration diagrams.

Note: Saving mutation detection tests is not available.

Note: Amplitude multiplexing is not supported for Mutation Detection analysis – targets in amplitude multiplexing mode (“Low” and “High”) are disabled for selection.

7.6.16.1. Setting up a mutation detection analysis

1. Open the **Mutation Detection** tab.

The screenshot displays the 'Mutation Detection' tab in a software interface. At the top, there are navigation tabs: 'Absolute Quantification', 'Mutation Detection' (selected), 'Genome Editing', 'Copy Number Variation', and 'Gene Expression'. Below these is a header bar with 'Select source of mutation detection (0 wells)' and a 'Help' icon. The main area features a 96-well plate grid (rows A-H, columns 1-12). To the right of the grid is a sidebar with the following content:

- Select imaging step:** A dropdown menu showing 'Imaging info'.
- Targets:** A dropdown menu showing 'Hide details'.
- Mutation Detection:** This analysis identifies genetic mutations in samples.
- Selection requirements:**
 1. Please make sure that the plate layout including the reaction mix and samples is defined for the respective well(s).
 2. Please note that targets in Amplitude Multiplexing mode cannot be applied for Mutation Detection analysis.
 3. Please check for any warnings or errors in Absolute Quantification and Plate Configurator environment.
 4. Please ensure that the same sample is assigned for the selection of simplex wells.
- How to set up analysis:**
 1. Select wells for analysis.
 2. Specify wild type target.
 3. Specify mutant target.
 4. Create as many pairs as necessary.

At the bottom of the sidebar, there are two dropdown menus: 'Wild type target *' and 'Mutant target *', both showing '1. Select'. Below these is a 'Create report' button. At the bottom of the main interface, there is a 'Back to plate configurator' button and a '0 items selected' status.

2. Before selecting wells for analysis, read analysis details carefully, then click the **Hide details** button or select wells to collapse the panel. If needed, the panel can be expanded again anytime using the opposite **See details** option.

This screenshot shows the 'Mutation Detection' sidebar details. The sidebar is expanded, showing the following content:

- Targets:** A dropdown menu showing 'Hide details'.
- Mutation Detection:** This analysis identifies genetic mutations in samples.
- Selection requirements:**
 1. Please make sure that the plate layout including the reaction mix and samples is defined for the respective well(s).
 2. Please note that targets in Amplitude Multiplexing mode cannot be applied for Mutation Detection analysis.
 3. Please check for any warnings or errors in Absolute Quantification and Plate Configurator environment.
 4. Please ensure that the same sample is assigned for the selection of simplex wells.
- How to set up analysis:**
 1. Select wells for analysis.
 2. Specify wild type target.
 3. Specify mutant target.
 4. Create as many pairs as necessary.

3. Group hyperwells if needed and select wells for analysis. For more information, see Section 7.6.14.1 Selecting wells for analysis.

- Prepare pairs of wild type target and mutant target for analysis by selecting the applicable wild-type target (WT) from the Wild type target list and mutant target (MT) from the Mutant target list. The drop-down list will automatically limit choices only to targets that are available for the pair that the user is creating:

The screenshot shows the 'Mutation Detection' tab in the software. On the left is a 12x8 grid of wells labeled A-H and 1-12. A dropdown menu is open for 'Wild type target *', showing options RM2, T1, and T3. To the right, 'Mutant target *' is set to T2 with a yellow color indicator. Below the grid are buttons: 'Select all', 'Unselect all', 'Group as hyperwells', and 'Ungroup hyperwells'. On the right side, there's a 'Select imaging step' dropdown set to '1', a 'Targets' dropdown, and a 'Show results' button. At the bottom, there are tabs for 'List', 'Heatmap', 'Point diagram', and 'Concentration diagram'. A message box at the bottom states: 'To see the analysis results, select the source wells and mutant and wildtype targets in the "Select source of mutation detection" section above.'

Important: There are several rules according to the mutant detection pairs definition:

- In general, the wild type and mutant target pair selection is limited to the reaction mix. Only within one reaction mix a pair combination for a wild type target and a mutant target can be defined.

Note: In case simplex reaction mixes are available (wild type and mutant targets are split over two reaction mixes), the identical sample assignment must be available to allow a mutant detection pair combination.

- A target selected as WT cannot be used as a mutant target (MT) at the same time and vice versa.
- One WT target can be paired with a different MT target several times.
- One MT target can be paired with a different WT target several times.
- Pairs cannot be duplicated.

- To add another pair, use the **Add pair** button. To remove a particular pair, use button next to that pair. To clear all pairs, use **Reset all** button or change the selected well.
- When all desired pairs are prepared, click **Show results** to view the results of the analysis.

This screenshot shows the same interface as the previous one, but with multiple target pairs added. The 'Wild type target *' list now includes T1, T3, and 1. The 'Mutant target *' list includes T2 and t1. Each pair has a color indicator (Green, Red, Yellow). At the bottom, there is a 'Reset all' button and a 'Show results' button.

- The results are divided into several tabs. To view the contents of the tab, click the tab title.

7.6.16.2. List tab for mutation detection

The **List** tab contains a table with an overview of the analyzed wells. The following columns are available in the table.

1. **Well** – This column represents the well position in the plate layout. If gradient cycling was used the temperature is also displayed.
2. **Sample/NTC/Control** – This column shows the sample, NTC, or control name with its corresponding icon that identifies the sample or indicates whether the entry is an NTC or control.
3. **Reaction mix** – This column contains the icon and the name of the Reaction mix.
4. **Target** – This column shows all target names with their corresponding target type. Targets that were selected as wild type or mutant are marked accordingly.
5. **Conc. [copies/μL]** – This column shows the concentration assigned to each target.
6. **CI (95%)** – This column shows the value of the confidence interval at a 95% confidence level.
7. **Mutation fraction** – This column shows the Mutant fraction value in percentage.
8. **CI (95%)** – This column shows the value of the confidence interval for mutant fraction at a 95% confidence level.

List

Heatmap

Point diagram

Concentration diagram

☐ Add to report
 ☐ Show mean values for replicates
 [Export to CSV...](#)

Well	Sample/NTC/Control	Reaction Mix	Target			Concentration		Mutant fraction	CI (95%)
			Name	IC	Type	dPCR Reaction cp/μL	CI (95%)		
A5	1ng gDNA	RM2 Ref. channel: Std-Ref	T2	-	MT	25.77	23.8%	44.4189%	17.9%
			T1	-	WT	32.24	21.3%	-	-
			T2	-	MT	25.77	23.8%	63.5922%	14.6%
			T3	-	WT	14.75	31.4%	-	-
A6	1ng gDNA	RM2 Ref. channel: Std-Ref	T2	-	MT	30.56	21.8%	44.4753%	16.4%
			T1	-	WT	38.16	19.5%	-	-
			T2	-	MT	30.56	21.8%	62.3535%	13.6%
			T3	-	WT	18.45	28.0%	-	-
A7	1ng gDNA	RM2 Ref. channel: Std-Ref	T2	-	MT	29.27	22.5%	50.3326%	16.0%
			T1	-	WT	28.88	22.6%	-	-
			T2	-	MT	29.27	22.5%	65.0057%	13.5%
			T3	-	WT	15.76	30.6%	-	-
B2	1ng gDNA	Simplex B Ref. channel: Std-Ref	t1	-	MT	57.65	16.0%	68.3228%	9.1%
A2	1ng gDNA	Simplex A Ref. channel: Std-Ref	1	-	WT	26.51	23.4%	-	-

Note: Columns related to Concentration and Mean concentration can also provide additionally sub-columns, depending on whether dilution factor and/or conversion factor (described in Sections 7.6.14.7 Dilution calculation option and 7.6.14.9 Conversion factor, accordingly) have been selected.

By checking the “Show mean values for replicates” options, system is able to calculate additional values for replicates:

- Replicates are analyzed as separate wells, but in addition, the mean concentration and mean mutant fraction values together with the corresponding mean CI are provided on demand.
- The list view still shows independent rows for each selected well, but replicates are grouped together. Replicates from the same group are next to each other in the list view. The list view is extended by four columns indicating the following mean values:
 - **Mean conc. [copies/μL]** – mean concentration value
 - **CI (95%)** – CI of mean concentration as percentage

- **Mean mutation fraction** – mean mutation fraction as percentage
- **CI (95%)** – CI of mean mutation fraction as percentage

List	Heatmap	Point diagram	Concentration diagram										
				☐ Add to report ☒ Show mean values for replicates Export to CSV...									
Well	Sample/NTC/Control	Reaction Mix	Target			Concentration		Mean concentration		Mutant fraction	CI (95%)	Mean mutant fraction	CI (95%)
			Name	IC	Type	dPCR Reaction cp/μL	CI (95%)	dPCR Reaction cp/μL	CI (95%)				
A5	1ng gDNA	RM2 Ref. channel: Std-Ref	T2	-	MT	25.77	23.8%	28.53	21.6%	44.4189%	17.3%	46.2756%	24.3%
			T1	-	WT	32.24	21.3%	33.13	35.2%	-	-	-	-
			T2	-	MT	25.77	23.8%	28.53	21.6%	63.5922%	14.6%	63.6037%	14.0%
			T3	-	WT	14.75	31.4%	16.33	29.1%	-	-	-	-
A6	1ng gDNA	RM2 Ref. channel: Std-Ref	T2	-	MT	30.56	21.8%	28.53	21.6%	44.4753%	16.4%	46.2756%	24.3%
			T1	-	WT	38.16	19.5%	33.13	35.2%	-	-	-	-
			T2	-	MT	30.56	21.8%	28.53	21.6%	62.3535%	13.6%	63.6037%	14.0%
			T3	-	WT	18.45	28.0%	16.33	29.1%	-	-	-	-
A7	1ng gDNA	RM2 Ref. channel: Std-Ref	T2	-	MT	29.27	22.5%	28.53	21.6%	50.3326%	16.0%	46.2756%	24.3%
			T1	-	WT	28.88	22.6%	33.13	35.2%	-	-	-	-
			T2	-	MT	29.27	22.5%	28.53	21.6%	65.0057%	13.5%	63.6037%	14.0%
			T3	-	WT	15.76	30.6%	16.33	29.1%	-	-	-	-
B2	1ng gDNA	Simplex B Ref. channel: Std-Ref	t1	-	MT	57.65	16.0%	57.65	16.0%	68.3228%	9.1%	68.3228%	9.1%
A2	1ng gDNA	Simplex A Ref. channel: Std-Ref	1	-	WT	26.51	23.4%	26.51	23.4%	-	-	-	-

7.6.16.3. CSV export: Current results

To export the list view from Mutation detection analysis as .csv file, click **Export to CSV** and select current results.

1. Click the **Export to CSV...** button, and select the **Current results** option.
2. Remember that data in CSV reflect data from List view are structured as follows:
 - **Plate name** – name of the plate
 - **Plate ID** – unique identifier of the plate
 - **Plate type** – type of the plate
 - **Well** – identifier of well or hyperwell (if defined)
 - **Hyperwell** – list of wells being part of hyperwell
 - **Sample ID** – unique identifier of the sample
 - **Sample/NTC/Control** – name of Sample/NTC/Control
 - **Type** – Type (Sample/Control/Non Template Control)
 - **Reaction Mix** – name of reaction mix
 - **Target (name)** – name of the target
 - **Target (IC)** – internal control (if selected)
 - **Target (type)** – type of the target: mutant (MT) or wild-type (WT)
 - **Conc. [cp/μL] (dPCR reaction)** – calculated concentration in dPCR reaction
 - **Conc. [unit] (dPCR reaction)** – converted concentration in dPCR reaction, in user-defined unit
 - **CI (95%) (dPCR reaction)** – confidence interval parameter in dPCR reaction
 - **Conc. [cp/μL] (undiluted sample)** – calculated concentration in undiluted sample

- **Conc. [unit] (undiluted sample)** – converted concentration in undiluted sample and in user-defined unit
- **Mean conc. [cp/μL] (dPCR reaction)** – calculated mean concentration in dPCR reaction for replicates
- **Mean conc. [unit] (dPCR reaction)** – converted mean concentration in dPCR reaction in user-defined unit for replicates
- **CI (95%) (dPCR reaction)** – confidence interval parameter for mean concentration in dPCR reaction in custom unit of replicates
- **Mean conc. [cp/μL] (undiluted sample)** – calculated mean concentration in undiluted sample for replicates
- **Mean conc. [unit] (undiluted sample)** – converted mean concentration in undiluted sample and in custom unit for replicates
- **Mutant fraction** – value of mutant fraction
- **CI (95%)** – confidence interval parameter for mutant fraction
- **Mean mutant fraction** – value of mean mutant fraction for replicates
- **CI (95%)** – confidence interval parameter for mean mutant fraction
- **Concentration factor** – value of concentration factor given by user during sample creation
- **Template volume [μL]** – value of template volume given by user during sample creation
- **Total volume [μL]** – value of total volume given by user during reaction mix creation
- **Conversion factor** – value of conversion factor given by user during sample creation
- **Conversion unit** – conversion factor's unit given by user during sample creation
- **REF** – type of detected Reference channel. Standard Reference channel (Std- Ref) or High- Multiplexing Reference channel (Std-Ref or HM-Ref)
- **Partitions (Valid)** – number of valid partitions
- **Partitions (Positive)** – number of positive partitions
- **Partitions (Negative)** – number of negative partitions
- **Volume per well [μL]** – volume per well, includes VPF if applied
- **Actual cycled vol/partition [nL]** – actual (real) cycled volume per partition
- **Actual cycled vol/well [nL]** – actual (real) cycled volume per partition
- **Mean RFU positives** – arithmetic average of RFU of all positive partitions at certain threshold
- **Mean RFU negatives** – arithmetic average of RFU of all negative partitions by certain threshold
- **Mean RFU positives for replicates** – mean of arithmetic average of RFU of all positive partitions at certain threshold for replicates
- **Mean RFU negatives for replicates** – mean of arithmetic average of RFU of all negative partitions at certain threshold for replicates

The **Heatmap** tab contains a heatmap that shows the mutant fraction as a percentage in each of the wells. If a well is not selected as a source for the analysis, the value is not displayed on the heatmap and its background color is gray. For each WT-MT pair that is defined, a separate heatmap is presented. Each heatmap contains a header that presents the following information:

- For example, for a pair with target “T1” in the Green channel selected as the wild type target and target “T2” in the Yellow channel selected as the mutant target, the header displays like this:

To view an additional toolbar that enables actions related to the diagram, such as downloading the plot, hold the pointer over the diagram. For more details about the toolbar, refer to [Section 7.6.14.5 Diagram options](#).

1. **Use sample dilution** – enables calculations related to dilution factor. Results in undiluted sample is additionally presented on well tiles. Described in Section 7.6.14.7 Dilution calculation option.
2. **Use conversion factor** – conversion of results into unit given by user. Results in converted unit replace standard ones on well tiles. See Section 7.6.14.9 Conversion factor.
3. **Show mean values for replicates** – showing the mean concentration values for replicates. For simplex tests, the mean values view is always shown for replicates and cannot be disabled.



To add the heatmap diagram to a report, the following option can be used:

- **Add to report** – add heatmap for a single pair to the report
- **Add all to report** – add heatmaps for all pairs to the report at once (when this option is selected, the “Add to report” checkbox will automatically be checked)

For more information on reports, see Section 7.7 Reports.

To copy particular Heatmap to Windows clipboard, click **Copy**. To save the Heatmap as an image file, click **Download**. To copy all heatmaps displayed in the current tab use option **Copy all**.

7.6.16.5. Point diagram tab for mutation detection


The **Point diagram** tab shows a diagram that displays the percentage of mutant fractions in each analyzed well. A point diagram has two axes. The x-axis shows the analyzed wells and samples, and the y-axis represents the mutant fraction, shown as a percentage.

Each combination of wild-type target and mutant target in one sample throughout the selected wells is represented in the diagram, with one point showing the concentration value together with the confidence interval. To view detailed information, hold the mouse pointer over its corresponding point. A tooltip with detailed information opens.

For each WT–MT pair, a separate point diagram is presented. Each point diagram contains the header with information about WT and MT – the same as in heatmap.


The y-axis scale can be modified from linear to logarithmic scale using the buttons located on the left below the diagram. To view the values on a linear scale, click **lin**. To view the values on a logarithmic scale, click **log10**.

To view an additional toolbar that enables actions related to the diagram, such as downloading the plot, hold the pointer over the diagram. For more details about the toolbar, refer to Section 7.6.14.5 Diagram options.



For point diagram, there is one additional option that user can select:

- **Show mean values for replicates** – showing the mean concentration values for replicates. If the user checks the checkbox to select the mean representation for replicates, the points of individual replicates disappear and only one point that represents the mean mutant fraction value of the replicates is presented. The corresponding well IDs of the replicates are shown on the x-axis. When there are no replicates within selected wells for mutant target the points do not change.



To add point diagrams to a report, the following options can be used:

- **Add to report** – add point diagram for a single pair to the report
- **Add all to report** – add point diagrams for all pairs to the report at once (when this option is selected, the “Add to report” checkbox will automatically be checked)

For more information on reports, see Section 7.7 Reports.

To copy particular point diagram to Windows clipboard, click **Copy**. To save the point diagram as an image file, click **Download**. To copy all point diagrams displayed in the current tab, click **Copy all**.

7.6.16.6. Concentration diagram for mutation detection

The **Concentration diagram** tab shows a diagram that displays the distribution of concentration values in the wells together with their confidence intervals. A concentration diagram has two axes. The x-axis shows the analyzed wells and samples, and the y-axis represents the concentration values.

Each combination of wild-type target and mutant target in one sample throughout the selected wells is represented in the diagram with one bar showing the concentration value together with the confidence interval. To view detailed information, hold the mouse pointer over its corresponding bar. A tooltip with detailed information opens.

For each WT–MT pair, a separate concentration diagram is presented. Each concentration diagram contains the header displaying information about WT and MT – the same as in heatmap and point diagram.

The y-axis scale can be modified using the buttons located below graph to view the values on a linear scale, click **lin**. To view the values on a logarithmic scale, click **log10**.

To view an additional toolbar that enables actions related to the diagram, such as downloading the plot, hold the pointer over the diagram. For more details about the toolbar, refer to Section 7.6.14.5 Diagram options.



There are three additional options that user can select:

- **Use sample dilution** – enables calculations related to dilution factor, which as described in Section 7.6.14.7 Dilution calculation option. Results in undiluted sample are additionally presented on tooltips; y-axis scale is adjusted to results.
- **Use conversion factor** – conversion of results into a unit specified by the user, which is described in Section 7.6.14.9 Conversion factor. Results in converted unit replace standard ones on tooltips; y-axis scale is adjusted to results.
- **Show mean values for replicates** – showing the mean concentration values for replicates. If the user checks the checkbox to select the mean representation for replicates, the bars of individual replicates disappear and only one bar that represents the mean mutant fraction value of the replicates is presented. The corresponding well IDs of the replicates are shown on the x-axis. When there are no replicates within the selected wells for mutant target, the bars do not change.



To add the concentration diagram to a report, the following options can be used:

- **Add to report** – add point diagram for a single pair to the report
- **Add all to report** – add point diagrams for all pairs to the report at once (when this option is selected, the “Add to report” checkbox will automatically be checked)

For more information on reports, see Section 7.7 Reports.

To copy a Concentration diagram to the Windows clipboard, click **Copy**. To save the Concentration diagram as an image file, click **Download**. To copy all Concentration diagrams displayed in the current tab, click **Copy all**.

7.6.17. Genome editing

The **Genome editing** tab contains views that provide insight into the number of edited genomes in analyzed wells. The analysis results are put into list views, heatmaps, point diagrams, and concentration diagrams.

Select imaging step

 1

Imaging info

Wild type target *

Select

Edited target *

Select

One or more targets are not available for selection because Amplitude Multiplexing is applied, they are excluded by Quality Control rules, or there is an issue with Imaging.

Note: Saving genome editing tests is not yet provided.

7.6.17.1. Setting up a genome editing analysis

Note: Amplitude multiplexing is not supported for Genome editing analysis. Targets in amplitude multiplexing mode (“Low” and “High”) are unavailable for selection. In addition, targets associated with channels invalidated by analysis rules cannot be selected.

1. Click the applicable wells in the plate layout. For more information, see Section 7.6.14.1 Selecting wells for analysis.

Absolute QuantificationMutation DetectionGenome EditingCopy Number VariationGene Expression

Select source of genome editing analysis (9 wells)

	1	2	3	4	5	6	7	8	9	10	11	12
A												
B												
C												
D												
E												
F												
G												
H												

Select allUnselect allGroup as hyperwellsUngroup hyperwells

Select imaging step

 1

Imaging info

Wild type target *

Select

Edited target *

Select

Reset all

Show results

2. Select the applicable wild-type target from the **Wild type target** list.

Select source of genome editing analysis (9 wells)

	1	2	3	4	5	6	7	8	9	10	11	12
A	01	01	01	01	01	01	01	01	01	01		
B	02	02	02	02	02	02	02	02	02	02		
C	03	03	03	03	03	03	03	03	03	03		
D	04	04	04	04	04	04	04	04	04	04		
E	05	05	05	05	05	05	05	05	05	05		
F	06	06	06	06	06	06	06	06	06	06		
G	07	07	07	07	07	07	07	07	07	07		
H	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC		

Select all Unselect all Group as hyperwells Ungroup hyperwells

Select imaging step
 1 Imaging info

Wild type target *
 Select
 DPH218 ERBB2 + DPH186 TERT
 DPH218 ERBB2 Green
 DPH186 TERT Yellow

Edited target *
 Select

Show results

3. Select the applicable edited target from the **Edited target** list.

Select source of genome editing analysis (9 wells)

	1	2	3	4	5	6	7	8	9	10	11	12
A	01	01	01	01	01	01	01	01	01	01		
B	02	02	02	02	02	02	02	02	02	02		
C	03	03	03	03	03	03	03	03	03	03		
D	04	04	04	04	04	04	04	04	04	04		
E	05	05	05	05	05	05	05	05	05	05		
F	06	06	06	06	06	06	06	06	06	06		
G	07	07	07	07	07	07	07	07	07	07		
H	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC	NTC		

Select all Unselect all Group as hyperwells Ungroup hyperwells

Select imaging step
 1 Imaging info

Wild type target *
 DPH218 ERBB2 Green

Edited target *
 Select
 DPH218 ERBB2 + DPH186 TERT
 DPH186 TERT Yellow

Reset all

Show results

4. To view the results of the analysis, click **Show results**.
5. The results are divided into several tabs. To view the contents of the tab, click the tab title.

7.6.17.2. List tab for genome editing

The **List** tab contains a table with an overview of the analyzed wells. The following columns are available in the table:

1. **Well ID** – Like A1, B2, when gradient was selected there is also temperature in the well (temperature range instead of single one, if hyperwells were selected).
2. **Sample/NTC/Control** – This column shows the sample, NTC, or control name with its corresponding icon that identifies the sample or indicates whether the entry is an NTC or control.
3. **Reaction mix** – This column contains the icon and the name of the reaction mix.
4. **Target** – This column shows all target names with its corresponding target type. Targets that were selected as wild type or mutant are marked accordingly.
5. **Conc. [copies/ μ L]** – This column shows the concentration assigned to each target.
6. **CI (95%)** – This column shows the value of the confidence interval at a 95% confidence level.

a. When checkbox “Show mean values for replicates” is checked additionally two columns are displayed:

- **Mean conc. [copies/μL]** – This column shows the mean concentration assigned to each target or channel per well for replicates.
- **CI (95%)** – This column shows the value of the confidence interval at a 95% confidence level for the mean concentration.

Note: Columns related to Concentration and Mean concentration can be additionally divided into several sub-columns depending if dilution factor and/or conversion factor (described in Sections 7.6.14.7 Dilution calculation option and 7.6.14.9 Conversion factor, accordingly) have been selected.

7. **Edited fraction** – This column shows the Mutant fraction value in %.

8. **CI (95%)** – This column shows the value of the confidence interval for mutant fraction at a 95% confidence level.

List

Heatmap

Point diagram

Concentration diagram

Add to report

Show mean values for replicates

Export to CSV...

Well	Sample/NTC/Control	Reaction Mix	Target			Concentration		Edited fraction	CI (95%)
			Name	IC	Type	dPCR Reaction	CI (95%)		
			cp/L						
A2	181 1ng gDNA	DPH218 ERB82 + DPH186 TERT Ref. channel: 596-Ref	DPH186 TERT	-	ET	23.09	25.1%	46.5512%	18.6%
			DPH218 ERB82	-	WT	26.51	23.4%	-	-
A3	182 1ng gDNA	DPH218 ERB82 + DPH186 TERT Ref. channel: 596-Ref	DPH186 TERT	-	ET	23.50	24.9%	44.9064%	18.7%
			DPH218 ERB82	-	WT	28.83	22.5%	-	-
A4	183 1ng gDNA	DPH218 ERB82 + DPH186 TERT Ref. channel: 596-Ref	DPH186 TERT	-	ET	27.51	23.1%	52.9534%	16.1%
			DPH218 ERB82	-	WT	24.44	24.5%	-	-
B2	184 1ng gDNA + 0.2ng SKBR3	DPH218 ERB82 + DPH186 TERT Ref. channel: 596-Ref	DPH186 TERT	-	ET	37.16	19.9%	39.1935%	15.6%
			DPH218 ERB82	-	WT	57.65	16.0%	-	-
B3	185 1ng gDNA + 0.2ng SKBR3	DPH218 ERB82 + DPH186 TERT Ref. channel: 596-Ref	DPH186 TERT	-	ET	33.80	21.0%	36.9342%	16.8%
			DPH218 ERB82	-	WT	57.72	16.1%	-	-
B4	186 1ng gDNA + 0.2ng SKBR3	DPH218 ERB82 + DPH186 TERT Ref. channel: 596-Ref	DPH186 TERT	-	ET	39.61	19.5%	38.0220%	15.5%
			DPH218 ERB82	-	WT	64.56	15.3%	-	-
C2	187 1ng gDNA + 0.48ng SKBR3	DPH218 ERB82 + DPH186 TERT Ref. channel: 596-Ref	DPH186 TERT	-	ET	39.53	19.4%	30.3698%	16.3%
			DPH218 ERB82	-	WT	66.63	15.2%	-	-

Back to plate configurator

0 items selected

Create report

2. Simplex test (configured wild-type and edited targets are part of different reaction mixes):
 - a. For tests having the configured targets in different wells/reaction mixes, the mean result is calculated and shown for replicates in the selection. The list view is extended by four columns indicating the following mean values:
 - Mean conc. [copies/ μ L] – mean concentration value
 - CI (95%) – CI of mean concentration as percentage
 - Mean edited fraction as percentage
 - CI (95%) – CI of mean edited fraction as percentage

The replicate results are shown in one row per replicate group. To export the list view information as a .csv file, click **Export to CSV**.


7.6.17.3. Heatmap tab for genome editing

The **Heatmap** tab contains heatmaps that show the edited fraction as percentage in each of the wells. If a well is not selected as a source for the analysis, the value is not displayed on the heatmap and its background color is gray.

To view detailed information about a particular well, point the cursor over the well. A tooltip with detailed information opens.

To view an additional toolbar that enables actions related to the diagram, such as downloading the plot, hold the pointer over the diagram. For more details about the toolbar, refer to Section 7.6.14.5 Diagram options.

1. **Use sample dilution** – as described in Section 7.6.14.7 Dilution calculation option, enables calculations related to dilution factor. Results in undiluted sample is additionally presented on well tiles.
2. **Use conversion factor** – as described in Section 7.6.14.9 Conversion factor, enables conversion of results into unit given by user. Results in converted unit replace standard ones on well tiles.
3. **Show mean values for replicates** – showing the mean concentration values for replicates.



To copy a Heatmap to the Windows clipboard, click **Copy**. To save the Heatmap as an image file, click **Download**.

To add the heatmap to the report, click **Add to report**. For more information on reports, see Section 7.7 Reports.

7.6.17.4. Point diagram tab for genome editing


The **Point diagram** tab shows a diagram that displays the percentage of edited fractions in each analyzed well. A point diagram has two axes. The x-axis shows the analyzed wells and samples, and the y-axis represents the edited fraction, shown as a percentage.

To view an additional toolbar that enables actions related to the diagram, such as downloading the plot, hold the pointer over the diagram. For more details about the toolbar, refer to Section 7.6.14.5 Diagram options.

The y-axis scale can be modified using the buttons located below each graph. The buttons are visible when the pointer is held over a graph. To view the values on a linear scale, click **lin**. To view the values on a logarithmic scale, click **log10**.

Each combination of wild-type target and edited target in one sample throughout the selected wells is represented in the diagram with one point showing the concentration value together with the confidence interval. To view detailed information, hold the mouse pointer over its corresponding point. A tooltip with detailed information opens.

To view the mean values for replicates, click **Show mean values for replicates**. If the user clicks into the checkbox to select the mean representation for replicates, the points of individual replicates disappear and only one point is shown at the sample label that represents the mean edited fraction value of the replicates. When there are no replicates within selected wells for edited target the points do not change. The corresponding well IDs of the replicates are shown on the x-axis. This is also applied in the same way by default to the view where targets are in different reaction mixes. In this case, individual replicate results are not available. Mean values are calculated and shown over all replicates that are included in the well selection only. If there are further replicates of the same sample that are not included in well selection, they are not considered in the calculated mean value and show their individual results values.



To copy a Point diagram to the Windows clipboard, click **Copy**. To save the Point diagram as an image file, click **Download**.

To add the Point diagram to the report, click **Add to report**. For more information on reports, see Section 7.7 Reports.

7.6.17.5. Concentration diagram tab for genome editing

The **Concentration diagram** tab shows a diagram that displays the distribution of concentration values in the wells together with their confidence intervals. A concentration diagram has two axes. The x-axis shows the analyzed wells and samples, and the y-axis represents the concentration values. The y-axis scale can be modified using the buttons located below each graph. The buttons are visible when you hold the pointer over a graph. To view the values on a linear scale, click **lin**. To view the values on a logarithmic scale, click **log10**.

To view an additional toolbar that enables actions related to the diagram, such as downloading the plot, hold the pointer over the diagram. For more details about the toolbar, refer to Section 7.6.14.5 Diagram options.

Each combination of wild-type target and edited target in one sample throughout the selected wells is represented in the diagram with one bar showing the concentration value together with the confidence interval. To view detailed information, hold the mouse pointer over its corresponding bar. A tooltip with detailed information opens.

To view the mean values for replicates on the concentration diagram, click **Show mean values for replicates**. If the user clicks into the checkbox to select the mean representation for replicates, the bars of individual replicates disappear and only one bar is shown at the sample label that represents the mean edited fraction value of the replicates. When there are no replicates within selected wells for edited target, the bars do not change. The corresponding well IDs of the replicates are shown on the x-axis. This is also applied in the same way by default to the view where targets are in different reaction mixes. In this case, individual replicate results are not available. Mean values are calculated and shown over all replicates that are included in the well selection only. If there are further replicates of the same sample that are not included in the well selection, they are not considered in the calculated mean value and show their individual results values.

There are two additional options that user can select. First option is Use sample dilution – as described in Section 7.6.14.7 Dilution calculation option, enables calculations related to dilution factor. Results in undiluted sample is additionally presented on well tiles; y-axis scale is adjusted to results. Second option is Use conversion factor – as described in Section 7.6.14.9 Conversion factor, enables conversion of results into unit given by user. Results in converted unit replace standard ones on well tiles; y-axis scale is adjusted to results.



To copy a Concentration diagram to the Windows clipboard, click **Copy**. To save the concentration diagram as an image file, click **Download**.

To add the Concentration diagram to the report, click **Add to report**. For more information on reports, see Section 7.7 Reports.

7.6.18. Copy Number Variation

The **Copy Number Variation** tab contains analysis that visualizes the data related to copied genes in targets of interest comparing to reference targets or reference sample. Copy Number Variation analysis (CNV) is based on concentrations (see Section 7.6.15 Absolute quantification). To use this analysis, targets must be defined in the reaction mixes, samples must be defined, and then reaction mixes and samples must be assigned in plate layout. For more information, see Section 7.3 Setting up an experiment.

In both analyses, user can define up to 3 combinations (C1–C3) – each combination behaves like a separate analysis and there are no interdependencies between them. The analysis results of each combination are put into list views, heatmaps, point diagrams, and concentration diagrams.

Note: Amplitude multiplexing is not supported for Copy Number Variation analysis – targets associated in amplitude multiplexing mode (“Low” and “High”) are disabled during selection. Targets associated with channels invalidated by analysis rules cannot be used too.

Interface for Copy Number Variation analysis setup:

- Tabs: CNV with reference sample (selected), CNV with reference target, See details
- Combinations: + Add
- Combination 1 (C1):
 - Reference sample *: S1
 - Reference selection: Select
 - Reference target(s) *: Select
 - Copies / genome *: 1 - 99
 - Target of interest *: Select
- Note: One or more targets are not available for selection because Amplitude Multiplexing is applied, they are excluded by Quality Control rules, or there is an issue with Imaging. Make sure you meet selection requirements described in details. See details


7.6.18.1. Setting up a Copy Number Variation analysis with reference target

CNV with reference target analyzes how the copy number/genome of a particular target of interest varies from one sample to another in relation to the reference target present in the selected samples. The copy number per genome of the reference target is considered to remain constant among all samples being analyzed.


To set up the analysis:

1. Open the **Copy Number Variation** tab.
2. Select the **CNV with reference target** option.
3. Before selecting wells for analysis, read analysis details carefully, then click the **Hide details** button or select wells to collapse the panel. If needed, the panel can be expanded again anytime using the opposite **See details** option.

4. Group hyperwells if needed, and select wells for analysis. For more information, see Section 7.6.14.1 Selecting wells for analysis.
5. Set up Combination 1 (C1).
 - Select the applicable reference target from the Reference target list.




- Enter the number of copies per genome in the Copies/genome field for the target of interest in the reference sample. The value should be between 1 and 99.
- Select the applicable target or multiple targets for investigation from the Target(s) of interest list.



6. To add another combination (C1 and C2), use the **+ Add** button; to remove a combination, use the **Delete Combination** button on the bottom of the combination's panel.

7. When all desired combinations are prepared, click **Show results** to view the results of the analysis.



8. The results are divided into several tabs. To view the contents of the tab, click the tab title.

7.6.18.2. Setting up a Copy Number Variation analysis with reference sample

CNV based on reference sample analyzes how the copy number of a target of interest varies from one sample to another in relation to the known copy number of the reference sample.

To set up the analysis:

1. Open the **Copy Number Variation** tab.
2. Select the **CNV with reference sample** option.
3. Before selecting wells for analysis, read analysis details carefully, then click the **Hide details** button or select wells to collapse the panel. If needed, the panel can be expanded again anytime using the opposite **See details** option.
4. Group hyperwells if needed, and select wells for analysis. For more information, see Section 7.6.14.1 Selecting wells for analysis.
5. Set up Combination 1 (C1).

- Select the applicable reference sample from the Reference sample list.
- If the selected reference sample contains both hyperwells and replicates, choose which one is the reference – select hyperwell or replicates from the Reference selection list.


The screenshot shows the 'Copy Number Variation' configuration window. On the left is a 16-well plate grid (A-H, 1-12). The right panel has tabs for 'Imaging info', 'CNV with reference sample', and 'CNV with reference target'. Under 'CNV with reference sample', 'Combination 1' is selected. The 'Reference sample' is '1ng gDNA'. The 'Reference selection' dropdown is open, showing 'Hyperwell 1 (A2-A3)' and 'Replicates (A4)'. The 'Copies / genome' field is set to '1-99'. At the bottom, it says '0 items selected' and 'Create report'.

- Select one or more applicable reference targets from the Reference target(s) list.


This screenshot is similar to the previous one, but the 'Reference target(s)' dropdown is open. It shows 'T1' (Green) and 'T2' (Yellow). The 'Copies / genome' field remains '1-99'. The '0 items selected' and 'Create report' buttons are at the bottom.

- Enter the number of copies per genome in the Copies/genome field for the target of interest in the reference sample. The value should be between 1 and 99.

- Select the applicable target for investigation from the Target of interest list.



- To add another combination (C1 and C2), use the **+ Add** button; to remove a combination, use the **Delete Combination** button on the bottom of the combination's panel.
- When all desired combinations are prepared, click **Show results** to view the results of the analysis.



7.6.18.3. List tab for copy number variation

The List tab contains a table with an overview of the analyzed wells. The following columns are available in the table:

- Well** – This column represents the well position in the plate layout and Combination indicator (C1–C3). If gradient cycling was used the temperature is also displayed.
 - Sample/NTC/Control** – This column shows the sample, NTC, or control name with its corresponding icon that identifies the sample or indicates whether the entry is an NTC or control. Reference samples are marked with the word “Ref”.
 - Ref** – This column is presented in CNV with reference sample only, and in this column, there is “Ref” indicator, informing that particular sample was selected as reference sample.
 - Reaction mix** – This column contains the icon and the name of the Reaction mix.
 - Target** – This column shows all target names with their corresponding target type. Targets selected as reference are marked as REF and targets selected as targets of interest are marked as TOI.
 - Conc. [copies/μL]** – This column shows the concentration assigned to each target or channel.
 - CI (95%)** – This column shows the value of the confidence interval at a 95% confidence level.
 - When checkbox “Show mean values for replicates” is checked two additional columns are displayed:
 - Mean conc. [copies/μL]** – This column shows the mean concentration assigned to each target or channel per well for replicates.
- Note:** When the reference sample is split into several wells and replicates, this option is automatically enforced.
- CI (95%)** – This column shows the value of the confidence interval at a 95% confidence level for the mean concentration.
- Note:** Columns related to Concentration and Mean concentration can be further divided on whether several sub-columns depending if dilution factor and/or conversion factor (described in Sections 7.6.14.7 Dilution calculation option and 7.6.14.9 Conversion factor, accordingly) have been selected.
- Copies/genome** – This column shows the number of copies per genome in each of the targets of interest.
 - CI (95%)** – This column shows the value of the confidence interval for the target of interest at a 95% confidence level.
 - Ratio** – This column shows the ratio between copies/genome from input to calculated copies/genome.

List	Heatmap	Point diagram	Concentration diagram													
☐ Add to report ☒ Show mean values for replicates Export to CSV...																
Well	Sample/NTC/Control			Reaction Mix	Target			Concentration		Mean concentration		Copies/genome	CI (95%)	Mean copies/genome	CI (95%)	Ratio
	Name		Ref		Name	IC	Type	dPCR Reaction cp/μL	CI (95%)	dPCR Reaction cp/μL	CI (95%)					
A4	1ng gDNA	Ref	RM1 Ref channel: ☹ SKd-Ref	I2	-	TOI	27.51	23.1%	27.51	23.1%	1.0000	0%	1.0000	0%	1.0000	
				I1	-	REF	24.44	24.5%	24.44	24.5%	n.a	-	n.a	-	n.a	
B4	1ng gDNA + 0.2ng SKBR3	-	RM1 Ref channel: ☹ SKd-Ref	I2	-	TOI	39.61	19.5%	39.61	19.5%	0.5450	43.6%	0.5450	43.6%	1.8347	
				I1	-	REF	64.56	15.3%	64.56	15.3%	n.a	-	n.a	-	n.a	
A5	1ng gDNA	Ref	RM2 Ref channel: ☹ SKd-Ref	T2	-	TOI	25.77	23.8%	25.77	23.8%	1.0000	0%	1.0000	0%	1.0000	
				T1	-	REF	32.24	21.3%	32.24	21.3%	n.a	-	n.a	-	n.a	
B5	1ng gDNA + 0.2ng SKBR3	-	RM2 Ref channel: ☹ SKd-Ref	T2	-	TOI	41.24	19.1%	41.24	19.1%	0.8133	42.1%	0.8133	42.1%	1.2296	
				T1	-	REF	63.45	15.4%	63.45	15.4%	n.a	-	n.a	-	n.a	
A8	1ng gDNA	Ref	RM3 Ref channel: ☹ SKd-Ref	I2	-	TOI	29.18	22.3%	29.18	22.3%	1.0000	0%	1.0000	0%	1.0000	
				I1	-	REF	18.16	28.3%	18.16	28.3%	n.a	-	n.a	-	n.a	
B8	1ng gDNA + 0.2ng SKBR3	-	RM3 Ref channel: ☹ SKd-Ref	I2	-	TOI	40.96	19.3%	40.96	19.3%	0.8796	49.6%	0.8796	49.6%	1.1369	
				I1	-	REF	28.97	22.9%	28.97	22.9%	n.a	-	n.a	-	n.a	

List view for CNV with reference sample.

List Heatmap Point diagram Concentration diagram														
☐ Add to report ☒ Show mean values for replicates Export to CSV...														
Well	Sample/NTC/Control	Reaction Mix	Target			Concentration		Mean concentration		Copies/genome	CI (95%)	Mean copies/genome	CI (95%)	Ratio
			Name	IC	Type	dPCR Reaction		dPCR Reaction						
A4	1ng gDNA	RM1 Ref. channel	I2	-	TOI	27.51	23.1%	27.51	23.1%	1.1256	35.3%	1.1256	35.3%	0.8885
			I1	-	REF	24.44	24.5%	24.44	24.5%	1.0000	-	1.0000	-	n.a.
B4	1ng gDNA + 0.2ng SKBR3	RM1 Ref. channel	I2	-	TOI	39.61	19.5%	39.61	19.5%	0.6135	25.2%	0.6135	25.2%	1.6301
			I1	-	REF	64.56	15.3%	64.56	15.3%	1.0000	-	1.0000	-	n.a.
A5	1ng gDNA	RM2 Ref. channel	T2	-	TOI	25.77	23.8%	25.77	23.8%	0.7992	33.0%	0.7992	33.0%	1.2513
			T1	-	REF	32.24	21.3%	32.24	21.3%	1.0000	-	1.0000	-	n.a.
B5	1ng gDNA + 0.2ng SKBR3	RM2 Ref. channel	T2	-	TOI	41.24	19.1%	41.24	19.1%	0.6499	25.0%	0.6499	25.0%	1.5386
			T1	-	REF	63.45	15.4%	63.45	15.4%	1.0000	-	1.0000	-	n.a.
A8	1ng gDNA	RM3 Ref. channel	I2	-	TOI	29.18	22.3%	29.18	22.3%	1.6070	38.6%	1.6070	38.6%	0.6223
			I1	-	REF	18.16	28.3%	18.16	28.3%	1.0000	-	1.0000	-	n.a.
B8	1ng gDNA + 0.2ng SKBR3	RM3 Ref. channel	I2	-	TOI	40.96	19.3%	40.96	19.3%	1.4135	31.3%	1.4135	31.3%	0.7074
			I1	-	REF	28.97	22.9%	28.97	22.9%	1.0000	-	1.0000	-	n.a.

List view for CNV with reference target.

7.6.18.3.1. CSV export: Current results

To export the list view from Copy Number Variation analysis as a CSV file, click **Export to CSV** and select current results.

- Click the **Export to CSV...** button, and select the **Current results** option.
- Remember that data in the CSV file reflect the data from the List view and are structured as follows (the same structure for CNV with reference sample and CNV with reference target):
 - Plate name** – name of the plate
 - Plate ID** – unique identifier of the plate
 - Plate type** – type of the plate
 - Well** – identifier of well or hyperwell (if defined)
 - Hyperwell** – list of wells being part of hyperwell
 - Sample ID** – unique identifier of the sample
 - Sample/NTC/Control** – name of Sample/NTC/Control
 - Type** – Type (Sample/Control/Non Template Control)
 - Reaction Mix** – name of reaction mix
 - Target (name)** – name of the target
 - Target (IC)** – internal control (if selected)
 - Target (type)** – type of target: reference (REF) or target of interest (TOI)
 - Conc. [cp/μL] (dPCR reaction)** – calculated concentration in dPCR reaction
 - Conc. [unit] (dPCR reaction)** – converted concentration in dPCR reaction, in user-defined unit
 - CI (95%) (dPCR reaction)** – confidence interval parameter in dPCR reaction
 - Conc. [cp/μL] (undiluted sample)** – calculated concentration in undiluted sample
 - Conc. [unit] (undiluted sample)** – converted concentration in undiluted sample and in user-defined unit
 - Mean conc. [cp/μL] (dPCR reaction)** – calculated mean concentration in dPCR reaction for replicates
 - Mean conc. [unit] (dPCR reaction)** – converted mean concentration in dPCR reaction in user-defined unit for replicates

- **CI (95%) (dPCR reaction)** – confidence interval parameter for mean concentration in dPCR reaction in custom unit of replicates
- **Mean conc. [cp/μL] (undiluted sample)** – calculated mean concentration in undiluted sample for replicates
- **Mean conc. [unit] (undiluted sample)** – converted mean concentration in undiluted sample and in custom unit for replicates
- **Copies/genome (copies/genome)** – value of copies/genome
- **CI (95%)** – confidence interval parameter for copies/genome
- **Mean copies/genome (copies/genome)** – value of mean copies/genome for replicates
- **CI (95%)** – confidence interval parameter for mean copies/genome
- **Concentration factor** – value of concentration factor given by user during sample creation
- **Template volume [μL]** – value of template volume given by user during sample creation
- **Total volume [μL]** – value of total volume given by user during reaction mix creation
- **Conversion factor** – value of conversion factor given by user during sample creation
- **Conversion unit** – conversion factor's unit given by user during sample creation
- **REF** – type of detected Reference channel. Standard Reference channel (Std-Ref) or High-Multiplexing Reference channel (Std-Ref or HM-Ref)
- **Partitions (Valid)** – number of valid partitions
- **Partitions (Positive)** – number of positive partitions
- **Partitions (Negative)** – number of negative partitions
- **Volume per well [μL]** – volume per well, includes VPF if applied
- **Actual cycled vol/partition [nL]** – actual (real) cycled volume per partition
- **Actual cycled vol/well [nL]** – actual (real) cycled volume per partition
- **Mean RFU positives** – arithmetic average of RFU of all positive partitions at certain threshold
- **Mean RFU negatives** – arithmetic average of RFU of all negative partitions by certain threshold
- **Mean RFU positives for replicates** – mean of arithmetic average of RFU of all positive partitions at certain threshold for replicates
- **Mean RFU negatives for replicates** – mean of arithmetic average of RFU of all negative partitions at certain threshold for replicates
- **Ratio** – value of ratio parameter
- **Combination** – indication from which combination (C1-C3) values come from

7.6.18.4. Heatmap tab for Copy Number Variation

The **Heatmap** tab contains a heatmap that shows the number of copies per genome in each of the wells. If a well is not selected as a source for the analysis, the value is not displayed on the heatmap and its background color is gray. For each combination: C1, C2, and C3, a separate heatmap is presented. Each heatmap contains a header that presents the following information and can be expanded or collapsed:

- Combination indicator and number (consistent with pair selection made by user)
- Reference sample with sample ID and name (only for CNV with reference sample mode)
- Reference selection with hyperwells or replicates indicator and well IDs (only for CNV with reference sample mode)
- Reference target(s) displaying the names of the selected targets, reaction mix color icon and target indicator, and the channels associated with the above targets
- Target(s) of interest displaying the names of the selected targets, reaction mix color icon and target indicator, and the channels associated with the above targets

For example, for CNV analysis in reference sample mode, for combination 1 with reference sample “s1”, hyperwell 1 selected as reference selection, reference target “t1” in Green channel selected and target “t2” in Yellow channel selected as target of interest, the header displays like this:

C1

Combination 1

Details ▲

Reference sample

01

s1

Reference selection

Hyperwell 1 (A2-A3)

Reference target(s)

t1

Green


Target(s) of interest

t2

Yellow


To view detailed information about a well, point the cursor over the well tile. A tooltip with detailed information opens.

To view an additional toolbar that enables actions related to the diagram, such as downloading the plot, hold the pointer over the diagram. For more details about the toolbar, refer to Section 7.6.14.5 Diagram options.




There is an additional option that user can select:

- **Show mean values for replicates** – showing the mean copies/genome values for replicates. Mean values replace standard ones on well tiles and tooltips.



Note: If the selected analysis source contains replicates of the reference sample, results can be calculated only by using mean results for replicates. In this case, the “Show mean values for replicates” checkbox is marked and cannot be changed.



To copy a Heatmap to the Windows clipboard, click **Copy**. To save the Heatmap as an image file, click **Download**. To copy all Heatmaps displayed in the current tab, click **Copy all**.

To add heatmaps to a report, the following option can be used:

- **Add to report** – add heatmap for a single combination to the report
- **Add all to report** – add heatmaps for all combinations to report at once (when this option is selected, the Add to report checkbox will automatically be checked)

For more information on reports, see Section 7.7 Reports.

7.6.18.5. Point diagram tab for Copy Number Variation

The **Point diagram** tab shows the diagram that displays the number of copies per genome of the configured Copy Number Variation analysis and the confidence intervals related to every value. A point diagram has two axes. The x-axis shows the analyzed wells and samples, and the y-axis represents the number of copies per genome. A confidence interval displayed as an error bar is shown for each of the points on the diagram.

The diagram shows the values as points with the CI value as error bars for the selected samples. The point color reflects the color assigned to the corresponding target of interest. The samples are sorted by sample ID, but the reference sample is always shown. The well IDs and sample IDs are labeled on the x-axis. To view detailed information, hold the mouse pointer over its corresponding point. A tooltip with detailed information opens.

For each combination, a separate point diagram is presented. Each point diagram contains the header with information about analysis parameters – the same as in heatmap.


The y-axis scale can be modified using the buttons located below each graph. To view the values on a linear scale, click **lin**. To view the values on a logarithmic scale, click **log10**.

To view an additional toolbar that enables actions related to the diagram, such as downloading the plot, hold the pointer over the diagram. For more details about the toolbar, refer to Section 7.6.1 4.5 Diagram options.



For point diagram, there is one additional option that user can select:

- **Show mean values for replicates** – showing the mean concentration values for replicates. If the user checks the checkbox to select the mean representation for replicates, the points of individual replicates disappear and only one point is shown that represents the mean copies/genome of the replicates is presented. The corresponding well IDs of the replicates are shown on the x-axis. When there are no replicates within selected wells for mutant target the points do not change.



To copy a Point diagram to the Windows clipboard, click **Copy**. To save the Point diagram as an image file, click **Download**. To copy all Point diagrams displayed in the current tab, click **Copy all**.

To add point diagrams to a report, the following option can be used:

- **Add to report** – add point diagram for a single combination to the report
- **Add all to report** – add point diagrams for all combinations to the report at once (when this option is selected, the Add to report checkbox will automatically be checked)

For more information on reports, see Section 7.7 Reports.

7.6.18.6. Concentration diagram tab for Copy Number Variation


The **Concentration diagram** tab shows a diagram that displays the distribution of concentration values in the wells together with their confidence intervals. A concentration diagram has two axes. The x-axis shows the analyzed wells and samples, and the y-axis represents the concentration values.

The diagram consists of all possible combinations. Each sample on the diagram is represented by the number of bars according to targets that were selected as target of interests and reference targets. Samples on the diagram are sorted by the sample ID. Each bar represents reference target or target of interest; color of the bar reflects the corresponding targets. To view detailed information, hold the mouse pointer over its corresponding bar. A tooltip with detailed information opens.

For each combination, a separate point diagram is presented. Each point diagram contains the header with information about analysis parameters – the same as in heatmap and point diagram.


The y-axis scale can be modified using the buttons located below each graph. To view the values on a linear scale, click **lin**. To view the values on a logarithmic scale, click **log10**.

To view an additional toolbar that enables actions related to the diagram, such as downloading the plot, hold the pointer over the diagram. For more details about the toolbar, refer Section 7.6.14.5 Diagram options.



There are three additional options that can be selected:

- **Use sample dilution** – enables calculations related to dilution factor, which is described in Section 7.6.14.7 Dilution calculation option. Results in undiluted sample is additionally presented on tooltips; y-axis scale is adjusted to results.
- **Use conversion factor** – conversion of results into unit given by user, which is described in Section 7.6.14.9 Conversion factor. Results in converted unit replacing standard ones on tooltips; y-axis scale is adjusted to results.
- **Show mean values for replicates** – showing the mean concentration values for replicates. If the user checks the checkbox to select the mean representation for replicates, the bars of individual replicates disappear and common bars for replicates are shown instead. The corresponding well IDs of the replicates are shown on the x axis. When there are no replicates within selected wells for mutant target the bars do not change.



To copy a Concentration diagram to the Windows clipboard, click **Copy**. To save the Concentration diagram as an image file, click **Download**. To copy all Concentration diagrams displayed in the current tab, click **Copy all**.

To add concentration diagrams to a report, the following option can be used:

- **Add to report** – add concentration diagram for a single combination to the report
- **Add all to report** – add concentration diagram for all combinations to the report at once (when this option is selected, the Add to report checkbox will automatically be checked)

For more information on reports, see Section 7.7 Reports.

7.6.19. Gene expression

The Software Suite analyzes the gene expression of the samples. The analysis results are put into list views, heatmaps, point diagrams, and concentration diagrams.

Note: Saving gene expression tests is not yet provided.

Note: Amplitude multiplexing is not supported for Gene expression analysis. Targets in amplitude multiplexing mode (“Low” and “High”) are unavailable for selection. In addition, targets associated with channels invalidated by Analysis rules cannot be selected.

Select imaging step

 1

Imaging info ▾

Reference sample * ⓘ

01

S1

▾

Reference selection ⓘ

Select

▾

Reference target(s) * ⓘ

Select

▾

One or more targets are not available for selection because Amplitude Multiplexing is applied, they are excluded by Quality Control rules, or there is an issue with Imaging.

Target of interest * ⓘ

Select

▾

Show results

7.6.19.1. Setting up a gene expression analysis

1. Group hyperwells, if required, and select the wells for analysis.

Select source of gene expression (4 wells, 1 hyperwell)

	1	2	3	4	5	6	7	8	9	10	11	12
A												
B												
C												
D												
E												
F												
G												
H												

Select all Unselect all Group as hyperwells Ungroup hyperwells

Select imaging step
 1 Imaging info

Reference sample *

Select

Reference selection

Select

Reference target(s) *

Select

Target of interest *

Select

Show results

2. If the selected reference sample contains both hyperwells and replicates, select the reference type from the Reference selection list: **Hyperwell** or **Replicates**.

Absolute Quantification Mutation Detection Genome Editing Copy Number Variation **Gene Expression**

Select source of gene expression (4 wells, 1 hyperwell)

	1	2	3	4	5	6	7	8	9	10	11	12
A												
B												
C												
D												
E												
F												
G												
H												

Select all Unselect all Group as hyperwells Ungroup hyperwells

Select imaging step
 1 Imaging info

Reference sample *

01 s1

Reference selection

Select

Hyperwell 1 (A2-A3)

Replicates (A4)

Target of interest *

Select

Show results

3. Select the applicable reference sample from the Reference sample list.

Absolute Quantification

Mutation Detection

Genome Editing

Copy Number Variation

Gene Expression

Select source of gene expression (4 wells, 1 hyperwell)

	1	2	3	4	5	6	7	8	9	10	11	12
A												
B												
C												
D												
E												
F												
G												
H												

Select all

Unselect all

Group as hyperwells

Ungroup hyperwells

Select imaging step

1 Imaging info

Reference sample *

Select

01 s1

02 s2

Reference target(s) *

Select

Target of interest *

Select

Show results

4. Select one or more reference targets from the Reference target(s) list.

Absolute Quantification

Mutation Detection

Genome Editing

Copy Number Variation

Gene Expression

Select source of gene expression (4 wells, 1 hyperwell)

	1	2	3	4	5	6	7	8	9	10	11	12
A												
B												
C												
D												
E												
F												
G												
H												

Select all

Unselect all

Group as hyperwells

Ungroup hyperwells

Select imaging step

1 Imaging info

Reference sample *

01 s1

Reference selection

Hyperwell 1 (A2-A3)

Reference target(s) *

☒ t1 Green

☐ Select all

☒ RM1

☒ t1 Green

☐ t2 Yellow

Show results

5. Select the applicable target from the Target of interest list.

Absolute QuantificationMutation DetectionGenome EditingCopy Number VariationGene Expression

Select source of gene expression (4 wells, 1 hyperwell)

12

10987654321

A

B

C

D

E

F

G

H

NTC

NTC

NTC

NTC

NTC

NTC

NTC

NTC

NTC

NTC

NTC

NTC

Select allUnselect allGroup as hyperwellsUngroup hyperwells

Select imaging step

1Imaging info

Reference sample *

s1

Reference selection

Hyperwell 1 (A2-A3)

Reference target(s) *

t1Green

Target of interest *

Select

RM1

t2Yellow

Show results

6. To view the results of the analysis, click **Show results**.

Absolute QuantificationMutation DetectionGenome EditingCopy Number VariationGene Expression

Select source of gene expression (4 wells, 1 hyperwell)

12

10987654321

A

B

C

D

E

F

G

H

NTC

NTC

NTC

NTC

NTC

NTC

NTC

NTC

NTC

NTC

NTC

NTC

Select allUnselect allGroup as hyperwellsUngroup hyperwells

Select imaging step

1Imaging info

Reference sample *

s1

Reference selection

Hyperwell 1 (A2-A3)

Reference target(s) *

t1Green

Target of interest *

t2Yellow

Show results

7. The results are divided into several tabs. To view the contents of the tab, click the tab title.

328

QIAcuity User Manual | 07/2026

7.6.19.2. List tab for gene expression

The List tab contains a table with an overview of the analyzed wells. The following columns are available in the table:

1. **Well ID** – like A1, B2, when gradient was selected there is also temperature in the well (temperature range instead of single one, if hyperwells were selected).
2. **Sample/NTC/Control Name** – This column shows the sample, NTC, or control name with its corresponding icon that identifies the sample or indicates whether the entry is an NTC or control. Reference samples are marked with the word “Ref”.
3. **Reaction mix** – This column contains the icon and the name of the reaction mix.
4. **Target** – This column shows all target names with its corresponding target type. Targets that were selected as target of interest (TOI) or reference target (Ref) are marked accordingly.
5. **Conc. [copies/μL]** – This column shows the concentration assigned to each target.
6. **CI (95%)** – This column shows the value of the confidence interval at a 95% confidence level.
 - a. When checkbox “Show mean values for replicates” is checked, additional two columns are displayed:
 - **Mean conc. [copies/μL]** – This column shows the mean concentration assigned to each target or channel per well for replicates.
 - **CI (95%)** – This column shows the value of the confidence interval at a 95% confidence level for the mean concentration.

Note: Columns related to Concentration and Mean concentration can be additionally divided into several sub-columns depending if dilution factor and/or conversion factor (described in Sections 7.6.14.7 Dilution calculation option and 7.6.14.9 Conversion factor, accordingly) have been selected.

1. **Fold change** – This column shows the change in the level of gene expression in the sample.
2. **CI (95%)** – This column shows the value of the confidence interval for the fold change at a 95% confidence interval.
3. **Fold regulation** – This column shows the change in the level of gene expression compared to the reference sample.

ListHeatmapPoint diagramConcentration diagram												☐ Add to report	☐ Show mean values for replicates	Export to CSV...
Well	Sample/NTC/Control		Reaction Mix	Target			Concentration		Fold change	CI (95%)	Fold regulation			
	Name	Ref		Name	IC	Type	dPCR Reaction	CI (95%)						
A5	s1	Ref	RM2 Ref channel: SM-Ref	T2	-	TOI	25.77	23.8%	1.0000	0%	1.0000			
				T1	-	REF	32.24	21.3%	n.a.	-	n.a.			
B5	s2	-	RM2 Ref channel: SM-Ref	T2	-	TOI	41.24	19.1%	0.8133	42.1%	-1.2296			
				T1	-	REF	63.45	15.4%	n.a.	-	n.a.			

Replicates are treated differently for multiplex and simplex test setup:

1. **Multiplex test** (configured target of interest and reference targets are part of the same reaction mix):
 - a. On the right side above the table, there is a checkbox that allows the user to show mean values for replicates in addition. By default, the button is unchecked and results are displayed without mean values. When the button is checked, the list view still shows independent rows for each selected well but replicates are grouped together. Replicates from the same group are next to each other in the list view. The list view is extended by five columns

indicating the following mean values:

- Mean conc. [copies/ μ L] – mean concentration value
- CI (95%) – CI of mean concentration as percentage
- Mean fold change
- CI (95%) – CI of mean fold change as percentage
- Mean fold regulation

2. Simplex test (configured target of interest and reference targets are part of different reaction mixes):

a. For tests having the configured targets in different wells/reaction mixes, the mean result is calculated and shown for replicates in the selection. The list view is extended by four columns indicating the following mean values:

- Mean conc. [copies/ μ L] – mean concentration value
- CI (95%) – CI of mean concentration as percentage
- Mean fold change
- CI (95%) – CI of mean fold change as percentage
- Mean fold regulation

Note: If the selected analysis source contains replicates of the reference sample, the results can be calculated only by using mean results for replicates. In this case, the “Show mean values for replicates” checkbox is marked and cannot be changed. In this case, there is a warning message above the table, and when the user hovers on the checkbox, a tooltip appears to inform the user that selected analysis source contains replicates of the reference sample and result is calculated only by using mean results for replicates.

As the selected analysis source contains replicates of the reference sample, your results can be calculated only by using mean results for replicates. If you want to see results for the particular well containing reference sample, deselect all the other replicates.

Warnings (2)

As the reference sample is split into several wells and replicates are used, your results can be calculated only by using mean results for replicates.

ListHeatmapPoint diagramConcentration diagram

☐ Add to report

☒ Show mean values for replicates

[Export to CSV](#)

Well	Sample/NTC/Control		Reaction Mix	Target			Concentration		Mean concentration		Fold change	CI (95%)	Mean fold change	CI (95%)	Fold regulation	Mean fold regulation
	Name	Ref		Name	IC	Type	dPCR Reaction	CI (95%)	dPCR Reaction	CI (95%)						
01 s1		Ref	RM1 Ref. channel: Std-Ref	t1	-	REF	-	-	26.64	102.3%	n.a.	-	n.a.	-	n.a.	n.a.
			RM2 Ref. channel: Std-Ref	T1	-	TOI	-	-	32.24	21.3%	n.a.	-	1.0000	0%	1.0000	1.0000
02 s2		-	RM1 Ref. channel: Std-Ref	t1	-	REF	-	-	61.13	71.1%	n.a.	-	n.a.	-	n.a.	n.a.
			RM2 Ref. channel: Std-Ref	T1	-	TOI	-	-	63.45	15.4%	n.a.	0.8575	100.0%	-1.1661	-1.1661	

To export the results to an CSV file, click **Export to CSV** and select **Current results**.

7.6.19.3. Heatmap for gene expression


The **Heatmap** tab contains a heatmap view that shows the fold change in each of the wells. If a well is not selected as a source for the analysis, the value is not displayed on the heatmap and its background color is gray. In case a fold change is not applicable for a well, n.a. is shown.

To view an additional toolbar that enables actions related to the diagram, such as downloading the plot, hold the pointer over the diagram. For more details about the toolbar, refer to Section 7.6.14.5 Diagram options.

To view detailed information about a particular well, point the cursor over the well. A tooltip with detailed information opens.

To view the mean values for replicates in multiplex tests, click **Show mean values for replicates**. For simplex tests, the mean values view is always shown for replicates and cannot be disabled.

Note: If the selected analysis source contains replicates of the reference sample, the results can be calculated only by using mean results for replicates. In this case, the “Show mean values for replicates” checkbox is marked and cannot be changed. When the user hovers on the checkbox, a tooltip appears to inform the user that selected analysis source contains replicates of the reference sample and result is calculated only by using mean results for replicates.



To copy a Heatmap to the Windows clipboard, click **Copy**. To save the Heatmap as an image file, click **Download**.

To add the heatmap to the report, click **Add to report**. For more information on reports, see Section 7.7 Reports.

7.6.19.4. Point diagram for gene expression

The **Point diagram** tab shows a point diagram view that displays the fold change values of configured gene expression test and the confidence intervals related to every value. A point diagram has two axes. The x-axis shows the analyzed wells and samples, and the y-axis represents the fold change. A confidence interval displayed as an error bar is shown for each of the points on the diagram.

To view an additional toolbar that enables actions related to the diagram, such as downloading the plot, hold the pointer over the diagram. For more details about the toolbar, refer to Section 7.6.14.5 Diagram options.

The y-axis scale can be modified using the buttons located below each graph. The buttons are visible when you hold the pointer over a graph. To view the values on a linear scale, click **lin**. To view the values on a logarithmic scale, click **log10**.


The diagram shows the values as points with the CI as interval for the selected samples. In case the targets are in the same reaction mix, each sample is represented by 1 point. The point color reflects the color assigned to the corresponding target of interest.

The samples are sorted by sample ID but the reference sample of a test is always shown first. The well IDs and sample IDs are labeled on the x-axis.

In case targets are in different reaction mixes, each combination of target of interest and reference targets in one sample throughout the selected wells is shown in the diagram with a point for the result. To view detailed information, hold the mouse pointer over its corresponding point. A tooltip with detailed information opens.

To view the mean values for replicates, click **Show mean values for replicates**. If the user clicks into the checkbox to select the mean representation for replicates, the points of individual replicates disappear and only one point is shown at the sample label that represents the mean fold change value of the replicates. When there are no replicates within selected wells the points do not change. The corresponding well IDs of the replicates are shown on the x-axis. This is also applied in the same way by default to the view where targets are in different reaction mixes. In this case, individual replicate results are not available. Mean values are calculated and shown over all replicates that are included in the well selection only. If there are further replicates of the same sample that are not included in well selection, they are not considered in the calculated mean value and show their individual results values.

Note: If the selected analysis source contains replicates of the reference sample, the results can be calculated only by using mean results for replicates. In this case, the “Show mean values for replicates” checkbox is marked and cannot be changed. In this case, there is a warning message above the diagram title and, when the user hovers on the checkbox, a tooltip appears to inform the user that selected analysis source contains replicates of the reference sample and result is calculated only by using mean results for replicates.



To copy a Point diagram to the Windows clipboard, click **Copy**. To save the Point diagram as an image file, click **Download**.

To add any of the point diagrams to the report, click **Add to report** next to the corresponding diagram. For more information on reports, see Section 7.7 Reports.

7.6.19.5. Concentration diagram for gene expression

The **Concentration diagram** tab shows the diagram that displays the concentration values of the configured gene expression test and the confidence intervals related to every value. A concentration diagram has two axes.

1. X-axis represents labels of wells and samples that it belongs to.
2. Y-axis represents the concentration values for selected targets or channels for each well. A confidence interval displayed as an error bar is shown for each of the bars on the diagram.

The y-axis scale can be modified using the buttons located below each graph. The buttons are visible when you hold the pointer over a graph. To view the values on a linear scale, click **lin**. To view the values on a logarithmic scale, click **log10**.

To view an additional toolbar that enables actions related to the diagram, such as downloading the plot, hold the pointer over the diagram. For more details about the toolbar, refer to Section 7.6.14.5 Diagram options.

The Concentration diagram is a bar plot which presents two values:

1. Concentration value as bar
2. CI value as bar

The diagram consists of all possible combinations. Each sample on the diagram is represented by the number of bars according to targets that was selected as a target of interest and reference targets. Samples on the diagram are sorted by the sample ID. Target bars in the sample show one concentration bar for target of interest at first position and concentration bars for reference targets sorted by their well ID. The bar color reflects the color assigned to the corresponding targets. The sample ID is shown center-aligned below the bars.

The bar size is fixed if:


1. The reference targets and target of interests are situated on one well; there is one well label for all that belongs to the same well.
2. The reference targets and target of interests are situated on two wells or more wells; there is one well label per target that are within this well.

When hovering over a bar in the diagram, a tooltip appears presenting details about the actual values of concentration and CI and results of tests.

To view the mean values for replicates on the diagram, click **Show mean values for replicates**. When this checkbox is checked, the concentration diagram shows bars that represents mean concentration value for replicates within the well selection. The label below the bar shows well positions that are included in the replicates value of mean concentration. When hovering on the bar, there is a tooltip with details about wells, samples, and targets that are part of replicate group and the results are shown as mean result values with a corresponding mean label. This is also applied in the same way by default to the view where targets are in different reaction mixes. In this case individual replicate results are not available. When selected well has no replicates within all selected wells, individual result values are shown.

Note: If the selected analysis source contains replicates of the reference sample, the results can be calculated only by using mean results for replicates. In this case, the "Show mean values for replicates" checkbox is marked and cannot be changed. In this case, there is a warning message above the diagram title, and when the user hovers on the checkbox, a tooltip appears to inform the user that selected analysis source contains replicates of the reference sample and result is calculated only by using mean results for replicates.

- There are two additional options that user can select. First option is “Use sample dilution” – as described in Section 7.6.14.7 Dilution calculation option; it enables calculations related to dilution factor. Results in undiluted sample is additionally presented on well tiles; y-axis scale is adjusted to results. Second option is “Use conversion factor” – as described in Section 7.6.14.9 Conversion factor; it enables conversion of results into unit given by user. Results in converted unit replace the standard ones on well tiles, y-axis scale is adjusted to results.



To copy a Concentration diagram to the Windows clipboard, click **Copy**. To save the Concentration diagram as an image file, click **Download**.

To add the concentration diagram to the report, click **Add to report**. For more information on reports, see Section 7.7 Reports.


7.7. Reports

In the QIAcuity Software Suite, user can create reports about your analysis results of a plate. All created reports remain accessible in the Software Suite and can be downloaded. Only unsigned reports can be deleted.

7.7.1. Manual creation of a new plate report from analysis results


To create a new report from your analysis results, follow these steps:

1. Enter the Analysis environment of a finished plate. For more information about analyzing a plate, see Section 7.6 Analysis.
2. To include a diagram or table of the analysis in the report, check the **Add to report** box of the corresponding diagram you want to include. Checking this box saves and pre-selects the corresponding diagram in the report.



Example of a diagram to be included in a report.

Note: In case of custom analysis of 1D Scatterplot and 2D Scatterplot, user can add/remove whole overview by clicking **Add all to report**.



Example of a 2D Scatterplot Custom analysis overview to be included in a report.

Note: The total number of diagrams selected for inclusion in the report is displayed in the footer. There is no limit to the number of diagrams or tables that can be included in a report for a plate; however, increasing the number of included items may increase report generation time. Clicking **Back to plate configurator** or **Create report** navigates away from the current view. Any diagrams selected for inclusion in the report for the current plate are not retained.

- To remove the pre-selection of diagram, clear the selected **Add to report** or **Add all to report** checkbox.
- Click **Create report**.

5. In the Create report dialog box, select which information to include in the report. By default, all options are selected.

Create Report view for a plate.

Use this table as a guide in selecting which information to include in the report.

Table 15. Report elements

Element	Description
Report name	Every Report needs a specific name, without special characters ~ ‘ “ ! @ ^ () = [] { } : ; , < > \ .
Run details	Author, Start and end time, Run steps, Run status, Software & Instrument version
Plate general data	Plate name, type, description, labels, plate owners, barcode, dPCR parameters
Plate layout	List of all the elements added to each well
Reaction mixes list	List of all your defined reaction mixes with details about each target
Warnings	List of all warnings
Comments	More information/details/descriptions about the report

Important: Clicking **Back to analysis** opens the plate analysis view but the preselected diagrams will be lost!

6. To finish creating the report, click **Generate report PDF**.
7. Report is created and automatically downloaded in the download folder of the PC as a PDF file. In the meantime, user can normally operate the application.

8. The report is stored in the Software Suite and accessible via the **Report** tab of the plate.

Files

Templates

Data Space

Archive

Tools

Configuration

Admin

REPORTS

20220322_JA_ProbeCNV_Marketing_Exp15_P3

Manual Reports

System Reports

Name	Creation date and time	Created by	Role	Your signature
Plate_8_plex_automatic_report Report ID: 4026110-4656-9426-735d-4e56-1a0b0e41a0b0	06/03/2026, 11:44:12 UTC+01:00	admin admin (admin)	Administrator	unsigned Add signature

← Back to plate configurator

New analysis & report

Note: Starting with QIAcuity Software Suite version 3.5, all analysis warnings use a fixed enumeration scheme. Each warning type is assigned a unique warning number, which is referenced in the List view.

3.5.120.0.0.524.LV_3plex_2ImagingSteps_missing_images_on_2nd_imaging_automatic_report

3.5.120.0.0.524.LV_3plex_2ImagingSteps_missing_images_on_2nd_imaging_automatic_report

Warnings

Skipped Analysis Rules

Analysis Rules

Warning number: 11

In analysis: Absolute Quantification

In column(s): Well

Some analysis rules were skipped for this Reaction mix.

Reaction Mix

RM2

RM1

Minimum Valid Partitions

Analysis Rules

Warning number: 39

In analysis: Absolute Quantification

In column(s): Well

Based on QC rules defined in Analysis Rules:

Min. valid partitions level has not been reached for Sample(s) or Control(s).

Legend:

Failed

Warning

*This affects the Overall Quality Control Status in Absolute Quantification.

Absolute Quantification (Imaging step 2)

Well	Sample / NTC / Control	Reaction Mix	Overall Quality Control Status	Channel		Concentration ¹⁾		Partitions		Threshold
				Channel	IC	Control	dPCR reaction	Valid	Positive	
A1	-	RM1 Ref. channel: 3 H&A Ref	Passed	Green	-	-	0.000	-	8249	35.96

1) Presented results do not include the Volume Precision Factor

Sample to Insight

Generated by admin admin (admin) on 06/03/2026, 11:44:12 UTC+01:00 via QIAcuity Software Suite 3.5.0.0 | Report ID: 4026110-4656-9426-735d-4e56-1a0b0e41a0b0

Sample to Insight

Generated by admin admin (admin) on 06/03/2026, 11:44:12 UTC+01:00 via QIAcuity Software Suite 3.5.0.0 | Report ID: 4026110-4656-9426-735d-4e56-1a0b0e41a0b0

7.7.2. Automatic creation of report – Report template


Starting with QIAcuity Software Suite version 3.5, plate reports can be generated automatically using the Report template feature. The primary purpose of Report template is to configure report settings in advance, before analysis, in the Plate Configurator.

After a run has been processed successfully, reports are generated automatically and become available in the QIAcuity Software Suite download location and in the Report environment for the plate. For more information, refer to Section 7.7.3 Managing reports of a plate in the report environment.

Important: Report templates are available only for Absolute Quantification analysis.

To use Report template, follow the instructions below:

1. Select a plate in the Plate Overview and navigate to the **Report template** tab in the Plate Configurator.



2. Enable the **Report Template** toggle. The configuration form expands and additional options become available.

☒ Report template


Enable the report template and configure the report settings below to automatically generate reports after a plate run.

3. Enter a report name. This field is required and supports a maximum of 125 characters. The following special characters are not permitted:


~ ‘ “ ! ? @ ^ * () = [] { } : ; , < > | / \

Report name * Characters left: 104

- In the Reaction Mixes section, review which reaction mixes will be included in the report. Expand **Included in report template** to display the included reaction mixes.



Important: Only reaction mixes assigned to wells in the plate layout are included in the Report Template. Reaction mixes that are defined for the plate but not assigned to any wells are excluded and displayed in the **Not included in report template** section.



- In the General Report settings section, select the information to include in the report. These options correspond to those available during manual report creation. The following items can be included:
 - Run detail
 - General data
 - Reaction mixes list
 - Plate layout
 - Warnings
 - Comments

General Report settings	
☒ Run detail	• Author. • Start and end time. • Run steps. • Run status. • Software & Instrument version.
☒ General data	• Plate name. • Type. • Description. • Labels. • Plate owners. • Barcode.
☒ Reaction mixes list	List of all your defined reaction mixes with details about each target.
☒ Plate layout	List of all the elements added to each well.
☒ Warnings	List of warnings
☒ Comments	More information / details / description about the report. my comment

6. The Analysis section contains the Absolute Quantification subsection, which is used to configure General settings and Analysis per Reaction mix. The **Apply settings to all Reaction Mixes** option can be used to apply the same settings to all reaction mixes.

The Download CSV subsection allows CSV files to be generated automatically. Available file types are:

- Current results
- RFU values
- RFU values (compact)

Analysis

^ Absolute Quantification

▼ RM1

▼ RM2

☐ Download CSV

☒ Current result

☐ RFU values

☒ RFU values (compact)

General settings allows to configure the following:

- a. **Analyze per** – Select **Channel** or **Target** to define the analysis type. All available channels and targets are included in the report. By default, Analyze per Channel is selected.

General settings

Analyze per

☒ Channel

☐ Target

- b. **Wells results presentation** – Select **Horizontal** or **Vertical** to define how well results are displayed in the report. By default, **Horizontal** is selected.

Wells results presentation

☒ Horizontal →

☐ Vertical ↓

- c. **Group** – Select **Hyperwells** to group replicates as hyperwells, similar to the **Group as hyperwells** option in the plate layout. Select **Replicates** to display mean values for replicate groups, similar to the **Show mean values for replicates** option in the Analysis view. By default, neither option is selected.

- d. **Factors** – Select **Dilution** to include parameters based on the dilution factor. For more information, refer to Section 7.6.14.7 Dilution calculation option. Select **Conversion** to include parameters based on the conversion factor. For more information, refer to Section 7.6.14.9 Conversion factor. By default, neither option is selected.

- e. **Apply settings to all Reaction Mixes** – Applies the configured settings to all reaction mixes included in the Report template.

7. The Analysis section allows configuration of settings for individual analysis tabs. These settings correspond to those available during regular analysis.

- a. **List** – Enables inclusion of the List view in the report. No additional configuration options are available. This option is enabled by default.

- b. **Heatmap** – Enables inclusion of Heatmaps in the report. Select **Concentration** to include the Concentration heatmap and **Partitions** to include the Partitions heatmap. Both options can be selected simultaneously. When the **Heatmap** option is enabled, at least one Heatmap type must be selected. By default, this option is disabled.

- c. **Histogram** – Enables inclusion of Histograms in the report. Select the **Y-axis scale** using the corresponding control. Either a linear or logarithmic scale can be applied. Optionally, select **Show reference channel** to include a histogram for the reference channel and **Unify max Y-axis scale** to standardize the maximum Y-axis value across all Histograms. Selection of a Y-axis scale is required when this option is enabled.

Y-scale

☒ lin ☐ log10

☐ Show reference channel

☐ Unify max Y-axis scale

- d. **1D Scatterplot** – Enables inclusion of 1D Scatterplots in the report.
- All selected wells** or **Individual wells** – At least one option must be selected when 1D Scatterplots are enabled. **All selected wells** option groups wells into combined scatterplots per target or channel, whereas **Individual wells** generates separate plots for each well and each target or channel.
 - Show reference channel** – Optionally includes a 1D Scatterplot for the reference channel.
 - Unify max Y-axis scale** – Optionally standardizes the maximum Y-axis value across all 1D Scatterplots.

Plots presentation *

☒ All selected wells ☐ Individual wells

☐ Show reference channel

☐ Unify max Y-axis scale

- e. **2D Scatterplot** – Enables inclusion of 2D Scatterplots in the report. Assign channels to the X-axis and Y-axis and click **Add pair**. After a channel pair has been created, select the 2D Scatterplots to generate by enabling the corresponding options:
- Main 2D Scatterplots
 - Custom Analysis plots (All wells)
 - Custom Analysis plots (Samples)

Multiple options can be selected simultaneously. To remove a channel pair, click the **delete** icon. Optionally, select **X-axis** and/or **Y-axis** to standardize the maximum axis value across plots.

2D Scatterplot

Concentration diagram

Download multiple occupancy file

Select pair(s) *

X-axis *

Select channel

Green

Yellow

Orange

Red

Crimson

Far red

Green / Yellow

Y-axis *

Select channel

Add pair

Select pair(s)

X-axis

Select channel

Y-axis

Select channel

Add pair

Selected pair(s)

X-axis

Y-axis

Main 2D Scatterplot

Custom analysis ⓘ

Green

Yellow

All wells

Samples

Unify max scale for

X-axis

Y-axis

f. **Concentration diagram** – Enables inclusion of Concentration diagrams in the report. Select the Y-axis scale using the corresponding control. Either a linear or logarithmic scale can be applied. Optionally, select **Unify max Y-axis scale** to standardize the maximum Y-axis value across all diagrams.

Concentration diagram

Y-scale

lin

log10

Unify max Y-axis scale

344

QIAcuity User Manual | 07/2026

- g. **Download multiple occupancy file** – Enables generation of a multiple occupancy CSV file that is downloaded together with the PDF report. Select a minimum of two and a maximum of eight channels. After selecting the channels, specify the groups to include, as described in Section 7.6.15.7.2 Multiple occupancy. All configuration steps are required when this option is enabled.

- h. **Apply settings to all Reaction Mixes** – Applies the configured settings to all reaction mixes in the Report template.

8. The Download CSV section allows selection of CSV file types to be generated and downloaded together with the PDF report. When this option is enabled, at least one of the following file types must be selected:
- Current results
 - RFU values
 - RFU values (compact)

Multiple file types can be selected simultaneously. These files are generated in the same manner as during regular analysis. By default, this option is disabled. After the run has been processed successfully, the selected CSV files are generated automatically and become available in the QIAcuity Software Suite download location.

9. The Report file(s) section defines how report content is distributed across report files. The configuration consists of two linked sections:

Report file(s)
Select how the report content should be combined in the report file(s). Choose at least one option from the Imaging and Reaction Mix(es) and/or Samples sections. Both sections are linked.

Report file(s) ⓘ

1. Imaging

Imaging ⓘ

☒ All in one
☐ Separate report for each Imaging

2. Reaction Mix(es) and/or Samples

Reaction mixes ⓘ

☒ All in one
☐ Separate report for each Reaction Mix

Samples ⓘ

☐ Separate report for each Sample
☐ Separate report for each Sample label

- a. **Imaging** – Defines report behavior based on the Imaging settings configured for the plate. For more information, refer to Section 7.4.5.4 Imaging tab. At least one option must be selected. The selected option is combined with the settings configured in the Reaction Mix(es) and/or Samples section to determine the final report file structure.

Imaging
Select at least one report option to apply.

Note: The report file is always a combination of selected options from the Imaging and Reaction Mix(es) and/or Samples sections.

All in one
Results from all imaging steps will be combined in Reaction Mix(es) and/or Samples.

1. Separate report for each Imaging
Results from each imaging step will be saved in a separate report file.

Imaging ⓘ

☒ All in one
☐ Separate report for each Imaging

- i. **All in one** – Combines results from all configured imaging steps into a single report file. This option is selected by default.
- ii. **Separate report for each Imaging** – Generates a separate report file for each configured imaging step.
- b. **Reaction Mix(es) and/or Samples** – Defines how results are grouped by reaction mix and sample. At least one option must be selected. The selected configuration is combined with the Imaging settings to determine the final report file structure. For more information, refer to Section 7.4.6 Reaction mixes tab and 7.4.10 Defining samples, controls, and non-template controls.

Report file(s) ⓘ

1. Imaging

Imaging ⓘ

☒ All in one
☐ Separate report for each Imaging

2. Reaction Mix(es) and/or Samples

Reaction mixes ⓘ

☒ All in one
☐ Separate report for each Reaction Mix

Samples ⓘ

☐ Separate report for each Sample
☐ Separate report for each Sample label

i. Reaction mixes

All in one – Combines results from all reaction mixes included in the Report template into a single report file. This option is selected by default.

Separate report for each Reaction Mix – Generates a separate report file for each reaction mix.

The screenshot shows the 'Report file(s)' configuration window. It has two main sections: '1. Imaging' and '2. Reaction Mix(es) and/or Samples'. In the '1. Imaging' section, the 'All in one' option is selected. In the '2. Reaction Mix(es) and/or Samples' section, the 'All in one' option is also selected. A tooltip is visible over the 'All in one' option in the '2. Reaction Mix(es) and/or Samples' section, explaining that results from all Reaction Mix(es) will be combined into one report file. Another tooltip is visible over the 'Separate report for each Reaction Mix(es)' option, explaining that results for each Reaction Mix will be saved in a separate report file.

ii. Samples

Separate report for each Sample – Generates a separate report file for each Sample, Control and NTC.


Separate report for each Sample label – Generates a separate report file for each Sample label.

The screenshot shows the 'Report file(s)' configuration window. It has two main sections: '1. Imaging' and '2. Reaction Mix(es) and/or Samples'. In the '1. Imaging' section, the 'All in one' option is selected. In the '2. Reaction Mix(es) and/or Samples' section, the 'All in one' option is also selected. A tooltip is visible over the 'All in one' option in the '2. Reaction Mix(es) and/or Samples' section, explaining that results from all Reaction Mix(es) will be combined into one report file. Another tooltip is visible over the 'Separate report for each Sample label' option, explaining that results from each Sample label will be saved in a separate report file. A 'New Sample' dialog box is also visible, showing fields for 'Sample name' and 'Labels'.

10. After completing the configuration, click **Save changes**.

When a Report template is configured for a plate, reports are generated automatically after image transfer from the instrument has been completed for all required imaging steps and wells. If Analysis Rules are defined for the plate, they are applied during report generation.

Alternatively, reports can be generated on demand from the Analysis view using the Report template settings. To generate a report manually, navigate to the Analysis section, click **Generate Report from Template** at the bottom of the screen, and confirm the action by clicking **Generate Report** in the dialog box.



7.7.2.1. Skipping items in reports

Important: Report generation continues even if some items are skipped.

If an item configured in the Report template cannot be included in the report, a Skipped items section is added to the report. This section is included only when at least one item is skipped during report generation.

Items may be skipped when specific wells or channels are unavailable or excluded due to defined conditions. The Skipped items section applies to reports generated from a Report Template, regardless of whether the report is generated automatically or on demand.

Skipped items can originate from the following Absolute Quantification report sections:

- List
- 1D Scatterplot
- 2D Scatterplot
- Histogram
- Heatmap
- Concentration Diagram

Items may be skipped for the following reasons:

1. **Amplitude Multiplexing** – The following configuration combinations are not supported:
 - a. Analysis per Target is selected in the Report template and the threshold mode for target results is set to AM, or the target is defined as an AM target.

- b. Analysis per Channel is selected in the Report template and 2D Scatterplot is enabled, while the threshold mode for a channel included in the selected channel pair is set to AM.
2. **Missing images** – Images are not available for one or more well channels required for the selected imaging step.
3. **Reference channel discrepancy** – Std-Ref is used as the reference channel for a well, while Far Red is configured as a signal channel in a reaction mix.


AM_plate_report

Warnings

Amplitude Multiplexing Discrepancy

In analysis: All types
In column/s: n.a.
One or more wells have channel-based Amplitude Multiplexing applied.

Imaging step	Reaction mix	Target	Channel	Wells
1	RM	t1	Green	A1, A2, A3, A4, A5, A6, A7, A8, A9, A10, A11, A12

Skipped Data in this Report

In analysis: Absolute Quantification
Some items could not be included in this report due to configuration or data issues.

Analysis	Imaging Step	Channel	Wells	Reason
2DS	1	Green	A1, A2, A3, A4, A5, A6, A7, A8, A9, A10, A11, A12	Amplitude Multiplexing Wells configured with Amplitude Multiplexing thresholds have been excluded from analysis, because this mode doesn't support target-based analysis.

CI (95%) Value Notice


Warning number: 9)
In analysis: Copy Number Variation, Gene Expression
In column/s: Copies/genome, Mean copies/genome, Fold change, Mean fold change
A high relative CI (95%) value was estimated, which is subject to a high degree of uncertainty. Potential reasons could be a significant variation in replicates (if applied), too high concentrations of the target gene compared to the reference gene(s) or a too small ratio in the reference sample.

— Sample to Insight —
38/39
Generated by admin admin (admin) on 13/05/2026, 15:04:17 UTC+02:00
via QIAcuity Software Suite 3.5.0.0 | Report ID: 4835cda4-86c1-46ec-a385-a9ea6c57e4c7

Exemplary page from report with skipped data warning.

7.7.3. Managing reports of a plate in the report environment

The report environment of a plate provides an overview of all created reports for this plate. User can use this environment to manage the created reports. To enter the report environment of a plate, go to the plate tile in the plates overview. Click the three-dotted icon, then click **Reports**.



Note: Alternatively, click the plate name in the tile to enter the plate configurator view, then click **Reports** in the context menu.

The Reports environment is divided into two tabs:

- **Manual Reports** – Contains reports generated manually, including reports created using the **Generate Report from Template** option.

The screenshot shows the 'Manual Reports' tab selected. The header includes the QIAGEN logo, navigation icons for Plates, Templates, Disk Space, and Archive, and user settings for Tools, Configuration, and admin. The main content area displays a table of reports. The table has columns for Name, Creation date and time, Created by, Role, and Your signature. A single report is listed with the name '20220322_JA_ProbeCNV_Marketing_Exp15_P3_report' and a report ID. At the bottom, there are links to 'Back to plate configurator' and 'New analysis & report'.

Name	Creation date and time	Created by	Role	Your signature
20220322_JA_ProbeCNV_Marketing_Exp15_P3_report Report ID: 0ab456be-ee18-4394-a939-8011621a2f7f	13/05/2026, 13:22:22 UTC+02:00	admin admin (admin)	Administrator	unsigned Add signature

- **System Reports** – Contains reports generated automatically after image transfer from the instrument has been completed.

The screenshot shows the 'System Reports' tab selected. The header and navigation elements are identical to the previous screenshot. The table of reports shows a single entry with the name '20220322_JA_ProbeCNV_Marketing_Exp15_P3_report' and a report ID. The 'Created by' field is empty, and the 'Role' is 'unsigned'. At the bottom, there are links to 'Back to plate configurator' and 'New analysis & report'.

Name	Creation date and time	Created by	Role	Your signature
20220322_JA_ProbeCNV_Marketing_Exp15_P3_report Report ID: 1458d735-4c3a-43a6-8225-2d0c0808a3b	13/05/2026, 13:43:14 UTC+02:00		unsigned	Add signature

Use the following table as a guide in managing your created reports for a specific plate.

Table 16. Action button in report environment

Action	Description
 Download as PDF	Downloads the report in PDF format
 Delete report	Delete the report
New analysis & report	Back to Analysis view of this plate
 Back to plate configurator	Back to plates configurator
 Add signature	Add signature to the report
 Check signers	List signers: user name, role, date, and reason

7.7.4. Sign report

To support GMP/GLP requirements, the QIAcuity system provides an option to electronically sign existing reports. To do so, the user has to follow the steps given below.

1. Go to report list view.



PlatesTemplatesData SpacesArchive

ToolsConfigurationAdmin

REPORTS
20220322_JA_ProbeCNV_Marketing_Exp15_P3

Manual Reports

System Reports

Name	Creation date and time	Created by	Role	Your signature	
 20220322_JA_ProbeCNV_Marketing_Exp15_P3 Report ID: x16f1n7b33ba-4dc7-adbb-w4473ad0737	1405/2026, 15:15:07 UTC+02:00	admin-admin (admin)	Administrator	unsigned	 Add signature ...
 20220322_JA_ProbeCNV_Marketing_Exp15_P3_report Report ID: 33ba4566-ea18-4284-ad39-8513523a237	1305/2026, 13:22:22 UTC+02:00	admin-admin (admin)	Administrator	signed	 Check signers ...

 Back to plate configurator

New analysis & report

2. Select the **Add signature** button.

 Add signature

3. A pop-up window will appear with confirmation request. User needs to download and read report, then:
 - a. Add user login
 - b. Add password
 - c. Add reason for signing and finally click **Sign the report** button.

Sign the report

After signing the report removing the signature and signed report will not be possible.
The signature will contain your name, surname, role, date and reason for signing. All this information will be added to the report (PDF).

1 Download and read report *

Download report

2 Add login *

Provide your login used for QIAcuity access

3 Add password *

Provide your password used for QIAcuity access

4 Add reason for signing *

21 CFR part 11 / Internal approval / etc.

Characters left: 30

Cancel

Sign the report

If wrong password will be typed user will be presented with following information:

Sign the report

After signing the report removing the signature and signed report will not be possible.
The signature will contain your name, surname, role, date and reason for signing. All this information will be added to the report (PDF).

1 Download and read report *

Download report

2 Add login *

admin

Provide your login used for QIAcuity access

3 Add password *

admin1

The password is incorrect.

Incorrect password

You've got 2 more attempts before you are logged out.

4 Add reason for signing *

21 CFR part 11

Characters left: 16

Cancel

Sign the report

After three incorrect attempts in adding password, user will be automatically logged out and a corresponding event is tracked in the audit trail.

1. When the report is signed, an appropriate message will be presented on the report list and the **Add signature** button will be disabled.

2. It is enabled in the system if more than one user can sign the report, but the user cannot overwrite his signature for an already signed report.

Manual Reports				
System Reports				
Name	Creation date and time	Created by	Role	Your signature
20220322_JA_ProbeCNV_Marketing_Exp15_P3 Report ID: e7a67e7b-934a-4ac7-88ba-93e473ea2737	14/05/2026, 15:15:07 UTC+02:00	admin admin (admin)	Administrator	unsigned Add signature
20220322_JA_ProbeCNV_Marketing_Exp15_P3_report Report ID: 0ab45e66-ee18-4394-a939-8011621a2397	13/05/2026, 13:22:22 UTC+02:00	admin admin (admin)	Administrator	signed Check signers

When the report is signed, a user has an option to check who has performed such action. To do so, follow the instructions below:

1. Go to report list view.
2. Click the **Check signers** button.
3. A pop-up window will appear with information about signers.
 - a. Name and surname (Login in brackets)
 - b. Role
 - c. Date and time of signature (taking into account UTC timezones)
 - d. Reason (of signing)

Name	Role	Date and time	Reason
1. admin admin (admin)	Administrator	13/05/2026, 13:41:49 UTC+02:00	21 CFR part 11

Moreover, during PDF export of the signed report, an additional page with information about signers (same as the list above) is added at the end of the document: name and surname (login name), role, and date of signature.



Signers

Name	Role	Date and time	Reason
1. admin admin (admin)	Administrator	13/05/2026, 13:41:49 UTC+02:00	21 CFR part 11

Sample To Insight

Generated by admin admin (admin) on 13.05.2026 13:22:22 UTC+02:00
via OIAcuity Software Suite 3.5.0.0 | Report ID: 0ab45eb6-ee18-4394-a939-8011621a23f7

7.7.5. Run details in report

On the first page of report in section Run details, all information about particular run steps are listed in table:

					KIKUCHI_006
Run details					
	Run step	Software Suite version	Instrument ID	CSW version	Date and time
1	Run started	3.1.1.0	qiacuity-03470	3.1.3.6	21/04/2026, 11:03:29 UTC+02:00
2	Priming started	3.1.1.0	qiacuity-03470	3.1.3.6	21/04/2026, 11:04:53 UTC+02:00
3	Priming completed	3.1.1.0	qiacuity-03470	3.1.3.6	21/04/2026, 11:22:58 UTC+02:00
4	Cycling started	3.1.1.0	qiacuity-03470	3.1.3.6	21/04/2026, 11:24:15 UTC+02:00
5	Cycling completed	3.1.1.0	qiacuity-03470	3.1.3.6	21/04/2026, 12:29:22 UTC+02:00
6	Imaging started	3.1.1.0	qiacuity-03470	3.1.3.6	21/04/2026, 12:35:20 UTC+02:00
7	Imaging completed	3.1.1.0	qiacuity-03470	3.1.3.6	21/04/2026, 12:59:27 UTC+02:00
8	Run completed	3.1.1.0	qiacuity-03470	3.1.3.6	21/04/2026, 12:59:45 UTC+02:00

Sample to Insight

2/14

Generated by admin admin [admin] on 14/05/2026, 15:21:53 UTC+02:00
via QIAcuity Software Suite 3.5.0.1 | Instrument ID: F166531_680 | Run ID: d526e2070f-

Note: Software Suite version, instrument ID, and CSW version are not available for software versions earlier than 2.5.



20220322_JA_ProbeCNV_Marketing_Exp15_P3_report

Run details

	Run step	Software Suite version	Instrument ID	CSW version	Date and time
1	Run started	n/a ¹⁾	n/a ¹⁾	n/a ¹⁾	22/03/2022, 17:58:58 UTC+01:00
2	Priming started	n/a ¹⁾	n/a ¹⁾	n/a ¹⁾	22/03/2022, 18:00:21 UTC+01:00
3	Priming completed	n/a ¹⁾	n/a ¹⁾	n/a ¹⁾	22/03/2022, 18:18:05 UTC+01:00
4	Cycling started	n/a ¹⁾	n/a ¹⁾	n/a ¹⁾	22/03/2022, 18:24:23 UTC+01:00
5	Cycling completed	n/a ¹⁾	n/a ¹⁾	n/a ¹⁾	22/03/2022, 19:26:49 UTC+01:00
6	Imaging started	n/a ¹⁾	n/a ¹⁾	n/a ¹⁾	22/03/2022, 19:32:13 UTC+01:00
7	Imaging completed	n/a ¹⁾	n/a ¹⁾	n/a ¹⁾	22/03/2022, 20:02:06 UTC+01:00
8	Run completed	n/a ¹⁾	n/a ¹⁾	n/a ¹⁾	22/03/2022, 20:02:26 UTC+01:00

1) SW version, instrument ID and CSW version before software version 2.5 are not available

Where Instrument ID is the name if the instrument connected to the Software Suite:



PlatesTemplatesData SpaceArchive

ToolsConfigurationadmin

Configuration

Instrument name

Archive

User Management

Account Security

Audit Trail

Lab Automation

Instrument name

Instrument ID	Device name
test-instrument	yourDeviceName
qiacluity-flash-00ed6f	Flash-0001
plate_uploader-LocholsH1-L1-LochOlsh1	plate_uploader-LocholsH1-L1-LochOlsh1
qiacluity-flash-5f65bf	Flash-0001
NewInstrument	QIAcuity-01527

While some plate general data are now presented on the second page of the report:

QIAGEN

20220322_JA_ProbeCNV_Marketing_Exp15_P3_report

Plate general data

Plate name

20220322_JA_ProbeCNV_Marketing_Exp15_P3

Plate type

Plate upgraded

Nanoplate 8.5K 96-well

Barcode

0302666210024800000000664

Labels

-

VPF

Applied

Description

-

Plate Owners

User name	User login	Status
admin admin	admin	Active

Sample to Insight

3/152

Generated by admin admin (admin) on 13/05/2026, 13:22:22 UTC+02:00
via QIAcuity Software Suite 3.5.0.0 | Report ID: 0ab45eb6-ee18-4394-a939-8011621a23f7

7.8. Archive

In the QIAcuity Software Suite, user can set up an archive on an external drive. This will allow you to store the old plates and save disk space on the laptop.

Only the user with Administrator role can set up an archive; to do so, go to **Configuration** and select the **Archive** tab:

QIAGEN

Plates Templates Disk Space Archive

Tools Configuration admin

Configuration

Instrument name

Archive

User Management

Account Security

Audit Trail

Lab Automation


Archive location

Add Archive


Automatic archiving

Automatic plate archiving: OFF

When **Add archive** is clicked, the user can provide a path to the external drive and click **Save**.



When the archive is configured, suitable information is presented on the Archive configuration screen.




7.8.0.1. Configuring network drive as archive

A network location can be configured as the archive location. Before configuring a network location, several changes must be made in the operating system. For detailed instructions, refer to Appendix D – Archive QIAcuity Plates to a Network Drive.

7.8.1. Automatic archiving


When the archive is set up, the administrator can turn on automatic plate archiving. It will automatically move plates older than the selected time duration to the archive. The default value is 6 months. When automatic archiving is turned on, suitable information is displayed on the Archive Configuration screen.



Note: Automatic archiving is running at 1 AM every day.

7.8.2. Manual plate archiving

When the archive is set up, the user can manually move the plate to the archive. To do so, click the three dots (...) on any of the plates on the Plates Overview screen and select **Archive**. The plate will be moved to the archive.




Note: Archiving plates can take a while depending on the speed of data transfer to the external drive.


7.8.3. Bulk plate archiving

To bulk archive plates, user needs to select plates:


1. One by one, using checkboxes in upper left corner of each plate:



2. Using checkbox "Select all plates" selects all plates on plate overview and then adjust selection using checkboxes on plates:



3. When all plates intended to be archived are selected, user should click **Actions** button and select **Archive** from drop-down menu:




4. Archiving process should start as usually.


Note: Plates exhibiting the status Drafted and Running during upgrade and plates locked by instrument, cannot be archived and remain in Plate Overview.

7.8.4. Archive and restore a plate from the archive

User can browse and search plates in the archive. Go to **Archive** on the navigation bar. User can then see all your archived plates.




On plate tile there is option to check who (user login) archived the plate:



To restore plates from the archive, go to the Archive screen and click the three dots (...) on any of the plates on the Archive screen and select **Restore**. This operation can take a while depending on the plate size and speed of data transfer from the external drive.



User should confirm the decision on the pop-up window, and restoring process will start, which will be indicated with blue pulse indicator:



Note: All imported and restored, plates will automatically receive the VPF assignment, if a VPF is loaded in the system.

7.9. Audit trail

The Audit trail is a functionality in the QIAcuity Software Suite that supports users meeting Good Manufacturing Practice (GMP)/Good Laboratory (GLP) regulations. The default setting of the QIAcuity Software Suite is the Audit trail tracker switched on. This functionality may be switched off by an Administrator if the QIAcuity systems are not operated in a GMP/GLP lab.


Important: The audit trail may only be switched off when GMP compliance is not required, for example, in RUO labs. There is no data (events) stored and displayed when the tracker is turned OFF. In GMP environments, this toggle must not be set to OFF to maintain 21 CFR Part 11 compliance support.

When switched on, the Audit Trail records all actions that happened in the system. Each record consists of the following:


1. Time stamps: day, month, year, hour, minutes, second, and UTC Offset
2. User login that initiated the event that happened in the system
3. Category of the event (Instrument, Suite, or Plate)
4. Event type, what/who was affected by the action (Plate ID, User login, or Instrument ID)
5. Description of details after a change in table format

7.9.1. Audit trail tracker settings


1. To turn the Audit trail tracker ON/OFF, on the main toolbar, click the **Configuration** tab.
2. On the left-hand side, user can see the tabs menu. Click the **Audit Trail** tab. On the center of the page is the second tabs menu panel, click the **Audit trail tracker settings** tab.



As shown below, when the Audit trail tracker is turned off, the circle is at the left-hand side, the toggle is gray, and an “OFF” label appears at the right-hand side.




Moreover, the following indicator in the bottom left corner of the application footer informs that tracking is disabled:




3. To turn the tracker on, click the toggle.

When the Audit trail tracker is turned on, the circle is at the right-hand side, the toggle is blue, and an “ON” label appears at the right-hand side.



Moreover, the following indicator in the bottom left corner of the application footer informs that tracking is enabled:



7.9.2. Events List

7.9.2.1. Events list table

The events list shows all events (logs) that happened in the system. There is no possibility of removing an event from the system by the User or Administrator.

To display the Events list, on the main toolbar, click the **Configuration** tab.

From the left-hand side menu, user can see the tabs menu. Click the **Audit Trail** tab. After clicking the **Audit Trail** tab, the following tab menu panel will appear. Click the **Events list** tab. Below the filters, user can find the Events list from the past months. The Events list is sorted chronologically, from the newest events to the oldest.

The screenshot shows the QIAGEN Audit Trail interface. The top navigation bar includes 'Tools', 'Configuration', and 'Admin'. The left sidebar has 'Audit Trail' selected. The main panel shows the 'Events list' tab. Below the filters, there is a table of events.

Configuration

Instrument name: [Field]
 Archive: [Field]
 User Management: [Field]
 Account Security: [Field]
Audit Trail
 Lab Automation: [Field]

Events list

Start date: 14/04/2026
 End date: 14/05/2026
 Search for: [Field]
 Category: Suite / Instrument / Plate
 Event type: e.g. Calibration
 Initiated by: User login

Events (10/605)

Date and time	Initiated by	Category	Event type	Affected entity	Instrument ID
14/05/2026, 15:48:02 UTC+02:00	admin	Suite	Audit trail toggle	-	-
14/05/2026, 15:45:53 UTC+02:00	admin	Suite	Audit trail toggle	-	-
14/05/2026, 15:43:51 UTC+02:00	admin	Plate	Set plate ownership	305c5287-5084-42d3-9400-1b80a8ed9484 (Plate ID)	-
14/05/2026, 15:43:49 UTC+02:00	admin	Plate	Restore plate	305c5287-5084-42d3-9400-1b80a8ed9484 (Plate ID)	-
14/05/2026, 15:37:32 UTC+02:00	admin	Suite	Log off	admin (User login)	-
14/05/2026, 15:34:28 UTC+02:00	admin	Suite	Archive configuration schedule	-	-
14/05/2026, 15:33:27 UTC+02:00	admin	Suite	Archive configuration schedule	-	-

Export to PDF

ON Audit trail enabled. Tracking activities.

QIAGEN Software Suite 3.5.0.0

To find a specific event, user can scroll the list down or use the following filters.

Start date *	End date *	Search for
14/04/2026	14/05/2026	Instrument ID / Plate ID / User login / Role name
Category	Event type	Initiated by
Suite / Instrument / Plate	e.g. Calibration	User login
Clear all filters		

7.9.3. Search

7.9.3.1. Search for instrument ID, affected plate ID, user login, and role name

User can search for the instrument ID number, affected plate ID, affected user login, or affected role name. Click the search field: “Search for”.

Search for
Instrument ID / Plate ID / User login / Role name

Input user's query. After a few seconds, the records on the events list will be updated automatically (example of Plate ID number: **b0bd01c1-0c6d-4377-b030-677f12711831**, example of instrument ID number: **QIAcuity-00617**).

7.9.4. Filters

7.9.4.1. Filter by specific date or specific time frame


To find all events that happened in one specific day or time period, user need to use the filters “Start date” and “End date”.

Start date *	End date *
07/07/2024	07/08/2024

Click the “Start date” input field or click the calendar icon.

Start date *
07/07/2024

Set the date that are you interested in from the calendar.



Then specify “End date” in similar manner.


Note: User can select the same day as in “Start date” to filter only a single, specific day. Afterwards, the records on events list will be updated automatically.

7.9.4.2. Filter: Category


User needs to use the “Category” filter to check all data related to one specific category (Instrument, Suite, or Plate). Category refers to device/tool: instrument, Suite (PC Software), or Plate, on which the action has been taken.

1. **Instrument** – all events related to the instrument
2. **Suite** – all events that happened on the QIAcuity Software Suite (PC software)
3. **Plate** – all events related to Plates

Use the “Category” filter.



Click the drop-down arrow to view the three category options.



Select only one option from drop-down list: Instrument, Plate, or Suite.



Afterwards, the records list will be updated automatically.

Events (50/212) Export to PDF

Date and time	Initiated by User Login	Category	Event type	Affected entity	Instrument ID	
14/05/2026, 15:43:51 UTC+02:00	admin	Plate	Set plate ownership	3a5c5287-5084-42d3-9400-1b8dd8ed8484 (Plate ID)	-	⋮
14/05/2026, 15:43:49 UTC+02:00	admin	Plate	Restore plate	3a5c5287-5084-42d3-9400-1b8dd8ed8484 (Plate ID)	-	⋮
14/05/2026, 15:22:39 UTC+02:00	admin	Plate	Create report	888aafd3-0d4b-448c-b5ab-a3410240f27b (Plate ID)	-	⋮
14/05/2026, 15:22:14 UTC+02:00	admin	Plate	Create report	f3f985cc-8632-4cb1-90c0-2c8bc60c9416 (Plate ID)	-	⋮
14/05/2026, 15:18:18 UTC+02:00	admin	Plate	Signing report - failed	54c6e664-c7ee-4168-a5eq-869ca610d742 (Plate ID)	-	⋮
14/05/2026, 15:15:45 UTC+02:00	admin	Plate	Create report	54c6e664-c7ee-4168-a5eq-869ca610d742 (Plate ID)	-	⋮
13/05/2026, 15:04:44 UTC+02:00	admin	Plate	Create report	888aafd3-0d4b-448c-b5ab-a3410240f27b (Plate ID)	-	⋮

7.9.4.3. Filter: Event type

Event type refers to the action that happened in the system on the Instrument, Suite (PC software), or Plate. If user does not choose any option from the category, the filter displays a list of all event types (a sum of events type from all the three categories).

List of possible events: Plate experiment finish, User unlock plate, Archive plate, Restore plate, Import plate, Export plate, Support package download, Barcode removal, Instrument registration, Calibration, Plate schedule update, Experiment run (plate), Experiment canceled, Support package created, Update started, Drawer opening/closing during run, Clear error, Audit trail toggle, Archive configuration create, Archive configuration update, Archive configuration delete, Archive configuration schedule, Upload VPF, Apply VPF, Delete template, Update template, Create template, Create report, Delete report, Sign report, System version change, Create user, Edit user, Change password, User activation, User deactivation, Log on – success, Log on – failure, Log off, Automatic log off, Role creation, Role edition, Role deletion, Create plate, Update plate, Delete plate, Upgrade plate, Plate upgrade failed, Plate experiment change.

Note: The event type depends on the selected category. After filtering for a category, the event type list will only show event types related to the chosen category.

Use the “Event type” filter.

Event type

e.g. Calibration ▼

Click the arrow icon and choose one option from the drop-down list.

Event type

Update plate ▼

Afterwards, the records list will be updated automatically.

Events (10/41) Export to PDF

Date and time	Initiated by User Login	Category	Event type	Affected entity	Instrument ID	
13/05/2026, 15:03:35 UTC+02:00	admin	Plate	Update plate	888aafd3-0d4b-448c-b5ab-a3410240f27b (Plate ID)	-	
13/05/2026, 15:02:59 UTC+02:00	admin	Plate	Update plate	888aafd3-0d4b-448c-b5ab-a3410240f27b (Plate ID)	-	
13/05/2026, 14:58:19 UTC+02:00	admin	Plate	Update plate	54c6e664-c7ee-4168-a5ea-869ca610d742 (Plate ID)	-	
13/05/2026, 14:55:49 UTC+02:00	admin	Plate	Update plate	54c6e664-c7ee-4168-a5ea-869ca610d742 (Plate ID)	-	
13/05/2026, 13:17:32 UTC+02:00	admin	Plate	Update plate	54c6e664-c7ee-4168-a5ea-869ca610d742 (Plate ID)	-	
08/05/2026, 15:01:08 UTC+02:00	admin	Plate	Update plate	54c6e664-c7ee-4168-a5ea-869ca610d742 (Plate ID)	-	
08/05/2026, 14:58:19 UTC+02:00	admin	Plate	Update plate	54c6e664-c7ee-4168-a5ea-869ca610d742 (Plate ID)	-	

7.9.4.4. Filter: Initiated by

The filter “Initiated by” is related to a person (search for user login) that performed actions in the system. Login is unique and cannot be duplicated, so filtering for it will provide the user specific results.

Initiated by

admin

User login

X

Note: This filter allows you to even search for multiple users.

7.9.5. Check details

In the Events list, user can find the last option in the row, which is check details. Click it.

Events (10/15) Export to PDF

Date and time	Initiated by User Login	Category	Event type	Affected entity	Instrument ID	Check details
06/05/2026, 12:17:54 UTC+02:00	admin	Plate	Plate experiment change	54c6e664-c7ee-4168-a5ea-869ca610d742 (Plate ID)	-	

The check details option allows user to see all detailed changes that happened in the system. Changes are displayed as a table.

Plates

Templates

Disk Space

Archive

Tools

Configuration

Admin

EVENT DETAILS

Plate experiment change

Event details

Event details

Date and time

06/05/2026, 12:17:54

UTC+02:00

Login

admin

Event category

Plate

Event action

Plate experiment change

Affected entity

54-5e6824-c7ee-4368-05e0-8630c610d742

(Plate ID)

Instrument ID

-

wellPosition

41

channel

emission

GREEN

excitation

GREEN

modified

lowerCutoff

from

variable

to

77.37

thresholdStrategy

from

lasso

to

manual

dpcStepIndex

2

wellPosition

41

channel

emission

YELLOW

excitation

YELLOW

Back to Events List

ON

Audit trail enabled
Tracking activities.

QACRY Software Suite 3.5.0.0

7.9.5.1. Tracked differences in detailed audit trail events

To track changes, an Audit Trail event can contain up to 3 sections: created, modified and deleted. To view the differences for a specific event, open the [Check details](#) page for the corresponding Audit Trail event.

7.9.5.1.1. Created

This section contains newly added information only.

Changes are displayed in the created section of the table.

created	
reactionMixes	
4b445b11-d795-4016-a81c-6af7657605ec	
name	RM2
analysisRules	-
totalReactionVolume [μL]	-
id	4b445b11-d795-4016-a81c-6af7657605ec
customCrosstalkMatrix	-
targets	
1b23af6ed-9bc8-408d-864f-66102937a39	
internalControl	false
dyeName	TAMRA
name	1
channel	
thresholdMode	ST
channel	
emission	ORANGE
excitation	ORANGE
id	1b23af6ed-9bc8-408d-864f-66102937a39

7.9.5.1.2. Modified

For the following event types, the difference between existing and newly changed parameters (old to new value) is supported:

- 1. Update plate including, for example, threshold changes
- 2. Set plate ownership
- 3. Update template
- 4. Update template – reaction mix
- 5. Edit user
- 6. Edit role
- 7. Archive configuration update
- 8. Archive configuration schedule
- 9. Password expiration timeframe change

There are two values presented in fields:

- From — contains information about the previous value.
- To — contains information about the new value that replaced the one listed in the “from” section.

Changes are displayed in the modified section of the table.

modified	
reactionMixes	
080307c7-2b32-498b-9068-449033f8bccb	
targets	
31489e88-4a6b-47db-bbfd-00b73a02811b	
dyeName	
from	FAM
to	SYBR Green

7.9.5.1.3. Deleted

This section contains information that was previously available but has been removed from the entity.

Changes are displayed in the deleted section of the table.

deleted	
reactionMixes	
d7e15971-adf8-44b6-88e6-e04e3131df1f	
name	RM2
analysisRules	-
totalReactionVolume [µL]	-
id	d7e15971-adf8-44b6-88e6-e04e3131df1f
customCrosstalkMatrix	-
targets	
03ddeccd-2bd1-4468-8647-0c63e5ddf8e	
internalControl	false
dyeName	VIC
name	1
channel	
thresholdMode	ST
channel	
emission	YELLOW
excitation	YELLOW
id	03ddeccd-2bd1-4468-8647-0c63e5ddf8e

7.9.6. AT part of plate

From the QIAcuity Software Suite version 2.5 onwards, all dedicated plate-related audit trail events became part of the plate and are preserved during plate archiving and exporting. It means that plates originated from Software version 2.5 retain the previous history of all plate related audit trail events in a PDF file format. The dedicated PFD file is part of the details of the audit trail event Import plate.

Moreover, user can directly open all events related to particular plate from left-hand side panel in plate configurator with the option Plate Audit Trail.

Note: The Plate Audit Trail link of the plate configurator is only visible for logged in user exhibiting the permission for audit trail view.

PLATE CONFIGURATOR

Plate_8-plex

General Data

dPCR parameters

Reaction mixes

Samples & controls

Plate layout

Report template

Analyze

Reports

Export

Archive

Support package

Delete

Plate Audit Trail

After clicking **Plate Audit Trail**, the screen automatically redirects to the audit trail environment and plate dedicated events are filtered by plate ID.

QIAGEN

Plates

Templates

Blank Space

Archive

Tools

Configuration

Admin

Configuration

Instrument name

Archive

User Management

Account Security

Audit Trail

Lab Automation

Events list

Audit trail tracker settings

Event list

Start date *
01/01/2000

End date *
15/05/2026

Search for
c36d73c1-8a97-488e-bac9-20b4d3f00474

Category
Suite / Instrument / Plate

Event type
e.g. Calibration

Initiated by
User login


Clear all filters

Events (8/9)

Export to PDF

Date and time	Initiated by User Login	Category	Event type	Affected entity	Instrument ID
08/05/2026, 11:17:55 UTC+02:00	admin	Plate	Create report	c36d73c1-8a97-488e-bac9-20b4d3f00474 (Plate ID)	-
08/05/2026, 11:14:39 UTC+02:00	admin	Plate	Trigger Report Template	c36d73c1-8a97-488e-bac9-20b4d3f00474 (Plate ID)	-
08/05/2026, 11:14:17 UTC+02:00	admin	Plate	Update plate	c36d73c1-8a97-488e-bac9-20b4d3f00474 (Plate ID)	-
08/05/2026, 11:01:44 UTC+02:00	admin	Plate	Create report	c36d73c1-8a97-488e-bac9-20b4d3f00474 (Plate ID)	-
08/05/2026, 11:00:10 UTC+02:00	admin	Plate	Trigger Report Template	c36d73c1-8a97-488e-bac9-20b4d3f00474 (Plate ID)	-
08/05/2026, 10:59:39 UTC+02:00	admin	Plate	Update plate	c36d73c1-8a97-488e-bac9-20b4d3f00474 (Plate ID)	-

To check the plate-related audit trail events from a plate originated in another Software Suite instance, click **check details** in one of the following events: Import plate or **Restore plate**. Click **Imported Audit Trail** from left-hand side panel. Separate modal will be presented, from where PDF file with historical audit trail events can be downloaded:



7.9.7. Exporting to PDF


All event details can be exported to a PDF file.

Note: Depending on the data throughput, the audit trail PDF export of all existing entries can take several minutes. Therefore, it is recommended to filter for the desired events first and then perform a PDF report export.

1. Click the Audit trail **Events list** tab.



2. Apply filters to select for those events that should be exported.
3. At the right-hand side, above the Event list, user can find the **Export to PDF** option. Click it.



4. Depending on the audit trail data amount, a zip archive exhibiting PDF files will be downloaded. After 1000 audit trail elements, a separated PDF file will be created automatically. The audit trail export zip file name contains date and time of report generation. Each PDF file contains date and time of first and last event from this document.

7.10. General software use

7.10.1. Entering data

These shortcut functions are available in the QIAcuity Software Suite:

Table 17. Shortcut functions in QIAcuity Software Suite

Shortcut Function	Use
Ctrl + C	Copy
Ctrl + V	Paste
Tab and arrow keys	Navigate from one field to another

7.10.2. Displaying errors, warnings, and additional information


The QIAcuity Software Suite displays errors, warnings, and additional information messages throughout the experiment to prompt the user to perform a required action.

Table 18. Messages displayed in QIAcuity Software Suite

Priority level	Type	Color	Description	Required action from user
1	System error	Red	Combination of events requiring an action	User interaction required
2	Warning	Yellow	Situation could be optimized by further input	User interaction not required, but possible
3	Information	Gray	Message containing additional information about the current situation	No user interaction required


7.10.3. System error

In case of a system error, a red text box appears to describe the error and inform you of the required action. User must perform the required action described in the system error to proceed with the next step. The pop-up window must be explicitly closed by the user.



7.10.4. Warning message

A warning message is displayed in yellow in case further optimization of the experimental setup is recommended. A user interaction is not required to proceed with this step.



7.10.5. Information message

At certain fields in the experiment, user can view additional information regarding the required data to be entered on a field.

Offset *

266

▲▼

Max. value is 255.

Fields with information messages are marked with **i** icon. Clicking this icon displays a text box that provides additional information about the data needed in the field. No user interaction is required to proceed with this step.

Auto threshold offset
The auto threshold can be adjusted by specifying an offset RFU value:

- **positive** (e.g. 20 RFU) increases threshold
- **negative** (e.g. -20 RFU) decreases threshold


The threshold remains unchanged when the default value 0 is used.

0

▲▼

7.11. QIAcuity Lab Automation Service

Next to standard usage, the QIAcuity system offers an extension called QIAcuity Lab Automation Service that allows third-party Lab Automation software to control a robot to interact with our system, run dPCR experiments, and analyze results without human interaction.



The QIAcuity Lab Automation Service is compatible to all QIAcuity systems, QIAcuity One, QIAcuity Four, and QIAcuity Eight, and several QIAcuity systems can be controlled in parallel.

For more guidance, please refer to *QIAcuity Lab Automation Service User Guide* (www.qiagen.com/HB-3537-005) available on QIAcuity webpage.

8. Maintenance Procedures

WARNING/ CAUTION



Risk of personal injury and material damage

Only perform maintenance that is specifically described in this user manual.

The following maintenance procedures must be carried out to ensure reliable operation of the QIAcuity:

1. Regular maintenance
2. Periodic maintenance

Optionally, these procedures may be performed to check and ensure the reliability of operation of the QIAcuity.

Select the cleaning agent according to the objective of the cleaning procedure, the sample material used, and the downstream assay.

WARNING

Risk of fire or explosion



When using ethanol or ethanol-based liquids on the QIAcuity, handle such liquids carefully and in accordance with the required safety regulations. If liquid has been spilled, wipe it off and allow flammable vapors to disperse.

Before using any cleaning or decontamination methods except those recommended by the manufacturer, users should check with the manufacturer that the proposed method will not damage the equipment.

8.1. Cleaning agents

The following disinfectants and detergents are recommended for cleaning the QIAcuity.

Note: To use disinfectants different from those recommended, ensure that their compositions are similar to those described below.

8.1.0.1. General cleaning of the QIAcuity

1. Mild Detergents (e.g., Mikrozid® AF sensitive)
2. 25% ethanol

8.1.1. Disinfection

Ethanol-based disinfectants can be used for disinfection of surfaces (e.g., 25 g ethanol and 35 g 1-propanol per 100 g liquid or Mikrozid Liquid (Schülke & Mayr GmbH, cat. no. 109160)).

Disinfectants based on glyoxal and quaternary ammonium salt can be used (e.g., 10 g glyoxal, 12 g lauryl dimethyl benzyl ammonium chloride, 12 g myristyl dimethyl benzyl ammonium chloride, and 5–15% nonionic detergent per 100 g liquid, Lysetol® AF [Gigasept Instru AF in Europe, cat. no. 107410, or DECON-QUAT® 100, Veltek Associates, Inc., in the USA, cat. no. DQ100-06-167-01]).

8.1.1.1. Removal of RNase contamination

RnaseZap® RNase Decontamination Solution (Ambion, Inc., cat. no. AM9780) can be used for cleaning surfaces. RnaseZap can also be used to perform decontamination by spraying the respective items.

8.1.1.2. Removal of nucleic acid contamination

DNA-ExitusPlus™ (AppliChem, cat. no. A7089,0100) can be used for cleaning surfaces. DNA-ExitusPlus can also be used to perform decontamination by spraying the respective items. DNA-ExitusPlus is very sticky and foamy. For this reason, after cleaning the items with DNA-ExitusPlus, user must clean the items with a wet cloth several times, or rinse them with running water, until the DNA-ExitusPlus is completely removed.

8.1.1.3. General instructions

1. Do not use spray bottles to spray cleaning or disinfectant liquids onto surfaces of the QIAcuity.
2. If solvents or saline, acidic, or alkaline solutions are spilled on the QIAcuity, wipe the spilled liquid away immediately.
3. Follow the manufacturer's safety instruction for handling cleaning agents.
4. Follow the manufacturer's instruction for soaking time and concentration of the cleaning agents.

Important: Immersing for longer than the recommended soak time can harm the instrument.

Note: Disinfection reagents shall be distributed equally on the instrument surface and drops shall be avoided.

5. Ensure that no liquid runs down the touchscreen. Liquid may be drawn through the dust protection sealing by capillary forces and cause malfunction of the display. To clean the touchscreen, moisten a soft lint-free cloth with water, ethanol, or a mild detergent and carefully wipe the display. Wipe dry with a paper towel.

CAUTION

Damage to the instrument



Do not use bleach, solvents, or reagents containing acids, alkalis, or abrasives to clean the QIAcuity.

CAUTION

Damage to the instrument



Do not use spray bottles containing alcohol or disinfectant to clean surfaces of the QIAcuity. Take special care while cleaning the extended drawer that no liquid is spilled into the inside of the instrument.

WARNING

Risk of fire



Do not allow cleaning fluid or decontamination agents to come into contact with the electrical parts of the QIAcuity. Take special care while cleaning the extended drawer that no liquid is spilled into the inside of the instrument.

WARNING

Risk of electric shock



Do not open any panels on QIAcuity.

Risk of personal injury and material damage

Only perform maintenance that is specifically described in this user manual. Any other maintenance or repair may only be carried out by an authorized Field Service Specialist.

WARNING**Hazardous chemicals and infectious agents**

The plates may contain hazardous material and must be disposed of properly. Refer to your local safety regulations for proper disposal procedures.

**WARNING/
CAUTION****Risk of personal injury and material damage**

Improper use of the QIAcuity may cause personal injuries or damage to the instrument. The QIAcuity must only be operated by qualified personnel who have been appropriately trained. Servicing of the QIAcuity must only be performed by a QIAGEN Field Service Specialist.

WARNING**Risk of explosion**

When cleaning the QIAcuity with alcohol-based disinfectant, allow flammable vapors to disperse.

WARNING**Risk of fire or explosion**

When using ethanol or ethanol-based liquids on the QIAcuity, handle such liquids carefully and in accordance with the required safety regulations. If liquid has been spilled, wipe it off and allow flammable vapors to disperse.

WARNING**Toxic fumes**

Do not use bleach to clean or disinfect the QIAcuity.

WARNING**Toxic fumes**

Do not use bleach to disinfect used labware.

8.2. Servicing

Contact QIAGEN Technical Service or your local distributor for more information about flexible Service Support Agreements from QIAGEN.

**WARNING/
CAUTION****Risk of personal injury and material damage**

Improper use of the QIAcuity may cause personal injuries or damage to the instrument. The QIAcuity must only be operated by qualified personnel who have been appropriately trained. Servicing of the QIAcuity must only be performed by a QIAGEN Field Service Specialist.

8.3. Regular maintenance procedure of QIAcuity

Clean the instrument on a regular basis, especially if fluids have been spilled on the instrument. See Section 8.1 Cleaning agents for the recommended cleaning agents that can be used to clean the QIAcuity instrument. All outer surfaces of the instrument, including the touch display, and the extended drawer can be cleaned.

8.4. Periodic maintenance

8.4.1. Air filter change

We recommend changing the air inlet filter of the instrument once per year. This will be part of an annual scheduled service visit. When operating the instrument in unusual dusty environments, a more frequent filter change might be necessary.


Note: Air filters can be ordered separately. See Appendix B — QIAcuity Accessories, Ordering information, for more information.

Follow these steps for changing the air filter:


1. Turn off the instrument and remove the power cord.
2. Reach under the front of the instrument and push both buttons simultaneously.



3. Remove the filter from the swing-out filter compartment.



4. Replace with a new filter and push the compartment to the top to close.



8.4.2. Calibration of thermal cycler

The thermal cycler is designed to operate with the same specifications over the lifetime of the instrument. The cyclers are factory calibrated in production and the specification is controlled as part of the final instrument QC. This is part of the provided certificate of manufacture, where the SN of the calibrated module is referenced, and the passed calibration and temperature accuracy is checked. To ensure and verify the quality of the cycler, the calibration of the thermal cycler is part of an annual scheduled service visit.

8.5. Decontaminating the QIAcuity

If the QIAcuity is contaminated with infectious material, it should be decontaminated. If hazardous material is spilled on the outer surfaces or the plate trays of the QIAcuity, the user is responsible for carrying out appropriate decontamination. If damaged plates are used and the inside of the instrument is contaminated, contact QIAGEN Technical Service.

The QIAcuity should also be decontaminated before shipping (e.g., back to QIAcuity). In this case, a decontamination certificate must be completed to confirm that the decontamination procedure has been carried out.

To decontaminate the QIAcuity, follow the procedure in Section 8.1.1 Disinfection, using the recommended disinfection agents.

8.6. Regular maintenance procedure for QIAcuity instrument software


The QIAcuity stores various information about the runs and plates used in the instrument. Images created during the runs are deleted automatically after they are transferred to the QIAcuity Software Suite. If the instrument is not connected to the Software Suite, the data are cached on the local storage until a connection to the Software Suite is established. Other plate information is saved on the local storage of the device as temporary data.

8.6.1. Deleting temporary data


User can remove temporary data from the instrument to save space on the local storage or to clear some space on the disk when the disk space becomes full. The current state of available storage is shown in the Storage Info pane and the **Disk Monitor** icon below (once clicked).

When the disk space is running low, a notification is shown to all users. Operators do not have permission to delete the temporary files, and they are instructed to contact their administrator.

1. Tap the **Tools**  icon.
2. Tap **Data Management**.




3. To clear the data, tap **Force clear images**. Click **OK** in the confirmation dialog box to delete the data. Images from the system and database will be removed.



8.7. Regular maintenance procedure for QIAcuity Software Suite

To monitor the space of your disk, click **Disk monitor** in the main toolbar. This shows an overview about the state of the disk, disk name, and disk path. It also shows the remaining free space and total space of your disk.



Disk monitor overview.

There are four different disk states possible regarding the availability of free space.

Table 19. Disk status

State	Meaning	Flag
Normal	No threshold has been reached.	None
Warning	Disk space reached the warning level, there is only disk space for a few runs left.	Yellow dot in disk monitor icon
Critical	No disk space left to store more run data.	Red dot in disk monitor icon
Unavailable	The disk is not available.	None

To free up disk space, user can export and delete used plates. See Section 7.4.14 Managing your plates for more information about exporting and deleting plates.

Note: It is recommended to check the free disk space on a regular manner and to archive or delete data appropriately.

9. Troubleshooting

9.1. General information

This section provides information about what to do if an error occurs while using the QIAcuity.

9.2. Contacting QIAGEN Technical Service

Whenever a QIAcuity error is encountered, ensure to have the following information at hand:

1. Software version
2. Sample input material
3. Detailed description of the error situation
4. Serial number of the instrument

This information will help you and your QIAGEN Technical Service Specialist to deal most efficiently with your issue.

Note: For most cases, to allow proper analysis of an error situation, the support package either from the instrument and/or the Software Suite is required. Refer to Section 9.4 Creating a support package with the QIAcuity instrument software.

Note: Information about the latest software and protocol versions can be found at www.qiagen.com/QIAcuity. In some cases, updates may be available for addressing specific problems.


9.3. Performing a system testing on the QIAcuity instrument

The QIAcuity software can perform a self-check of the instrument to check the state of the device. There are two types of self-checks:

1. **Quick test:** This test does not include any hardware movement
2. **Extended test:** This test includes hardware movement. All modules return to their initial positions. If a plate is detected in the gripper, the plate is returned to the drawer.

To start a self-check, follow these steps:

1. Tap **Tools** .
2. Tap **System testing**.
3. Tap **Start Quick Test** or **Start Extended Test** depending on the type of test you want to perform.
4. The instrument starts the test. The ongoing actions and their statuses are shown in the Log File Preview pane. The log from the test can be downloaded as part of a support package. For more information about support package, see Section 9.4 Creating a support package with the QIAcuity instrument software.




9.4. Creating a support package with the QIAcuity instrument software

User can create a support package in case of an error. The support package can be uploaded to the Software Suite or saved to a USB drive.

To create a support package and upload it to the Software Suite, follow the steps below. The QIAcuity Software Suite will combine the support package from the instrument and the Software Suite.

1. On the toolbar, tap **Tools**.
2. Tap **System support**.



3. In the Support package pane, select **Upload to Software Suite**.
4. To set the timeframe of the support package, tap **Set timeframe** . The default timeframe is the last two weeks.
5. Tap the applicable option for your preferred timeframe.
 - a. Tap **Today** to create a support package for the current day.
 - b. Tap **Last week** or **Last 2 weeks** to select either the last week or the last 2 weeks.
 - c. To set a custom timeframe, tap **From** and select a start date from the calendar. Then, tap **To** and select an end date from the calendar.

6. Tap **Apply** to save the changes. After package generation, proceed to Section 9.5.1 Problem with starting the Software Suite.

Set Support Package Timeframe

Today Last week

Last 2 weeks

From 2023/04/06 To 2023/04/20

March 2023							April 2023						
Su	Mo	Tu	We	Th	Fr	Sa	Su	Mo	Tu	We	Th	Fr	Sa
			1	2	3	4							1
5	6	7	8	9	10	11	2	3	4	5	6	7	8
12	13	14	15	16	17	18	9	10	11	12	13	14	15
19	20	21	22	23	24	25	16	17	18	19	20	21	22
26	27	28	29	30	31		23	24	25	26	27	28	29
							30						

Cancel Apply

Set Support Package Timeframe dialog box.

7. Tap **Create & Download**.
8. A progress bar is shown. To cancel the download, tap the progress bar. Once the download is complete, a notification is displayed.

To create a support package and save it on a USB drive, follow the steps below.

1. On the toolbar, tap **Tools** .
2. Tap **System support**.

Running Status
Tools
Configuration
Disk Monitor
Network
Alarm

System support
System testing
System status
Labware synchronization

USB drive is not connected. Connect the USB drive to download the file.

Support Package

Select your preferred time frame to be covered within the support package:

Last 2 weeks

☒ Download to USB stick

☐ Upload to Software Suite

Create & Download

Storage Info

Disk space usage

Total: 29.82 GB

Free: 25.11 GB

Force clear images


In order to remove all images, please click the following button. All the images will be permanently removed.

Force clear


Hand: Idle Scanner: Idle Prime/Roller: Idle Cyclor 1: Idle Cyclor 2: Run Imager: Idle

admin

3. Connect a USB drive to the instrument. Wait for the device to detect the USB drive. A notification is displayed once the drive is connected.



4. In the Support Package pane, select **Download to USB drive**.
5. To set the timeframe of the support package, tap **Set timeframe** . The default timeframe is the last two weeks.
6. Tap the applicable option for your preferred timeframe.
 - a. Tap **Today** to create a support package for the current day.
 - b. Tap **Last week** or **Last 2 weeks** to select either the past week or the past two weeks.
 - c. To set a custom timeframe, tap **From** and select a start date from the calendar. Then, tap **To** and select an end date from the calendar.
7. Tap **Apply** to save the changes.



8. Tap **Create download**.
9. A progress bar is shown. To cancel the download, tap the progress bar. Once the download is complete, a notification is displayed, and the USB drive can be removed from the instrument.

9.4.1. Problem starting the QIAcuity instrument software

If the QIAcuity instrument software cannot be started (e.g., immediately after a software upgrade), a fallback page is displayed instead of the standard login screen.



QIAcuity Control Software unable to connect

We apologize for the inconvenience. Control Software is unable to start.

Please refer to the troubleshooting section of the QIAcuity User Manual and try again. Otherwise, don't hesitate to contact our Technical Service Team for assistance.

Please download the **support package** and send it to your QIAcuity Technical Service contact, details of which can be found in the user manual.

Download support package

USB drive is not detected, please ensure it is properly connected.

To create a support package and save it to a USB drive, follow the steps below:

1. Connect a USB drive to the instrument. Wait until the instrument detects the USB drive. A notification is displayed when the USB drive is detected.
2. Tap **Download support package**.
3. A progress indicator is displayed within the button while the support package is being generated and downloaded.
4. When the download is complete, a confirmation notification is displayed. The USB drive can then be safely removed from the instrument.

9.5. Software support package


The QIAcuity Software Suite offers possibility to automatically generate software support package that can automatically collect required logs from Software Suite and instrument as well. The package is password protected.

Software support package can be generated in following scenarios:

1. Problem with running Software Suite
2. Problem at logging screen
3. Problem during Software Suite runtime


9.5.1. Problem with starting the Software Suite

When there is a problem with starting the Software Suite, for example, directly after upgrade application cannot start-up correctly, special fallback page is presented instead of regular login screen:




1. On the above window, user should select package type:

- a. Software Suite package — all available logs for the Software Suite will be automatically collected



- b. Software Suite and instrument — all available logs for the Software Suite and logs for connected instrument will be automatically collected:



- **Note:** User needs to trigger collecting and sending logs to the Software Suite on instrument first. Refer to Section 9.4 Creating a support package with the QIAcuity instrument software for detailed instructions.

- User needs to point the instrument from which logs should be collected by selecting it from instrument drop-down list shown on window below:

Software support package

Package type

Suite package Suite and instrument package

Instrument

NewInstrument

☒ NewInstrument

Last 3 days Last 2 weeks 23/09/2023 - 26/09/2023

Download

Close

2. User needs to select appropriate time period using one of:

- Time frame** buttons
- From/To** selectors

3. Finally user has to click **Download** button.

9.5.2. Problem at logging screen

On the application login screen, when there is a problem with logging in, for example, user's credentials are fine but user still cannot login, user should click **Cannot log in?** next to Login button. After clicking, similar window, as described in Section 9.5.1, Problem with starting the Software Suite, will appear. Also here, user needs to select package type, specific instrument (if the Software Suite and instrument package has been selected) and time period to collect the logs. Finally user has to click **Download** button to generate the package. For downloading Suite and instrument Support Package, see Section 9.4, Creating a support package with the QIAcuity instrument software.

Cannot log in? X

Contact Support Team via QIAGEN.com website

- 1 Go to QIAGEN SUPPORT CONTACT FORM
- 2 Fill out the contact form
- 3 Attach the Software Support Package to the e-mail and send it to the Support Team

Alternatively, please call the QIAGEN Technical Service or our commercial partners.

Software support package

Package type


Suite package Suite and instrument package

Download

Close

9.5.3. Problem during the Software Suite runtime

When there is a problem during application runtime, user can navigate to **Tools** on top bar and then click **Generate software support package** button from **Troubleshooting** menu:




After clicking the above button, a similar window as described in previous sections will be presented and user needs to follow the same procedure.

9.6. Creating a support package with the QIAcuity Software Suite

1. Select a plate in the plates overview.
2. Click the left side of the screen on the Support Package.

A new window pops up, where user can specify what kind of support package needs to be generated and from which time frame.



Note: The standard package includes the log files and a combined image view of all wells. The extended package includes the log files and the raw images of each single well. By clicking the calendar symbol, user can define the time frame from which the support package shall be generated. Click **Download** to download the support package as zip file. Download package is password protected.

9.7. Troubleshooting the instrument and software

Comments and suggestions

Installation and maintenance	
1. Instrument does not power on	Check if the power outlet is working properly and the correct voltage is applied. Check the correct connection of the power cable between power outlet and instrument power inlet. If the instrument fuses are blown, contact QIAGEN Technical Service.
2. Handler blocked	If the hand cannot move freely during initialization of the instrument, check if the transport locking screw was removed according to the installation procedure.
3. Overheating	If an overheating error is shown or the instrument shuts off during an operation, ensure correct ventilation of the instrument and correct environmental conditions according to the installation section requirements. Ensure that the air filter is not clogged and exchanged on a regular basis.
Plate loading	
1. Plate presence/orientation	The instrument detects the proper orientation of the plate. Ensure that the barcode is pointed to the instrument back and the microstructures to the bottom.
2. Plate Seal presence	A missing Plate Seal is detected by the instrument. Ensure that always a closed plate with Plate Seal is loaded into the instrument. A run cannot be started if a plate seal is not detected by the instrument. Only use QIAGEN products for closing the plates.
3. Drawer blocking	If the drawer is retrieved and blocked, ensure that the plate is correctly loaded into the drawer and parallel to the base surface of the drawer.
4. Plate retrieving	If a plate could not be retrieved correctly in the instrument, ensure that the Plate Seal is applied properly and not overlapping more than 1 mm at the plate side surfaces. Check for any typographical error in the plate barcode of the experiment in the QIAcuity Software Suite.
5. Run cannot start	Check if the QIAcuity Software Suite is online.
Mechanical	
Frame of instrument is distorted (e.g., uneven, unstable or not level)	Ensure that the instrument is placed on a stable, flat and level surface as described in Section 4.4 Installing the QIAcuity.
Electronic	
1. Display does not turn on	Do not touch the display with excessive force or use corrosive chemicals to clean the display surface. Contact QIAGEN Technical Service for repair.
2. Error when copying files to USB	Power OFF the QIAcuity, wait for a few minutes, and power it ON again. Save the file(s) to the USB stick again. Check the USB stick on a PC to ensure it is functional. If the error persists, contact QIAGEN Technical Service.
3. USB device not detected	Power OFF the QIAcuity, wait for a few minutes, and power it ON again. Insert the USB stick into the USB port. Check the USB stick on a PC to ensure it is functional. If the error persists, contact QIAGEN Technical Services.
4. Login screen not visible when starting instrument	If the touchscreen does not display the login screen, but instead a software update message is shown, power OFF the QIAcuity and wait for a few minutes. Ensure that the USB stick is not inserted in the USB port. Power ON the QIAcuity again. The login screen should be visible. If the error persists, contact QIAGEN Technical Service.
5. Starting of instrument takes long	After Update of the instrument software the Firmware Update might be run in the background causing a long starting period (up to 60 min).
Application	
1. Images or analysis data cannot be viewed	Check the connection to the QIAcuity instrument.
2. Poor or no amplification	Check if the correct protocols and reagents have been used. Check if the reaction was set up correctly. Check the cycling and imaging conditions. Check if correct restriction enzyme was used when using gDNA as template material. Check the starting quality and quantity of the template. We recommend that you use QIAGEN kits for sample preparation.

Comments and suggestions

3. No clear separation between positive and negative partitions	Check if the correct protocols and reagents have been used. Check if the reaction was set up correctly. Check the cycling and imaging conditions. Check if correct restriction enzyme was used when using gDNA as template material. Check the starting quality and quantity of the template. We recommend that you use QIAGEN kits for sample preparation.
4. Images are saturated	Re-image the plate with 30% lower exposure duration (see also Section 7.6.5.1 Image quality control)
5. Sample result is 0 copies/ μ L or infinite in absolute quantification	If your concentration is 0 copies/ μ L, although the sample is not an NTC, check the Histogram or 1D Scatterplot for this well. In case of having nearly only positive partitions in the well, a proper auto-threshold setting was likely not possible. Check also if the image of the well is too dark, and in case re-image the plate with 30% higher exposure time or gain settings.
6. Sample results of replicates differ a lot	Check the images for blacked-out areas, that can occur, e.g., due to bad filling or areas of low amplification (see Section 7.6.7 Image corrective measures)
7. High copy number in NTC	Check the images or signal map for dust or other particles. In case, wipe the plate with a lint-free tissue (optionally, use ethanol) and re-image the plate.
8. Lower RFU of negative partitions in NTC/samples with low number of positive partitions	The signal intensity might be lower in images with high number of negative partitions. There is no influence on the result analysis, as the signal to noise is not affected.
9. The confidence interval is wide	The number of valid partitions is low. Check the images for blacked-out areas, that can occur, e.g., due to bad filling or areas of low amplification (see Section 7.6.7 Image corrective measures)
10. Vertical stripes in the images	Re-image the plate for proper image analysis
11. Double positive or double negative signals	The double positive or double negative signals could have different root causes. One of the reasons for observing double signal bands could be suboptimal assay designs, such as cross-hybridization of probes to unspecific targets or secondary off-target amplification products. Besides assays-related causes, improper cross talk compensation could also be the root cause. An insufficient compensation or overcompensation of cross talk from neighboring channels could also result in extra signal bands. To determine the main root cause, re-image the plate with 30% less exposure times for affected channel. If double bands disappear or get much closer to each other after re-imaging, they are most likely to be caused by improper cross talk compensation rather than assay-related issues.
12. Fetch error while accessing the Users list in User Management	If such error occurs, contact QIAGEN Technical Service to solve the issue.

Software

1. The QIAcuity Software Suite does not start	Check that the software is installed on the laptop. Check the operating system. The QIAcuity Software Suite can only be operated on Windows 11.
2. Installation of QIAcuity Software Suite failed	Check the firewall settings on Windows and router to make sure that the following ports: 8687, 9595, 44321 are available and opened in the network.
3. User cannot create new plate after rollback	During rollback Suite should be closed – if user forgot to close it then relog after rollback is needed
4. Disc space is critical in the QIAcuity Software Suite	Delete plates from the plates overview.
5. User forgot password	Administrator to log-in, change the password for the user. If administrator forgot the password, contact QIAGEN Technical Service.
6. Communication error between QIAcuity instrument and software	This error occurs when the data received from the instrument does not conform to the expected pattern. Further investigations are required by a QIAGEN Field Service Specialist to diagnose the problem with the instrument. Contact your distributor or QIAGEN Technical Service.

Comments and suggestions

7. Instrument software or Software Suite is unresponsive	Re-start the QIAcuity instrument or the notebook where the QIAcuity Software Suite is installed
8. Startup of instruments displays an error	The required plate recovery task cannot be performed because there are no plate slots available in the tray. Remove all loaded plates before you proceed. Press Restart to start recovery.
9. Error 205 or Error 32	The error can occur in different situations: (A) Make sure that the selected Plate type corresponds with the entered barcode, if manually entered. If not matching, it will lead to an error on the instrument (error 205). (B) Make sure that after the first successful suite connection, the instrument is restarted to allow automatic synchronization of labware files.
10. Error 490	The error can occur after a plate was processed and a failure in image transfer to the Suite was detected. The Suite rejected a data package due to improper format. See if all images are available in the Suite. If you find images missing, add an additional imaging step to recover the data.
11. Unidentified error occurs during upgrade	Check the log file for following entries: "Backup failed: Backup fail: There is not enough disk space for backup" or "Data size: x MB, free disk space: x MB"
13. Error 300 during startup of instrument	The Thermocycle requires a minimum ambient temperature inside the instrument of 17°C. Thus, the Error 300 might occur in locations, where room temperature could sink below 17°C. If the Error 300 is raised during start up, when the instrument has been shut down for a longer period, a warm-up phase is required. Turn on the instrument for 30–60 min. After this time clear the Error and restart. The instrument should start without an Error. If the Error persists, contact QIAGEN Technical Service.
14. Error 33	The error can occur if the instrument was shut down with plates loaded to all plate slots or an error occurred in a fully loaded instrument. During startup, the instrument starts a recovery sequence requiring a free slot in the drawer. Therefore, Error 33 is raised and asks you to unload at least 1 slot, clear the error, and restart.
15. Empty running screen and CSW version 0.0.0.0 and no connection with Network and Software Suite	The error can occur very rarely after clearing errors and can be solved by restarting the instrument.
16. Error 177	This error can occur when the teaching for the Hand was not performed properly and can occur for following modules: Drawer, Primer, and Thermocycler. Automatic positioning is implemented to prevent system from throwing the error, yet if it happens, the error needs to be cleared manually via Tools > System status > Clear errors . If the error keeps appearing, Hand teaching needs to be performed by the FSE team member.
17. Error 145	This error can occur when plate was dropped inside of the instrument – it means that the plate was not discovered in Hand nor in the any other module.


9.8. Accessing the system status and clearing errors

Note: Only administrators can access the instrument status.

The QIAcuity allows you to see the status of each of its modules. This is especially useful when a hardware error occurs. Details about errors that occurred on the instrument are shown in the **System Status** section. After viewing the information, administrators can clear errors and restart the instrument to initialize all the modules.

To access the System Status environment and clear errors, follows the steps below.


1. On the toolbar, tap **Tools**.
2. Tap **Servicing**.
3. In the Servicing tab, tap **System Status**.



System status environment on the QIAcuity Eight after an error occurs.

4. To clear an error, tap **Clear error**.
5. If the error that occurred affects the tray(s), tap **More details**. To clear a tray-related error, tap **Clear error** in the dialog. The dialog box contains five items that can be cleared for each tray, such as motor and slot numbers (based on the instrument version).

Note: In QIAcuity Eight, the **More details** button is located in the Upper Tray and Lower Tray panes. In the QIAcuity Four and QIAcuity One, the **More details** button is located in the Tray pane.



6. Restart the instrument. The instrument initializes and all modules are returned to their home positions.

Note: If the affected module is not working after you cleared the error and restarted the instrument, contact QIAGEN Technical Services.

10. Technical Specifications

QIAGEN reserves the right to change specifications at any time.

10.1. Operating conditions

Power	100–240 V AC, 50/60 Hz, Mains supply voltage fluctuations are not to exceed 10% of nominal supply voltages. Maximum power consumption: QIAcuity One, 2plex: 1000 VA QIAcuity Four: 1000 VA QIAcuity Eight: 1500 VA
--------------	--

Fuse	2x T12A L 250 V
Overvoltage category	II
Air temperature	15–32°C (59.0–89.6°F)
Relative humidity	10–75% (non-condensing)
Altitude	Up to 2000 m (6500 ft.)
Place of operation	For indoor use only
Pollution level	2
Environmental class	3K21 (IEC 60721-3-3)

10.2. Transport conditions

Air temperature	–25°C to 60°C (–13°F to 140°F) in manufacturer's package
------------------------	--

Relative humidity	5% to 85% (non-condensing)
Environmental class	2K11 & 2M4 (IEC 60721-3-2)
Ambient pressure	700 to 1060 hPa

10.3. Storage conditions

Air temperature	5°C to 40°C (41°F to 104°F) in manufacturer's package
------------------------	---

Relative humidity	5% to 85% (non-condensing)
Environmental class	1K21 (IEC 60721-3-1)
Ambient pressure	700 to 1060 hPa

10.4. Mechanical data and hardware features

Dimensions	Width: 60 cm (23.6 in.)
Four/Eight	Height: 58 cm (22.8 in.)
	Depth: 65 cm (25.6 in.)

Dimensions One	Width: 38 cm (15.0 in.) Height: 45 cm (17.7 in.) Depth: 65 cm (25.6 in.)																					
Mass	QIAcuity One: 36.0 kg (79.4 lb.) QIAcuity Four: 43.0 kg (94.8 lb.) QIAcuity Eight: 55.0 kg (121.3 lb.) Accessories: 3.0 kg (6.6 lb.)																					
Thermal specifications	Process temperature: 35°C to 99°C Ramp rate: approx. 3.0°C/s Accuracy: ±1°C Homogeneity (over plate surface): ±1°C The QIAcuity Eight features two thermal cyclers that are operated in parallel																					
Optical specifications	The 2-plex version features the channels Green and Yellow and the 5-plex version all following channels: <table><thead><tr><th>Channel</th><th>Green</th><th>Yellow</th><th>Orange</th><th>Red</th><th>Crimson</th><th>Far red</th></tr></thead><tbody><tr><td>Excitation in nm</td><td>463–503</td><td>513–534</td><td>541–563</td><td>568–594</td><td>588–638</td><td>651–690</td></tr><tr><td>Emission in nm</td><td>519–549</td><td>551–565</td><td>582–608</td><td>613–655</td><td>656–694</td><td>709–759</td></tr></tbody></table> Excitation by high power white LED with average 4750 lumens Image acquisition by CMOS camera with 6.3 MP	Channel	Green	Yellow	Orange	Red	Crimson	Far red	Excitation in nm	463–503	513–534	541–563	568–594	588–638	651–690	Emission in nm	519–549	551–565	582–608	613–655	656–694	709–759
Channel	Green	Yellow	Orange	Red	Crimson	Far red																
Excitation in nm	463–503	513–534	541–563	568–594	588–638	651–690																
Emission in nm	519–549	551–565	582–608	613–655	656–694	709–759																
Capacity	Up to 96 samples per plate. Maximum plate capacity depends on the configuration (One, Four, Eight)																					
Touchscreen (Four/Eight)	10.1" LCD Touch, active area 218.0 × 136.6 mm, resolution 1280*800 HD																					
Touchscreen (One)	7.0" LCD Touch, active area 150.4 × 94.2 mm, resolution 1280*800 HD																					
Acoustic emission	QIAcuity One: Max. 57.4 dB (A) QIAcuity Four/Eight: Max. 54.6 dB (A)																					
USB drive	USB2.0 8GB or higher Compatible OS: Windows 10 or later; Mac OS 12 or later Formatting: FAT32																					
Handheld scanner (optional)	Scan Pattern: Area Image (1280 × 800 pixel array) Motion Tolerance: Up to 89 cm/s (35 in/s) Print Contrast Ratio: 15% (minimum) Decode Capability: Reads standard 1D, 2D, Postal and stacked codes Resolution: 1D Linear: 0.102 mm/4 mils; PDF417: 0.127 mm/5 mils; Data Matrix: 0.195 mm/7.5 mils																					

11. Glossary

Glossary terms are listed in alphabetical order.

Term	Description
Acquisition	The collection of fluorescent data at the end of the run
Channel	A channel consists of a light emitting diode (LED) with an excitation filter paired with an emission filter The LED and excitation filter excite samples at a given wavelength. Fluorescence emitted by samples is passed through the emission filter, before being detected by the camera.
Confidence Interval	Indicates the range of values that is likely to contain the true parameter value
dPCR parameters	Parameters specifying a PCR run (e.g., number of cycles, temperature, acquisitions, etc.)
Environment	The QIAcuity Software Suite consists of several environments (e.g., "Plates", "Templates", "Analysis", "Report"). In these environments, certain tasks can be performed, such as setting up a run or analyze data.
Error code	A 3- or 4-digit number that indicates an error of the QIAcuity
Exposure duration	The length of time the samples are exposed to light during the fluorescence acquisition
Gain	A setting to amplify the fluorescence signal If the gain is set too high, the signal is oversaturated. If the gain is set too low, it is not possible to differentiate signal from background noise.
GUI	Graphical user interface
Initialization	An operation performed automatically when the QIAcuity is switched on or by initiating a self-check of the instrument, if required
LTS	Long-term support
Nanoplate	dPCR plate with several single partitions
Optical configuration	The optical configuration of a QIAcuity instrument is described by the available channels to detect fluorescence signals. The optical configuration differs between different types of the QIAcuity instruments.
Partition	Compartment in the Nanoplate where the PCR reaction takes place
Plate seal	Foil to be applied on top of the plate to prevent evaporation and contamination
Power switch	A button located at the front of the QIAcuity in the bottom-right corner It allows the user to switch the QIAcuity on and off; inner position is ON and outer position is OFF.
Priming	Filling of the partitions with the reaction volume
Rolling	Separation of the single partitions filled with the reaction volume
Support Package	Information wrapped up in a *.zip file to be sent via an email program to QIAGEN Technical Services to inform QIAGEN what went wrong at the customer's site and how to help the customer
Touchscreen	The user interface that allows the user to operate the QIAcuity
VPF	Volume Precision Factor. The VPF specifies the exact cycled volume of a well within a Nanoplate and therefore further increases precision of concentration calculation in each well.

Appendix A – Legal

Declaration of conformity

Name and address of the legal manufacturer:

QIAGEN GmbH
QIAGEN Strasse 1
40724 Hilden
Germany

An up-to-date declaration of conformity can be requested from QIAGEN Technical Services.

Waste Electrical and Electronic Equipment (WEEE)

This section provides information about disposal of waste electrical and electronic equipment by users.

The crossed-out wheeled bin symbol (see below) indicates that this product must not be disposed of with other waste; it must be taken to an approved treatment facility or to a designated collection point for recycling, according to local laws and regulations.

The separate collection and recycling of waste electronic equipment at the time of disposal helps to conserve natural resources and ensures that the product is recycled in a manner that protects human health and the environment.



Recycling can be provided by QIAGEN upon request at additional cost. In the European Union, in accordance with the specific WEEE recycling requirements and where a replacement product is being supplied by QIAGEN, free recycling of its WEEE-marked electronic equipment is provided.

To recycle electronic equipment, contact your local QIAGEN sales office for the required return form. Once the form is submitted, you will be contacted by QIAGEN either to request follow-up information for scheduling collection of the electronic waste or to provide you with an individual quote.

California Proposition 65

WARNING



Using this product can expose you to chemicals including lead acetate, which is known to the state of California to cause cancer and DEHP, which is known to the State of California to cause birth defects and/or other reproductive harm. For more information, go to www.P65Warnings.ca.gov

Liability Clause

QIAGEN shall be released from all obligations under its warranty in the event repairs or modifications are made by persons other than its own personnel, except in cases where the Company has given its written consent to perform such repairs or modifications.

All materials replaced under this warranty will be warranted only for the duration of the original warranty period, and in no case beyond the original expiration date of original warranty unless authorized in writing by an officer of the Company. Read-out devices, interfacing devices, and associated software will be warranted only for the period offered by the original manufacturer of these products. Representations and warranties made by any person, including representatives of QIAGEN, which are inconsistent or in conflict with the conditions in this warranty shall not be binding upon the Company unless produced in writing and approved by an officer of QIAGEN.

Declaration list of China RoHS (SJT 11364-2014)

The environmental friendly use period of the QIAcuity instruments is 25 years. The marking for the Restricted Use of Hazardous Substances in Electronic and Electrical Products (SJ/T 11364-2014) is shown in Table 20.

Table 20. Marking for the restricted use of hazardous substances in electronic and electrical products (SJ/T 11364-2014)

Part Name 部件名称	Toxic or Hazardous Substances and Element 有毒或有害的物质成分					
	Lead (Pb) 铅	Mercury (Hg) 汞	Cadmium (Cd) 镉	Hexavalent Chromium (Cr6+) 六价铬	Polybrominated biphenyls (PBB) 多溴联苯	Polybrominated diphenyl ethers (PBDE) 多溴联苯醚
Plastics 塑料						
Enclosure/ Plastics parts 外壳/ 塑料部件	○	○	○	○	○	○
Mechanical units 机械部分						
Chassis/ Moving parts 底盘/ 可动部分	○	○	○	○	○	○
Shielding/ apertures/ covers 罩/ 光圈/ 盖	○	○	○	○	○	○
Electrical Units 电器部分						
PCBs a. components/ Sensors 印刷电路板部分/ 传感器	X	○	○	○	○	○
Power supply 电源	X	○	○	○	○	○

Table 20. Marking for the restricted use of hazardous substances in electronic and electrical products (SJ/T 11364-2014) (continued)

Part Name 部件名称	Toxic or Hazardous Substances and Element 有毒或有害的物质成分					
	Lead (Pb) 铅	Mercury (Hg) 汞	Cadmium (Cd) 镉	Hexavalent Chromium (Cr6+) 六价铬	Polybrominated biphenyls (PBB) 多溴联苯	Polybrominated diphenyl ethers (PBDE) 多溴联苯醚
Cables 电缆						
Connecting cables 连接电缆	○	○	○	○	○	○
Motors 电机						
Motors/ Pumps/ Fans 电机/ 泵/ 风扇	○	○	○	○	○	○
Optical Parts 光学部件						
Filter/ Lenses 滤光器/ 镜头	○	○	○	○	○	○
Heating Unit 加热装置						
Thermocycler 散热片	○	○	○	○	○	○

Note: This table is prepared in accordance with the provisions of SJ/T 11364.

○: Indicates that this toxic or hazardous substance contained in all of the homogeneous materials for this part is below the limit requirement in GB/T 26572.

○: 代表用于此部件的所有同类型的包含该种有毒或者有害物质的材料均在GB/T 26572的规定界限以下

X: Indicates that this toxic or hazardous substance contained in at least one of the homogeneous materials used for this part may be above the limit requirement in GB/T 26572.

X: 代表用于此部件的至少一种此类型的包含该种有毒或者有害物质的材料可能在GB/T 26572的规定界限以上

Appendix B — QIAcuity Accessories

For more information and an up-to-date list of available protocols, visit www.qiagen.com

Ordering information

Product	Contents	Cat. no.
QIAcuity One, 2plex Device	One-plate digital PCR instrument for detecting up to 2 fluorescent dyes, enabling up to 4plex analysis operating under software version 3.1 or higher, roller, USB flash memory and QIAcuity Software Suite: includes 1 preventive maintenance visit. 1 year warranty on labor, travel, and parts also included. Does not include installation and training.	911001
QIAcuity One, 2plex System	One-plate digital PCR instrument for detecting up to 2 fluorescent dyes, enabling up to 4plex analysis operating under software version 3.1 or higher, roller, USB flash memory and QIAcuity Software Suite: includes installation, training, and 1 preventive maintenance visit. 1 year warranty on labor, travel, and parts also included.	911002
QIAcuity One, 2plex System FUL-1	One-plate digital PCR instrument for detecting up to 2 fluorescent dyes, enabling up to 4plex analysis operating under software version 3.1 or higher, roller, USB flash memory and QIAcuity Suite Software: includes installation, training, Full Agreement for 1 year with a 2 business day response time, and 1 preventive maintenance visit	911005
QIAcuity One, 2plex System FUL-2	One-plate digital PCR instrument for detecting up to 2 fluorescent dyes, enabling up to 4plex analysis operating under software version 3.1 or higher, roller, USB flash memory and QIAcuity Software Suite: includes installation, training, Full Agreement for 2 years with a 2 business day response time, and 2 preventive maintenance visits.	911006
QIAcuity One, 2plex System FUL-3	One-plate digital PCR instrument for detecting up to 2 fluorescent dyes, enabling up to 4plex analysis operating under software version 3.1 or higher, roller, USB flash memory and QIAcuity Software Suite: includes installation, training, Full Agreement for 3 years with a 2 business day response time, and 3 preventive maintenance visits.	911007
QIAcuity One, 2plex Platform Device	One-plate digital PCR instrument for detecting up to 2 fluorescent dyes, enabling up to 4plex analysis operating under software version 3.1 or higher, notebook computer, roller, USB flash memory and QIAcuity Suite Software: includes 1 preventive maintenance visit. 1 year warranty on labor, travel, and parts also included. Does not include installation and training.	911014
QIAcuity One, 2plex Platform System	One-plate digital PCR instrument for detecting up to 2 fluorescent dyes, enabling up to 4plex analysis operating under software version 3.1 or higher, notebook computer, roller, USB flash memory and QIAcuity Suite Software: includes installation, training, and 1 preventive maintenance visit. 1 year warranty on labor, travel, and parts also included.	911012
QIAcuity One 2plex Platform System FUL-1	One-plate digital PCR instrument for detecting up to 2 fluorescent dyes, enabling up to 4plex analysis operating under software version 3.1 or higher, notebook computer, roller, USB flash memory and QIAcuity Suite Software: includes installation, training, Full Agreement for 1 year with a 2 business day response time, and 1 preventive maintenance visit.	911015
QIAcuity One 2plex Platform System FUL-2	One-plate digital PCR instrument for detecting up to 2 fluorescent dye, enabling up to 4plex analysis operating under software version 3.1 or higher, notebook computer, roller, USB flash memory and QIAcuity Suite Software: includes installation, training, Full Agreement for 2 years with a 2 business day response time, and 2 preventive maintenance visits.	911016
QIAcuity One 2plex Platform System FUL-3	One-plate digital PCR instrument for detecting up to 2 fluorescent dyes, enabling up to 4plex analysis operating under software version 3.1 or higher, notebook computer, roller, USB flash memory and QIAcuity Suite Software: includes installation, training, Full Agreement for 3 years with a 2 business day response time, and 3 preventive maintenance visits.	911017

Product	Contents	Cat. no.
QIAcuity One, 5plex Device	One-plate digital PCR instrument for detecting up to 5 fluorescent dyes or up to 8 fluorescent dyes operating under software version 3.1 or higher, enabling up to 12plex analysis, roller, USB flash memory and QIAcuity Software Suite: includes 1 preventive maintenance visit. 1 year warranty on labor, travel, and parts also included. Does not include installation and training.	911021
QIAcuity One, 5plex System	One-plate digital PCR instrument for detecting up to 5 fluorescent dyes or up to 8 fluorescent dyes operating under software version 3.1 or higher, enabling up to 12plex analysis, roller, USB flash memory and QIAcuity Software Suite: includes installation, training, and 1 preventive maintenance visit. 1 year warranty on labor, travel, and parts also included.	911022
QIAcuity One, 5plex System FUL-1	One-plate digital PCR instrument for detecting up to 5 fluorescent dyes or up to 8 fluorescent dyes operating under software version 3.1 or higher, enabling up to 12plex analysis, roller, USB flash memory and QIAcuity Suite Software: includes installation, training, Full Agreement for 1 year with a 2 business day response time, and 1 preventive maintenance visit	911025
QIAcuity One, 5plex System FUL-2	One-plate digital PCR instrument for detecting up to 5 fluorescent dyes or up to 8 fluorescent dyes operating under software version 3.1 or higher, enabling up to 12plex analysis, roller, USB flash memory and QIAcuity Software Suite: includes installation, training, Full Agreement for 2 years with a 2 business day response time, and 2 preventive maintenance visits.	911026
QIAcuity One, 5plex System FUL-3	One-plate digital PCR instrument for detecting up to 5 fluorescent dyes or up to 8 fluorescent dyes operating under software version 3.1 or higher, enabling up to 12plex analysis, roller, USB flash memory and QIAcuity Software Suite: includes installation, training, Full Agreement for 3 years with a 2 business day response time, and 3 preventive maintenance visits.	911027
QIAcuity One, 5plex Platform Device	One-plate digital PCR instrument for detecting up to 5 fluorescent dyes or up to 8 fluorescent dyes operating under software version 3.1 or higher, enabling up to 12plex analysis, notebook computer, roller, USB flash memory and QIAcuity Suite Software: includes 1 preventive maintenance visit. 1 year warranty on labor, travel, and parts also included. Does not include installation and training.	911034
QIAcuity One, 5plex Platform System	One-plate digital PCR instrument for detecting up to 5 fluorescent dyes or up to 8 fluorescent dyes operating under software version 3.1 or higher, enabling up to 12plex analysis, notebook computer, roller, USB flash memory and QIAcuity Suite Software: includes installation, training, and 1 preventive maintenance visit. 1 year warranty on labor, travel, and parts also included.	911032
QIAcuity One 5plex Platform System FUL-1	One-plate digital PCR instrument for detecting up to 5 fluorescent dyes or up to 8 fluorescent dyes operating under software version 3.1 or higher, enabling up to 12plex analysis, notebook computer, roller, USB flash memory and QIAcuity Suite Software: includes installation, training, Full Agreement for 1 year with a 2 business day response time, and 1 preventive maintenance visit.	911035
QIAcuity One 5plex Platform System FUL-2	One-plate digital PCR instrument for detecting up to 5 fluorescent dyes or up to 8 fluorescent dyes operating under software version 3.1 or higher, enabling up to 12plex analysis, notebook computer, roller, USB flash memory and QIAcuity Suite Software: includes installation, training, Full Agreement for 2 years with a 2 business day response time, and 2 preventive maintenance visits.	911036
QIAcuity One 5plex Platform System FUL-3	One-plate digital PCR instrument for detecting up to 5 fluorescent dyes or up to 8 fluorescent dyes operating under software version 3.1 or higher, enabling up to 12plex analysis, notebook computer, roller, USB flash memory and QIAcuity Suite Software: includes installation, training, Full Agreement for 3 years with a 2 business day response time, and 3 preventive maintenance visits.	911037
QIAcuity Four Platform System	Four-plate digital PCR instrument for detecting up to 5 fluorescent dyes or up to 8 fluorescent dyes operating under software version 3.1 or higher, enabling up to 12plex analysis, notebook computer, barcode scanner, roller, USB flash memory and QIAcuity Software Suite: includes installation, training, and 1 preventive maintenance visit. 1 year warranty on labor, travel, and parts.	911042

Product	Contents	Cat. no.
QIAcuity Four Platform System FUL-1	Four-plate digital PCR instrument for detecting up to 5 fluorescent dyes or up to 8 fluorescent dyes operating under software version 3.1 or higher, enabling up to 12plex analysis, notebook computer, barcode scanner, roller, USB flash memory and QIAcuity Suite Software: includes installation, training, Full Agreement for 1 year with a 2 business day response time, and 1 preventive maintenance visit.	911045
QIAcuity Four Platform System FUL-2	Four-plate digital PCR instrument for detecting up to 5 fluorescent dyes or up to 8 fluorescent dyes operating under software version 3.1 or higher, enabling up to 12plex analysis, notebook computer, barcode scanner, roller, USB flash memory and QIAcuity Software Suite: includes installation, training, Full Agreement for 2 years with a 2 business day response time, and 2 preventive maintenance visits.	911046
QIAcuity Four Platform System FUL-3	Four-plate digital PCR instrument for detecting up to 5 fluorescent dyes or up to 8 fluorescent dyes operating under software version 3.1 or higher, enabling up to 12plex analysis, notebook computer, barcode scanner, roller, USB flash memory and QIAcuity Software Suite: includes installation, training, Full Agreement for 3 years with a 2 business day response time, and 3 preventive maintenance visits.	911047
QIAcuity Eight Platform System	Eight-plate digital PCR instrument detecting up to 5 fluorescent dyes or up to 8 fluorescent dyes operating under software version 3.1 or higher, enabling up to 12plex analysis, notebook computer, barcode scanner, nanoplate roller, USB flash memory and QIAcuity Software Suite: includes installation, training, and 1 preventive maintenance visit. 1 year warranty on labor, travel, and parts.	911052
QIAcuity Eight Platform System FUL-1	Eight-plate digital PCR instrument detecting up to 5 fluorescent dyes or up to 8 fluorescent dyes operating under software version 3.1 or higher, enabling up to 12plex analysis, notebook computer, barcode scanner, nanoplate roller, USB flash memory and QIAcuity Suite Software: includes installation, training, Full Agreement for 1 year with a 2 business day response time, and 1 preventive maintenance visit.	911055
QIAcuity Eight Platform System FUL-2	Eight-plate digital PCR instrument detecting up to 5 fluorescent dyes or up to 8 fluorescent dyes operating under software version 3.1 or higher, enabling up to 12plex analysis, USB flash memory and QIAcuity Software Suite: includes installation, training, Full Agreement for 2 years with a 2 business day response time, and 2 preventive maintenance visits.	911056
QIAcuity Eight Platform System FUL-3	Eight-plate digital PCR instrument detecting up to 5 fluorescent dyes or up to 8 fluorescent dyes operating under software version 3.1 or higher, enabling up to 12plex analysis, notebook computer, barcode scanner, nanoplate roller, USB flash memory and QIAcuity Software Suite: includes installation, training, Full Agreement for 3 years with a 2 business day response time, and 3 preventive maintenance visits.	911057
Related products		
Notebook, QIAcuity One	Notebook computer for QIAcuity One	911100
QIAcuity Nanoplate 26k 24-well (10)	10 QIAcuity Nanoplate 26k 24-well, 11 Nanoplate Seals	250001
QIAcuity Nanoplate 8.5k 24-well (10)	10 QIAcuity Nanoplate 8.5k 24-well, 11 Nanoplate Seals	250011
QIAcuity Nanoplate 8.5k 96-well (10)	10 QIAcuity Nanoplate 8.5k 96-well, 11 Nanoplate Seals	250021
Nanoplate Tray (2)	2x Nanoplate Tray	250098
Nanoplate Seals (11)	11x Nanoplate Seals	250099
Barcode Hand Scanner, QIAcuity	Separate 2D barcode scanner for reading of QIAcuity Nanoplate IDs outside of the QIAcuity instrument	911106
Roller, QIAcuity	Nanoplate Roller for fixing the Nanoplate seal on QIAcuity Nanoplates	911105
Air Filter, QIAcuity One (1)	Replacement air inlet filter for QIAcuity One	9026699
Air Filter, QIAcuity Four/Eight (1)	Replacement air inlet filter for QIAcuity Four and QIAcuity Eight	9026700
QIAcuity Nanoplate 26k 24-well (10)	24-well dPCR Nanoplate with 26K partitions and 40 µL reaction volume per well, including Nanoplate seals	250001
QIAcuity Nanoplate 8.5k 24-well (10)	24-well dPCR Nanoplate with 8.5K partitions and 12 µL reaction volume per well, including Nanoplate seals	250011

Product	Contents	Cat. no.
QIAcuity Nanoplate 8.5k 96-well (10)	96-well dPCR Nanoplate with 8.5K partitions and 12 µL reaction volume per well, including Nanoplate seals	250021
QIAcuity Nanoplate 26k 8-well (10)	8-well dPCR Nanoplate with 26K partitions and 40 µL reaction volume per well, including Nanoplate seals	250031
Nanoplate Seals (11)	Nanoplate seal for sealing QIAcuity Nanoplates	250099
Nanoplate Tray (2)	Nanoplate Tray improving plate-handling during pipetting or carrying	250098
QIAcuity Probe PCR Kit (1 mL)	1 mL 4× concentrated QIAcuity Probe Mastermix, 2 × 1.9 mL Water	250101
QIAcuity Probe PCR Kit (5 mL)	5 × 1 mL 4× concentrated QIAcuity Probe Mastermix, 8 × 1.9 mL Water	250102
QIAcuity Probe PCR Kit (25 mL)	5 × 5 mL 4× concentrated QIAcuity Probe Mastermix, 4 × 20 mL Water	250103
QIAcuity EG PCR Kit (1 mL)	1 mL 3× concentrated QIAcuity EvaGreen Mastermix, 2 × 1.9 mL Water	250111
QIAcuity EG PCR Kit (5 mL)	5 × 1 mL 3× concentrated QIAcuity EvaGreen Mastermix, 8 × 1.9 mL Water	250112
QIAcuity EG PCR Kit (25 mL)	5 × 5 mL 3× concentrated QIAcuity EvaGreen Mastermix, 4 × 20 mL Water	250113

For up-to-date licensing information and product-specific disclaimers, see the respective QIAGEN kit handbook or user manual. QIAGEN kit handbooks and user manuals are available at www.qiagen.com or can be requested from QIAGEN Technical Service or your local distributor.

Appendix C – User Management Permissions

The table below shows all available permissions for the user management including short descriptions and technical names. These technical names are shown in audit trail details in case a user has made changes to any users or roles.

Permission	Technical name	Description
Log in [Instrument and PC software]		
Instrument	CSW_USER_LOGIN	User can login to Instrument (login and password is needed).
Suite Software	SUITE_USER_LOGIN	User can login to Suite Software (PC software) (login and password is needed).
Instrument accesses [Instrument software]		
Instrument Maintenance	CSW_INSTRUMENT_MAINTENANCE	User can update the instrument, change instrument connectivity settings and configure auto log-off time for the instrument. User can also go to System support, System Testing, System status and Labware synchronization
Experiment Schedule	CSW_PLATE_EXPERIMENTSCHEDULE	User can change or set the order of plates processing.
Create Support Package	CSW_INSTRUMENT_CREATESUPPORTPACKAGE	User can download and upload support package.
Plates [Instrument and PC software]		
Create Plate	QIACUITY_PLATE_CREATE	User can set up dPCR parameters (priming, cycling, imaging), reaction mixes (reagents), samples (control, non-control) and create Plate layout.
All Plates		
Run Experiment	CSW_PLATE_ALL_RUN	User can run/stop an experiment and eject Plate(s) from Instrument.
Edit Plate Data	QIACUITY_PLATE_ALL_EDITDATA	User can check and edit parameters of existing Plate (dPCR parameters, Plate layout (samples, reaction mixes (reagents), controls), and mark it as primed.
Edit Analysis Data	SUITE_PLATE_ALL_EDITANALYSIS	User can change the threshold and use polygon selection on the Analysis page of all Plates to verify the accuracy of the results.
Read Plate	QIACUITY_PLATE_ALL_READ	User can search for specific Plate, see all created Plates, analyze a Plate, check details about a Plate (dPCR parameters, plate layout (samples, reaction mixes, controls)) and export Plate to CSV.
Delete Plate	SUITE_PLATE_ALL_DELETE	User can delete any Plates.
Owned plates		
Run Experiment	CSW_PLATE_OWNED_RUN	User can run/stop an experiment and eject owned Plate(s) from Instrument.
Edit Plate Data	QIACUITY_PLATE_OWNED_EDITDATA	User can check and edit parameters of owned Plate (dPCR parameters, plate layout (samples, reaction mixes (reagents), controls), and mark it as primed.
Edit Analysis Data	SUITE_PLATE_OWNED_EDITANALYSIS	User can change the threshold and use polygon selection on the Analysis page of the owned Plates to verify the accuracy of the results.

Permission	Technical name	Description
Read Plate	QIACUITY_PLATE_OWNED_READ	User can search the Plate, analyze the Plate, see all created Plates, check details about owned Plate (dPCR parameters, plate layout (samples, reaction mixes, controls)), export plate to CSV.
Delete Plate	SUITE_PLATE_OWNED_DELETE	User can delete owned Plates.
Other permissions		
Import Plate	SUITE_PLATE_OTHER_IMPORT	User can import the Plate as a ZIP file.
Export Plate	SUITE_PLATE_OTHER_EXPORT	User can export the Plate as a password protected ZIP file.
Unlock Plate	SUITE_PLATE_OTHER_UNLOCK	User can unlock locked Plate.
Set Plate Ownership	SUITE_PLATE_OTHER_SETPLATEOWNERSHIP	User can set owners of the plate.
Upload VPF	SUITE_PLATE_OTHER_UPLOADVPF	User can upload Volume Precision Factor.
Upgrade Plate	SUITE_PLATE_OTHER_UPGRADE	User can upgrade the Plate.
Create Support Package	SUITE_PLATE_OTHER_CREATESUPPORTPACKAGE	User can download and export support package for the Plate.
Create Report for Analysis	SUITE_PLATE_OTHER_CREATEREPORT	User can create and generate report using the charts and data from the Analysis of the Plate.
Sign Report	SUITE_PLATE_OTHER_SIGNREPORT	User can add signature to the report.
Delete Report	SUITE_PLATE_OTHER_DELETEREPORT	User can delete report.
Templates [Instrument and PC software]		
Create Template	SUITE_TEMPLATE_ALL_CREATE	User can create new Template.
Edit Template	SUITE_TEMPLATE_ALL_EDITDATA	User can edit existing Template.
Read Template	SUITE_TEMPLATE_ALL_READ	User can read information about existing Templates and use them while creating and editing plates (if also has appropriate plate permissions). Access to all created Templates.
Delete Template	SUITE_TEMPLATE_ALL_DELETE	User can delete existing Templates.
Manage Analysis rules	MANAGE_ANALYSIS_RULES	User can create, edit, or delete Analysis rules.
Archive [PC software]		
Plate Archiving	SUITE_PLATE_ARCHIVE_ARCHIVE	User can archive the Plate.
Archive Overview	SUITE_ARCHIVE_ARCHIVE_READ	User has access to list of archived Plates. User can see all archived Plates, search for archived Plates, check general information about archived Plate and disk space usage for the Archive in the Disk Monitor.
Restore Plate from Archive	SUITE_PLATE_ARCHIVE_ARCHIVERESTORE	User can restore archived Plates.
Delete plate from Archive	SUITE_PLATE_ARCHIVE_ARCHIVEDDELETE	User can delete any Plate from Archive.
User Management [PC software]		
Read Users and Roles	SUITE_USER_ROLE_READ	User can see the list of users and the list of roles in the system.
Create and Edit Users and Roles	SUITE_USER_ROLE_CREATEANDEDIT	User can create and edit a user, and create and edit a role.
Activate and Deactivate User	SUITE_USER_ACTIVATEANDDEACTIVATE	User can activate and deactivate a user.
Delete Role	SUITE_ROLE_DELETE	User can delete existing roles in the system.

Permission	Technical name	Description
Manage password expiration	SUITE_MANAGE_PASSWORD_EXPIRATION	User can change password expiration timeframe
System configuration [PC software]		
Registered Instruments	SUITE_SYSTEM_REGISTERINSTRUMENT	User can see list of registered instruments.
Manage Archive	SUITE_SYSTEM_MANAGEARCHIVE	User can edit Archive location, detach Archive, turn on/off and configure automatic archiving.
Audit Trail Configuration		
View Audit Trail	SUITE_AUDITTRAIL_READ	User can see the list of Audit Trail events, search for specific event, check details of the event and export it to PDF.
Audit Trail Toggle	SUITE_AUDITTRAIL_TURNONOFF	User can turn on/off the Audit Trail (events tracker).

Appendix D – Archive QIAcuity Plates to a Network Drive

The information about archiving QIAcuity plates to a network drive is available in www.qiagen.com/Archive-QIAcuity-plates.

Document Revision History

Revision	Description
July 2026	Manual content adjusted to Software Release 3.5
August 2025	Manual content adjusted to Software Release 3.2
December 2024	Manual content adjusted to Software Release 3.1

Trademarks: QIAGEN®, Sample to Insight®, QIAcuity®, QIAgility® (QIAGEN Group); RNaseZap® (Ambion, Inc.); DNA-ExitusPlus™ (AppliChem); EvaGreen® (Biotium, Inc.); Cy® (GE Healthcare); Alexa Fluor® (Life Technologies Corporation); Windows® (Microsoft Corporation); Texas Red® (Molecular Probes, Inc.); Lysetol®, Mikrozid® (Schülke & Mayr GmbH); FAM™, HEX™, ROX™, TAMRA™, VIC® (Thermo Fisher Scientific or its subsidiaries); DECON-QUAT® (Veltek Associates, Inc.). Registered names, trademarks, etc. used in this document, even when not specifically marked as such, are not to be considered unprotected by law.

07/2026 HB-2717-012 © 2026 QIAGEN, all rights reserved.

Page left intentionally blank.

Page left intentionally blank.

